

Assignment 10

1.

(A B C D E F G)

$X=0$ 0 0 1 1 0 0 0

$X=1$ 0 0 0 0 0 0 0

P_1 (A B E F G) (C D)

$X=0$ B A A B A D D

$X=1$ C C F G E C $\bar{E}$

P_2 (A B) (E F G) (C) (D)

P_3 (A B) (E F G) (C) (D)

$\begin{matrix} \text{"} & \text{"} & \text{"} & \text{"} \\ A' & B' & C' & D' \\ x & & & \end{matrix}$

$P_2 = P_3$ 停止迭代

	0	1
A'	A'/0	C'/0
B'	A'/0	B'/0
C'	D'/1	C'/0
D'	D'/1	B'/0

2.

χ

	0	1
S_0	$S_1/0$	$S_4/0$
S_1	$S_2/0$	$S_1/0$
S_2	$S_1/0$	$S_6/0$
S_3	$S_1/0$	$S_3/0$
S_4	$S_5/0$	$S_4/0$
S_5	$S_2/0$	$S_1/0$
S_6	$S_5/0$	$S_3/$

等价对为

$$(S_0, S_4, S_3) = A$$

$$(S_1, S_5) = B$$

$$(S_2) = C$$

$$(S_6) = D_\chi$$

	S_0	S_1	S_2	S_3	S_4	S_5
S_1	$S_1 S_2$ $S_1 S_4$					
S_2	$S_4 S_6$ $S_1 S_6$	$S_1 S_2$ $S_1 S_6$				
S_3	$S_3 S_4$	$S_1 S_2$ $S_1 S_3$	$S_3 S_6$			
S_4	$S_1 S_5$	$S_2 S_5$ $S_1 S_4$	$S_1 S_5$ $S_4 S_6$	$S_1 S_5$ $S_3 S_4$		
S_5	$S_1 S_2$ $S_1 S_4$	✓	$S_1 S_2$ $S_1 S_6$	$S_1 S_2$ $S_1 S_3$	$S_2 S_5$ $S_1 S_4$	
S_6						

	0	1
A	$B/0$	$A/0$
B	$C/0$	$B/0$
C	$B/0$	$D/0$
D	$B/0$	$A/1$