



TSSOP-16 -> DIP-16 300 mil adapter, PicoGUS THT v1.3.2. Use: U3, U4 (SN74CB3T3257) on PicoGUS THT v1.3.2.
Mapping: TSSOP pin n -> DIP pin n for every pin (net names Pn_<pin name>); nothing else in the signal path.
Board: 10.16 x 20.32 mm, 1 mm chamfer at the pin-1 corner = the body outline of the main-board footprint DIP-16_W7.62mm_TSSOP-16_Adapter (it fits that courtyard).
Assembly: solder the TSSOP first. Then fit two 1x8 round machined pin strips from the BOTTOM (insulator under the board), solder them on the top and cut the tails flush. J1 holes 1.0 mm. The round 0.47 mm pins fit machined DIP sockets (On Shore SA163000) and the 1.0 mm main-board holes.
Square 0.64 mm header pins also fit the 1.0 mm holes, but only for soldering straight into the main board: never push square pins into a machined socket.

J1: two 1x8 round machined pin strips (0.47 mm pins, fit machined sockets)
TSSOP pin n = DIP pin n (1:1); DIP pins counter-clockwise from pin 1 (top view)
Board 10.16 x 20.32 mm, FR4 1.6 mm, 2 layers, outline = Chip Quik PA0034C
PicoGUS THT v1.3.2: U3/U4 SN74CB3T3257 on the main-board DIP-16 adapter footprint
PicoGUS

Sheet: /
File: TSSOP16-DIP16-300mil.kicad_sch

Title: TSSOP-16 to DIP-16 adapter (U3/U4)

Size: A4	Date: 2026-10-24	**Rev: v1.3.2**
KiCad E.D.A. 10.0.6		Id: 1/1