

ISLAMIC UNIVERSITY OF TECHNOLOGY (IUT)
ORGANISATION OF ISLAMIC COOPERATION (OIC)
Department of Computer Science and Engineering (CSE)

QUIZ 1 SET A

SUMMER SEMESTER, 2024-2025

DURATION: 30 MINUTES

FULL MARKS: 20

CSE 4205: Digital Logic Design

Programmable calculators are not allowed.

Answer **all 5 (five)** questions. Figures in the right margin indicate full marks of questions with corresponding COs and POs in parentheses.

ID:

1. Simplify the following boolean expression using cut and try method:

4 + 1
(CO2)
(PO1)

(i) $F_1(A, B, C) = \bar{A}\bar{B}\bar{C} + \bar{A}B\bar{C} + A\bar{B}\bar{C} + \bar{A}\bar{B}C + A\bar{B}C$

(ii) $F_2(A, B) = (A \oplus B) + \overline{(A \oplus B)}$

2. Perform the following subtraction using the Radix complement (r's complement) method without converting the numbers to another base: 4
- (CO1)
- (PO1)
- $$(725)_9 - (368)_9$$

3. Perform the following addition using BCD addition (you have to convert the numbers to BCD, perform the addition, and convert the result back to decimal):
- 5
(CO1)
(PO1)
- $$(567)_{10} + (654)_{10}$$

4. A number $(964)_b$ in an unknown base b is equivalent to the hexadecimal number $(A7D)_{16}$. Determine the base b .

3
(CO1)
(PO1)

5. Pick the correct option for the following question:

1×3
(CO1,2)
(PO1)

- (A) Can $(101101011)_{GRAY}$ and $(1011011011)_{GRAY}$ be two consecutive numbers in the Gray code sequence?

☐ Yes

☐ No

- (B) Does $(101101)_2$ maintain even parity?

☐ Yes

☐ No

- (C) Let $F(A, B, C) = \sum m(0, 3, 5, 7)$. Is $\bar{F} = \sum M(1, 2, 4, 6)$ true?

☐ Yes

☐ No