BACS2063 Data Structures and Algorithms

Abstract Data Types (ADTs)

Chapter 2

Learning Outcomes

At the end of this lecture, you should be able to

- Explain the benefits of abstract data types (ADTs).
- Write ADT specifications.
- Implement ADTs using Java interfaces and classes.

Winning Strategies in Programming

Increase Productivity

- Projects can be finished on time
- More projects can be handled

Assure Quality

Reliable: bug-free

How to ... increase productivity and assure quality?

Code reuse

Code maintainability

To achieve *reuse*

Abstraction

ADT specification

Encapsulation

ADT implementation

To achieve maintainability

Encapsulation
/ Information
Hiding

ADT implementation

Abstraction

- Abstraction is a fundamental concept in computer science and software engineering that involves
 - simplifying complex systems by hiding unnecessary details and exposing only the essential features.
 - to manage complexity, enhance understanding, and improve the efficiency of software development and usage.

Benefits

Manage Complexity:

 By focusing on high-level concepts: - helps manage the complexity of software systems, making them easier to design, develop, and maintain.

Enhance Reusability:

 promotes code reuse by allowing developers to create general-purpose components that can be used in different contexts.

Improve Maintainability:

 helps in isolating changes. When implementation details change, the high-level interface remains the same, reducing the impact on the rest of the system.

Facilitate Communication:

 High-level abstractions provide a common language for developers, designers, and stakeholders to communicate effectively about system functionality and design.

Benefits of

Abstraction

 Can focus on the abstract properties without worrying about how it is going to be implemented.

Encapsulation

 Can use the components without knowing the implementation details.

Abstraction & Encapsulation

Abstraction

Specifying the data type

Encapsulation

Using the data type

2 sides of the same coin

2020 October, Q1c

Analyze **TWO (2)** benefits of using abstraction in the data structures. Justify your answer with relevant examples. (8 marks)

2020 October, Q1c

Analyze TWO (2) benefits of using abstraction in the data structures. Justify your answer with relevant examples.
 (8 marks)

The main benefits of using abstraction in data structures are:

Reusability


By defining the ADT and creating its implementation with Generic data type, a particular ADT can later be used in any system that needs a collection of data which has the same characteristics as the ADT.

Maintainability

The definition of the ADT and its implementation are separate, so if the implementation needs to be changed, the users of the ADT do not need to change their code. Also, ADT is written in modules, so any code modifications are easy to be maintained.







Case Study



Mr. Gru set up MinionSoft in January 2013. Since then, his company has successfully completed 7 projects. As Gru reflected on his projects, he suddenly realized a similarity in all his projects – each of them used a *list* of some sort. *E.g.*,

- The BananaBananana MP5 player software had a playlist for songs.
- In the MonsterMinion game, each character had a weapon list.
- The OhPotato! productivity app had a task list.

Gru's observation

- Code duplication reinventing the wheel
- Not-so-maintainable code

MinionSoft's code duplication

- The list is a "thing" that appears in all of the software applications.
- It has specific characteristics
 - Data in the list is organized in a certain way
 - There are certain operations that are performed on the list
- The declaration for the array to hold the list elements and the coding for the operations were repeated in all the software applications.

MinionSoft's not-so-maintainable code

 If a bug is discovered, the changes to the code would need to be applied to every single software module or application which used a list.

How to...

- Enable reuse?
- Increase maintainability?

Solution Steps

1. Abstraction

- Identify the general/abstract properties and operations of the list.
 - An abstract data type
- Produce a specification of the list
 - O What are the characteristics of the data?
 - What are the operations for manipulating the data?

Solution Steps (cont'd)

2. Encapsulation

- Implement the list in such a way that a programmer can use the list without knowing how it is implemented.
 - > Information hiding

An ADT is

"An abstraction of a commonly appearing data structure along with a set of defined operations on the data structure. It specifies the logical properties without the implementation details. In Java, ADT is achieved through the use of classes."

Malik & Nair (2003)

ADT Specifications

- refers to the definition and description of an ADT, focusing on its behavior and operations rather than its implementation details.
- Written in a natural language (e.g. English) and are independent of any programming language.
- Used as specifications for concrete data types (i.e. the actual data types used in programs).

What to include in an ADT specification?

1. ADT title

- Description of the characteristics (logical properties) of the data type
- 3. Description of each operation:
 - Operation header: return type (if any), operation name, parameters (if any)
 - Brief description of what the operation does
 - Precondition (*if any*, i.e. this is optional)
 - Postcondition
 - What is returned by the operation (if any, i.e. this is optional)

Preconditions and Postconditions

Precondition

 A statement specifying the condition(s) that must be true before the operation is invoked.

Postcondition

 A statement specifying what is true after the operation is completed.

– Malik & Nair (2003)

Problem: A Counter ADT

 Counter devices are used for counting things such as cars entering a parking lot, people taking numbers at the post-office, etc. A counter object would have a non-negative integer value representing the current count. It can be incremented, decremented, reset to zero and have its value read at any time.

Exercise 2.1


• Write the ADT specification for a counter whose instances would represent counter objects.

Implementing Encapsulation

- In object-oriented programming, encapsulation is achieved in a class by
 - Making its data fields private, and
 - Providing public methods for controlled access to and manipulation of the data fields



Data Abstraction



An interface provides wellregulated communication between a hidden implementation and a client.

Carrano (2011)

To implement an ADT in Java

- Translate the ADT specification into a Java interface
- 2. Write a **class** which implements the Java interface

Sample Code: Counter ADT

In Chapter2\carpark\

- CounterInterface.java
- Counter.java
- CarParkSystem.java
 - A GUI application which simulates the use of the counter in a car park with 2 wings

Summary: Designing & Implementing a new ADT

Step 1 Write the ADT specification

Write an ADT specification which describes the characteristics
of that data type and the set of operations for manipulating the
data. Should not include any implementation or usage details.

Step 2 Implement the ADT

- a. Write a Java interface
 - Include all the operations from the ADT specification
- b. Write a Java class
 - This class implements the Java interface from part a.
 - Determine how to represent the data
 - Implement all the operations from the interface

Step 3 Use the ADT in a client program or application

An ADT specification

 Defines the structure, behavior and operations of a "new" data type without specifying how those structure, behavior and operations are actually implemented.

ADT: Rationale

Separation of Concerns

- By separating the definition of the data structure from the implementation, we can use the new data structure in programs without regard for its implementation.
- Hence, the implementation can be changed (improved, updated, etc) and the client programs (i.e. the programs that use the data structure) will only have to change the name of the class that implements the new data structure.

Review Learning Outcomes

You should now be able to

- Explain the benefits of abstract data types (ADTs).
- Write ADT specifications.
- Implement ADTs using Java interfaces and classes.

Post-Lecture Exercise

Past-Year-Question

PYQ 19-Jan-2023 (Question)



Question 1

Figure 1 shows the formula for area of various shapes. Consider an Abstract Data Type (ADT) called **AreaShape** which represents area of a shape or size of the shape.




Figure 1: Area of shapes

ADT Title: AreaShape

Area of a shape is the size of the surface.

Description of each operation as below:

- triangleArea (b, h), which calculate the area of a triangle
- rectangleArea (w, h), which calculate the area of a rectangle
- squareArea(a), which calculate the area of a square
- circleArea(r), which calculate the area of a circle
- a) Write an ADT specification named AreaShape which include operations that mentioned above and state any assumptions made. (10 marks)

Sample Answer:

ADT AreaShape

Area of a shape is the size of the surface.

Integer triangleArea (Integer base, Integer height)

Description: calculate the area of a triangle

Pre-condition: must be integer value

Post-condition: area of triangle calculated

Return: result of area calculation



Description : calculate the area of a rectangle

Pre-condition: must be integer value

Post-condition: area of rectangle calculated

Return: result of area calculation

Integer squareArea (Integer width)

Description: calculate the area of a square

Pre-condition: must be integer value

Post-condition: area of square calculated

Return: result of area calculation

double circleArea (Integer radius)

Description: calculate the area of a circle

Pre-condition: must be integer value Post-condition: area of circle calculated

Return: result of area calculation



PYQ 8-June-2023 (Question)



Question 1

Figure 1 shows a sample output screen of the Meter conversion. Consider an Abstract Data Type (ADT) called **Converter** which converts a unit of meter to miles, meter to feet and meter to inches.

Please enter a Measurement in Meters: 50

The conversion measurement is as follows

Miles : 0.0311 Feet : 164.0420 Inches : 1968.5039

Figure 1: Sample output screen of meter conversion application

ADT Converter

Converter is a conversion that converts meters to miles, feet and inches.

Description of each operation as below:

- miles (m), which convert meters to miles
- feet (m), which convert meters to feet
- inches(m), which convert meters to inches
- a) Write an ADT specification named **Converter** which, includes the above-mentioned operations. State any assumptions made. (10 marks)

Sample Answer

ADT Converter

Converter is a conversion that convert meters to miles, feet and inches.

Double *miles* (Integer meter)

Description: convert given meter value to miles

Pre-condition: must be integer value

Post-condition: given meter value remain unchanged

Return: miles value returned

Double feet (Integer meter)

Description: convert given meter value to feet

Pre-condition: must be integer value

Post-condition: given meter value remain unchanged

Return: feet value returned

Double inches (Integer meter)

Description: convert given meter value to inches

Pre-condition: must be integer value

Post-condition: given meter value remain unchanged

Return: inches value returned



PYQ 14-October-2022 Q1a

BACS2063 DATA STRUCTURES AND ALGORITHMS

Question 1

If a number is **not** completely **divisible by two**, then it is considered an **odd number**. For such numbers, dividing them by two always leaves a **remainder** of **one**. If a number is completely divisible by two without any remainder, then it is considered an **even number**. Create a simple program that determine if an input number is an odd or even number.

a) Write an ADT specification to represent the above scenario. Include operations that determine odd and even numbers. (10 marks)

Sample Answer:

ADT oddEven

A number **not** completely **divisible by two**, is an odd number and otherwise is an even number.

Boolean **oddNumber**(Integer number)

Description: determine a given value is odd number.

Pre-condition: number must be integer and not zero

Post-condition: the number remain unchanged

Returns: true if odd number; otherwise false

Boolean **evenNumber**(Integer number)

Description: determine a given value is even number.

Pre-condition: number must be integer and not zero

Post-condition: the number remain unchanged.

Returns: true if even number; otherwise false

Appendix - ADT Specification

Important notes (Useful for your assignment)

An ADT Specification must be *generic* in nature

- An ADT specification must not indicate what programming language would be used to implement it.
- An ADT specification for a collection ADT must be generic in nature and free from these 2 things:
 - Implementation details (e.g. using array or linked nodes)
 - Detail of the specific objects contained (e.g *Product* objects, or *Customer* objects, etc.)
- For Example, for the ADT specification of a List ADT, you
 must not indicate whether the List will be implemented
 with array or with linked nodes. You must also not specify
 that this List will contain Customer objects or Product
 objects.

Words you should not use in an ADT Specification (1/2)

• Examples of words that you can use



- List
- Stack
- Queue
- Examples of words that you cannot use
 - Array List / Linked List
 - Array Stack / Linked Stack
 - Array Queue / Linked Queue

Words you should not use in an ADT Specification (2/2)

- For example, here are 3 method definitions:
 - add(T newEntry) ← CORRECT
 - 2. add(Customer newEntry) ← WRONG
 - add(Product newEntry) ← WRONG
- The add method defines the add operation of an ADT. The object to be added is received as a parameter. This object should be generic to allow reusability. Reusability means I can use this ADT in Project X to store *customer* objects. I can also use this ADT in Project Y to store *product* objects.
- <u>The first one</u> is done correctly, because the parameter is of a generic type.
- The second & third ones are wrong and should not be done in an ADT specification because Customer and Product are specific types and not generic. When the object is specific, it no longer allow reusability.

Sample for common mistakes (1)

2. Abstract Data Type (ADT) Specification

ADT ArrayList

An array list is a resizable list that is used to store the elements. It will grow its size to accommodate the new elements and it will shrink the size when the elements are removed. It also allows retrieval of the elements by their index.

Boolean insert(T newData)		
Description	Add newData to the list.	
Precondition	-	
Postcondition	The newData is added to the list.	
Return	Return <i>true</i> if the newData is successfully added to the list, else return <i>false</i> .	

Sample for common mistakes (2)

2. Abstract Data Type (ADT) Specification

ADT: List

Implementation method: Array List

Boolean add(T newEntry)		
Description	Add newEntry into the list	
Precondition	-	
Postcondition	newEntry has been added to the end of the list	
Returns	True if newEntry is successfully added	

Sample for common mistakes (3)

2. Abstract Data Type (ADT) Specification

ADT LinkedListDoubly

A LinkedListDoubly is used to make some operations such as add, remove and get number of entries etc.

boolean addFirst(T newEntry)		
Description	Add newEntry to the first place of the doubly linked list.	
Postcondition	newEntry has been added to the doubly linked list.	
Returns	True if newEntry successfully added, false if not.	

boolean addLast(T newEntry)		
Description	Add newEntry to the last place of the doubly linked list.	
Postcondition	newEntry has been added to the doubly linked list.	
Returns	True if newEntry successfully added, false if not.	

Sample for common mistakes (4)

2. Abstract Data pe (ADT) Specification

enqueue(T newEntry)		
Description	adds a newEntry node to after rear and moves the rear to the next node.	
Pre Condition	-	
Post Condition	newEntry has been added to the rear Node of the queue	
Returns	-	

Sample for common mistakes (5)

2. Abstract Data Type (ADT) Specification ADT: Queue Implementation method: Circular Linked Queue void enqueue (T newEntry) Description Adds new entry at the back of the queue Pre Condition Post Condition New entry is added to the queue Returns -

Sample for ADT Specs done correctly



Boolean add (T newElement)		
Description	Add newElement to the end of the list	
Pre-condition	-	
Post-condition	The newElement is added to the end of the list	
Returns	Return true if newElement successfully added, else return false	