

MIPI Camera Deployment Matrix

Generated: 2026-04-01 16:17:46

 Tested
  Theoretical (not yet tested)
  Not supported
  No data

Jetson Nano (T210)

SoM: Tegra X1 | L4T: 32.x | CSI lanes: 2

L4T	Dione	MicroCube	Crius1280	SmartIR640	iLumos	Microlynx
32.5.1	 Tested	—	—	—	—	—
32.6.1	 Tested	—	—	—	—	—
32.7.1	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical
32.7.4	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical
32.7.5	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical
32.7.6	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical

Xavier NX (T194)

SoM: Tegra194 | L4T: 32.x, 35.x | CSI lanes: 2

L4T	Dione	MicroCube	Crius1280	SmartIR640	iLumos	Microlynx
32.5.1	 Tested	—	—	—	—	—
32.6.1	 Tested	—	—	—	—	—
32.7.1	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical
32.7.4	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical
32.7.5	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical
32.7.6	 Tested	 Tested	 Tested	 Tested	 Theoretical	 Theoretical
35.1	 Tested	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.3.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.4.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.5.0	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.0	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.2	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical

AGX Orin devkit

SoM: Tegra234 | L4T: 35.x, 36.x | CSI lanes: 4

L4T	Dione	MicroCube	Crius1280	SmartIR640	iLumos	Microlynx
35.3.1	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.4.1	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.5.0	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.0	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.1	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.2	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.4.3	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.4.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.5.0	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical

AGX Orin Auvideo X230D

SoM: Tegra234 | L4T: 35.x, 36.x | CSI lanes: 4

L4T	Dione	MicroCube	Crius1280	SmartIR640	iLumos	Microlynx
35.3.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.4.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
36.4	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
36.4.3	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
36.4.4	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested

Orin NX / Nano devkit

SoM: Tegra234 | L4T: 35.x, 36.x | CSI lanes: 2

L4T	Dione	MicroCube	Crius1280	SmartIR640	iLumos	Microlynx
35.3.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.4.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.5.0	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.0	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.1	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.2	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
35.6.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.4	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
36.4.3	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
36.4.4	 Tested	 Tested	 Tested	 Tested	 Tested	 Tested
36.5.0	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical

Forecr DSBOARD ORNXS

SoM: Tegra234 | L4T: 35.x, 36.x | CSI lanes: 4

L4T	Dione	MicroCube	Crius1280	SmartIR640	iLumos	Microlynx
35.3.1	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.4.1	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.5.0	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.0	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.1	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.2	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
35.6.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.4.3	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.4.4	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical
36.5.0	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical	 Theoretical

Camera Details

Dione

640x480 — 2 lane(s)

Format	Pix clock	CSI clock
RGB888	20 MHz	120 MHz

1280x1024 — 2 lane(s)

Format	Pix clock	CSI clock
RGB888	83 MHz	498 MHz

320x240 — 2 lane(s)

Format	Pix clock	CSI clock
RGB888	20 MHz	120 MHz

1024x768 — 2 lane(s)

Format	Pix clock	CSI clock
RGB888	83 MHz	498 MHz

MicroCube

640x480 — 1 lane(s)

Format	Pix clock	CSI clock
Y16	20 MHz	160 MHz
RGB888	20 MHz	240 MHz
YUYV	20 MHz	160 MHz

Crius1280

1280x1024 — 2 lane(s)

Format	Pix clock	CSI clock
Y16	100 MHz	400 MHz
RGB888	133.3 MHz	800 MHz
YUYV	100 MHz	400 MHz

SmartIR640

640x480 — 2 lane(s)

Format	Pix clock	CSI clock
Y16	100 MHz	400 MHz
RGB888	100 MHz	600 MHz
YUYV	100 MHz	400 MHz

iLumos

2048x2048 — 2 lane(s)

Format	Pix clock	CSI clock
Y16	100 MHz	450 MHz
Y14	100 MHz	450 MHz

2048x1088 — 2 lane(s)

Format	Pix clock	CSI clock
Y16	100 MHz	450 MHz
Y14	100 MHz	450 MHz

1280x1024 — 2 lane(s)

Format	Pix clock	CSI clock
Y16	51 MHz	149.5 MHz
Y14	100 MHz	450 MHz

Microlynx		
1024x128 — 2 lane(s)		
Format	Pix clock	CSI clock
Y16	87.5 MHz	350 MHz
Y14	100 MHz	350 MHz