

Alcohol Detection and Engine Locking System - Arduino Code

Arduino UNO | MQ3 Alcohol Sensor | Relay Module | Buzzer | DC Motor

```
// Alcohol Detection and Engine Locking System

const int alcoholSensor = A0;
const int relayPin = 7;
const int buzzerPin = 8;

int sensorValue;
int threshold = 400;

void setup()
{
  Serial.begin(9600);
  pinMode(relayPin, OUTPUT);
  pinMode(buzzerPin, OUTPUT);

  digitalWrite(relayPin, HIGH);
  digitalWrite(buzzerPin, LOW);
}

void loop()
{
  sensorValue = analogRead(alcoholSensor);

  Serial.print("Alcohol Sensor Value: ");
  Serial.println(sensorValue);

  if(sensorValue > threshold)
  {
    Serial.println("Alcohol Detected!");
    Serial.println("Engine Locked");

    digitalWrite(buzzerPin, HIGH);
    digitalWrite(relayPin, LOW);
  }
  else
  {
    Serial.println("No Alcohol Detected");
    Serial.println("Engine Running");

    digitalWrite(buzzerPin, LOW);
    digitalWrite(relayPin, HIGH);
  }

  delay(1000);
}
```