[0x21]

"real part" "imaginary part"

is $z = \overbrace{Re(z)}^{\text{"real part"}} + \overbrace{Im(z)}^{\text{"imaginary part"}} \cdot i$

$$Re(z) = \overset{rax_{final}}{\overset{\shortparallel}{(rax_0 + rbx_0)\, rcx}} - (rdx_0 + rcx_0)$$

$$Im(z) = rax_0 (rdx_0 \cancel{+} - rcx_0) + \cancel{(rax_0 + rbx_0)\, rcx_0}$$

$$\underset{rbx_{final}}{\shortparallel} = rax_0 \cdot rdx_0 + rbx_0 \cdot rcx_0$$

$rsi = rax_0$	mov	rsi, rax
$rax = rax_0 + rbx_0$	add	rax, rbx
$rdi = rdx_0$	mov	rdi, rdx
$rdx = rdx_0 - rcx_0$	sub	rdx, rcx
$rdi = rdi + rcx = rdx_0 + rcx_0$	add	rdi, rcx
	imul → signed mult	
$rax = rax \cdot rcx = (rax_0 + rbx_0) \cdot rcx_0$	imul	rax, rcx
$rsi = rsi \cdot rdx = rax_0 \cdot (rdx_0 - rcx_0)$	imul	rsi, rdx
$rdi = rdi \cdot rbx = (rdx_0 + rcx_0) \cdot rbx_0$	imul	rdi, rbx
	add	rsi, rax
	mov	rbx, rsi
	sub	rax, rdi

$rsi = rsi + rax$
$= rax_0 (rdx_0 - rcx_0) + (rax_0 + rbx_0) \cdot rcx_0 =: rbx \}\ Im(z)$

$rax = rax - rdi = (rax_0 + rbx_0) \cdot rcx_0 - (rdx_0 + rcx_0) \}\ Re(z)$