

敏感体电阻—负载电阻——负载输出电压对照表

敏感体 电阻/ $K\Omega$	负载电阻 R_L (测试回路电压 $V_c:5V$)										
	0.51K	1.00K	2.00K	2.20K	4.70K	10.00K	15.00K	20.00K	22.00K	47.00K	100.00K
1.0	1.689	2.500	3.333	3.438	4.123	4.545	4.688	4.762	4.783	4.896	4.950
2.0	1.016	1.667	2.500	2.619	3.507	4.167	4.412	4.545	4.583	4.796	4.902
3.0	0.726	1.250	2.000	2.115	3.052	3.846	4.167	4.348	4.400	4.700	4.854
4.0	0.565	1.000	1.667	1.774	2.701	3.571	3.947	4.167	4.231	4.608	4.808
5.0	0.463	0.833	1.429	1.528	2.423	3.333	3.750	4.000	4.074	4.519	4.762
6.0	0.392	0.714	1.250	1.341	2.196	3.125	3.571	3.846	3.929	4.434	4.717
7.0	0.340	0.625	1.111	1.196	2.009	2.941	3.409	3.704	3.793	4.352	4.673
8.0	0.300	0.556	1.000	1.078	1.850	2.778	3.261	3.571	3.667	4.273	4.630
9.0	0.268	0.500	0.909	0.982	1.715	2.632	3.125	3.448	3.548	4.196	4.587
10.0	0.243	0.455	0.833	0.902	1.599	2.500	3.000	3.333	3.438	4.123	4.545
11.0	0.222	0.417	0.769	0.833	1.497	2.381	2.885	3.226	3.333	4.052	4.505
12.0	0.204	0.385	0.714	0.775	1.407	2.273	2.778	3.125	3.235	3.983	4.464
13.0	0.189	0.357	0.667	0.724	1.328	2.174	2.679	3.030	3.143	3.917	4.425
14.0	0.176	0.333	0.625	0.679	1.257	2.083	2.586	2.941	3.056	3.852	4.386
15.0	0.164	0.313	0.588	0.640	1.193	2.000	2.500	2.857	2.973	3.790	4.348
16.0	0.154	0.294	0.556	0.604	1.135	1.923	2.419	2.778	2.895	3.730	4.310
17.0	0.146	0.278	0.526	0.573	1.083	1.852	2.344	2.703	2.821	3.672	4.274
18.0	0.138	0.263	0.500	0.545	1.035	1.786	2.273	2.632	2.750	3.615	4.237
19.0	0.131	0.250	0.476	0.519	0.992	1.724	2.206	2.564	2.683	3.561	4.202
20.0	0.124	0.238	0.455	0.495	0.951	1.667	2.143	2.500	2.619	3.507	4.167
30.0	0.084	0.161	0.313	0.342	0.677	1.250	1.667	2.000	2.115	3.052	3.846
40.0	0.063	0.122	0.238	0.261	0.526	1.000	1.364	1.667	1.774	2.701	3.571
45.0	0.056	0.109	0.213	0.233	0.473	0.909	1.250	1.538	1.642	2.554	3.448
50.0	0.050	0.098	0.192	0.211	0.430	0.833	1.154	1.429	1.528	2.423	3.333
55.0	0.046	0.089	0.175	0.192	0.394	0.769	1.071	1.333	1.429	2.304	3.226
60.0	0.042	0.082	0.161	0.177	0.363	0.714	1.000	1.250	1.341	2.196	3.125
65.0	0.039	0.076	0.149	0.164	0.337	0.667	0.938	1.176	1.264	2.098	3.030
70.0	0.036	0.070	0.139	0.152	0.315	0.625	0.882	1.111	1.196	2.009	2.941
75.0	0.034	0.066	0.130	0.142	0.295	0.588	0.833	1.053	1.134	1.926	2.857

敏感体电阻—负载电阻——负载输出电压对照表

敏感体 电阻/ $K\Omega$	负载电阻 R_L (测试回路电压 $V_c:5V$)										
	0.51K	1.00K	2.00K	2.20K	4.70K	10.00K	15.00K	20.00K	22.00K	47.00K	100.00K
80.0	0.032	0.062	0.122	0.134	0.277	0.556	0.789	1.000	1.078	1.850	2.778
85.0	0.030	0.058	0.115	0.126	0.262	0.526	0.750	0.952	1.028	1.780	2.703
90.0	0.028	0.055	0.109	0.119	0.248	0.500	0.714	0.909	0.982	1.715	2.632
95.0	0.027	0.052	0.103	0.113	0.236	0.476	0.682	0.870	0.940	1.655	2.564
100.0	0.025	0.050	0.098	0.108	0.224	0.455	0.652	0.833	0.902	1.599	2.500
105.0	0.024	0.047	0.093	0.103	0.214	0.435	0.625	0.800	0.866	1.546	2.439
110.0	0.023	0.045	0.089	0.098	0.205	0.417	0.600	0.769	0.833	1.497	2.381
115.0	0.022	0.043	0.085	0.094	0.196	0.400	0.577	0.741	0.803	1.451	2.326
120.0	0.021	0.041	0.082	0.090	0.188	0.385	0.556	0.714	0.775	1.407	2.273
125.0	0.020	0.040	0.079	0.086	0.181	0.370	0.536	0.690	0.748	1.366	2.222
130.0	0.020	0.038	0.076	0.083	0.174	0.357	0.517	0.667	0.724	1.328	2.174
135.0	0.019	0.037	0.073	0.080	0.168	0.345	0.500	0.645	0.701	1.291	2.128
140.0	0.018	0.035	0.070	0.077	0.162	0.333	0.484	0.625	0.679	1.257	2.083
145.0	0.018	0.034	0.068	0.075	0.157	0.323	0.469	0.606	0.659	1.224	2.041
150.0	0.017	0.033	0.066	0.072	0.152	0.313	0.455	0.588	0.640	1.193	2.000
155.0	0.016	0.032	0.064	0.070	0.147	0.303	0.441	0.571	0.621	1.163	1.961
160.0	0.016	0.031	0.062	0.068	0.143	0.294	0.429	0.556	0.604	1.135	1.923
165.0	0.015	0.030	0.060	0.066	0.138	0.286	0.417	0.541	0.588	1.108	1.887
170.0	0.015	0.029	0.058	0.064	0.135	0.278	0.405	0.526	0.573	1.083	1.852
175.0	0.015	0.028	0.056	0.062	0.131	0.270	0.395	0.513	0.558	1.059	1.818
180.0	0.014	0.028	0.055	0.060	0.127	0.263	0.385	0.500	0.545	1.035	1.786
185.0	0.014	0.027	0.053	0.059	0.124	0.256	0.375	0.488	0.531	1.013	1.754
190.0	0.013	0.026	0.052	0.057	0.121	0.250	0.366	0.476	0.519	0.992	1.724
195.0	0.013	0.026	0.051	0.056	0.118	0.244	0.357	0.465	0.507	0.971	1.695
200.0	0.013	0.025	0.050	0.054	0.115	0.238	0.349	0.455	0.495	0.951	1.667
205.0	0.012	0.024	0.048	0.053	0.112	0.233	0.341	0.444	0.485	0.933	1.639
210.0	0.012	0.024	0.047	0.052	0.109	0.227	0.333	0.435	0.474	0.914	1.613
215.0	0.012	0.023	0.046	0.051	0.107	0.222	0.326	0.426	0.464	0.897	1.587
220.0	0.012	0.023	0.045	0.050	0.105	0.217	0.319	0.417	0.455	0.880	1.563

敏感体电阻—负载电阻——负载输出电压对照表

敏感体 电阻/ $K\Omega$	负载电阻 R_L (测试回路电压 $V_c:5V$)										
	0.51K	1.00K	2.00K	2.20K	4.70K	10.00K	15.00K	20.00K	22.00K	47.00K	100.00K
225.0	0.011	0.022	0.044	0.048	0.102	0.213	0.313	0.408	0.445	0.864	1.538
230.0	0.011	0.022	0.043	0.047	0.100	0.208	0.306	0.400	0.437	0.848	1.515
235.0	0.011	0.021	0.042	0.046	0.098	0.204	0.300	0.392	0.428	0.833	1.493
240.0	0.011	0.021	0.041	0.045	0.096	0.200	0.294	0.385	0.420	0.819	1.471
245.0	0.010	0.020	0.040	0.044	0.094	0.196	0.288	0.377	0.412	0.805	1.449
250.0	0.010	0.020	0.040	0.044	0.092	0.192	0.283	0.370	0.404	0.791	1.429
255.0	0.010	0.020	0.039	0.043	0.090	0.189	0.278	0.364	0.397	0.778	1.408
260.0	0.010	0.019	0.038	0.042	0.089	0.185	0.273	0.357	0.390	0.765	1.389
265.0	0.010	0.019	0.037	0.041	0.087	0.182	0.268	0.351	0.383	0.753	1.370
270.0	0.009	0.018	0.037	0.040	0.086	0.179	0.263	0.345	0.377	0.741	1.351
275.0	0.009	0.018	0.036	0.040	0.084	0.175	0.259	0.339	0.370	0.730	1.333
280.0	0.009	0.018	0.035	0.039	0.083	0.172	0.254	0.333	0.364	0.719	1.316
285.0	0.009	0.017	0.035	0.038	0.081	0.169	0.250	0.328	0.358	0.708	1.299
290.0	0.009	0.017	0.034	0.038	0.080	0.167	0.246	0.323	0.353	0.697	1.282
295.0	0.009	0.017	0.034	0.037	0.078	0.164	0.242	0.317	0.347	0.687	1.266
300.0	0.008	0.017	0.033	0.036	0.077	0.161	0.238	0.313	0.342	0.677	1.250
305.0	0.008	0.016	0.033	0.036	0.076	0.159	0.234	0.308	0.336	0.668	1.235
310.0	0.008	0.016	0.032	0.035	0.075	0.156	0.231	0.303	0.331	0.658	1.220
315.0	0.008	0.016	0.032	0.035	0.074	0.154	0.227	0.299	0.326	0.649	1.205
320.0	0.008	0.016	0.031	0.034	0.072	0.152	0.224	0.294	0.322	0.640	1.190
325.0	0.008	0.015	0.031	0.034	0.071	0.149	0.221	0.290	0.317	0.632	1.176
330.0	0.008	0.015	0.030	0.033	0.070	0.147	0.217	0.286	0.313	0.623	1.163
335.0	0.008	0.015	0.030	0.033	0.069	0.145	0.214	0.282	0.308	0.615	1.149
340.0	0.007	0.015	0.029	0.032	0.068	0.143	0.211	0.278	0.304	0.607	1.136
345.0	0.007	0.014	0.029	0.032	0.067	0.141	0.208	0.274	0.300	0.599	1.124
350.0	0.007	0.014	0.028	0.031	0.066	0.139	0.205	0.270	0.296	0.592	1.111
355.0	0.007	0.014	0.028	0.031	0.065	0.137	0.203	0.267	0.292	0.585	1.099
360.0	0.007	0.014	0.028	0.030	0.064	0.135	0.200	0.263	0.288	0.577	1.087
365.0	0.007	0.014	0.027	0.030	0.064	0.133	0.197	0.260	0.284	0.570	1.075

敏感体电阻—负载电阻——负载输出电压对照表

敏感体 电阻/ $K\Omega$	负载电阻 R_L (测试回路电压 $V_c:5V$)										
	0.51K	1.00K	2.00K	2.20K	4.70K	10.00K	15.00K	20.00K	22.00K	47.00K	100.00K
370.0	0.007	0.013	0.027	0.030	0.063	0.132	0.195	0.256	0.281	0.564	1.064
375.0	0.007	0.013	0.027	0.029	0.062	0.130	0.192	0.253	0.277	0.557	1.053
380.0	0.007	0.013	0.026	0.029	0.061	0.128	0.190	0.250	0.274	0.550	1.042
385.0	0.007	0.013	0.026	0.028	0.060	0.127	0.188	0.247	0.270	0.544	1.031
390.0	0.007	0.013	0.026	0.028	0.060	0.125	0.185	0.244	0.267	0.538	1.020
395.0	0.006	0.013	0.025	0.028	0.059	0.123	0.183	0.241	0.264	0.532	1.010
400.0	0.006	0.012	0.025	0.027	0.058	0.122	0.181	0.238	0.261	0.526	1.000
410.0	0.006	0.012	0.024	0.027	0.057	0.119	0.176	0.233	0.255	0.514	0.980
420.0	0.006	0.012	0.024	0.026	0.055	0.116	0.172	0.227	0.249	0.503	0.962
430.0	0.006	0.012	0.023	0.025	0.054	0.114	0.169	0.222	0.243	0.493	0.943
440.0	0.006	0.011	0.023	0.025	0.053	0.111	0.165	0.217	0.238	0.483	0.926
450.0	0.006	0.011	0.022	0.024	0.052	0.109	0.161	0.213	0.233	0.473	0.909
460.0	0.006	0.011	0.022	0.024	0.051	0.106	0.158	0.208	0.228	0.464	0.893
470.0	0.005	0.011	0.021	0.023	0.050	0.104	0.155	0.204	0.224	0.455	0.877
480.0	0.005	0.010	0.021	0.023	0.048	0.102	0.152	0.200	0.219	0.446	0.862
490.0	0.005	0.010	0.020	0.022	0.048	0.100	0.149	0.196	0.215	0.438	0.847
500.0	0.005	0.010	0.020	0.022	0.047	0.098	0.146	0.192	0.211	0.430	0.833
550.0	0.005	0.009	0.018	0.020	0.042	0.089	0.133	0.175	0.192	0.394	0.769
600.0	0.004	0.008	0.017	0.018	0.039	0.082	0.122	0.161	0.177	0.363	0.714
700.0	0.004	0.007	0.014	0.016	0.033	0.070	0.105	0.139	0.152	0.315	0.625
800.0	0.003	0.006	0.012	0.014	0.029	0.062	0.092	0.122	0.134	0.277	0.556
1000.0	0.003	0.005	0.010	0.011	0.023	0.050	0.074	0.098	0.108	0.224	0.455
2000.0	0.001	0.002	0.005	0.005	0.012	0.025	0.037	0.050	0.054	0.115	0.238
3000.0	0.001	0.002	0.003	0.004	0.008	0.017	0.025	0.033	0.036	0.077	0.161
4000.0	0.001	0.001	0.002	0.003	0.006	0.012	0.019	0.025	0.027	0.058	0.122
5000.0	0.001	0.001	0.002	0.002	0.005	0.010	0.015	0.020	0.022	0.047	0.098
6000.0	0.000	0.001	0.002	0.002	0.004	0.008	0.012	0.017	0.018	0.039	0.082
8000.0	0.000	0.001	0.001	0.001	0.003	0.006	0.009	0.012	0.014	0.029	0.062
10000.0	0.000	0.000	0.001	0.001	0.002	0.005	0.007	0.010	0.011	0.023	0.050

敏感体电阻—负载电阻——负载输出电压对照表

负载输出 电压/V	负载电阻 R_L (测试回路电压 $V_c:5V$)										
	0.51K	1.00K	2.00K	2.20K	4.70K	10.00K	15.00K	20.00K	22.00K	47.00K	100.00K
0.005	509.49	999.00	1998.00	2197.80	4695.30	9990.00	14985.00	19980.00	21978.00	46953.00	99900.00
0.010	254.49	499.00	998.00	1097.80	2345.30	4990.00	7485.00	9980.00	10978.00	23453.00	49900.00
0.015	169.49	332.33	664.67	731.13	1561.97	3323.33	4985.00	6646.67	7311.33	15619.67	33233.33
0.020	126.99	249.00	498.00	547.80	1170.30	2490.00	3735.00	4980.00	5478.00	11703.00	24900.00
0.025	101.49	199.00	398.00	437.80	935.30	1990.00	2985.00	3980.00	4378.00	9353.00	19900.00
0.030	84.49	165.67	331.33	364.47	778.63	1656.67	2485.00	3313.33	3644.67	7786.33	16566.67
0.035	72.35	141.86	283.71	312.09	666.73	1418.57	2127.86	2837.14	3120.86	6667.29	14185.71
0.040	63.24	124.00	248.00	272.80	582.80	1240.00	1860.00	2480.00	2728.00	5828.00	12400.00
0.045	56.16	110.11	220.22	242.24	517.52	1101.11	1651.67	2202.22	2422.44	5175.22	11011.11
0.050	50.49	99.00	198.00	217.80	465.30	990.00	1485.00	1980.00	2178.00	4653.00	9900.00
0.055	45.85	89.91	179.82	197.80	422.57	899.09	1348.64	1798.18	1978.00	4225.73	8990.91
0.060	41.99	82.33	164.67	181.13	386.97	823.33	1235.00	1646.67	1811.33	3869.67	8233.33
0.065	38.72	75.92	151.85	167.03	356.84	759.23	1138.85	1518.46	1670.31	3568.38	7592.31
0.070	35.92	70.43	140.86	154.94	331.01	704.29	1056.43	1408.57	1549.43	3310.14	7042.86
0.075	33.49	65.67	131.33	144.47	308.63	656.67	985.00	1313.33	1444.67	3086.33	6566.67
0.080	31.37	61.50	123.00	135.30	289.05	615.00	922.50	1230.00	1353.00	2890.50	6150.00
0.085	29.49	57.82	115.65	127.21	271.77	578.24	867.35	1156.47	1272.12	2717.71	5782.35
0.090	27.82	54.56	109.11	120.02	256.41	545.56	818.33	1091.11	1200.22	2564.11	5455.56
0.095	26.33	51.63	103.26	113.59	242.67	516.32	774.47	1032.63	1135.89	2426.68	5163.16
0.100	24.99	49.00	98.00	107.80	230.30	490.00	735.00	980.00	1078.00	2303.00	4900.00
0.125	19.89	39.00	78.00	85.80	183.30	390.00	585.00	780.00	858.00	1833.00	3900.00
0.150	16.49	32.33	64.67	71.13	151.97	323.33	485.00	646.67	711.33	1519.67	3233.33
0.175	14.06	27.57	55.14	60.66	129.59	275.71	413.57	551.43	606.57	1295.86	2757.14
0.200	12.24	24.00	48.00	52.80	112.80	240.00	360.00	480.00	528.00	1128.00	2400.00
0.225	10.82	21.22	42.44	46.69	99.74	212.22	318.33	424.44	466.89	997.44	2122.22
0.250	9.69	19.00	38.00	41.80	89.30	190.00	285.00	380.00	418.00	893.00	1900.00
0.275	8.76	17.18	34.36	37.80	80.75	171.82	257.73	343.64	378.00	807.55	1718.18
0.300	7.99	15.67	31.33	34.47	73.63	156.67	235.00	313.33	344.67	736.33	1566.67
0.325	7.34	14.38	28.77	31.65	67.61	143.85	215.77	287.69	316.46	676.08	1438.46

敏感体电阻—负载电阻——负载输出电压对照表

负载输出 电压/V	负载电阻 R_L (测试回路电压 $V_c:5V$)										
	0.51K	1.00K	2.00K	2.20K	4.70K	10.00K	15.00K	20.00K	22.00K	47.00K	100.00K
0.350	6.78	13.29	26.57	29.23	62.44	132.86	199.29	265.71	292.29	624.43	1328.57
0.375	6.29	12.33	24.67	27.13	57.97	123.33	185.00	246.67	271.33	579.67	1233.33
0.400	5.87	11.50	23.00	25.30	54.05	115.00	172.50	230.00	253.00	540.50	1150.00
0.425	5.49	10.76	21.53	23.68	50.59	107.65	161.47	215.29	236.82	505.94	1076.47
0.450	5.16	10.11	20.22	22.24	47.52	101.11	151.67	202.22	222.44	475.22	1011.11
0.475	4.86	9.53	19.05	20.96	44.77	95.26	142.89	190.53	209.58	447.74	952.63
0.500	4.59	9.00	18.00	19.80	42.30	90.00	135.00	180.00	198.00	423.00	900.00
0.550	4.13	8.09	16.18	17.80	38.03	80.91	121.36	161.82	178.00	380.27	809.09
0.600	3.74	7.33	14.67	16.13	34.47	73.33	110.00	146.67	161.33	344.67	733.33
0.650	3.41	6.69	13.38	14.72	31.45	66.92	100.38	133.85	147.23	314.54	669.23
0.700	3.13	6.14	12.29	13.51	28.87	61.43	92.14	122.86	135.14	288.71	614.29
0.750	2.89	5.67	11.33	12.47	26.63	56.67	85.00	113.33	124.67	266.33	566.67
0.800	2.68	5.25	10.50	11.55	24.68	52.50	78.75	105.00	115.50	246.75	525.00
0.850	2.49	4.88	9.76	10.74	22.95	48.82	73.24	97.65	107.41	229.47	488.24
0.900	2.32	4.56	9.11	10.02	21.41	45.56	68.33	91.11	100.22	214.11	455.56
0.950	2.17	4.26	8.53	9.38	20.04	42.63	63.95	85.26	93.79	200.37	426.32
1.000	2.04	4.00	8.00	8.80	18.80	40.00	60.00	80.00	88.00	188.00	400.00
1.100	1.81	3.55	7.09	7.80	16.66	35.45	53.18	70.91	78.00	166.64	354.55
1.200	1.62	3.17	6.33	6.97	14.88	31.67	47.50	63.33	69.67	148.83	316.67
1.300	1.45	2.85	5.69	6.26	13.38	28.46	42.69	56.92	62.62	133.77	284.62
1.400	1.31	2.57	5.14	5.66	12.09	25.71	38.57	51.43	56.57	120.86	257.14
1.500	1.19	2.33	4.67	5.13	10.97	23.33	35.00	46.67	51.33	109.67	233.33
1.600	1.08	2.13	4.25	4.68	9.99	21.25	31.88	42.50	46.75	99.88	212.50
1.700	0.99	1.94	3.88	4.27	9.12	19.41	29.12	38.82	42.71	91.24	194.12
1.800	0.91	1.78	3.56	3.91	8.36	17.78	26.67	35.56	39.11	83.56	177.78
1.900	0.83	1.63	3.26	3.59	7.67	16.32	24.47	32.63	35.89	76.68	163.16
2.000	0.77	1.50	3.00	3.30	7.05	15.00	22.50	30.00	33.00	70.50	150.00
2.100	0.70	1.38	2.76	3.04	6.49	13.81	20.71	27.62	30.38	64.90	138.10
2.200	0.65	1.27	2.55	2.80	5.98	12.73	19.09	25.45	28.00	59.82	127.27

敏感体电阻—负载电阻——负载输出电压对照表

负载输出 电压/V	负载电阻 R_L (测试回路电压 $V_c:5V$)										
	0.51K	1.00K	2.00K	2.20K	4.70K	10.00K	15.00K	20.00K	22.00K	47.00K	100.00K
2.300	0.60	1.17	2.35	2.58	5.52	11.74	17.61	23.48	25.83	55.17	117.39
2.400	0.55	1.08	2.17	2.38	5.09	10.83	16.25	21.67	23.83	50.92	108.33
2.500	0.51	1.00	2.00	2.20	4.70	10.00	15.00	20.00	22.00	47.00	100.00
2.600	0.47	0.92	1.85	2.03	4.34	9.23	13.85	18.46	20.31	43.38	92.31
2.700	0.43	0.85	1.70	1.87	4.00	8.52	12.78	17.04	18.74	40.04	85.19
2.800	0.40	0.79	1.57	1.73	3.69	7.86	11.79	15.71	17.29	36.93	78.57
2.900	0.37	0.72	1.45	1.59	3.40	7.24	10.86	14.48	15.93	34.03	72.41
3.000	0.34	0.67	1.33	1.47	3.13	6.67	10.00	13.33	14.67	31.33	66.67
3.100	0.31	0.61	1.23	1.35	2.88	6.13	9.19	12.26	13.48	28.81	61.29
3.200	0.29	0.56	1.13	1.24	2.64	5.63	8.44	11.25	12.38	26.44	56.25
3.300	0.26	0.52	1.03	1.13	2.42	5.15	7.73	10.30	11.33	24.21	51.52
3.400	0.24	0.47	0.94	1.04	2.21	4.71	7.06	9.41	10.35	22.12	47.06
3.500	0.22	0.43	0.86	0.94	2.01	4.29	6.43	8.57	9.43	20.14	42.86
3.600	0.20	0.39	0.78	0.86	1.83	3.89	5.83	7.78	8.56	18.28	38.89
3.700	0.18	0.35	0.70	0.77	1.65	3.51	5.27	7.03	7.73	16.51	35.14
3.800	0.16	0.32	0.63	0.69	1.48	3.16	4.74	6.32	6.95	14.84	31.58
3.900	0.14	0.28	0.56	0.62	1.33	2.82	4.23	5.64	6.21	13.26	28.21
4.000	0.13	0.25	0.50	0.55	1.18	2.50	3.75	5.00	5.50	11.75	25.00
4.100	0.11	0.22	0.44	0.48	1.03	2.20	3.29	4.39	4.83	10.32	21.95
4.200	0.10	0.19	0.38	0.42	0.90	1.90	2.86	3.81	4.19	8.95	19.05
4.300	0.08	0.16	0.33	0.36	0.77	1.63	2.44	3.26	3.58	7.65	16.28
4.400	0.07	0.14	0.27	0.30	0.64	1.36	2.05	2.73	3.00	6.41	13.64
4.500	0.06	0.11	0.22	0.24	0.52	1.11	1.67	2.22	2.44	5.22	11.11
4.600	0.04	0.09	0.17	0.19	0.41	0.87	1.30	1.74	1.91	4.09	8.70
4.700	0.03	0.06	0.13	0.14	0.30	0.64	0.96	1.28	1.40	3.00	6.38
4.800	0.02	0.04	0.08	0.09	0.20	0.42	0.63	0.83	0.92	1.96	4.17
4.900	0.01	0.02	0.04	0.04	0.10	0.20	0.31	0.41	0.45	0.96	2.04
5.000	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00