



Cambridge International AS & A Level

CANDIDATE
NAME

Zak, Askz & Teaching Assistant.

CENTRE
NUMBER

--	--	--	--	--

CANDIDATE
NUMBER

--	--	--	--

COMPUTER SCIENCE

9618/33

Paper 3 Advanced Theory

October/November 2024

1 hour 30 minutes

CSwithzak.com

You must answer on the question paper.

No additional materials are needed.

INSTRUCTIONS

- Answer **all** questions.
- Use a black or dark blue pen.
- Write your name, centre number and candidate number in the boxes at the top of the page.
- Write your answer to each question in the space provided.
- Do **not** use an erasable pen or correction fluid.
- Do **not** write on any bar codes.
- You may use an HB pencil for any diagrams, graphs or rough working.
- Calculators must **not** be used in this paper.

INFORMATION

- The total mark for this paper is 75.
- The number of marks for each question or part question is shown in brackets [].
- No marks will be awarded for using brand names of software packages or hardware.

This document has **16** pages. Any blank pages are indicated.



1 Numbers are stored in a computer using binary floating-point representation with:

- 10 bits for the mantissa
- 6 bits for the exponent
- two's complement form for both the mantissa and the exponent.

(a) Calculate the normalised binary floating-point representation of +201.125 in this system.

Show your working.

Mantissa

Exponent

0	1	1	0	0	1	0	0	1	0
---	---	---	---	---	---	---	---	---	---

0	0	1	0	0	0
---	---	---	---	---	---

Working $+201.125$

$\leftarrow 11001001.001$

0.11001001001×2^8

$01100100100 + 01000$

$0110010010 001000$

[3]

(b) Calculate the denary value of the given normalised binary floating-point number.

Show your working.

Mantissa

Exponent

1	0	1	0	1	1	0	0	1	1
---	---	---	---	---	---	---	---	---	---

$+ve$ $4 + 1 = +5$

0	0	0	1	0	1
---	---	---	---	---	---

 $+5$

Working 0101001101

$0.101001101 000101$

0.101001101×2^5

10100.1101

$16 + 4 = 20.8125$

Answer

[3]



2 Reduced Instruction Set Computers (RISC) is a type of processor.

Identify **four** features of a RISC processor.

- 1 *Small set of instruction*
 - 2 *Instruction is executed in a single clock cycle.*
 - 3 *Fixed length.*
 - 4 *Large number of general-purpose registers.*
- [4]

3 (a) Describe circuit switching as a method of data transmission.

- Dedicated Comms circuit.*
 - Circuit remains active*
 - Bidirectional Comms.*
- [3]

(b) State **one** benefit and **one** drawback of circuit switching as a method of data transmission.

- Benefit *In-order delivery.*
- Drawback *Inefficient use of bandwidth.*
- [2]





- 4 The TCP/IP protocol may be viewed as a stack that contains four layers: Application, Transport, Internet, Link.

Describe how the layers of the TCP/IP protocol stack interact with each other.

- Each layer communicates only with its adjacent layer.
 - Defined interface b/w each pair layers.
 - As data moves down the stack (sender side), each layer adds header. (encapsulation)
 - As data moves up the stack (receiver side), each layer removes its own header and passes data above. (decapsulation)
 - User interaction occurs at the application layer.
 - Hardware interaction occurs at the link layer.
- [4]

- 5 (a) Explain what is meant by a hashing algorithm in the context of file access.

- It is a mathematical function
- It takes key field and computes it to a storage
- Result tells where to save the data.

[3]

- (b) The use of a hashing algorithm can result in the same storage location being identified for more than one record.

Outline **two** methods of overcoming this issue.

- 1 Linear probing: Save at the next available location.
- 2 Overflow area: Go out and save in an open area.

[2]





6 (a) Describe the user-defined data type **set**.

- Composite data type.
- Same type elements.
- Values should be unique.
- Based on set theory, like union etc.

[3]

(b) Write **pseudocode** statements to declare the set data type, `SymbolSet`, to hold the following set of mathematical operators, using the variable `Operators`.

+ - * / ^

TYPE `SymbolSet` = SET OF CHAR

DEFINE `Operators` : `SymbolSet`

`Operators` ← ('+', '-', '*', '/', '^')

[4]





7 The truth table for a logic circuit is shown.

INPUT				OUTPUT
A	B	C	D	T
0	0	0	0	0
0	0	0	1	1
0	0	1	0	0
0	0	1	1	1
0	1	0	0	0
0	1	0	1	0
0	1	1	0	0
0	1	1	1	0
1	0	0	0	0
1	0	0	1	1
1	0	1	0	0
1	0	1	1	1
1	1	0	0	0
1	1	0	1	1
1	1	1	0	0
1	1	1	1	1

- (a) Write the Boolean logic expression that corresponds to the given truth table as the sum-of-products.

$$T = \overline{A}\overline{B}\overline{C}D + \overline{A}\overline{B}CD + \overline{A}B\overline{C}D + \overline{A}BCD + AB\overline{C}D + ABCD$$

[3]



(b) Complete the Karnaugh map (K-map) for the given truth table.

		AB			
		00	01	11	10
CD	00				
	01	—		—	—
	11	—		—	—
	10				

[2]

(c) Draw loop(s) around appropriate group(s) in the K-map to produce an optimal sum-of-products. [2]

(d) (i) Write the Boolean logic expression from your answer to part (c) as the simplified sum-of-products.

T = $AD + \bar{B}D$ [2]

(ii) Use Boolean algebra to write your answer to part (d)(i) in its simplest form.

T = $D \cdot (A + \bar{B})$ [1]





8 (a) Describe the process of segmentation for memory management.

- variable sized logical blocks of code
 - Each segment might be a function, procedure, array, or data structure (class/object)
 - Each segment has base address and length
 - Programs can access memory using segment number & offset
 - It enables protection and sharing of memory b/w processes
 - It makes it easier to manage growing data structures since segments can vary in size.
- [4]

(b) Explain what is meant by **disk thrashing**.

- Spend more time swapping data b/w RAM & VM and less time executing actual instructions.
 - Happens when low on RAM (insufficient RAM)
 - Constant paging in and out of memory causes high disk activity and reduces system's performance. System becomes unresponsive.
- [3]



- 9 A veterinary surgery wants to create a class for individual pets. Some of the attributes required in the class are listed in the table.

Attribute	Data type	Description
PetID	STRING	unique ID assigned at registration
PetType	STRING	type of pet assigned at registration
OwnerTelephone	STRING	telephone number of owner assigned at registration
DateRegistered	DATE	date of registration

- (a) State **one** reason why the attributes would be declared as `PRIVATE`.

To enforce encapsulation, which means data is protected.

[1]

- (b) Complete the class diagram for `Pet`, to include:

- an attribute and data type for the name of the pet
- an attribute and data type for the name of the owner
- a method to create a `Pet` object and set attributes at the time of registration
- a method to assign a pet ID
- a method to assign the date of registration
- a method to return the pet name
- a method to return the owner's telephone number.



Pet	
PetID	: STRING
PetType	: STRING
OwnerTelephone	: STRING
DateRegistered	: DATE
<i>PetName</i>	<i>: STRING</i>
<i>OwnerName</i>	<i>: STRING</i>
<i>PUBLIC PROCEDURE SetPetID (APetID : STRING)</i>	
<i>PUBLIC PROCEDURE SetDateRegistered (RegDate : DATE)</i>	
<i>PUBLIC FUNCTION GetPetName ()</i>	
<i>PUBLIC FUNCTION GetOwnerTelephone ()</i>	
<i>Constructor ()</i>	

[5]









10 Several syntax diagrams are shown.



$\langle \text{operator} \rangle ::= + \mid - \mid * \mid /$



$\langle \text{Label} \rangle ::= \langle \text{letter} \rangle \langle \text{digit} \rangle \mid \langle \text{letter} \rangle \langle \text{digit} \rangle \langle \text{digit} \rangle$



$\langle \text{equation} \rangle ::= \langle \text{Label} \rangle = \langle \text{Label} \rangle \langle \text{operator} \rangle \langle \text{Label} \rangle$



- (a) Complete the Backus-Naur Form (BNF) for the given syntax diagrams.

<operator> ::=

.....

<label> ::=

.....


<equation> ::=

.....

[4]

- (b) A new syntax rule, **password**, is required. It must begin with a letter or a symbol, followed by a digit and end with one or two symbols.

- (i) Draw a syntax diagram for **password**.



[3]

- (ii) Write the BNF for **password**.

$\langle \text{password} \rangle ::= \langle x \rangle \langle \text{digit} \rangle \langle \text{symbol} \rangle \langle \text{symbol} \rangle \langle x \rangle \langle \text{digit} \rangle \langle \text{symbol} \rangle$


$\langle x \rangle ::= \langle \text{letter} \rangle / \langle \text{symbol} \rangle$

[2]






11 The following diagram shows an ordered binary tree.



- (a) A linked list of nodes is used to store the data. Each node consists of a left pointer, the data and a right pointer.

–1 is used to represent a null pointer.

Complete this linked list to represent the given binary tree.



- (b) A user-defined record structure is used to store the nodes of the linked list in part (a).

Complete the diagram, using your answer for part (a).

RootPtr	Index	LeftPtr	Data	RightPtr
0	0	1	Red	2
	1	3	Green	4
	2	6	Yellow	-1
	3	-1	Blue	-1
	4	5	Orange	-1
	5	-1	Indigo	-1
FreePtr	6	-1	Violet	-1
7	7			

[4]

- (c) The linked list in part (a) is implemented using a 1D array of records. Each record contains a left pointer, data and a right pointer.

The following pseudocode represents a function that searches for an element in the array of records `BinTree`. It returns the index of the record if the element is found, or it returns a null pointer if the element is **not** found.

Complete the pseudocode for the function.

```

FUNCTION SearchTree(Item : STRING) ..... RETURNS INTEGER .....
    NowPtr ← RootPtr
    WHILE NowPtr <> -1
        IF BinTree[NowPtr].Data > Item ..... THEN
            NowPtr ← BinTree[NowPtr].LeftPtr
        ELSE
            IF BinTree[NowPtr].Data < Item THEN
                NowPtr ← BinTree[NowPtr].RightPtr
            ELSE
                RETURN NowPtr
            ENDIF
        ENDIF
    ENDWHILE
    RETURN NowPtr
ENDFUNCTION
  
```

[4]





BLANK PAGE

BYE!!!
Happy Prep!!!



DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN





DO NOT WRITE IN THIS MARGIN





BLANK PAGE

DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN

DO NOT WRITE IN THIS MARGIN

Permission to reproduce items where third-party owned material protected by copyright is included has been sought and cleared where possible. Every reasonable effort has been made by the publisher (UCLES) to trace copyright holders, but if any items requiring clearance have unwittingly been included, the publisher will be pleased to make amends at the earliest possible opportunity.

To avoid the issue of disclosure of answer-related information to candidates, all copyright acknowledgements are reproduced online in the Cambridge Assessment International Education Copyright Acknowledgements Booklet. This is produced for each series of examinations and is freely available to download at www.cambridgeinternational.org after the live examination series.

Cambridge Assessment International Education is part of Cambridge Assessment. Cambridge Assessment is the brand name of the University of Cambridge Local Examinations Syndicate (UCLES), which is a department of the University of Cambridge.

