

MovementLogger — Sensor & Module Catalog

7 Teile · 2026-05-20 08:56 UTC · BOM aus movement_logger_firmware · via crawl2pump

7 neu (7 Tage)

0 aktualisiert

Dev Boards 4

STEVAL-MKBOXPRO (SensorTile.box PRO Rev_C)

OSS firmware

USB-C pluggable

☒ USB-C

☐ WiFi

☒ Bluetooth

☐ GPS

☒ Motion sensors


☒ SD-card

L×B×H 6.3 × 4 × 2 cm

MCU: STM32U585 · Cortex-M33 @160 MHz · 2 MB flash / 786 KB SRAM · TrustZone · ultra-low-power

Datasheet: https://www.st.com/resource/en/user_manual/um3133-sensortilebox-pro-stmicroelectronics.pdf

OSS firmware: https://github.com/zdavatz/movement_logger_firmware



neu STEVAL-MKBOXPRO (SensorTile.box PRO Rev_C) · STEVAL-MKBOXPRO @ DigiKey

STMicroelectronics @ DigiKey · in stock

Primary target board. USB-C for charge + STM32 DFU flashing. · USB-C · firmware: open-source

<https://www.digikey.com/en/products/detail/stmicroelectronics/STEVAL-MKBOXPRO/19721662>

CHF 94.56

GPS / GNSS 11

ARM Cortex JTAG/SWD 14-pin Cable (1.27 mm → 0.1" DuPont, ~100 mm)

OSS firmware

SMA / U.FL

☐ USB-C

☐ WiFi


☐ Bluetooth

☐ GPS

☐ Motion sensors

☐ SD-card

L×B×H 10 × 0.5 × 0.2 cm



neu ARM Cortex JTAG/SWD 14-pin Cable (1.27 mm → 0.1" DuPont, ~100 mm) · Generic (Amazon / AliExpress OEMs) @ Generic (Amazon / AliExpress OEMs) (vendor page (reference))

Generic (Amazon / AliExpress OEMs) (manufacturer store)

Solderless JP2 plug. One end: 14-pin 1.27 mm shrouded female socket (mates with the STEVAL's FTSH-107 programming header — keyed, only goes on one way). Other end: 14 loose female DuPont leads labelled by SWD/JTAG net name. Pick the four...

<https://www.amazon.de/s?k=JTAG+SWD+14+pin+1.27mm+cable+female+dupont>

GPS/GNSS Magnetic Mount Antenna 3 m (active, SMA)

OSS firmware

SMA / U.FL

☐ USB-C

☐ WiFi

☐ Bluetooth

☐ GPS

☐ Motion sensors

☐ SD-card

L×B×H 4 × 4 × 1.3 cm

Datasheet: <https://www.sparkfun.com/products/14986>



neu GPS/GNSS Magnetic Mount Antenna 3 m (active, SMA) · GPS-14986 @ DigiKey

SparkFun @ DigiKey · out of stock

Active GPS antenna (~28 dB LNA, 3 m RG-174 coax, SMA male). Magnetic base — sits on the board's non-metal top or the case lid for best sky view. Needs a U.FL → SMA pigtail to mate with the MAX-M10S breakout's U.FL connector — see next...

<https://www.digikey.com/en/products/detail/sparkfun-electronics/14986/9682235>

CHF 12.85

Interface Cable SMA → U.FL, 100 mm (pigtail)

OSS firmware

SMA / U.FL

☐ USB-C

☐ WiFi

☐ Bluetooth

☐ GPS

☐ Motion sensors

☐ SD-card

L×B×H 10 × 0.3 × 0.3 cm

Datasheet: <https://www.sparkfun.com/products/9145>



neu Interface Cable SMA → U.FL, 100 mm (pigtail) · SparkFun 9145 @ sparkfun.com

SparkFun

100 mm pigtail: U.FL female (plugs into the SparkFun MAX-M10S breakout) ↔ SMA female bulkhead (mates with the antenna above's SMA male). Buy with the magnetic antenna or skip both if the onboard chip antenna is enough. · SMA / U.FL · ...

<https://www.sparkfun.com/products/9145>

USD 5.75

SparkFun GPS Breakout - MAX-M10S (Qwiic)

OSS firmware

Qwiic / I²C

☐ USB-C

☐ WiFi

☐ Bluetooth

☒ GPS

☐ Motion sensors

☐ SD-card

L×B×H 2.54 × 2.54 × 0.6 cm

Datasheet: https://cdn.sparkfun.com/assets/7/5/9/a/a/MAX-M10S_DataSheet_UBX-20035208.pdf

OSS firmware: https://github.com/zdavatz/movement_logger_firmware



neu SparkFun GPS Breakout - MAX-M10S (Qwiic) · GPS-18037 @ DigiKey

SparkFun @ DigiKey · in stock

Recommended MAX-M10S carrier. Open-hardware breakout. · Qwiic / I²C · firmware: open-source

<https://www.digikey.com/en/products/detail/sparkfun-electronics/18037/16719314>

CHF 35.80

u-blox MAX-M10S GNSS module

OSS firmware

UART pins

☐ USB-C

☐ WiFi

☐ Bluetooth

☒ GPS

☐ Motion sensors

☐ SD-card

L×B×H 1.01 × 0.97 × 0.25 cm

Datasheet: https://content.u-blox.com/sites/default/files/MAX-M10S_DataSheet_UBX-20035208.pdf

OSS firmware: https://github.com/zdavatz/movement_logger_firmware



neu u-blox MAX-M10S GNSS module · MAX-M10S-00B @ DigiKey

u-blox @ DigiKey · in stock

Wired to UART4 @ 38400. The firmware's GPS source. · UART pins · firmware: open-source

<https://www.digikey.com/en/products/detail/u-blox/MAX-M10S-00B/15712906>

CHF 10.38

Enclosure 4

Hammond 1554G2GYCL — IP66 PC enclosure, clear lid (120×90×60 mm)

OSS firmware

enclosure

☐ USB-C

☐ WiFi

☐ Bluetooth

☐ GPS

☐ Motion sensors

☐ SD-card

L×B×H 12 × 9 × 6 cm

Datasheet: <https://www.hammfg.com/electronics/small-case/plastic/1554.pdf>



neu Hammond 1554G2GYCL — IP66 PC enclosure, clear lid (120×90×60 mm) · 1554G2GYCL @ DigiKey

Hammond Manufacturing @ DigiKey · in stock

Polycarbonate IP66 project box, external 120 × 90 × 60 mm, clear PC lid. Lid sealed with O-ring gasket and four corner screws. RF-transparent so onboard GPS (and any radar) reads through the wall. The Hall sensor reads a passing magnet...

<https://www.digikey.com/en/products/detail/hammond-manufacturing/1554G2GYCL/2359944>

CHF 22.77

Soldering the u-blox MAX-M10S GPS to the STEVAL-MKBOXPRO

The MovementLogger firmware reads GPS over **UART4** on MCU pins **PA0 (TX)** / **PA1 (RX)** at **38400 baud, 8N1, 3.3 V logic**. The MAX-M10S is **not** on the box — it must be wired by hand to **JP2**, the 14-pin programming connector (Samtec FTS-107-01-L-D, 1.27 mm pitch). Full source: [GPS_SOLDERING.md](#).

Tools you need

- Fine-conical-tip iron, flux, magnification (10× loupe or microscope), tweezers, steady bench.
- **30 AWG** enamelled / wire-wrap wire (≤ 0.5 mm), four lengths.
- Multimeter (continuity + DC volts).
- Kapton tape + a dab of hot glue for strain relief.

JP2 pinout — pin 1 = square pad / silk triangle

Pin	Net	Use?
1	1V8 rail (JTAG ref)	NOT power — 1.8 V, weak
4 / 6 / 8 / 10 / 12	SWDIO / SWCLK / SWO / JTDI / NRST	Leave alone (debug bus)
7	GND	OK for GPS GND
11	GND	OK for GPS GND
13	UART4_RX (PA1)	GPS TX → here
14	UART4_TX (PA0)	GPS RX → here

Pins 3, 5, 9 carry no signal — leave unconnected. **Meter-verify** pin 1 against the silkscreen triangle and continuity-check every pin before soldering — connector orientation differs between board builds.

Wiring — note the TX/RX crossover

GPS pin	→	JP2 pin	Net (MCU)
TX (GPS out)	→	13	UART4_RX (PA1)
RX (GPS in)	→	14	UART4_TX (PA0)
GND	→	7 or 11 (meter-verified)	GND
VCC 3.3 V	→	JP4 3 V pin (not JP2!)	Board 3 V rail

GPS power — 3.3 V from JP4

- JP4 is the 7-pin extension-board connector (Multicomp MC-SVT1-S07-G). Set its domain switch to **3 V** (not 1.8 V).
- Power the box and **meter the JP4 3 V pin** — must read **3.25–3.40 V** before connecting GPS VCC. Power down again before soldering VCC.
- GPS GND and box GND must be common — take GND from JP4 or a JP2 GND pin.
- No graceful shutdown: the Hall-sensor magnet cuts the whole supply rail at once (firmware F-PWR-5). The on-SD format tolerates it.

Safety — read before the iron is hot

- **3.3 V logic only**. PA0/PA1 are **not 5 V tolerant**. A 5 V GPS breakout's TX into PA1 will destroy the MCU — level-shift or use a 3.3 V-native MAX-M10S carrier (e.g. the SparkFun breakout above).
- **Never bridge to the SWD pins** (4/6/8/10/12) — solder bridge → bricked debug access.
- Keep each pad heated < 2 s. FTS-107 pads lift if cooked.
- **Strain-relieve all four wires** with Kapton + hot glue close to JP2 — a tugged wire rips the pad off the PCB.

Procedure

1. **Power down completely** — switch S1 off, USB unplugged, LiPo disconnected.
2. **Locate JP2** (14-pin fine-pitch header by the MCU). Identify pin 1.
3. **Continuity-check before soldering** (meter, board off): JP2 pin 13 ↔ MCU PA1, JP2 pin 14 ↔ MCU PA0, candidate GND pin ↔ battery (–). Confirm, don't assume.
4. **Pre-tin** the three JP2 pads and the wire ends with flux.
5. **Solder the data wires**: pin 13 ← GPS TX, pin 14 ← GPS RX. Then **GND**.
6. **GPS VCC last**: with the board powered, confirm 3.3 V at the JP4 3 V pin, power down again, solder the VCC wire.
7. **Inspect under magnification** for bridges — especially pin 14 to pin 12 and onto the SWD pins.
8. **Strain-relieve** all four wires (Kapton + hot glue).

Bring-up test

1. Insert the SD card, take the box **outdoors with clear sky**, power on.
2. The firmware sends the u-blox UBX config on boot, then expects 10 Hz NMEA. First fix is typically reached within **~30–60 s cold**.
3. Confirm a fix by **any** of: a growing GpsNNN.csv on the SD card · the BLE SensorStream gps_valid flag going set · (antenna-test build, make GPS_ANTENNA_BEEP=1) the buzzer beeping N times every 10 s with N = satellites.

No fix after several minutes outdoors? — in order of likelihood

1. **Swap the two data wires** (pin 13 ↔ pin 14). TX/RX reversed is the single most common wiring mistake and swapping is harmless to try.
2. Re-check **GND** continuity (cold/again) and that GPS VCC really is 3.3 V *at the module* under load.
3. Confirm the module is a 3.3 V part and actually powered (most MAX-M10S carriers have a power LED).
4. Give it a longer cold-start with an unobstructed sky view; indoors it will never fix.