

Display Digit	b8	b4	b2	b1	sq.	A	B	C	D	E	F	G	W
0	0	0	0	0	0	1	1	1	1	1	1	0	1
1	0	0	0	1	1	0	1	1	0	0	0	0	1
2	0	0	1	0	2	1	1	0	1	1	0	1	1
3	0	0	1	1	3	1	1	1	1	0	0	1	1
4	0	1	0	0	4	0	1	1	0	0	1	1	1
5	0	1	0	1	5	1	0	1	1	0	1	1	0
6	0	1	1	0	6	1	0	1	1	1	1	1	0
7	0	1	1	1	7	1	1	1	0	0	0	0	0
8	1	0	0	0	8	1	1	1	1	1	1	1	0
9	1	0	0	1	9	1	1	1	1	0	1	1	0
A	1	0	1	0	10	1	1	1	0	1	1	1	0
B	1	0	1	1	11	0	0	1	1	1	1	1	0
C	1	1	0	0	12	1	0	0	1	1	1	0	0
D	1	1	0	1	13	0	1	1	1	1	0	1	1
E	1	1	1	0	14	1	0	0	1	1	1	1	1
F	1	1	1	1	15	1	0	0	0	1	1	1	1

SEGMENT - A

CD AB	00	01	11	10
	1 0	0 1	1 3	1 2
	0 4	1 5	1 7	1 6
	1 12	0 13	1 15	1 14
10	1 8	1 9	0 11	1 10

$$A'BD + A'C + AB'C' + AD' + B'D' + BC$$

SEGMENT - B

CD \ AB	00	01	11	10
10	1 0	1 1	1 3	1 2
01	1 4	0 5	1 7	0 6
11	0 12	1 13	0 15	0 14
10	1 8	1 9	0 11	1 10

$$A'C'D' + A'CD + AC'D + B'C' + B'D'$$

SEGMENT - C

CD \ AB	00	01	11	10
10	1 0	1 1	1 3	0 2
11	1 4	1 5	1 7	1 6
11	0 12	1 13	0 15	0 14
01	1 8	1 9	1 11	1 10

$$A'B + AB' + C'D + A'C' + A'D$$

SEGMENT - D

CD \ AB	00	01	11	10
10	1 0	0 1	1 3	1 2
11	0 4	1 5	0 7	1 6
11	1 12	1 13	0 15	1 14
10	1 8	1 9	1 11	0 10

$$A'CD' + AC' + B'C'D' + B'CD + BC'D + BCD'$$

SEGMENT - E

CD \ AB	00	01	11	10
10	1 0	0 1	0 3	1 2
01	0 4	0 5	0 7	1 6
11	1 12	1 13	1 15	1 14
10	1 8	0 9	1 11	1 10

$$AB + AC + B'D' + CD'$$

SEGMENT - F

CD \ AB	00	01	11	10
10	1 0	0 1	0 3	0 2
01	1 4	1 5	0 7	1 6
11	1 12	0 13	1 15	1 14
10	1 8	1 9	1 11	1 10

$$A'BC' + AB' + AC + BD' + C'D'$$

SEGMENT - G

CD \ AB	00	01	11	10
10	0 0	0 1	1 3	1 2
01	1 4	1 5	0 7	1 6
11	0 12	1 13	1 15	1 14
10	1 8	1 9	1 11	1 10

$$A'BC' + AB' + AD + B'C + CD'$$

Warning LED:

CD AB	00	01	11	10
10	1 0	1 1	1 3	1 2
01	1 4	0 5	0 7	0 6
11	0 12	1 13	1 15	1 14
10	0 8	0 9	0 11	0 10

$$A'B' + A'C'D' + ABC + ABD$$