

MarioAI Benchmark. Level Generator. Usage examples.

Here are some examples how to use combination of various options.

Launch the benchmark as usual : `java ch.idsia.scenarios.Main [params]`.

Short form is used further in the text: `Main -lco off`.

1. A flat level:
`-lco off -lb off -le off -lhb off -lg off -ltb off -lhs off -lc off -lde off`.
2. A flat level with blocks:
`Main -lco off -lb on -le off -lhb off -lg off -ltb off -lhs off -lc off -lde off`.
3. A flat level with blocks and coins:
`Main -lco on -lb on -le off -lhb off -lg off -ltb off -lhs off -lc off -lde off`.
4. A flat level with blocks, creatures and coins:
`Main -lco on -lb on -le on -lhb off -lg off -ltb off -lhs off -lc off -lde off`.
5. A flat level with blocks, hidden blocks and coins:
`Main -lco on -lb on -le off -lhb on -lg off -ltb off -lhs off -lc off -lde off`.
6. A flat level with blocks, hidden blocks, coins and creatures:
`Main -lco on -lb on -le on -lhb on -lg off -ltb off -lhs off -lc off -lde off`.
7. A level with deadends and blocks:
`Main -lco off -lb on -le off -lhb off -lg off -ltb off -lhs off -lc off -lde on`.
8. A level with deadends, blocks and hidden blocks:
`Main -lco off -lb on -le off -lhb on -lg off -ltb off -lhs off -lc off -lde on`.
9. A level with deadends and hidden blocks:
`Main -lco off -lb off -le off -lhb on -lg off -ltb off -lhs off -lc off -lde on`.
10. A level with deadends, blocks, hidden blocks and creatures:
`Main -lco off -lb on -le on -lhb on -lg off -ltb off -lhs off -lc off -lde on`.
11. A flat level with tubes:
`Main -lco off -lb off -le off -lhb off -lg off -ltb on -lhs off -lc off -lde off`.
12. A flat level with gaps:
`Main -lco off -lb off -le off -lhb off -lg on -ltb off -lhs off -lc off -lde off`.
13. A flat level with tubes and gaps:
`Main -lco off -lb off -le off -lhb off -lg on -ltb on -lhs off -lc off -lde off`.
14. A flat level with cannons:
`Main -lco off -lb off -le off -lhb off -lg off -ltb off -lhs off -lc on -lde off`.
15. A flat level with tubes, gaps and cannons:
`Main -lco off -lb off -le off -lhb off -lg on -ltb on -lhs off -lc on -lde off`.