Handoff 03: 3D printing (Bambu X2D)

For: Claude Code in VS Code, in the `14MM47/3dprint` workflow, with Matt at the printer. **Only Matt starts prints.** He types CONFIRM or presses print; Claude never runs `x2d print`.

The print-ready files are `print/<part>.stl` and `print/<part>.3mf`. The geometry is already in print orientation, so don't let the slicer re-orient it. Settings, sizes and check results: `print/README.md` (generated). Every part builds PASS through the 3dprint-contract checks.

Order	Part	Material	Process	Notes
1	`coupon_fit`	PETG	0.20 mm	Bores for the gooseneck self-tap socket, the button caps, the skirt in the base bore, and the LED board pocket
2	`coupon_bayonet`	PETG	0.16 mm	Lugs enter, turn 30° and pull down onto a 1.0 mm disc, without forcing (VERIFY M4)
3	`coupon_litho_wedge`	**white PLA** (the moon's spool)	0.12 mm	0.6–3.0 mm steps. Backlight it with the LED board for VERIFY O1
4	`moon_base`	PETG	0.16 mm	Upright, no supports
5	`moon_ring`	PETG	0.20 mm	0.6 mm clamp ring (3 layers). Keeps the PLA moon off the warm LED board (round1 F5). **Do not print it in PLA**
6	`pack_front`	PETG	0.20 mm	Face down
7	`pack_back`	PETG	0.20 mm	Outer face down
8	`pack_clip`	PETG	0.20 mm	Flat, layers along the arm
9	`button_caps`	PETG	0.12 mm	One plate of 3 caps, flange down. Use a brim
10	`moon_shell`	**white PLA**	0.12 mm, 6 walls, 100 % infill	3 mm outer brim (only the skirt ring touches the bed). The inner dome closes as a short bridge at the top, which is expected
—	`jig_led_board`	PETG	0.20 mm	Assembly aid for the LED board's second side (handoff 05 §2). Print it before the boards arrive

Steps

1. Print the coupons first (rows 1–3). Record which fits work in `docs/verification/VERIFY.md` (M2–M4, O1). If they differ from the defaults in `cad/parts/_lib/moonlib.py` / `packlib.py`, change those constants and rebuild:

   ```
   python cad/tools/pipeline.py cad/parts/<part>.py --out out/<part>
   ```

   The build must PASS. Never relax a check. Then run `python cad/tools/export_print.py` to refresh `print/`.
2. Measure the delivered gooseneck thread and nut (VERIFY M1) and the battery (M7) **before** printing `moon_base` and `pack_back`.
3. Slicing: once the 3dprint pipeline's A-tasks exist, use `/slice` / `/make` on these modules. Until then, open the 3MF in the Bambu Studio GUI. Select the X2D with a 0.4 mm nozzle, pick the material and process above, apply the per-part overrides from `print/README.md`, slice, and check the preview. Treat slicer warnings like check failures: fix the part, never suppress the warning.

4. Print the moon last, after the step wedge has confirmed that the 0.9–2.6 mm range gives good contrast (VERIFY M11).

Done when

All parts are printed, the coupon results are recorded, and any constant changes are committed with PASS builds.