
Deep Groove Ball Bearings



Deep Groove Ball Bearings











Open type

Shielded type

Sealed type (non-contact)

Expansion compensating bearing

1. Design features and characteristics

Deep groove ball bearings are very widely used. A deep groove is formed on the inner and outer ring of the bearing enabling the bearing to sustain radial and axial loads in either direction as well as the complex loads which result from the combination of these forces. Deep groove ball bearings are suitable for high speed applications.

When two or more deep groove ball bearings are used in combination and mounted adjacent to each other a duplex set (D2) should be used. Duplex bearings (D2) utilize controlled tolerances to more evenly distribute the loading between the individual bearing rows which improves the overall performance of the assembly.

In addition to unsealed and unlubricated "open" bearings, **NTN** provides deep groove ball bearings that are pre-lubricated with grease and enclosed by seals or shields. See section "11. Lubrication" for a list of some of the greases which can be used.

Table 1 shows the construction and special characteristics of various sealed deep groove ball bearings.

Table 1 Sealed ball bearings: construction and characteristics

		Shielded type		Sealed type			
Т	ypes and codes	Non-contact type ZZ	Non-contact type LLB	Contact type LLU	Low torque type LLH		
	Construction	Metal shield plate is affixed to the outer ring; the inner ring incorporates a V-groove and labyrinth clearance.	• The outer ring incorporates synthetic rubber molded to a steel plate; seal edge is aligned with V-groove along inner ring surface with labyrinth clearance.	• The outer ring incorporates synthetic rubber molded to a steel plate; seal edge contacts V-groove along inner ring surface.	Basic construction is the same as LLU type, but a specially designed lip on the edge of the seal prevents foreign matter penetration; low torque construction.		
4)	Torque	Small	Small	Higher	Medium		
ance	Dust proofing	Good	Better than ZZ-type	Excellent	Much better than LLB-type		
Performance comparison	Water proofing	Poor	Poor	Very good	Good		
Perf	High speed capacity	Same as open type	Same as open type	Limited by contact seals	Much better than LLU-type		
_	Allowable temp. range ¹⁾	Depends on lubricant	−20 to 120 °C	−20 to 110 °C	-20 to 120 °C		

¹⁾ Please consult **NTN** Engineering about applications which exceed the allowable temperature range of products listed on this table. Note: This chart lists double shielded and double sealed bearings, but single shielded (Z) and single sealed (LB, LU, LH) are also available. Grease lubrication should be used with single shielded and single sealed bearings.

2. Standard cage type

As shown in **Table 2**, pressed cages are generally used for most deep groove ball bearings. Larger size deep groove ball bearings, and bearings operating at high rotational speeds often utilize a machined cage.

Table 2 Standard cage types

	•	
Cage	Pressed cage	Machined cage
Bearing series		
67 68 69 160 60 62 63 64	6700 to 6706 6800 to 6834 6900 to 6934 16001 to 16052 6000 to 6052 6200 to 6224 6300 to 6344 6403 to 6416	

3. Other deep groove ball bearing enhancements

3.1 Bearings with snap rings

A snap ring grove or snap ring grove with snap ring combination are optional enhancements for the outside diameter of most deep groove ball bearings. Snap rings allow for simpler axial positioning and installation in the housing. Snap rings can be utilized with both open type and sealed or shielded deep groove ball bearings. Consult **NTN** Engineering.

3.2 Expansion compensating bearings (creep prevention bearings)

NTN

NTN offers the innovative Expansion Compensating (EC) feature to help with bearing retention when mounted in light alloy housings which is often a problem at elevated temperatures due to property differences between the bearing steel and the housing. This functionality is achieved by machining circumferential grooves into the outside diameter of an otherwise standard outer ring. These grooves are filled with an optimized polymer which has an expansion rate higher than that of the typical light alloy housing. The net result is a more consistent interference fit across a wide operating temperature range. This more consistent fit condition helps prevent the bearing from rotating within the housing (known as bearing creep) which helps ensure good performance and long life.

(1) Allowable load

As a result of having grooves machined in the outside diameter, the ring strength is lower compared with a standard bearing. Thus, in order to prevent outer ring fracture, it is necessary to limit the maximum load applied to the bearing to be equal to or less than the allowable load $C_{\rm p}$ (see dimension table).

(2) Fit with housing

Table 3 shows the recommended fits for bearings with light metal alloy housings. In cases where the bearing is going to be interference fit with the housing, it is very important not to damage the polymer material. Therefore, it is essential that the lip of the housing diameter be given a 10 to 15° chamfer as shown in Fig. 2.

Furthermore, as shown in **Fig. 2**, it is also advisable to apply the interference fit using a press in order not to force the bearing into the housing in a misaligned position.

Table 3 Recommended fits for outer ring and housing bore

Co	ondition		6 11 11	Housing
Load type,	etc.	Housing material	Suitable bearing	bore tolerance class
Rotating outer ring load Rotating inner ring load Indeterminate load	Light load Normal load	Light alloys such as Al alloy and Mg alloy	Deep groove ball bearings Cylindrical roller bearings	Н6
Rotating outer ring load Indeterminate load	Heavy load Impact load	Light alloys such as Al alloy and Mg alloy	Thick-walled type deep groove ball bearings	N6




Fig. 1 Expansion compensating bearings




Fig. 2 Fitting method and housing bore diameter chamfer

(3) Radial internal clearance

Radial internal clearance are the same as those for standard deep groove ball bearings. With standard fit and application conditions, a C3 clearance is used. For more detailed information concerning this bearing, and the also manufactured of roller bearings contact **NTN** Engineering.

(4) Allowable temperature range

-20 to 120 °C

3.3 AC bearings (creep prevention bearings)

NTN Offers the AC type bearing which performs a similar function to the EC bearing. AC bearings have the same outside diameter dimensions as standard bearings with the addition of two O-rings located in circumferential grooves on the outside diameter of the outer ring (see **Fig. 3**).

While the EC bearing is more beneficial when using a light alloy housing at elevated temperatures, AC bearings are suitable for applications where a "tight fit" is not possible but outer ring creeping exists under rotating load on the outer ring. AC bearing can also be installed as a floating side bearing to accommodate expansion of shaft by heat as it is more axial. Before installing the bearing into the housing, a high viscosity oil (base oil viscosity, 100 mm²/s or more) or grease must be applied to the space between two O-rings. This lubricant forms a thin oil layer on the bearing outer ring which prevents contact between the outer ring and housing, lowers the friction, and can minimize the occurrence of creeping by utilizing the friction force of the O-rings.




Fig. 3 AC bearing

B-18 B-19

B-21



(1) Allowable load

As is the case with the EC bearing, the load applied to an AC bearing shall be limited to $C_{\rm p}$ (see dimension table) in order to ensure the strength limit of the modified outer ring is not exceeded.

(2) Housing dimensions and shape

Fig. 4 shows the recommended shape of steel housings, and **Table 4** shows the dimensions.




Fig. 4 Design of housing

Table 4 Dimensions and design

G7
Max. 30°
0.006D or more
2.5
1/2 of housing bore tolerance


B-20


(3) Allowable temperature range


-20 to 120 °C


NTN












(LLH)




Contact sealed type (LLU)

d 10-20 mm

u	10	-20	, ,,,,,,,,														
Βοι	unda	ry d	limensi	ions	Basic loa	d rating	Fatigue	Factor		Allowab	le spee	d	Be	aring	g num	ber	
							load		6		n ⁻¹						
		mı	m		dynamic k		limit kN		Grease	Oil Open type			Open type		Shi	elded	
			11	$r_{ m Ns}$	N	1 4	KIN		ZZ. LLB. LLF	Z, LB, LF	LLH	LLU	Орен туре	0	r seale	ed type	2)
d	D	B	$r_{\rm s min}^{1)}$	Min.	$C_{\rm r}$	C_{0r}	$C_{\rm u}$	f_0	Z, LB, LF	, ,	LH	LU		(See d	rawing	gs)
	15	3		_	0.950	0.435	0.018	15.7	10 000	12.000			6700				
	19	5	0.1		2.03	0.433	0.018		32 000		_	24 000	6800	ZZ	LLB	_	LLU
	22	6	0.3	0.3	2.99	1.27			30 000			21 000	6900	ZZ	LLB	LLH	LLU
10	26	8	0.3	U.3	5.05	1.96			29 000			21 000	6000	ZZ	LLB	LLH	LLU
	30	9	0.5	0.5	5.65	2.39					21 000		6200	ZZ	LLB	LLH	LLU
	35	11	0.6	0.5	9.10	3.50					20 000		6300	ZZ	LLB	LLH	LLU
	55	11	0.0	0.5	5.10	3.30	0.275	11.7	25 000	27 000	20 000	10 000	0300		LLD	LLII	LLU
	18	4	0.2	_	1.03	0.530	0.021	16.2	8 300	9 500	_	_	6701	_	LLF	_	_
	21	5	0.3	_	2.12	1.04	0.080	15.3	29 000	35 000	_	20 000	6801	ZZ	LLB	_	LLU
	24	6	0.3	0.3	3.20	1.46	0.115	14.5	27 000	32 000	22 000	19 000	6901	ZZ	LLB	LLH	LLU
12	28	7	0.3	_	5.65	2.39	0.187	13.2	26 000	30 000	_	_	16001JRX	_	_	_	_
	28	8	0.3	_	5.65	2.39	0.182	13.2	26 000	30 000	21 000	18 000	6001JRX	ZZ	LLB	LLH	LLU
	32	10	0.6	0.5	6.75	2.75	0.214	12.7	22 000	26 000	20 000	16 000	6201	ZZ	LLB	LLH	LLU
	37	12	1	0.5	10.8	4.20	0.325	11.1	20 000	24 000	19 000	15 000	6301	ZZ	LLB	LLH	LLU
	21	4	0.2	_	1.04	0.585	0.024		6 600	7 600	_		6702	_	LLF	_	
	24	5	0.3	_	2.30	1.26	0.091			31 000	_	17 000	6802	ZZ	LLB	_	LLU
4 =	28 32	7 8	0.3	0.3	4.05	2.00		-	24 000			16 000	6902	ZZ	LLB	_	LLU
15	32	9	0.3	0.3	6.20 6.20	2.84			22 000 22 000		18 000	15 000	16002 6002	ZZ	LLB	LLH	LLU
	35	11	0.5	0.5	8.60	3.60					18 000		6202	ZZ	LLB	LLH	LLU
	42	13	1	0.5	12.7	5.45					15 000		6302	ZZ	LLB	LLH	LLU
	42	13		0.5	12.7	3.43	0.425	12.5	17 000	21 000	13 000	12 000	0302	22	LLD	LLII	LLU
	23	4	0.2	_	1.11	0.660	0.027	16.3	5 000	6 700	_	_	6703	_	LLF	_	_
	26	5	0.3	_	2.47	1.46	0.102		24 000		_	15 000	6803	ZZ	LLB	_	LLU
	30	7	0.3	0.3	5.15	2.58	0.202	14.7	22 000	26 000	_	14 000	6903JRX	ZZ	LLB	_	LLU
47	35	8	0.3	_	7.55	3.35	0.263	13.6	20 000	24 000	—	_	16003	_	_	_	_
17	35	10	0.3	0.3	7.55	3.35	0.243	13.6	20 000	24 000	16 000	14 000	6003	ZZ	LLB	LLH	LLU
	40	12	0.6	0.5	10.6	4.60	0.355	12.8	18 000	21 000	15 000	12 000	6203	ZZ	LLB	LLH	LLU
	47	14	1	0.5	15.0	6.55	0.510	12.2	16 000	19 000	14 000	11 000	6303	ZZ	LLB	LLH	LLU
	62	17	1.1	_	25.2	10.8	0.840	11.1	14 000	16 000	_	_	6403	ZZ	_	—	_
	27	4	0.0		4.45	0.720	0.004	161	F 000	F 700			6704				
	27 32	7	0.2	0.3	1.15 4.45	0.730 2.47		16.1 15.5	5 000	5 700 25 000		13 000	6704 6804JR	ZZ	LLF	_	LLU
	37	9				3.70					_		6904 6904	ZZ	LLB		LLU
20	42	8	0.3	0.3	7.05 8.75	4.50			19 000 18 000		_	12 000	16004		LLB		LLU
20	42	12	0.3	0.5	10.4	5.05			18 000		13 000	11 000	6004	ZZ	LLB	LLH	LLU
	47	14	1	0.5	14.2	6.65			16 000			10 000	6204	ZZ	LLB	LLH	LLU
	52	15	1.1	0.5	17.6	7.90					12 000		6304	ZZ	LLB	LLH	LLU
	J2	TO	T. T	0.0	11.0	1.50	0.013	14.7	T- 000	11 000	12 000	TO 000	JJU-	~~			LLU

¹⁾ Smallest allowable dimension for chamfer dimension r. 2) This bearing number is for double sealed and double shielded type bearings, but single sealed and single shielded type are also available.



Deep Groove Ball Bearings

groove

Dynamic equivalent radial load $P_r = XF_r + YF_a$

$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}}$	> <i>e</i>
Cor		X	Y	X	Y
0.172 0.345 0.689 1.03 1.38 2.07 3.45 5.17 6.89	0.19 0.22 0.26 0.28 0.30 0.34 0.38 0.42 0.44	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15 1.04 1.00


Static equivalent radial load $P_{0r} = 0.6F_r + 0.5F_a$ When $P_{0r} < F_r$ use $P_{0r} = F_r$.


	earing ımber		ap ring	groov	re	Snap			Insta	llation	-related	d dim	ensio	ns		Mass 5)
	/ Snap ring ³⁾	,	mr			m					mm					kg
(See	drawings)	D_{l} Max.	a Max.	<i>b</i> Min.	$r_{ m o}$ Max.	D_2 Max.	f Max.	Min.	$l_{ m a}$ Max. ⁴⁾	D_{a} Max.	$D_{ m X}$ (approx.)	$C_{ m Y}$ Max.	$C_{\rm Z}$ Min.	$r_{ m as}$ Max.	$r_{ m Nas}$ Max.	(approx.)
_	_	_	_	_	_	_	_	10.8	_	14.2	_	_	_	0.1	_	0.0015
_	_	_	_	_	_	_	_	12	12.5	17	_	_	_	0.3	_	0.005
N	NR	20.8	1.05	0.8	0.2	24.8	0.7	12	13	20	25.5	1.5	0.7	0.3	0.3	0.009
6)	6)	_	_	_	_	_	_	12	13.5	24	_	_	_	0.3	_	0.019
N	NR	28.17	2.06	1.35	0.4	34.7	1.12	14	16	26	35.5	2.9	1.2	0.6	0.5	0.032
N	NR	33.17	2.06	1.35	0.4	39.7	1.12	14	17	31	40.5	2.9	1.2	0.6	0.5	0.053
_	_	_	_	_	_	_	_	13.6	13.8	16.4	_	_	_	0.2	_	0.002
_	_	_	_	_	_	_	_	14	14.5	19	_	_	_	0.3	_	0.002
N	NR	22.8	1.05	0.8	0.2	26.8	0.7	14	15	22	27.5	1.5	0.7	0.3	0.3	0.011
_	_	_	_	_	_	_	_	14	_	26	_	_	_	0.3	_	0.019
NX2	NX2RX3	26.44	2.20	0.90	0.3	32.7	0.85	14	16	26	33.4	2.8	0.9	0.3	0.3	0.021
N	NR	30.15	2.06	1.35	0.4	36.7	1.12	16	17	28	37.5	2.9	1.2	0.6	0.5	0.037
N	NR	34.77	2.06	1.35	0.4	41.3	1.12	17	18.5	32	42	2.9	1.2	1	0.5	0.06
_	_	_	_	_	_	_	_	16.6	16.8	19.4	_	_	_	0.2	_	0.0025
_	_	_	_	_	_	_	_	17	17.5	22	_	_	_	0.3	_	0.007
N	NR	26.7	1.3	0.95	0.25	30.8	0.85	17	17.5	26	31.5	1.9	0.9	0.3	0.3	0.016
_	_	_	_	_	_	_	_	17	_	30	_	_	_	0.3	_	0.025
N	NR	30.15	2.06	1.35	0.4	36.7	1.12	17	19	30	37.5	2.9	1.2	0.3	0.3	0.03
N	NR	33.17	2.06	1.35	0.4	39.7	1.12	19	20	31	40.5	2.9	1.2	0.6	0.5	0.045
N	NR	39.75	2.06	1.55	0.4	46.3	1.12	20	23	37	47	2.9	1.2	1	0.5	0.082
_	_	_	_	_	_	_	_	18.6	18.8	21.4	_	_	_	0.2	_	0.0025
_	_	_	_	_	_	_	_	19	19.5	24	_	_	—	0.3	_	0.008
N	NR	28.7	1.3	0.95	0.25	32.8	0.85	19	20	28	33.5	1.9	0.9	0.3	0.3	0.018
_	_		_	_	_		_	19	_	33	_	_	_	0.3	_	0.032
N	NR	33.17	2.06	1.35	0.4	39.7	1.12	19	21	33	40.5	2.9	1.2	0.3	0.3	0.039
N	NR	38.1	2.06	1.35	0.4	44.6	1.12	21	23	36	45.5	2.9	1.2	0.6	0.5	0.066
N	NR	44.6	2.46	1.35	0.4	52.7	1.12	22	25	42	53.5	3.3	1.2	1	0.5	0.115
			_				_	23.5	30	55.5				1	_	0.27
_	_	_	_	_	_	_	_	21.6	22.3	25.4	_	_	_	0.2	_	0.0045
N	NR	30.7	1.3	0.95	0.25	34.8	0.85	22	22.5	30	35.5	1.9	0.9	0.3	0.3	0.019
N	NR	35.7	1.7	0.95	0.25	39.8	0.85	22	24	35	40.5	2.3	0.9	0.3	0.3	0.036
_	_	_	_	_	_		_	22	_	40	_	_	_	0.3	_	0.051
N	NR	39.75	2.06	1.35	0.4	46.3	1.12	24	26	38	47	2.9	1.2	0.6	0.5	0.069
N	NR	44.6	2.46	1.35	0.4	52.7	1.12	25	28	42	53.5	3.3	1.2	1	0.5	0.106
N	NR	49.73	2.46	1.35	0.4	57.9	1.12	26.5	28.5	45.5	58.5	3.3	1.2	1	0.5	0.144


³⁾ Sealed and shielded bearings are also available. 4) This dimension applies to sealed and shielded bearings.


⁵⁾ Does not include bearings with snap rings. 6) Refer to page B-54.












(LLH)




Contact sealed type (LLU)

d 20-35 mm

-		-															
В	ounda	ary c	limens	ions	Basic lo	ad rating		Factor		Allowab	le spee	d	Be	aring	g num	ber	
					dynamic	ctatio	load limit		Grease	mi Oil	n ⁻¹						
		m	m			static N	kN						Open type		Shi	elded	
				$r_{\rm Ns}$					ZZ, LLB, LLF	Open type Z, LB, LF	LLH	LLU	open type	0	r seale	ed typ	e ²⁾
d	D	В	$r_{\rm s min}^{1)}$	Min.	$C_{\rm r}$	C_{0r}	$C_{ m u}$	f_0	Z, LB, LF		LH	LU		(See d	rawing	gs)
20	72	19	1.1	_	31.5	13.9	1.09	11.4	12 000	14 000	_	_	6404	ZZ	_	_	_
20	12	13	1.1		31.3	13.5	1.05	11.7	12 000	1+000			0101				
	44	12	0.6	0.5	10.4	5.05	0.395	13.9	17 000	20 000	13 000	10 000	60/22	ZZ	LLB	LLH	LLU
22	50	14	1	0.5	14.3	6.80	0.500	13.5	14 000	17 000	12 000	9 700	62/22	ZZ	LLB	LLH	LLU
	56	16	1.1	0.5	20.4	9.25			13 000			9 200	63/22	ZZ	LLB	LLH	LLU
	32	4	0.2	_	1.21	0.840	0.036	15.8	4 000	4 600	_	_	6705	_	LLF	_	_
	37	7	0.3	0.3	4.75	2.95	0.208	16.1	18 000	21 000	_	10 000	6805JR	ZZ	LLB	_	LLU
	42	9	0.3	0.3	7.80	4.55	0.345	15.4	16 000	19 000	11 700	9 800	6905	ZZ	LLB	LLH	LLU
25	47	8	0.3	_	9.25	5.10			15 000		_	_	16005	—	_	_	_
23	47	12	0.6	0.5	11.2	5.85	0.380	14.5	15 000	18 000	11 000	9 400	6005	ZZ	LLB	LLH	LLU
	52	15	1	0.5	15.5	7.85			13 000		11 000	8 900	6205	ZZ	LLB	LLH	LLU
	62	17	1.1	0.5	23.5	10.9			12 000		9 700	8 100	6305	ZZ	LLB	LLH	LLU
	80	21	1.5	_	38.5	17.5	1.36	11.6	10 000	12 000	_	_	6405	ZZ	_	_	_
	52	12	0.6	0.5	13.8	7.40	0.580		14 000			8 400	60/28	ZZ	LLB	LLH	LLU
28		16	1	0.5	19.8	9.75	0.720		12 000		9 700	8 100	62/28	ZZ	LLB	LLH	LLU
	68	18	1.1	0.5	29.6	14.0	1.10	12.4	11 000	13 000	8 900	7 400	63/28	ZZ	LLB	LLH	LLU
	37	4	0.2	_	1.27	0.950	0.041	157	3 300	3 800	_	_	6706	_	LLF	_	_
	42	7	0.3	0.3	5.20	3.65	0.244		15 000	18 000	10 500	8 800	6806JR	ZZ	LLB	LLH	LLU
	47	9	0.3	0.3	8.00	5.00			14 000		10 000	8 400	6906	ZZ	LLB	LLH	LLU
	55	9	0.3		12.5	7.35			13 000		_	_	16006	_	_	_	_
30	55	13	1	0.5	14.7	8.30			13 000		9 200	7 700	6006	ZZ	LLB	LLH	LLU
	62	16	1	0.5	21.6	11.3			11 000		8 800	7 300	6206	ZZ	LLB	LLH	LLU
	72	19	1.1	0.5	29.5	15.0	1.14	13.3	10 000	12 000	7 900	6 600	6306	ZZ	LLB	LLH	LLU
	90	23	1.5	_	48.0	23.9	1.86	12.3	8 800	10 000	_	_	6406	ZZ	_	_	_
	58	13	1	0.5	13.1	8.05	0.615	15.4	12 000	15 000	8 700	7 200	60/32	ZZ	LLB	LLH	LLU
32	65	17	1	0.5	23.0	11.6	0.840		11 000		8 400	7 100	62/32	ZZ	LLB	LLH	LLU
	75	20	1.1	0.5	33.0	16.9	1.30	13.1	9 500	11 000	7 700	6 500	63/32	ZZ	LLB	LLH	LLU
	47	7	0.0	0.2	F 4F	4.05	0.000	16.1	42.000	46.000		7.000	C0071D				
	47	7	0.3	0.3	5.45	4.05	0.268		13 000			7 600	6807JR	ZZ	LLB		LLU
	55	10	0.6	0.5	10.6	6.85	0.495		12 000		8 500	7 100	6907	ZZ	LLB	LLH	LLU
25	62	9	0.3		12.9	8.20			12 000				16007	 77	-		
35		14	1	0.5	17.7	10.3			12 000		8 200	6 800	6007	ZZ	LLB	LLH	LLU
	72	17	1.1 1.5	0.5	28.4	15.3	1.09	13.8		11 000	7 600	6 300	6207	ZZ	LLB	LLH	LLU
	80	21		0.5	37.0	19.1	1.47	13.1		10 000	7 300	6 000	6307	ZZ	LLB	LLH	LLU
	100	25	1.5	_	61.0	31.0	2.43	12.3	7 800	9 100	_	_	6407	22	_	_	_

¹⁾ Smallest allowable dimension for chamfer dimension r. 2) This bearing number is for double sealed and double shielded type bearings, but single sealed and single shielded type are also available.





Dynamic equivalent radial load $P_r = XF_r + YF_a$


$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_a}{F_r} > e$			
C0r		X	Y	X	Y		
0.172 0.345 0.689 1.03 1.38 2.07 3.45 5.17	0.19 0.22 0.26 0.28 0.30 0.34 0.38	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15		
6.89	0.42				1.04		


Static equivalent radial load $P_{0\mathrm{r}} = 0.6F_{\mathrm{r}} + 0.5F_{\mathrm{a}}$ When $P_{0\mathrm{r}} < F_{\mathrm{r}}$ use $P_{0\mathrm{r}} = F_{\mathrm{r}}$.


Be	Bearing Snap ring groove Snap ring Installation-related dimensions M									Mass 5)						
nu	mber		dimen mr	sions		dimen	sions				mm					kg
Groove /	Snap ring 3) Irawings)	D_1	a	b	14	D_2	f		J	D	$D_{\rm X}$	$C_{\rm Y}$	C	**		Ü
(See u	irawirigs <i>)</i>	Max.	<i>а</i> Мах.	Min.	$r_{ m o}$ Max.	D_2 Max.	Max.		l _a Max. ⁴⁾	$D_{ m a}$ Max.	(approx.)		Min.	$r_{ m as}$ Max.	Max.	(approx.)
_	_	_	_	_	_	_	_	26.5	35.5	65.5	_	_	_	1	_	0.4
N	NR	41.75	2.06	1.35	0.4	48.3	1.12	26	26.5	40	49	2.9	1.2	0.6	0.5	0.074
N	NR	47.6	2.46	1.35	0.4	55.7	1.12	27	29.5	45	56.5	3.3	1.2	1	0.5	0.117
N	NR	53.6	2.46	1.35	0.4	61.7	1.12	28.5	31	49.5	62.5	3.3	1.2	1	0.5	0.176
_	_	_	_	_	_	_	_	26.6	27.3	30.4	_	_	_	0.2	_	0.005
N	NR	35.7	1.3	0.95	0.25	39.8	0.85	27	28	35	40.5	1.9	0.9	0.3	0.3	0.022
N	NR	40.7	1.7	0.95	0.25	44.8	0.85	27	29	40	45.5	2.3	0.9	0.3	0.3	0.042
	_	_	_	_	_		_	27	_	45	_	_	_	0.3	_	0.06
N	NR	44.6	2.06	1.35	0.4	52.7	1.12	29	30.5	43	53.5	2.9	1.2	0.6	0.5	0.08
N	NR	49.73	2.46	1.35	0.4	57.9	1.12	30	32	47	58.5	3.3	1.2	1	0.5	0.128
N	NR —	59.61	3.28	1.9	0.6	67.7	1.7	31.5	35	55.5	68.5	4.6	1.7	1.5	0.5	0.232
_	_	_	_	_	_	_	_	33	41	72	_	_	_	1.5	_	0.53
N	NR	49.73	2.06	1.35	0.4	57.9	1.12	32	34	48	58.5	2.9	1.2	0.6	0.5	0.098
N	NR	55.6	2.46	1.35	0.4	63.7	1.12	33	35.5	53	64.5	3.3	1.2	1	0.5	0.171
N	NR	64.82	3.28	1.9	0.6	74.6	1.7	34.5	38.5	61.5	76	4.6	1.7	1	0.5	0.284
_	_	_	_	_	_	_	_	31.6	32.3	35.4	_	_	_	0.2	_	0.006
N	NR	40.7	1.3	0.95	0.25	44.8	0.85	32	33	40	45.5	1.9	0.9	0.3	0.3	0.026
N	NR	45.7	1.7	0.95	0.25	49.8	0.85	32	34	45	50.5	2.3	0.9	0.3	0.3	0.048
_	_	_			_		_	32	_	53	_	_	_	0.3	_	0.091
N	NR	52.6	2.08	1.35	0.4	60.7	1.12	35	37	50	61.5	2.9	1.2	1	0.5	0.116
N	NR	59.61	3.28 3.28	1.9	0.6	67.7	1.7	35 36.5	39 43	57	68.5	4.6	1.7	1	0.5	0.199
N	NR	68.81	3.28	1.9	0.6	78.6 —	1.7	38.5	43	65.5 82	80	4.6	1.7	1.5	0.5	0.36 0.735
								30	49	02		_	_	1.5		0.755
N	NR	55.6	2.08	1.35	0.4	63.7	1.12	37	39	53	64.5	2.9	1.2	1	0.5	0.129
N	NR	62.6	3.28	1.9	0.6	70.7	1.7	37	40	60	71.5	4.6	1.7	1	0.5	0.226
N	NR	71.83	3.28	1.9	0.6	81.6	1.7	38.5	43.5	68.5	83	4.6	1.7	1	0.5	0.382
N	NR	45.7	1.3	0.95	0.25	49.8	0.85	37	38	45	50.5	1.9	0.9	0.3	0.3	0.029
N	NR	53.7	1.7	0.95	0.25	57.8	0.85	39	40	51	58.5	2.3	0.9	0.6	0.5	0.074
_	_	_	_	_	_	_	_	37	_	60	_	_	_	0.3	_	0.11
N	NR	59.61	2.08	1.9	0.6	67.7	1.7	40	42	57	68.5	3.4	1.7	1	0.5	0.155
N	NR	68.81	3.28	1.9	0.6	78.6	1.7	41.5	45	65.5	80	4.6	1.7	1	0.5	0.288
N	NR	76.81	3.28	1.9	0.6	86.6	1.7	43	47	72	88	4.6	1.7	1.5	0.5	0.457
_	_	_	_	_	_	_	_	43	56.5	92	_	_	_	1.5	_	0.952


³⁾ Sealed and shielded bearings are also available. 4) This dimension applies to sealed and shielded bearings.

⁵⁾ Does not include bearings with snap rings.










(LLH)




Contact sealed type (LLU)

d 40-60 mm

u	70	0	, ,,,,,,,														
В	ounda	ry c	limens	ions	Basic loa	ad rating	Fatigue	Factor							ber		
						ŭ	load			mir				•			
		m	m			static N	limit kN		Grease	Oil Open type			Open type		Chi	elded	
		1111	111	$r_{ m Ns}$, ,	.I N	KIN		Open type, ZZ, LLB	Open type, Z, LB	LLH	LLU	Open type	0	r seale	ed type	e 2)
d	D	В	$r_{\rm s min}^{1)}$	Min.	$C_{\rm r}$	C_{0r}	$C_{\rm u}$	f_0	Z, LB	_,	LH	LU		(See d	rawing	zs)
	F2	7				4.40			12 000	14000	0.000	6 700	CONCID	77	LLB	1111	
	52 62	12	0.3	0.3	5.65 13.5	4.40 8.90	0.291	16.3 15.8	11 000		8 000 7 500	6 300	6808JR 6908	ZZ	LLB	LLH	LLU
	68	9	0.8	0.5	14.0	9.65	0.685	16.0	10 000		7 500	0 300	16008		LLD	LLI	LLU
40		15	1	0.5	18.6	11.5	0.890	15.2			7 300	6 100	6008	ZZ	LLB	LLH	LLU
40	80	18	1.1	0.5	32.5	17.8	1.24	14.0		10 000	6 700	5 600	6208	ZZ	LLB	LLH	LLU
	90	23	1.5	0.5	45.0	24.0	1.83	13.2	7 800	9 200	6 400	5 300	6308	ZZ	LLB	LLH	LLU
	110	27	2	0.5	70.5	36.5	2.85	12.3	7 000	8 200	—	_	6408	ZZ	LLD	LLII	LLU
	110	21			70.5	30.3	2.05	12.5	7 000	0 200			0400	22			
	58	7	0.3	0.3	5.95	4.95	0.325	16.1	11 000	12 000	_	5 900	6809JR	ZZ	LLB	_	LLU
	68	12	0.6	0.5	14.5	10.4	0.730	16.1		12 000	_	5 600	6909	ZZ	LLB	_	LLU
	75	10	0.6	_	14.3	10.5	0.725	16.2		11 000	_	_	16009	_	_	_	_
45		16	1	0.5	23.2	15.1	1.16	15.3	9 200	11 000	6 500	5 400	6009	ZZ	LLB	LLH	LLU
	85	19	1.1	0.5	36.0	20.4	1.60	14.1	7 800	9 200	6 200	5 200	6209	ZZ	LLB	LLH	LLU
	100	25	1.5	0.5	58.5	32.0	2.50	13.1	7 000	8 200	5 600	4 700	6309	ZZ	LLB	LLH	LLU
	120	29	2	_	85.5	45.0	3.50	12.1	6 300	7 400	_	_	6409	ZZ	_	_	_
	65	7	0.3	0.3	7.30	6.10	0.405	16.1	9 600	11 000	_	5 300	6810JR	ZZ	LLB	_	LLU
	72	12	0.6	0.5	14.9	11.2	0.765	16.3	8 900	11 000	6 100	5 100	6910	ZZ	LLB	LLH	LLU
	80	10	0.6	_	14.7	11.3	0.760	16.4	8 400	9 800	_	_	16010	_	_	_	_
50	80	16	1	0.5	24.2	16.6	1.24	15.5	8 400	9 800	6 000	5 000	6010	ZZ	LLB	LLH	LLU
	90	20	1.1	0.5	39.0	23.2	1.82	14.4	7 100	8 300	5 700	4 700	6210	ZZ	LLB	LLH	LLU
	110	27	2	0.5	68.5	38.5	2.99	13.2	6 400	7 500	5 000	4 200	6310	ZZ	LLB	LLH	LLU
	130	31	2.1	_	92.0	49.5	3.85	12.5	5 700	6 700	_	_	6410	ZZ	_	_	_
	72	9	0.3	0.3	9.75	8.10	0.540	16.2	8 700	10 000	_	4 800	6811JR	ZZ	LLB	_	LLU
	80	13	1	0.5	17.7	13.3	0.915	16.2	8 200	9 600	5 500	4 600	6911	ZZ	LLB	LLH	LLU
	90	11	0.6	-	20.6	15.3	1.06	16.2	7 700	9 000	_	- 000	16011	_		_	_
55		18	1.1	0.5	31.5	21.2	1.62	15.3	7 700	9 000		4 500	6011	ZZ	LLB		LLU
3.	100	21	1.5	0.5	48.0	29.2	2.29	14.3	6 400	7 600	_	4 300	6211	ZZ	LLB	_	LLU
	120	29	2	0.5	79.5	45.0	3.50	13.2	5 800	6 800	_	3 900	6311	ZZ	LLB	_	LLU
	140	33	2.1	-	98.5	54.0	4.20	12.7	5 200	6 100	_	_	6411	ZZ	_	_	_
		00			50.0	0	0		0 200	0 200							
	78	10	0.3	0.3	12.7	10.6	0.705	16.3	8 000	9 400	_	4 400	6812	ZZ	LLB	_	LLU
	85	13	1	0.5	18.2	14.3	0.965	16.4	7 600	8 900	_	4 300	6912	ZZ	LLB	_	LLU
	95	11	0.6	_	22.1	17.5	1.20	16.3	7 000	8 300	_	_	16012	_	_	_	_
60	95	18	1.1	0.5	32.5	23.2	1.73	15.6	7 000	8 300	_	4 100	6012	ZZ	LLB	_	LLU
	110	22	1.5	0.5	58.0	36.0	2.83	14.3	6 000	7 000	4 500	3 800	6212	ZZ	LLB	LLH	LLU
	130	31	2.1	0.5	90.5	52.0	4.10	13.2	5 400	6 300	_	3 600	6312	ZZ	LLB	_	LLU
	150	35	2.1	_	113	64.5	4.90	12.6	4 800	5 700	_	_	6412	ZZ	_	_	_

¹⁾ Smallest allowable dimension for chamfer dimension r. 2) This bearing number is for double sealed and double shielded type bearings, but single sealed and single shielded type are also available.



Deep Groove Ball Bearings

groove

Dynamic equivalent radial load $P_r = XF_r + YF_a$


$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}} > e$			
C0r		X	Y	X	Y		
0.172	0.19				2.30		
0.345	0.22				1.99		
0.689	0.26				1.71		
1.03	0.28				1.55		
1.38	0.30	1	0	0.56	1.45		
2.07	0.34				1.31		
3.45	0.38				1.15		
5.17	0.42				1.04		
6.89	0.44				1.00		

Static equivalent radial load $P_{0r} = 0.6F_r + 0.5F_a$ When $P_{0r} < F_r$ use $P_{0r} = F_r$.

							777677 01 11 GSC 1 01 1 1.									
	aring mber		ap ring dimen	sions	е	Snap	sions		Insta	allation	-related	dim	ensio	ns		Mass 5
iroove /	Snap ring 3)		mr	11		m	m				mm					kg
	rawings)	D_{l} Max.	<i>а</i> Мах.	<i>b</i> Min.	$r_{ m o}$ Max.	D_2 Max.	f Max.	Min.	$l_{ m a}$ Max. ⁴⁾	D_{a} Max.	$D_{ m X}$ (approx.)		$C_{\rm Z}$ Min.		$r_{ m Nas}$ Max.	(approx.
N	NR	50.7	1.3	0.95	0.25	54.8	0.85	42	43	50	55.5	1.9	0.9	0.3	0.3	0.033
N	NR	60.7	1.7	0.95	0.25	64.8	0.85	44	45	58	65.5	2.3	0.9	0.6	0.5	0.11
_	_	_	_	_	_	_	_	42	_	66	_	_	_	0.3		0.125
N	NR	64.82	2.49	1.9	0.6	74.6	1.7	45	47	63	76	3.8	1.7	1	0.5	0.19
N	NR	76.81	3.28	1.9	0.6	86.6	1.7	46.5	51	73.5	88	4.6	1.7	1	0.5	0.366
N	NR	86.79	3.28	2.7	0.6	96.5	2.46	48	54	82	98	5.4	2.5	1.5	0.5	0.63
_	_	_	_	_	_	_	_	49	61.5	101	_	_	_	2.0	_	1.23
N	NR	56.7	1.3	0.95	0.25	60.8	0.85	47	48	56	61.5	1.9	0.9	0.3	0.3	0.04
N	NR	66.7	1.7	0.95	0.25	70.8	0.85	49	51	64	72	2.3	0.9	0.6	0.5	0.128
_	_	_	_	_	_	_	_	49	_	71	_	_	_	0.6	_	0.171
N	NR	71.83	2.49	1.9	0.6	81.6	1.7	50	52.5	70	83	3.8	1.7	1	0.5	0.237
N	NR	81.81	3.28	1.9	0.6	91.6	1.7	51.5	55.5	78.5	93	4.6	1.7	1	0.5	0.398
N	NR	96.8	3.28	2.7	0.6	106.5	2.46	53	61.5	92	108	5.4	2.5	1.5	0.5	0.814
_	_	_	_	_	_	_	_	54	66.5	111	_	_	_	2	_	1.53
N	NR	63.7	1.3	0.95	0.25	67.8	0.85	52	54	63	68.5	1.9	0.9	0.3	0.3	0.052
N	NR	70.7	1.7	0.95	0.25	74.8	0.85	54	55.5	68	76	2.3	0.9	0.6	0.5	0.132
_	_	_	_	_	_	_	_	54	_	76	_	_	_	0.6	_	0.18
N	NR	76.81	2.49	1.9	0.6	86.6	1.7	55	57.5	75	88	3.8	1.7	1	0.5	0.261
N	NR	86.79	3.28	2.7	0.6	96.5	2.46	56.5	60	83.5	98	5.4	2.5	1	0.5	0.454
N	NR	106.81	3.28	2.7	0.6	116.6	2.46	59	68.5	101	118	5.4	2.5	2	0.5	1.07
_	_	_	_	_	_	_	_	61	73.5	119	_	_	_	2	_	1.88
N	NR	70.7	1.7	0.95	0.25	74.8	0.85	57	59	70	76	2.3	0.9	0.3	0.3	0.083
N	NR	77.9	2.1	1.3	0.4	84.4	1.12	60	61.5	75	86	2.9	1.2	1	0.5	0.18
_	_	_	_	_	_	_	_	59	_	86	_	_	_	0.6	_	0.258
N	NR	86.79	2.87	2.7	0.6	96.5	2.46	61.5	64	83.5	98	5	2.5	1	0.5	0.388
N	NR	96.8	3.28	2.7	0.6	106.5	2.46	63	67	92	108	5.4	2.5	1.5	0.5	0.601
N	NR	115.21	4.06	3.1	0.6	129.7	2.82	64	74	111	131.5	6.5	2.9	2	0.5	1.37
_	_	_	_	_	_	_	_	66	80	129	_	_	_	2	_	2.29
N	NR	76.2	1.7	1.3	0.4	82.7	1.12	62	64.5	76	84	2.5	1.2	0.3	0.3	0.106
N	NR	82.9	2.1	1.3	0.4	89.4	1.12	65	66.5	80	91	2.9	1.2	1	0.5	0.193
_	_		_	_	_			64	_	91		_	_	0.6	_	0.283
N	NR	91.82	2.87	2.7	0.6	101.6	2.46	66.5	69	88.5	103	5	2.5	1	0.5	0.414
N	NR	106.81	3.28	2.7	0.6	116.6	2.46	68	75	102	118	5.4	2.5	1.5	0.5	0.783
N	NR	125.22	4.06	3.1	0.6	139.7	2.82	71	80.5	119	141.5	6.5	2.9	2	0.5	1.73
_	_	_	_	_	_	_	_	71	86	139	_	_	_	2	_	2.77

³⁾ Sealed and shielded bearings are also available. 4) This dimension applies to sealed and shielded bearings.


⁵⁾ Does not include bearings with snap rings.



Open type



(ZZ)



sealed type

(LLB)



Contact sealed type (LLU)


d 65-85 mm

d															
E	Bound	ary o	dimensio	ns	Basic loa	d rating		Factor	Allov	wable sp	eed	В	earing	numbe	r
d	D	m B	m $r_{\rm s min}^{-1)}$	$r_{ m Ns}$ Min.	dynamic ki $C_{ m r}$		load limit kN Cu	f_0	Grease Open type ZZ, LLB Z, LB	min ⁻¹ Oil Open type Z, LB	LLU LU	Open type	or s	Shielded sealed ty	pe ²⁾
и									,				,		0 /
	85	10	0.6	0.5	12.8	11.0	0.730	16.2	7 400	8 700	4 100	6813	ZZ	LLB	LLU
	90	13	1 0.6	0.5	19.3 22.7	16.1	1.07 1.26	16.6	7 000 6 500	8 200	4 000	6913	ZZ	LLB	LLU
65	100	11 18	1.1	0.5	34.0	18.7 25.2	1.83	16.5 15.8	6 500	7 700 7 700	3 900	16013 6013	ZZ	LLB	LLU
05	120	23	1.5	0.5	63.5	40.0	3.15	14.4	5 500	6 500	3 600	6213	ZZ	LLB	LLU
	140	33	2.1	0.5	103	60.0	4.60	13.2	4 900	5 800	3 300	6313	ZZ	LLB	LLU
	160	37	2.1	-	123	72.5	5.35	12.7	4 400	5 200	_	6413	_		_
	100	٥,			123	7 2.5	5.55	12.7	1 100	3 200		0110			
	90	10	0.6	0.5	13.4	11.9	0.795	16.1	6 900	8 100	3 800	6814	ZZ	LLB	LLU
	100	16	1	0.5	26.3	21.2	1.45	16.3	6 500	7 700	3 700	6914	ZZ	LLB	LLU
	110	13	0.6	_	27.0	22.6	1.52	16.5	6 100	7 100	_	16014	_	_	_
70	110	20	1.1	0.5	42.0	31.0	2.30	15.6	6 100	7 100	3 600	6014	ZZ	LLB	LLU
	125	24	1.5	0.5	69.0	44.0	3.45	14.5	5 100	6 000	3 400	6214	ZZ	LLB	LLU
	150	35	2.1	0.5	115	68.0	5.10	13.2	4 600	5 400	3 100	6314	ZZ	LLB	LLU
	180	42	3	_	142	89.5	6.25	12.7	4 100	4 800	_	6414	_	_	_
	95	10	0.6	0.5	13.9	12.9	0.855	16.0	6 400	7 600	3 600	6815	ZZ	LLB	LLU
	105	16	1	0.5	27.0	22.6	1.52	16.5	6 100	7 200	3 500	6915	ZZ	LLB	LLU
	115	13	0.6		27.6	24.0	1.60	16.6	5 700	6 700	3 300	16015			LLO
75	115	20	1.1	0.5	44.0	33.5	2.44	15.8	5 700	6 700	3 300	6015	ZZ	LLB	LLU
	130	25	1.5	0.5	73.5	49.5	3.80	14.7	4 800	5 600	3 200	6215	ZZ	LLB	LLU
	160	37	2.1	0.5	126	77.0	5.55	13.2	4 300	5 000	2 900	6315	ZZ	LLB	LLU
	190	45	3	_	152	99.0	6.70	12.7	3 800	4 500	_	6415	_	_	_
	100	10	0.6	0.5	14.0	13.3	0.885	16.0	6 000	7 100	3 400	6816	ZZ	LLB	LLU
	110 125	16 14	1 0.6	0.5	27.6 28.1	24.0 25.1	1.59 1.64	16.6 16.4	5 700 5 300	6 700 6 200	3 200	6916 16016	ZZ	LLB —	LLU
80	125	22	1.1	0.5	53.0	40.0	2.91	15.6	5 300	6 200	3 100	6016	ZZ	LLB	LLU
80	140	26	2	0.5	80.5	53.0	3.95	14.6	4 500	5 300	3 000	6216	ZZ	LLB	LLU
	170	39	2.1	0.5	136	86.5	6.05	13.3	4 000	4 700	2 700	6316	ZZ	LLB	LLU
	200	48	3	_	181	125	8.20	12.3	3 600	4 200	_	6416	_	_	_
	110	13	1	0.5	20.7	19.0	1.26	16.2	5 700	6 700	3 100	6817	ZZ	LLB	LLU
	120	18	1.1	0.5	35.5	29.6	1.99	16.4	5 400	6 300	3 000	6917	ZZ	LLB	LLU
85	130	14	0.6	_	28.7	26.2	1.68	16.4	5 000	5 900	_	16017	_	_	_
03	130	22	1.1	0.5	55.0	43.0	3.00	15.8	5 000	5 900	2 900	6017	ZZ	LLB	LLU
	150	28	2	0.5	92.0	64.0	4.60	14.7	4 200	5 000	2 800	6217	ZZ	LLB	LLU
	180	41	3	0.5	147	97.0	6.55	13.3	3 800	4 500	2 600	6317	ZZ	LLB	LLU

¹⁾ Smallest allowable dimension for chamfer dimension r. 2) This bearing number is for double sealed and double shielded type bearings, but single sealed and single shielded type are also available.



groove



Dynamic equivalent radial load $P_r = XF_r + YF_a$

$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}}$	> <i>e</i>
Cor		X	Y	X	Y
0.172 0.345 0.689 1.03 1.38 2.07 3.45 5.17	0.19 0.22 0.26 0.28 0.30 0.34 0.38 0.42	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15 1.04
6.89	0.44				1.00


Static equivalent radial load $P_{0r} = 0.6F_r + 0.5F_a$ When $P_{0r} < F_r$ use $P_{0r} = F_r$.

D.		C			_	C			land 1	latia.				_		M 5)
	ring nber		p ring : limens mm	ions	е	Snap dimen	sions		instai	iation-i	related of mm	aime	nsion	ıs		Mass 5)
	Snap ring (3)	_								_		~	~			6
(See dr	awings)	D_1 Max.	a Max.	<i>b</i> Min.	$r_{ m o}$ Max.	D_2 Max.	f Max.	Min.	l _a Max. ⁴⁾	$D_{ m a}$ Max.	$D_{\rm X} \\ {\rm (approx.)}$		$C_{\rm Z}$ Min.	$r_{ m as}$ Max.		(approx.)
N	NR	82.9	1.7	1.3	0.4	89.4	1.12	69	70	81	91	2.5	1.2	0.6	0.5	0.128
N	NR	87.9	2.1	1.3	0.4	94.4	1.12	70	71.5	85	96	2.9	1.2	1	0.5	0.206
_	_	_	_	_	_	_	_	69	_	96	_	_	_	0.6	_	0.307
N	NR	96.8	2.87	2.7	0.6	106.5	2.46	71.5	74	93.5	108	5	2.5	1	0.5	0.421
N	NR	115.21	4.06	3.1	0.6	129.7	2.82	73	80.5	112	131.5	6.5	2.9	1.5	0.5	0.99
N	NR	135.23	4.9	3.1	0.6	149.7	2.82	76	86	129	152	7.3	2.9	2	0.5	2.08
_	_	_		_	_	_	_	76		149		_	_	2	_	3.3
N	NR	87.9	1.7	1.3	0.4	94.4	1.12	74	75.5	86	96	2.5	1.2	0.6	0.5	0.137
N	NR	97.9	2.5	1.3	0.4	104.4	1.12	75	77.5	95	106	3.3	1.2	1	0.5	0.334
_	_	_	_	_	_	_	_	74	_	106	_	_	_	0.6	_	0.441
N	NR	106.81	2.87	2.7	0.6	116.6	2.46	76.5	80.5	103.5	118	5	2.5	1	0.5	0.604
N	NR	120.22	4.06	3.1	0.6	134.7	2.82	78	85	117	136.5	6.5	2.9	1.5	0.5	1.07
N	NR	145.24	4.9	3.1	0.6	159.7	2.82	81	92.5	139	162	7.3	2.9	2	0.5	2.52
_	_	_		_	_	_	_	83		167	_	_	_	2.5	_	4.83
N	NR	92.9	1.7	1.3	0.4	99.4	1.12	79	80	91	101	2.5	1.2	0.6	0.5	0.145
N	NR	102.6	2.5	1.3	0.4	110.7	1.12	80	82.5	100	112	3.3	1.2	1	0.5	0.353
_	_	_	_	_	_	_	_	79	_	111	_	_	_	0.6	_	0.464
N	NR	111.81	2.87	2.7	0.6	121.6	2.46	81.5	85.5	108.5	123	5	2.5	1	0.5	0.649
N	NR	125.22	4.06	3.1	0.6	139.7	2.82	83	90.5	122	141.5	6.5	2.9	1.5	0.5	1.18
N	NR	155.22	4.9	3.1	0.6	169.7	2.82	86	99	149	172	7.3	2.9	2	0.5	3.02
		_			_			88		177		_	_	2.5	_	5.72
N	NR	97.9	1.7	1.3	0.4	104.4	1.12	84	85	96	106	2.5	1.2	0.6	0.5	0.154
N	NR	107.6	2.5	1.3	0.4	115.7	1.12	85	88	105	117	3.3	1.2	1	0.5	0.373
_	_	_	_	_	_	_	_	84	_	121	_	_	_	0.6	_	0.597
N	NR	120.22	2.87	3.1	0.6	134.7	2.82	86.5	91.5	118.5	136.5	5.3	2.9	1	0.5	0.854
N	NR	135.23	4.9	3.1	0.6	149.7	2.82	89	95.5	131	152	7.3	2.9	2	0.5	1.4
N	NR	163.65	5.69	3.5	0.6	182.9	3.1	91	105	159	185	8.4	3.1	2	0.5	3.59
_	_	_	_	_	_	_	_	93	_	187	_	_	_	2.5	_	6.76
N	NR	107.6	2.1	1.3	0.4	115.7	1.12	90	91	105	117	2.9	1.2	1	0.5	0.27
N	NR	117.6	3.3	1.3	0.4	125.7	1.12	91.5	94	113.5	127	4.1	1.2	1	0.5	0.536
_	_	_	_	_	_	_	_	89	_	126	_	_	_	0.6	_	0.626
N	NR	125.22	2.87	3.1	0.6	139.7	2.82	91.5	97	123.5	141.5	5.3	2.9	1	0.5	0.89
N	NR	145.24	4.9	3.1	0.6	159.7	2.82	94	103	141	162	7.3	2.9	2	0.5	1.79
N	NR	173.66	5.69	3.5	0.6	192.9	3.1	98	112	167	195	8.4	3.1	2.5	0.5	4.23


³⁾ Sealed and shielded bearings are also available. 4) This dimension applies to sealed and shielded bearings.

⁵⁾ Does not include bearings with snap rings.










(LLB)




Contact sealed type (LLU)

d 90-120 mm

Boundary dimensions Basic load rating Fatigue Factor Allowable speed Bearing number															
В	Bound	ary o	dimensio	ns	Basic loa	ad rating	Fatigue	Factor	Allov	wable sp	eed	В	earing	g numbe	r
							load		_	min ⁻¹					
		m	m		dynamic	static N	limit kN		Grease	Oil Open type		Open type		Shielded	4
		- 111	111	$r_{ m Ns}$	K	IN	KIN		Open type ZZ, LLB	Z, LB	LLU	open type	or	sealed ty	pe ²⁾
d	D	B	$r_{\rm s min}^{1)}$	Min.	$C_{\rm r}$	C_{0r}	C_{u}	f_0	Z, LB		LU		(S	ee drawii	ngs)
	115	13	1	0.5	21.1	19.7	1.30	16.1	5 400	6 300	3 000	6818	ZZ	LLB	LLU
	125	18	1.1	0.5	36.5	31.5	2.05	16.5	5 100	6 000	2 900	6918	ZZ	LLB	LLU
	140	16	1	_	37.0	33.5	2.07	16.5	4 700	5 600	_	16018		_	_
90	140	24	1.5	0.5	64.5	49.5	3.45	15.6	4 700	5 600	2 800	6018	ZZ	LLB	LLU
	160	30	2	0.5	106	71.5	5.00	14.5	4 000	4 700	2 600	6218	ZZ	LLB	LLU
	190	43	3	0.5	158	107	7.10	13.3	3 600	4 200	2 400	6318	ZZ	LLB	LLU
	120	13	1	0.5	21.4	20.5	1.31	16.1	5 000	5 900	2 800	6819	ZZ	LLB	LLU
	130	18	1.1	0.5	37.5	33.5	2.10	16.6	4 800	5 700	2 800	6919	ZZ	LLB	LLU
95	145	16	1	_	38.0	35.0	2.13	16.5	4 500	5 300	_	16019	_	_	
	145	24	1.5	0.5	67.0	54.0	3.55	15.8	4 500	5 300	2 600	6019	ZZ	LLB	LLU
	170	32	2.1	0.5	121	82.0	5.55	14.4	3 700	4 400	2 500	6219	ZZ	LLB	LLU
	200	45	3	0.5	169	119	7.65	13.3	3 300	3 900	2 300	6319	ZZ	LLB	LLU
	125	13	1	0.5	21.7	21.2	1.33	16.0	4 800	5 600	2 700	6820	ZZ	LLB	LLU
	140	20	1.1	0.5	45.5	39.5	2.44	16.4	4 500	5 300	2 600	6920	ZZ	LLB	LLU
	150	16	1	_	39.0	36.5	2.18	16.4	4 200	5 000	_	16020		_	_
100	150	24	1.5	0.5	66.5	54.0	3.50	15.9	4 200	5 000	2 600	6020	ZZ	LLB	LLU
	180	34	2.1	0.5	135	93.0	6.15	14.4	3 500	4 200	2 300	6220	ZZ	LLB	LLU
	215	47	3	_	192	141	8.75	13.2	3 200	3 700	2 200	6320	ZZ	LLB	LLU
	130	13	1	0.5	22.0	22.0	1.35	15.9	4 600	5 400	2 500	6821	ZZ	_	LLU
	145	20	1.1	0.5	47.0	42.0	2.52	16.5	4 300	5 100	2 500	6921	ZZ	LLB	LLU
105	160	18	1	_	57.5	50.5	3.00	16.3	4 000	4 700	_	16021	_	_	
	160	26	2	0.5	80.5	65.5	4.15	15.8	4 000	4 700	2 400	6021	ZZ	LLB	LLU
	190 225	36	2.1	0.5	147	105	6.75	14.4	3 400	4 000	2 300	6221	ZZ	LLB —	LLU
	225	49	3	_	204	153	9.35	13.2	3 000	3 600	2 100	6321	22		LLU
	140	16	1	0.5	27.5	28.2	1.68	16.0	4 300	5 100	2 400	6822	ZZ	LLB	LLU
	150	20	1.1	0.5	48.5	44.5	2.60	16.6	4 100	4 800	2 400	6922	ZZ	LLB	LLU
440	170	19	1	_	63.5	56.5	3.25	16.3	3 800	4 500	_	16022	_	_	_
110	170	28	2	0.5	91.0	73.0	4.55	15.6	3 800	4 500	2 300	6022	ZZ	LLB	LLU
	200	38	2.1	0.5	160	117	7.35	14.3	3 200	3 800	2 200	6222	ZZ	LLB	LLU
	240	50	3	_	227	179	10.5	13.1	2 900	3 400	1 900	6322	ZZ	LLB	LLU
	150	16	1	0.5	32.0	33.0	1.89	16.0	4 000	4 700	2 200	6824	ZZ	LLB	LLU
120	165	22	1.1	0.5	59.0	54.0	3.05	16.5	3 800	4 400	2 100	6924	ZZ	_	LLU
	180	19	1	0.5	70.0	63.5	3.50	16.4	3 500	4 100	2 100	16024	ZZ	_	LLU
	180	28	2	0.5	94.0	79.5	4.65	15.9	3 500	4 100	2 100	6024	77	LLB	LLU

¹⁾ Smallest allowable dimension for chamfer dimension r. 2) This bearing number is for double sealed and double shielded type bearings, but single sealed and single shielded type are also available.

Deep Groove Ball Bearings



Dynamic equivalent radial load $P_r = XF_r + YF_a$

$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}}$	> <i>e</i>
Cor		X	Y	X	Y
0.172 0.345 0.689 1.03 1.38 2.07 3.45 5.17 6.89	0.19 0.22 0.26 0.28 0.30 0.34 0.38 0.42 0.44	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15 1.04


Static equivalent radial load $P_{0r} = 0.6F_r + 0.5F_a$ When $P_{0r} < F_r$ use $P_{0r} = F_r$.

Bea num			p ring ; limens		е	Snap dimen			Instal	lation-ı	elated o	dime	nsion	s		Mass 5
	nap ring ³⁾	u	mm			mr					mm					kg
(See dr	awings)	$D_{ m l}$ Max.	<i>а</i> Мах.	<i>b</i> Min.	$r_{ m o}$ Max.	D_2 Max.	f Max.	Min.	$l_{ m a}$ Max. ⁴⁾	D_{a} Max.	$D_{\rm X} \\ {\rm (approx.)}$		$C_{\rm Z}$ Min.	$r_{ m as}$ Max.	$r_{ m Nas}$ Max.	(approx.)
N	NR	112.6	2.1	1.3	0.4	120.7	1.12	95	96	110	122	2.9	1.2	1	0.5	0.285
N	NR	122.6	3.3	1.3	0.4	130.7	1.12	96.5	99	118.5	132	4.1	1.2	1	0.5	0.554
_	_	_	_	_	_	_	_	95	_	135	_	_	_	1	_	0.848
N	NR	135.23	3.71	3.1	0.6	149.7	2.82	98	102	132	152	6.1	2.9	1.5	0.5	1.02
N	NR	155.22	4.9	3.1	0.6	169.7	2.82	99	109	151	172	7.3	2.9	2	0.5	2.15
N	NR	183.64	5.69	3.5	0.6	202.9	3.1	103	118	177	205	8.4	3.1	2.5	0.5	4.91
N	NR	117.6	2.1	1.3	0.4	125.7	1.12	100	101	115	127	2.9	1.2	1	0.5	0.3
N	NR	127.6	3.3	1.3	0.4	135.7	1.12	101.5	104	123.5	137	4.1	1.2	1	0.5	0.579
_			2.74	_	_	4547	_	100	_	140	457	_	_	1	_	0.885
N	NR	140.23 163.65	3.71 5.69	3.1	0.6	154.7 182.9	2.82	103	109	137	157	6.1	2.9	1.5	0.5	1.08
N N	NR NR	193.65	5.69	3.5	0.6	212.9	3.1	106 108	116 125	159 187	185 215	8.4	3.1	2.5	0.5	5.67
IN	INIK	195.05	5.09	5.5	0.0	212.9	5.1	100	125	107	215	0.4	5.1	2.5	0.5	5.07
N	NR	122.6	2.1	1.3	0.4	130.7	1.12	105	106	120	132	2.9	1.2	1	0.5	0.313
N	NR	137.6	3.3	1.9	0.6	145.7	1.7	106.5	110	133.5	147	4.7	1.7	1	0.5	0.785
_	_	_	_	_	_	_	_	105	_	145	_	_	_	1	_	0.91
N	NR	145.24	3.71	3.1	0.6	159.7	2.82	108	110	142	162	6.1	2.9	1.5	0.5	1.15
N	NR	173.66	5.69	3.5	0.6	192.9	3.1	111	122	169	195	8.4	3.1	2	0.5	3.14
N	NR	208.6	5.69	3.5	1	227.8	3.1	113	133	202	230	8.4	3.1	2.5	0.5	7
N	NR	127.6	2.1	1.3	0.4	135.7	1.12	110	111	125	137	2.9	1.2	1	0.5	0.33
N	NR	142.6	3.3	1.9	0.6	150.7	1.7	111.5	115	138.5	152	4.7	1.7	1	0.5	0.816
_	_	_	_	_	_	_	_	110	_	155	_	_	_	1	_	1.2
N	NR	155.22	3.71	3.1	0.6	169.7	2.82	114	119	151	172	6.1	2.9	2	0.5	1.59
N	NR	183.64	5.69	3.5	0.6	202.9	3.1	116	125	179	205	8.4	3.1	2	0.5	3.7
N	NR	217.0	6.5	4.5	1	237	3.5	118	134	212	239	9.6	3.5	2.5	0.5	8.05
N	NR	137.6	2.5	1.9	0.6	145.7	1.7	115	118	135	147	3.9	1.7	1	0.5	0.515
N	NR	147.6	3.3	1.9	0.6	155.7	1.7	116.5	120	143.5	157	4.7	1.7	1	0.5	0.849
_	_	_	_	_	_	_	_	115	_	165	_	_	_	1	_	1.46
N	NR	163.65	3.71	3.5	0.6	182.9	3.1	119	126	161	185	6.4	3.1	2	0.5	1.96
N	NR	193.65	5.69	3.5	0.6	212.9	3.1	121	132	189	215	8.4	3.1	2	0.5	4.36
N	NR	232.0	6.5	4.5	1	252	3.5	123	149	227	254	9.6	3.5	2.5	0.5	9.54
N	NR	147.6	2.5	1.9	0.6	155.7	1.7	125	128	145	157	3.9	1.7	1	0.5	0.555
N	NR	161.8	3.7	1.9	0.6	171.5	1.7	126.5	132	158.5	173	5.1	1.7	1	0.5	1.15
_	_	_	_	_	_	_	_	125	_	175	_	_	_	1	_	1.56
N	NR	173.66	3.71	3.5	0.6	192.9	3.1	129	136	171	195	6.4	3.1	2	0.5	2.07

³⁾ Sealed and shielded bearings are also available. 4) This dimension applies to sealed and shielded bearings.

⁵⁾ Does not include bearings with snap rings.








Contact sealed type (LLU)

d 120–170 mm

α	Boundary dimensions Basic load rating Fatigue Factor Allowable speed Bearing number													
E	Bounda	ary di	imensio	ns	Basic loa	ad rating	Fatigue	Factor	Allov		eed	Bear	ing num	ber
					dynamic	static	load limit		Grease	min ⁻¹ Oil				
		mn	n		k		kN		Open	Open		Open	Shie	elded
,	-		4)	$r_{ m Ns}$	<i>a</i>	<i>a</i>	<i>a</i>		type	týpe	LLU	týpe	or seale	d type 2)
d	D	В	$r_{\rm s min}^{1)}$	Min.	$C_{\rm r}$	C_{0r}	C_{u}	f_0	ZZ, Z	Z	LU		(See dr	awings)
120	215	40	2.1	_	172	131	7.95	14.4	2 900	3 400	2 000	6224	ZZ	LLU
120	260	55	3	_	229	185	10.5	13.5	2 600	3 100	1 700	6324	ZZ	LLU
	165	18	1 1	0.5	41.0	41.0	2.25	16.1	3 700	4 300	2.000	6826	ZZ	LLU
	180	24	1.1 1.5	0.5	72.0	67.5	3.65	16.1	3 500	4 100	2 000	6926	ZZ	LLU
	200	22	1.1	0.5	88.5	79.5	4.25	16.2	3 200	3 800		16026		LLU
130	200	33	2	0.5	118	101	5.70	15.8	3 200	3 800	1 900	6026	ZZ	LLU
	230	40	3	0.5	185	146	8.55	14.5	2 700	3 100	1 800	6226	ZZ	LLU
	280	58	4		254	214	11.7	13.6	2 400	2 800	_	6326	_	_
	200	50	4		254	214	11.7	15.0	2 400	2 800		0320		
	175	18	1.1	0.5	42.5	44.5	2.35	16.0	3 400	4 000	1 900	6828	ZZ	LLU
	190	24	1.5	0.5	74.0	71.5	3.70	16.6	3 200	3 800	1 800	6928	ZZ	LLU
140	210	22	1.1	_	91.0	85.0	4.35	16.4	3 000	3 500	_	16028	_	_
140	210	33	2	_	122	109	5.85	15.9	3 000	3 500	1 800	6028	ZZ	LLU
	250	42	3	_	184	150	8.40	14.8	2 500	2 900	1 600	6228	ZZ	LLU
	300	62	4	_	280	246	13.0	13.6	2 200	2 600	_	6328	_	_
	190	20	1.1	0.5	53.0	55.0	2.80	16.1	3 100	3 700	1 700	6830	ZZ	LLU
	210	28	2	U.5 —	94.0	90.5	4.55	16.1	3 000	3 500	1 700	6930	ZZ	
	225	24	1.1	_	107	101	5.00	16.4	2 800	3 200	1 700	16030		LLU
150	225	35	2.1		139	126	6.55	15.9	2 800	3 200	1 700	6030	ZZ	LLU
	270	45	3	_	195	168	9.05	15.1	2 300	2 700	1 500	6230	ZZ	LLU
	320	65	4		305	284	14.5	13.1	2 100	2 400	_	6330	_	_
	320	05	4		303	204	14.5	15.9	2 100	2 400		0330		
	200	20	1.1	0.5	53.5	57.0	2.82	16.1	2 900	3 400	1 600	6832	ZZ	LLU
	220	28	2	_	96.5	96.0	4.65	16.6	2 800	3 300	1 600	6932	ZZ	LLU
160	240	25	1.5	_	109	108	5.10	16.5	2 600	3 000	_	16032	_	_
100	240	38	2.1	_	158	144	7.30	15.9	2 600	3 000	1 600	6032	ZZ	LLU
	290	48	3	_	205	186	9.45	15.4	2 100	2 500	_	6232	_	_
	340	68	4	_	310	286	14.2	13.9	1 900	2 300	_	6332	_	_
	215	22	1.1	_	66.5	70.5	3.35	16.1	2 700	3 200	_	6834	ZZ	_
	230	28	2		95.0	95.5	4.50	16.5	2 600	3 100		6934	ZZ	
	260	28	1.5		131	128	5.90	16.4	2 400	2 800		16034		
170	260	42	2.1	_	187	172	8.55	15.8	2 400	2 800	_	6034	ZZ	_
	310	52	4		235	223	11.1	15.3	2 000	2 400		6234		
	360	72	4		360	355	17.0	13.6	1 800	2 100		6334	_	
	300	12	-		300	333	17.0	15.0	1 000	2 100		0334		

1) Smallest allowable dimension for chamfer dimension r. 2) This bearing number is for double sealed and double shielded type bearings, but single sealed and single shielded type are also available.



With snap ring

Deep Groove Ball Bearings

With snap ring

groove

Dynamic equivalent radial load $P_r = XF_r + YF_a$


•					
$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}}$	> e
Cor		X	Y	X	Y
0.172 0.345 0.689	0.19 0.22 0.26				2.30 1.99 1.71
1.03 1.38 2.07	0.28 0.30 0.34	1	0	0.56	1.55 1.45 1.31
3.45 5.17 6.89	0.38 0.42 0.44				1.15 1.04 1.00


Static equivalent radial load $P_{0r} = 0.6F_r + 0.5F_a$ When $P_{0r} < F_r$ use $P_{0r} = F_r$.

Bea num	ring nber		p ring limens		е	Snap dimen	sions		Insta	llation-	relate	d dim	ensio	ns		Mass 5
C/C	3)		mm	1		mr	n				mm					kg
(See dr	nap ring ³⁾ awings)	D_1 Max.	a Max.	<i>b</i> Min.	$r_{ m o}$ Max.	D_2 Max.	f Max.	Min.	l _a Max. ⁴⁾	D_{a} Max.	$D_{ m X}$ (approx.)	$C_{ m Y}$ Max.	$C_{\rm Z}$ Min.	$r_{ m as}$ Max.	$r_{ m Nas}$ Max.	(approx.)
N —	NR —	217.0 —	6.5 —	4.5 —	1	227.8 —	3.1	131 133	143 162	204 247	230 —	9.2 —	3.1	2.5	0.5 —	5.15 12.4
N	NR	161.8 176.8	3.3	1.9 1.9	0.6	171.5	1.7	136.5	139.5 144	158.5 172	173 188	4.7 5.1	1.7 1.7	1 1.5	0.5	0.8
N —	NR —	_			_	186.5	1.7	138 136.5	_	193.5	_	_	_	1	0.5	1.52 2.31
N N	NR NR —	193.65 222.0	5.69 6.5 —	3.5 4.5 —	0.6 1 —	212.9 242 —	3.1 3.5 —	139 143 146	148 158 —	191 217 264	215 244 —	8.4 9.6 —	3.1 3.5 —	2 2.5 3	0.5 0.5 —	3.16 5.82 15.3
N	NR	171.8	3.3	1.9	0.6	181.5	1.7	146.5	150	168.5	183	4.7	1.7	1	0.5	0.85
N —	NR —	186.8	3.7	1.9	0.6	196.5 —	1.7	148 146.5 149	154 — 158	182 203.5 201	198 —	5.1	1.7	1.5 1 2	0.5 —	1.62 2.45 3.35
N —	NR —	242.0	6.5	4.5 —	1	262	3.5	153 156	173 —	237 284	264 —	9.6	3.5	2.5	0.5	7.57 18.5
N	NR	186.8	3.3	1.9	0.6	196.5	1.7	156.5	161	183.5	198	4.7	1.7	1	0.5	1.16
_	_	_	_	_	_	_	_	159 156.5	167	201 218.5	_	_	_	2	_	2.47 3.07
_	_	_	_	_	_	_	_	161 163	169 188	214 257	_	_	_	2 2.5	_	4.08 9.41
_	_	_	_	_	_	_	_	166	_	304	_	_	_	3	_	22
N —	NR —	196.8 —	3.3	1.9	0.6	206.5 —	1.7	166.5 169	171 178	193.5 211	208 —	4.7 —	1.7	1	0.5	1.23 2.61
_	_	_	_	=	=	_	_	168 171	 183	232 229	_	_	_	1.5 2	=	3.64 5.05
_	_	_	_	_	_	_	_	173 176	_	277 324	_	_	_	2.5 3	_	11.7 26
_	_	_	_	_	_	_	_	176.5	182	208.5	_	_	_	1	_	1.63
_	_	_	_	_	_	_	_	179	188	221	_	_	_	2	_	2.74
_	_	_	_	_	_		_	178		252	_	_	_	1.5	_	4.93
_			_	_	_	_	_	181	196	249	_	_	_	2	_	6.76
_	_			_		_	_	186 186	_	294 344	_		_	3	_	14.5 30.7

³⁾ Sealed and shielded bearings are also available. 4) This dimension applies to sealed and shielded bearings.

⁵⁾ Does not include bearings with snap rings.





Open type

d 180-260 mm

	Boundary dimensions Basic load rating Fatigue Factor Allowable speed Bearing													
	В	Boundar	y dimens	sions	Basic loa dynamic	ad rating static	Fatigue Ioad Iimit	Factor	Allowab	le speed	Bearing number			
			mm			N	kN		_ mii	n ⁻¹				
		_			~	~	~		Grease	Oil				
C	l	D	B	$r_{\rm s min}^{1)}$	$C_{\rm r}$	C_{0r}	C_{u}	f_0	lubrication	lubrication	Open type			
		225	22	1.1	67.0	73.0	3.40	16.1	2 600	3 000	6836			
		250	33	2	122	119	5.45	16.5	2 400	2 900	6936			
18	20	280	31	2	129	134	5.85	16.5	2 300	2 700	16036			
10	0	280	46	2.1	210	199	9.70	15.6	2 300	2 700	6036			
		320	52	4	252	241	11.9	15.1	1 900	2 200	6236			
		380	75	4	390	405	19.0	13.9	1 700	2 000	6336			
		240	24	1.5	81.0	88.0	4.00	16.1	2 400	2 900	6838			
		260	33	2	125	127	5.65	16.6	2 300	2 700	6938			
		290	31	2	149	156	6.70	16.6	2 100	2 500	16038			
19	90	290	46	2.1	218	215	10.1	15.8	2 100	2 500	6038			
		340	55	4	282	281	13.5	15.0	1 800	2 100	6238			
		400	78	5	395	415	18.9	14.1	1 600	1 900	6338			
		250	24	1.5	82.0	91.5	4.05	16.1	2 300	2 700	6840			
		280	38	2.1	174	168	7.45	16.2	2 200	2 600	6940			
		310	34	2	157	160	6.65	16.6	2 000	2 400	16040			
20	00	310	51	2.1	241	243	11.2	15.6	2 000	2 400	6040			
		360	58	4	298	310	14.4	15.2	1 700	2 000	6240			
		420	80	5	455	500	22.3	13.8	1 500	1 800	6340			
		270	24	1.5	84.5	98.0	4.15	16.0	2 100	2 400	6844			
		300	38	2.1	178	180	7.55	16.4	2 000	2 300	6944			
22	20	340	37	2.1	200	216	8.65	16.5	1 800	2 200	16044			
		340	56	3	267	289	12.5	15.8	1 800	2 200	6044			
		400	65	4	330	365	15.8	15.3	1 500	1 800	6244			
		460	88	5	455	520	22.0	14.3	1 400	1 600	6344			
		300	28	2	94.0	112	4.55	15.9	1 900	2 200	6848			
		320	38	2.1	188	203	8.05	16.5	1 800	2 100	6948			
24	10	360	37	2.1	197	217	8.30	16.5	1 700	2 000	16048			
		360	56	3	276	310	12.8	16.0	1 700	2 000	6048			
		320	28	2	96.5	120	4.65	15.8	1 700	2 000	6852			
		360	46	2.1	245	280	10.9	16.3	1 600	1 900	6952			
26	0	400	44	3	252	299	11.1	16.5	1 500	1 800	16052			
		400	65	4	325	375	15.1	15.8	1 500	1 800	6052			

Dynamic equivalent radial load $P_r = XF_r + YF_a$


e	$\frac{F_{\rm a}}{F_{\rm r}}$	$\leq e$	$\frac{F_{\rm a}}{F_{\rm r}}$	> <i>e</i>
	X	Y	X	Y
0.19 0.22 0.26 0.28 0.30 0.34 0.38 0.42	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15 1.04
	0.19 0.22 0.26 0.28 0.30 0.34 0.38	$ \begin{array}{c c} e & \overline{F_r} \\ \hline X \\ \hline 0.19 \\ 0.22 \\ 0.26 \\ 0.28 \\ 0.30 \\ 0.34 \\ 0.34 \\ 0.38 \\ 0.42 \\ \end{array} $	$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	$\begin{array}{c ccccccccccccccccccccccccccccccccccc$


Static equivalent radial load $P_{0\mathrm{r}} = 0.6F_{\mathrm{r}} + 0.5F_{\mathrm{a}}$ When $P_{0\mathrm{r}} < F_{\mathrm{r}}$ use $P_{0\mathrm{r}} = F_{\mathrm{r}}$.

Illation-re dimension		Mass
$\overset{mm}{D_{a}}$ Max.	$r_{ m as}$ Max.	kg (approx.)
218.5	1	2.03
241	2	4.76
271	2	6.49
269	2	8.8
304	3	15.1
364	3	35.6
232	1.5	2.62
251	2	4.98
281	2	6.77
279	2	9.18
324	3	18.2
380	4	41
242	1.5	2.73
269	2	7.1
301		8.68
	_	11.9
		21.6
400	4	46.3
262	1.5	3
	2	7.69
		11.3
		15.7
		30.2
440	4	60.8
291	2	4.6
309	_	8.28
349		12.1
347	2.5	16.8
311	2	5
349	2	13.9
387	2.5	18.5
384	3	25
	$\begin{array}{c} \text{mm} \\ D_a \\ \text{Max}. \\ 218.5 \\ 241 \\ 271 \\ 269 \\ 304 \\ 364 \\ \\ 232 \\ 251 \\ 281 \\ 279 \\ 324 \\ 380 \\ \\ 242 \\ 269 \\ 301 \\ 299 \\ 344 \\ 400 \\ \\ 262 \\ 289 \\ 329 \\ 327 \\ 384 \\ 440 \\ \\ 291 \\ 309 \\ 349 \\ 347 \\ \\ 311 \\ 349 \\ 387 \\ \end{array}$	Da Max. ras Max. 218.5 1 241 2 271 2 269 2 304 3 364 3 232 1.5 251 2 281 2 279 2 324 3 380 4 242 1.5 269 2 301 2 299 2 344 3 400 4 262 1.5 289 2 329 2 329 2 327 2.5 384 3 440 4 291 2 349 2 347 2.5 311 2 349 2 387 2.5

B-35 B-34

¹⁾ Smallest allowable dimension for chamfer dimension r.





Open type

d 280-440 mm

a 200-440 Hilli											
	Boundar	y dimens	sions		oad rating	Fatigue Joad	Factor	Allowab	le speed	Bearing number	
		mm		dynamic static kN		limit kN		mi Grease	n ⁻¹ Oil		
d	D	В	$r_{\rm s min}^{1)}$	$C_{\rm r}$	C_{0r}	C_{u}	f_0		lubrication	Open type	
	350	33	2	151	177	6.65	16.1	1 600	1 900	6856	
28	380	46	2.1	252	299	11.1	16.5	1 500	1 800	6956	
28	420	44	3	257	315	11.3	16.5	1 400	1 600	16056	
	420	65	4	360	420	16.9	15.5	1 400	1 600	6056	
	380	38	2.1	179	210	7.60	16.1	1 500	1 700	6860	
	420	56	3	305	375	13.7	16.2	1 400	1 600	6960	
30	460	50	4	325	410	14.5	16.3	1 300	1 500	16060	
	460	74	4	395	480	18.4	15.6	1 300	1 500	6060	
	400	38	2.1	186	228	7.95	16.1	1 400	1 600	6864	
	440	56	3	315	405	14.1	16.4	1 300	1 500	6964	
32	480	50	4	335	440	14.9	16.4	1 200	1 400	16064	
	480	74	4	410	530	19.3	15.7	1 200	1 400	6064	
	420	38	2.1	189	236	8.05	16.0	1 300	1 500	6868	
	460	56	3	325	430	14.4	16.5	1 200	1 400	6968	
34	520	57	4	380	515	17.0	16.3	1 100	1 300	16068	
	520	82	5	465	610	21.9	15.6	1 100	1 300	6068	
	440	38	2.1	207	258	8.55	16.0	1 200	1 400	6872	
	400	56	3	330	455	14.8	16.5	1 100	1 300	6972	
36	o 540	57	4	390	550	17.6	16.4	1 100	1 200	16072	
	540	82	5	485	670	23.0	15.7	1 100	1 200	6072	
	340	02	<u> </u>	403	070	25.0	15.7	1 100	1200	0072	
	480	46	2.1	256	340	10.8	16.1	1 100	1 300	6876	
38		65	4	360	510	15.9	16.6	1 100	1 200	6976	
	560	82	5	505	725	24.1	15.9	990	1 200	6076	
	500	46	2.1	251	340	10.6	16.0	1 100	1 200	6880	
40	0 540	65	4	370	535	16.4	16.5	990	1 200	6980	
	600	90	5	565	825	26.9	15.7	930	1 100	6080	
	520	46	2.1	288	405	12.4	16.1	1 000	1 200	6884	
42	o 560	65	4	380	560	16.8	16.4	940	1 100	6984	
	620	90	5	590	895	28.3	15.8	880	1 000	6084	
	540	46	2.1	292	420	12.6	16.0	950	1 100	6888	
44	600	74	4	405	615	18.0	16.4	890	1 000	6988	
4) 0		In Land Sec.		- l C l' -		-0.0		000			

¹⁾ Smallest allowable dimension for chamfer dimension r.

Dynamic equivalent radial load $P_r = XF_r + YF_a$


Deep Groove Ball Bearings


$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}} > e$			
C0r		X	Y	X	Y		
0.172 0.345 0.689 1.03 1.38 2.07 3.45	0.19 0.22 0.26 0.28 0.30 0.34 0.38	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15		
5.17 6.89	0.42 0.44				1.04 1.00		

Static equivalent radial load $P_{0r} = 0.6F_r + 0.5F_a$

When $P_{0r} < F_r$ use $P_{0r} = F_r$.

	allation-re dimensior		Mass
d_{a}	$D_{ m a}$	$r_{ m as}$ Max.	kg
Min.	Max.	Max.	(approx.)
289	341	2	7.4
291	369	2	14.8
293	407	2.5	23
296	404	3	31
311	369	2	10.5
313	407	2.5	23.5
316	444	3	32.5
316	444	3	43.8
331	389	2	10.9
333	427	2.5	24.8
336	464	3	34.2
336	464	3	46.1
		_	
351	409	2	11.5
353	447	2.5	26.2
356	504	3	47.1
360	500	4	61.8
371	429	2	12.3
373	467	2.5	27.5
376	524	3	49.3
380	520	4	64.7
204	460	2	40.7
391 396	469 504	2	19.7 39.8
400	540	4	67.5
400	340	-	07.5
411	489	2	20.6
416	524	3	41.6
420	580	4	87.6
431	509	2	21.6
436	544	3	43.4
440	600	4	91.1
		•	
451	529	2	22.5
456	584	3	60





Open type

d 460-600 mm

	Boundary	/ dimens	sions	Basic loa	d rating	Fatigue load	Factor	Allowab	le speed	Bearing number
	mm			dynamic static kN		limit kN		mir Grease	n ⁻¹ Oil	number
d	D	B	$r_{\rm s min}^{1)}$	$C_{\rm r}$	C_{0r}	C_{u}	f_0	lubrication	lubrication	Open type
460	580 620	56 74	3 4	350 415	515 645	15.1 18.5	16.2 16.4	900 850	1 100 1 000	6892 6992
480	600 650	56 78	3 5	355 480	540 770	15.4 21.5	16.1 16.5	860 810	1 000 950	6896 6996
500	620 670	56 78	3 5	360 490	560 805	15.7 22.2	16.1 16.5	820 770	970 910	68/500 69/500
530	650	56	3	365	580	15.9	16.0	770	900	68/530
560	680	56	3	370	600	16.1	16.0	710	840	68/560
600	730	60	3	415	705	18.2	16.0	660	780	68/600

Dynamic equivalent radial load $P_r = XF_r + YF_a$

Deep Groove Ball Bearings

$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}} > e$			
Cor		X	Y	X	Y		
0.172 0.345 0.689 1.03 1.38 2.07 3.45 5.17 6.89	0.19 0.22 0.26 0.28 0.30 0.34 0.38 0.42 0.44	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15 1.04 1.00		

Static equivalent radial load $P_{0r} = 0.6F_r + 0.5F_a$


When $P_{0r} < F_r$ use $P_{0r} = F_r$.

	allation-re dimension		Mass
$d_{ m a}$ Min.	$\begin{array}{c} \operatorname{mm} \\ D_{\operatorname{a}} \\ \operatorname{Max.} \end{array}$	$r_{ m as}$ Max.	kg (approx.)
473 476	567 604	2.5 3	34.8 62.2
493 500	587 630	2.5 4	36.2 73
513 520	607 650	2.5 4	37.5 75.5
543	637	2.5	39.5
573	667	2.5	41.5
613	717	2.5	51.7







(ZZ)



sealed type (LLB)



sealed type (LLH)





Contact sealed type (LLU)

d 10-50 mm

Open type

a	10-	-50	mm													
Bou	indary	dim/	ensions	Basic loa	ad rating			Factor	1	Allowable			Bear	ing nur	nber	
d	r D	mm	$r_{\mathrm{s}\mathrm{min}}^{1)}$	dynamic k $C_{ m r}$		load limit kN	load kN $C_{ m p}$	f_0	Grease Open type ZZ, LLB Z, LB	min Oil Open type Z, LB	LLH LH	LLU LU	Open type	or sea	nielded lled typ drawin	oe ²⁾
u	26	8	0.3	5.05		0.138	1.65	12.4	29 000	34 000			EC-6000		B LLH	
10	30 35	9	0.6 0.6	5.65 9.10	2.39	0.182 0.273	2.39 3.45	13.2 11.4	25 000 23 000	30 000 27 000	21 000	18 000	EC-6200 EC-6300	ZZ LL	B LLH B LLH	LLU
12	28 32 37	8 10 12	0.3 0.6 1	5.65 6.75 10.8	2.75	0.182 0.214 0.325	1.78 2.29 3.65	13.2 12.7 11.1	26 000 22 000 20 000	30 000 26 000 24 000	20 000	16 000	EC-6001JRX EC-6201 EC-6301	ZZ LL	B LLH B LLH B LLH	LLU
15	32 35 42	9 11 13	0.3 0.6 1	6.20 8.60 12.7	3.60	0.199 0.279 0.425	2.83 2.78 4.40	13.9 12.7 12.3	22 000 19 000 17 000	26 000 23 000 21 000	18 000	15 000	EC-6002 EC-6202 EC-6302	ZZ LL	B LLH B LLH B LLH	LLU
17	35 40 47	10 12 14	0.3 0.6 1	7.55 10.6 15.0	4.60	0.263 0.243 0.355	2.88 3.45 6.55		20 000 18 000 16 000	24 000 21 000 19 000	15 000	12 000	EC-6003 EC-6203 EC-6303	ZZ LL	B LLH B LLH B LLH	LLU
20	47	12 14 15	0.6 1 1.1	10.4 14.2 17.6	6.65	0.355 0.505 0.615	5.05 5.05 7.90	13.9 13.2 12.4	18 000 16 000 14 000	21 000 18 000 17 000	12 000	10 000	EC-6004 EC-6204 EC-6304	ZZ LL	B LLH B LLH B LLH	LLU
25	47 52 62	12 15 17	0.6 1 1.1	11.2 15.5 23.5	5.85 7.85 10.9	0.380 0.550 0.855	5.85 6.55 10.9	14.5 13.9 12.6	15 000 13 000 12 000	18 000 15 000 14 000	11 000 11 000 9 700	8 900	EC-6005 EC-6205 EC-6305	ZZ LL	B LLH B LLH B LLH	LLU
30	55 62 72	13 16 19	1 1 1.1	14.7 21.6 29.5	8.30 11.3 15.0	0.650 0.795 1.14	8.30 9.85 15.0	14.8 13.8 13.3	13 000 11 000 10 000	15 000 13 000 12 000	9 200 8 800 7 900	7 300	EC-6006 EC-6206 EC-6306	ZZ LL	B LLH B LLH B LLH	LLU
35	62 72 80	14 17 21	1 1.1 1.5	17.7 28.4 37.0	10.3 15.3 19.1	0.805 1.09 1.47	10.3 14.5 18.5	14.8 13.8 13.1	12 000 9 800 8 800	14 000 11 000 10 000	8 200 7 600 7 300	6 300	EC-6007 EC-6207 EC-6307	ZZ LL	B LLH B LLH B LLH	LLU
40	68 80 90	15 18 23	1 1.1 1.5	18.6 32.5 45.0	11.5 17.8 24.0	0.890 1.24 1.83	11.5 17.5 23.4	15.2 14.0 13.2	10 000 8 700 7 800	12 000 10 000 9 200	7 300 6 700 6 400	5 600	EC-6008 EC-6208 EC-6308	ZZ LL	B LLH B LLH B LLH	LLU
45	75 85 100	16 19 25	1 1.1 1.5	23.2 36.0 58.5	15.1 20.4 32.0	1.16 1.60 2.50	15.1 20.3 27.4	15.3 14.1 13.1	9 200 7 800 7 000	11 000 9 200 8 200	6 500 6 200 5 600	5 200	EC-6009 EC-6209 EC-6309	ZZ LL	B LLH B LLH B LLH	LLU
	80	16	1	24.2	16.6	1.24	16.6	15.5	8 400	9 800	6 000		EC-6010		B LLH	
50	90	20 27	1.1	39.0 68.5	23.2 38.5	1.82 2.99	17.7 33.0	14.4 13.2	7 100 6 400	8 300 7 500	5 700 5 000		EC-6210 EC-6310		B LLH B LLH	LLU
			-	30.0	20.0		30.0	10.2	0 .00		5 5 5 5	0				





Dynamic equivalent radial load $P_{\rm r} = XF_{\rm r} + YF_{\rm a}$

$\frac{f_0 \cdot F_a}{C_{0r}}$	e	$\frac{F_{\rm a}}{F_{\rm r}}$	≤ <i>e</i>	$\frac{F_{\rm a}}{F_{\rm r}}$	> e
Cor		X	Y	X	Y
0.172 0.345 0.689 1.03 1.38 2.07 3.45 5.17 6.89	0.19 0.22 0.26 0.28 0.30 0.34 0.38 0.42 0.44	1	0	0.56	2.30 1.99 1.71 1.55 1.45 1.31 1.15 1.04 1.00

Static equivalent radial load $P_{0r} = 0.6F_{r} + 0.5F_{a}$


When $P_{0r} < F_r$ use $P_{0r} = F_r$.

li	nstallatio dimen		ed	Mass
	mi			kg
Min.	d _a Max. ³⁾	D_{a} Max.	$r_{ m as}$ Max.	Open type (approx.)
12	13.5	24	0.3	0.019
14	16	26	0.6	0.031
14	17	31	0.6	0.051
14	16	26	0.3	0.021
16	17.5	28	0.6	0.036
17	18.5	32	1	0.058
17	19	30	0.3	0.029
19	20.5	31	0.6	0.043
20	23	37	1	0.079
19	21	33	0.3	0.037
21	23	36	0.6	0.062
22	25	42	1	0.11
24	26	38	0.6	0.066
25	28	42	1	0.101
26.5	28.5	45.5	1	0.139
29	30.5	43	0.6	0.075
30	32	47	1	0.122
31.5	35	55.5	1	0.223
35	37	50	1	0.11
35	39	57	1	0.191
36.5	43	65.5	1	0.334
40	42	57	1	0.148
41.5	45	65.5	1	0.277
43	47	72	1.5	0.44
45	47	63	1	0.183
46.5	51	73.5	1	0.352
48	54	82	1.5	0.609
50	52.5	70	1	0.233
51.5	55.5	78.5	1	0.391
53	61.5	92	1.5	0.80
55	57.5	75	1	0.246
56.5	60	83.5	1	0.444
59	68.5	101	2	1.03


³⁾ This dimension applies to sealed and shielded bearings.









(ZZ)



sealed type (LLB)



sealed type (LLH)




Contact sealed type (LLU)

d 10-45 mm

Open type

u	-0	т.	, , , , , , , , ,												
Во	undary	din d	nensions	Basic loa	nd rating			Factor	1	Allowable			Bear	ng numbe	r
				dunamia	atatia	load	load		Crosss	min ⁻ Oil	-1				
		mm		dynamic kl		limit kN	kN		Grease Open type	Open type			Open type	Shield	led
,	-		43	~	<i>a</i>	~	~		ZZ, LĹB	Z, LB	LLH	LLU	-1 51	or sealed	type 2)
d	D	В	$r_{\rm s min}^{1)}$	$C_{\rm r}$	C_{0r}	C_{u}	C_{p}	f_0	Z, LB		LH	LU		(See drav	vings)
	26	8	0.3	5.05	1.96	0.138	1.53	12.4	29 000	34 000	25 000	21 000	AC-6000	ZZ LLB L	LH LLU
10	30	9	0.6	5.65	2.39	0.182	2.39	13.2	25 000	30 000	21 000	18 000	AC-6200	ZZ LLB L	LH LLU
	35	11	0.6	9.10	3.50	0.273	2.98	11.4	23 000	27 000	20 000	16 000	AC-6300	ZZ LLB L	LH LLU
		_													
	28	8	0.3	5.65		0.182	1.73		26 000	30 000			AC-6001JRX		
12		10	0.6	6.75		0.214		12.7	22 000	26 000			AC-6201	ZZ LLB L	
	37	12	1	10.8	4.20	0.325	3.00	11.1	20 000	24 000	19 000	15 000	AC-6301	ZZ LLB L	LH LLU
	32	9	0.3	6.20	2.83	0.199	2.43	13 9	22 000	26 000	18 000	15 000	AC-6002	ZZ LLB L	IH IIU
15		11	0.6	8.60		0.279		12.7	19 000	23 000			AC-6202	ZZ LLB L	
	42	13	1	12.7		0.425	3.90		17 000	21 000			AC-6302	ZZ LLB L	
	35	10	0.3	7.55	3.35	0.263	2.44	13.6	20 000	24 000	16 000	14 000	AC-6003	ZZ LLB L	LH LLU
17	40	12	0.6	10.6	4.60	0.243	3.50	12.8	18 000	21 000	15 000	12 000	AC-6203	ZZ LLB L	LH LLU
	47	14	1	15.0	6.55	0.355	5.10	12.2	16 000	19 000	14 000	11 000	AC-6303	ZZ LLB L	LH LLU
	42	12	0.6	10.4	E 0E	0.355	3.80	12.0	18 000	21 000	12 000	11 000	AC-6004	ZZ LLB L	
20		14	1	14.2		0.505	4.20		16 000	18 000			AC-6004 AC-6204	ZZ LLB L	
20	52	15	1.1	17.6		0.505	5.40		14 000	17 000			AC-6204 AC-6304	ZZ LLB L	
	32	13	1.1	17.0	1.50	0.013	3.70	12.7	14 000	17 000	12 000	10 000	AC-0304	22 LLD L	LII LLO
	47	12	0.6	11.2	5.85	0.380	4.50	14.5	15 000	18 000	11 000	9 400	AC-6005	ZZ LLB L	LH LLU
25	52	15	1	15.5	7.85	0.550	5.80	13.9	13 000	15 000	11 000	8 900	AC-6205	ZZ LLB L	LH LLU
	62	17	1.1	23.5	10.9	0.855	7.30	12.6	12 000	14 000	9 700	8 100	AC-6305	ZZ LLB L	LH LLU
	55	13	1	14.7		0.650	6.85		13 000	15 000	9 200		AC-6006	ZZ LLB L	
30		16	1	21.6	11.3	0.795		13.8	11 000	13 000	8 800		AC-6206	ZZ LLB L	
	72	19	1.1	29.5	15.0	1.14	11.0	13.3	10 000	12 000	7 900	6 600	AC-6306	ZZ LLB L	LH LLU
	62	14	1	17.7	10.3	0.805	8.95	14.8	12 000	14 000	8 200	6 800	AC-6007	ZZ LLB L	LH LLU
35		17	1.1	28.4	15.3	1.09	9.65	13.8	9 800	11 000	7 600		AC-6207		LH LLU
	80	21	1.5	37.0	19.1	1.47	13.4	13.1	8 800	10 000	7 300		AC-6307	ZZ LLB L	
40	80	18	1.1	32.5	17.8	1.24	11.6	14.0	8 700	10 000	6 700		AC-6208	ZZ LLB L	
40	90	23	1.5	45.0	24.0	1.83	16.6	13.2	7 800	9 200	6 400	5 300	AC-6308	ZZ LLB L	LH LLU
	0.5	4.0	4.4	26.0	00.4	4.60	447	442	7.000	0.000		F 000	10.000		
45	85	19	1.1	36.0	20.4	1.60	14.7	14.1	7 800	9 200	6 200		AC-6209	ZZ LLB L	
	100	25	1.5	58.5	32.0	2.50	21.8	13.1	7 000	8 200	5 600	4 /00	AC-6309	ZZ LLB L	LH LLU

¹⁾ Smallest allowable dimension for chamfer dimension r. 2) This bearing number is for double sealed and double shielded type bearings, but single sealed and single shielded type are also available.



Installation-related

dimensions mm

 $d_{\rm a}$ Max.³⁾

13.5 24

16

12

14

 D_{a} Max.

26

 $r_{
m as}$ Max.

0.3

0.6

$r_{\rm a}$
$r_{\rm a}$
D_a ϕd_a

Static equivalent radial load
$P_{0r} = 0.6F_r + 0.5F_a$
When $P_{0r} < F_r$ use $P_{0r} = F_r$.

Dynamic equivalent radial load

2.30 1.99

1.71

1.55

1.31

1.04

1.00

0.56 1.45

0

 $P_{\rm r} = XF_{\rm r} + YF_{\rm a}$ $f_0 \cdot F_a$ C_{0r} 0.172 0.345

0.689

1.03

1.38 2.07 3.45

5.17

6.89

Mass

kg

Open type

(approx.)

0.019

0.031

0.19 0.22

0.26

0.28

0.30

0.34 0.38

0.42

0.44

14	10	20	0.0	0.031
14	17	31	0.6	0.051
14	16	26	0.3	0.021
16	17.5	28	0.6	0.036
17	18.5	32	1	0.058
17	19	30	0.3	0.029
19	20.5	31	0.6	0.043
20	23	37	1	0.079
19	21	33	0.3	0.037
21	23	36	0.6	0.062
22	25	42	1	0.11
24	26	38	0.6	0.066
25	28	42	1	0.101
26.5	28.5	45.5	1	0.139
29	30.5	43	0.6	0.075
30	32	47	1	0.122
31.5	35	55.5	1	0.223
35	37	50	1	0.11
35	39	57	1	0.191
36.5	43	65.5	1	0.334
40	42	57	1	0.148
41.5	45	65.5	1	0.277
43	47	72	1.5	0.44
46.5	51	73.5	1	0.352
48	54	82	1.5	0.609
51.5	55.5	78.5	1	0.391
53	61.5	92	1.5	0.8

³⁾ This dimension applies to sealed and shielded bearings.