Training Checklist: **Sysmex pocH-100i**

INSTRUCTIONS: The Trainee will initial next to each Training Task Description upon reviewing the contents of all checklist items. The Trainer will initial next to each Training Task Description upon training the Trainee. Upon successful completion of this training checklist, the Trainee and Trainer will sign and date the checklist at the end.

<table>
<tr><th>Training Task Description</th><th>Trainee Initials</th><th>Trainer Initials</th></tr>
<tr><td>Analyzer Operation
a) Know the different parts of the analyzer: sample analysis area, start switch, display.
b) Know there are different tube adapters for whole blood, control, and microtainers.
c) Know the different testing modes for whole blood and pre-dilute operational modes.
d) Know to press Top to revive from “Timer or Sleep Mode.”
e) Know that if Background check is acceptable, the main menu will appear.</td><td></td><td></td></tr>
<tr><td>External Quality Control (QC)
a) QC is run after daily start-up procedures are completed and background check passes, after a reagent lot number changes, after calibration, when there is an unusual shift or trend in patient results, after maintenance procedures, service call or component replacement, and after software change or upgrade.
b) There are 3 levels of QC that are run, a high, normal, and a low control.
c) Check the QC vials are not expired. Expired QC should not be used.
d) Prior to QC testing, warm QC samples to room temperature for 15 minutes. Mix tubes by holding horizontally between palms and rolling back and forth for 20-30 seconds. Invert tube 8-10 times until the red cell sediment is completely resuspended.
e) Select the correct lot number of QC sample that is to be analyzed on the screen.
f) Use the control blood adapter to place the QC tube in the instrument.
g) Ensure all control results are within the QC ranges for each level. (No flags)
h) If control results are not within the expected value ranges, repeat the testing or troubleshoot before rerunning the QC according to the procedure.</td><td></td><td></td></tr>
<tr><td>Maintenance
a) Know to complete daily, bi-weekly, quarterly, and as needed preventive maintenance procedures.
<table><tr><td colspan="2">DAILY</td></tr><tr><td></td><td>Daily Shutdown</td></tr><tr><td colspan="2">BI-WEEKLY</td></tr><tr><td></td><td>Clean Transducer</td></tr><tr><td colspan="2">QUARTERLY</td></tr><tr><td></td><td>Clean waste chamber</td></tr><tr><td colspan="2">AS NEEDED</td></tr><tr><td></td><td>Clean the sample tube adapter</td></tr><tr><td></td><td>Perform auto-rinse</td></tr><tr><td></td><td>Remove clog from transducer aperture</td></tr><tr><td></td><td>Dispose waste fluid</td></tr><tr><td></td><td>Drain reagents</td></tr><tr><td></td><td>Calibrate LCD</td></tr><tr><td></td><td>Replace thermal printer paper</td></tr><tr><td></td><td>Replace reagent</td></tr></table></td><td></td><td></td></tr>
<tr><td>Sample Handling
a) Understand to appropriately label patient tubes with patient’s information.
b) Whole blood samples collected into the EDTA lavender tube is used for the test.
c) Whole blood samples should not be clotted or hemolyzed.
d) Specimen is stable at room temperature for 8 hours and at 2-8C for 24h.
e) Specimens should be at least 250 uL in volume and if previously refrigerated, be at room temperature prior to testing.</td><td></td><td></td></tr>
</table>

Training Checklist: **Sysmex pocH-100i**

Test Procedure a) Instrument display should show “Ready” before patient testing. b) Select the mode – [WB] c) Enter the sample identification. d) Mix the sample by gentle inversion 10x. e) Remove the patient tube cap, set the sample into the adapter and close the door. f) Press Run.		
Results Interpretation a) Results that fall outside a laboratory action limit can also indicate the need to repeat the sample, notifying the physician, or sending out the sample for smear review confirmation.		
Support a) Know to call Sysmex Quality Control Program Phone when requiring technical assistance, troubleshooting, and error reports – 1 888 879 7639, or insight@sysmex.com		
Trainee to run <u>one</u> level of QC for any test and attach result printout to the end of this training.		

Trainee signature:		Date:	
Trainer signature:		Date:	