



Dimensions:

Height **129.5mm**

Width **102mm / 20 HP** (horizontal pitch)

Rear Depth **38mm**

Front Depth **16mm** (aka knob height)

Total Depth **55mm**

Electrical characteristics:

Max current draw: **90mA** (+12v) / **5mA** (-12v)

Pitch output voltage: **0-8** volts

CV output voltage: **0-8** volts

Gate output voltage: **0-5** volts

Clock output voltage: **0-5** volts

Clock input voltage: **10v** maximum

Reset input voltage: **10v** maximum

Power connector:

Super Sixteen requires a standard "Eurorack" -12V / +12V power supply (2x5 pin connector). The red stripe of the ribbon cable (-12V side) must be oriented on the same side as the "Red stripe" marking on the circuit board.

The complete manual can be found online at:

<http://extralifeinstruments.com/docs/super-sixteen/manual.pdf>