

## WizFi360io-C V1.0 Partlist

| Item | Q.ty | Reference              | Part                      | Tech. Characteristics                                       | Package   |
|------|------|------------------------|---------------------------|---|-----------|
| 1    | 4    | C1, C2, C3,C4          | 0.1uF                     | 50V-10% Ceramic   | CASE 0603 |
| 2    | 6    | R1, R2, R3, R4, R5, R6 | 4.7k                      | 1/10W-5% SMD  | CASE 0603 |
| 3    | 2    | R7, R8                 | 330R                      | 1/10W-5% SMD  | CASE 0603 |
| 4    | 1    | L1                     | HH-1M1608-121JT           | Not Mount   | CASE 0603 |
| 5    | 1    | LED1                   | Yellow LED                | CHIP-LED, Yellow  | CASE 0603 |
| 6    | 1    | LED2                   | Green LED                 | Not Mount   | CASE 0603 |
| 7    | 1    | JP1                    | 2.54mm 1x6 Pin Header DIP | Not Mount   | DIP       |
| 8    | 1    | JP2                    | 2.54mm 1x4 Pin Header DIP | Not Mount   | DIP       |
| 9    | 1    | JP4                    | SMW200-H06G               | 2.00mm Pitch Connector                                      | SMD       |
| 10   | 3    | Q1, Q2, Q3             | 2N7002                    | N Channel MOSFET  | SOT23     |
| 11   | 1    | U1                     | IL1117C-33ET              | 3.3V 1A CMOS LDO  | SOT223    |
| 12   | 1    | M1                     | WizFi360-PA               | WIZnet WiFi Module  | SMD       |
| 13   | 1    |                        | PCB                       | 2-Layer, 45mm x 25mm, PCB Color : Green, Silk Color : White |           |