## 1. Overview

This instruction provides an overview of the entire PTO Kitting process within the Zebra Kenosha DC. Please see the attached SWIs for instructions on specific functions; refer to the Kitting Process Flow.

## 2. Staging

1. Once the Picking team has picked the product, it must be physically moved to the PTO Kitting Drop-Zone area, which will trigger Oracle MWA to print a Pick Drop Audit Label.
2. Once the last drop of an order has occurred, the system will generate a PCR. The Picker will then verify that the LPN's/Quantity is correct.
   - ✓ If the check has not passed, please escalate to Lead/Supervisor.
3. The PCR will be collected by the Kitting Lead, who confirms the locations of the drops as well as the quantity.
   - ✓ The lead will write the locations on the PCR in pen for the Kitting Team.
4. The lead will either assign specific deliveries to Kitting Stations or place the PCR on top of the order, allowing the Stager to retrieve their order.

## 3. Workstation Setup

1. Before any kitting can begin, the workstation must be appropriately configured to ensure that Kitting can be completed as efficiently as possible. Please reference PTO Workstation Set Up.

   A) The process is designed to allow users to scan barcodes for all actions required to create a Kit or Overpack; the following items must be present.

   - ✓ Two PC Displays
   - ✓ Two printers
   - ✓ Barcodes (Validate and Close, packing station #, Validate/Close Overpack LPN)
   - ✓ Barcode Scanner
   - ✓ Fixed Industrial Scanner

2. The station should also contain a sheet containing two barcodes (zDss/Oracle).
   - ✓ The Oracle barcode is applicable for Kitting Associates.
3. The top-rack line, closest to the monitor, should be used for empty cartons; all the other cartons or bins for product go where the associate sees fit.


*This document contains proprietary information which is the exclusive property of Zebra Technologies Corp.*

**The most recent version of this document is located on the ISO Library.**
**Verify revision number before use.**

## 4. Back-End

1. The kitting station should ideally contain three associates, the first being the 'Stager', who gathers all the LPNs associated with that order in the staging area.
2. The Stager brings the LPNs to the assigned Kitting area, along with cartons that are either pre-formed or formed by the Backer.
3. Before the product and cartons are loaded into the Kitting racks, the Stager will do a count of the product.
   A) Using the PCR, verify that the 'Picked Quantity' matches the present quantity.
   B) Determine which product can be loaded into the racking with the cartons it came in, versus placing it into separate bins.
      ✓ If loading product into bins, perform an additional count of the picked product to ensure the quantity is correct.
4. The Stager will cut open the cartons and load the product into the racking.
   C) Once enough product has been loaded into the racking, the Splitter can begin its process, even if the Backer is still loading.
      ✓ If any product remains, please return it to the Picking Supervisor along with the Pick Ticket so that it may be reprocessed.
5. Additionally, the Stager will be responsible for ensuring that the Splitters and Packers have enough cartons to complete the Kitting order, including cartons used for the Overpack.
   ✓ The Stager will also be responsible for cleaning and sorting the back area as needed, which includes removing any empty cartons and preparing for the following order.

## 5. Splitting

1. Before any Kitting, Splitting or Consolidating can take place, the PCR should be inspected to ensure that no Country of Origin (COO) is left with 'XX'.
   A) Please bring to the attention of Leads/Supervisor and reference the following SWIs: Updating The Country of Origin For A Delivery and Country of Origin Validation.
2. Two applications are needed to pack the material into Kits successfully: Oracle ERP/MWA, along with the station's printer.
   ✓ Please ensure that the 'H-File' is enabled.
3. The Splitter will then want to consolidate all the LPNs associated with the order into one single LPN (Parent LPN). Reference LPN Consolidate After LPN Picks.


*This document contains proprietary information which is the exclusive property of Zebra Technologies Corp.*

**The most recent version of this document is located on the ISO Library.**
**Verify revision number before use.**

4. Once logged into the necessary application, please follow the SWI PTO – Kit Creation to create the individual kits.
   - ✓ Once in LPN Split, ensure that the options Serial Triggered, Each Pack, and Kitting are selected under Packing Process in Packing Initialization.
5. Once the kit's components have been scanned, validated, and closed, place the newly printed 'TXK' label neatly on the carton.

## 6. Packing

1. Like the Splitter, the associate who will be Packing will have Oracle ERP open at their station.
   - ✓ Verify that 'LPN Pack' is selected under the Packing Process.
2. Once the Packers ERP screen is situated, please follow the instructions provided in the PTO – Overpack Creation SWI.
3. Once the Overpack Carton is full and the LPN is closed, a 'TXB' label should be printed.
   - ✓ Check the PCR for DG instructions, apply the corresponding DG label, if applicable, on the carton, along with the TXB.
4. Ensure that the proper amount of dunnage is added to the Overpack carton.
5. The final step would be to merge the LPNs and remove the Parent-Child link.
   - ✓ Ensure Label is printed before anything is merged-up.

## 7. Stage Moving

1. Once enough Overpack cartons have been created, the entire pallet must be Stage Moved before another Overpack carton can be made, as described in SWI Stage Move.
2. Continue with the stage moving process for each Overpack created for the Delivery Order.
   A) 'Stage Move' locators are the locators assigned to the Staging Lanes.
   - ✓ PTO Kitting uses the subinventory 'CVS' for TXK/TXB/TX4P.
3. If a Delivery Order is larger than two pallets/25 cases, it will have to be consolidated into a 'TX4P'

*This document contains proprietary information which is the exclusive property of Zebra Technologies Corp.*

**The most recent version of this document is located on the ISO Library.**
**Verify revision number before use.**

## 8. References

| Document # | Document Title |
|---|---|
| | PTO Workstation Set Up |
| | Kitting Process Flow |
| | Updating The Country of Origin For A Delivery |
| | Country of Origin Validation |
| | LPN Consolidate After LPN Picks |
| | PTO – Overpack Creation |
| | Stage Move |
| | PTO – Kit Creation |

## 9. Revision History

The following table lists all revisions (including the original document) to this procedure, the date, and the reason for the revision.

| Rev. | Rev. Date | Description of Change | Revised By |
|---|---|---|---|
| 01 | 06/12/2025 | Original issue | V. Savic |


*This document contains proprietary information which is the exclusive property of Zebra Technologies Corp.*

**The most recent version of this document is located on the ISO Library.**
**Verify revision number before use.**