WORK INSTRUCTIONS INSPECTION CHECKLIST PROCESS			ZEBRA
Work Instruction No.			Zebra Technologies
Revision No. 01	Site Code WI03	Page 1 OF 3	

1. OVERVIEW

The purpose of this work instruction is to provide the procedure for completing the Inspection Checklist and who to contact in the event the Robot was mishandled.

2. INBOUND

1. Before releasing the driver ensure the bill of lading is marked accordingly if there were any signs of mishandling.
2. Obtain a copy of the *Fetch Robot Inspection Checklist Rev01*.
3. Write the date the Robot was received and the name of the receiver.
4. Write the Part number and the Serial # on the Checklist.
5. Enter your initials in the Accepted or Rejected columns when completing sections 1.1 – 1.3 of the Inspection Checklist.
6. Inspect the Crate and the indicators.
   - ✓ The crate should be free of damage and hand-written elements.
   - ✓ The ShockWatch label should not display red.
   - ✓ The Tip 'N' Tell Indicators should not have any blue particles on the arrow tip.

7. If there are NO rejections, place Inspection Checklist Rev01 in a white pouch and affix it to the crate.
8. Follow regular receiving and put away process.

Indicators Mishandled

9. If the indicators show signs of mishandling, informed VAS, and QA, the Robot needs to be taken out and visually inspected. Reference *F100 & accessories - Cosmetic Surface Classification.*
   - ✓ Mark the Bill of Lading accordingly, the logistics team might need to file a claim against the carrier.
10. If the Robot is damaged, take pictures of the damage and send an email to the logistics team – **Eva Mireles** – Logistics Analyst, and **Mike Alaimo** – Senior Mgr. Fetch Operations, **Shailesh Jaiswal** – Manufacturing Engineer, **Eloy Rodas** – Quality Engineer, **Christian Cox** – Test Engineer
11. Move the Material to MRB1 holding area and await disposition.
12. If the Robot is not damaged, remove the indicators that were activated with the mishandling.
    - ✓ Apply 2 new Tip 'N' Tell and remove the pin holder to activate them.
    - ✓ Ensure they are placed in perpendicular format, 1 on the side and 1 in the back.
    - ✓ Do not place them on the door where the hinges are located.

13. Make a note in the comments section of the Inspection Checklist if the indicators were replaced.
14. Move units to stock.

This document contains proprietary information which is the exclusive property of Zebra Technologies Corp.

The most recent version of this document is located on the ISO Library.
Verify revision number before use.

Missing Indicators

15. The Robot needs to be visually inspected if the Tip 'N' Tell and ShockWatch indicators are missing.
16. If there is no damage, apply new indicators and remove the pin holders to activate them.

Indicators on the Crate

17. The Robot needs to be visually inspected if the pin holders are still in place.
18. Pull the pin holders to activate the indicators if there is NO damage. Make a note on the inspection checklist.
19. If the pin holders are not in perpendicular format remove the old ones and apply new ones.
20. There should be only 2 Tip 'N' Tell indicators on the perpendicular side of the crate.

    ✓ Remove any additional Tip 'N' Tell indicators.

21. If there are multiple indicators on the crate and only 2 are activated no visual inspection is needed, remove the additional indicators, ensure they are in a perpendicular format, and pull the pin holders.
22. For any damage that is not resolvable on-site send pictures of damages to contacts listed below

    Mike Alaimo – Senior Mgr. Fetch Operations,
    Shailesh Jaiswal – Manufacturing Engineer, **Eloy Rodas** – Quality Engineer, **Elba Maya** – SC Planner, and the onsite QA Team.

23. Move the material to MRB1 and await disposition from the Team listed above.
24. Place the checklist in the white pouch affixed to the crate's front.

3. Pre-Charging

1. Pull the Inspection Checklist Rev01 from the pouch that is affixed to the crate.
2. Add the date that corresponds with the charging time instance.
3. Enter your initials in the Accepted or Rejected Columns when completing sections 2.1 – 2.7 of the Inspection Checklist.

   ✓ Initials will be needed every time we are charging the Robots.
   ✓ If we are charging the Robot more than 4 times a year, use another Checklist and staple it to the original.

4. For rejections that are not resolvable on site contact the individuals listed in Section 2.22.

   Resolvable on-site:

   - Cleaning fingerprints, wheels, dust, or particles and/or replacing the desiccant bags and/or the cover bag.

5. If Robot is not charged the same day, it was plugged in to be charged leave for overnight charging.
6. Ensure the charging status is verified if the Robot was left for overnight charging.

This document contains proprietary information which is the exclusive property of Zebra Technologies Corp.

The most recent version of this document is located on the ISO Library.
Verify revision number before use.

4. Post-Charging

1. Pull the Inspection Checklist Rev01 from the pouch that is affixed to the crate.
2. Enter your initials in the Accepted or Rejected Columns when completing sections 3.1 – 3.7 of the Inspection Checklist.
3. For rejections that are not resolvable on site contact the individuals listed in Section 2.22.

Resolvable on-site:

- Cleaning fingerprints, wheels, dust, or particles and/or replacing the desiccant bags and/or the cover bag.

4. If need to clean the Robot with a Microfiber cloth to remove any fingerprints, dust, or particles.
5. When Robot is ready to be put away, contact an Inbound associate, and put a green cone on the crate.

✓ Only contact the Inbound associate when the Robot is ready to be put away to prevent idle time.

5. References

Document #	Document Title
	Fetch Robot Inspection Checklist Rev01.pdf
	Process flow - Tip N Tell Indicator issues Rev01.pdf
	F100 & Accessories - Cosmetic Surface Classification Rev01.pdf
	Specification, Cosmetic Standards Rev01.pdf

6. Revision History

The following table lists all revisions (including the original document) to this procedure, the date, and the reason for the revision.

Rev.	Rev. Date	Description of Change	Revised By
01	07/10/23	Original issue	A.Cabrera

This document contains proprietary information which is the exclusive property of Zebra Technologies Corp.

The most recent version of this document is located on the ISO Library.
Verify revision number before use.