

1 Configuration eKanban

Basic configuration

If you want to install the e-kanban functions on an already existing HYDRA 8 system, proceed as described below:

1. Activate the patch dbp_mpl_ekanban as follows:
 - a. UNIX systems (run in the server prompt of the HYDRA directory):
`hydsr.out db_sql/dbp_mpl_ekanban.hsc`
 - b. Windows systems (run in a DOS window of the HYDRA directory):
`hydsr.exe db_sql/dbp_mpl_ekanban.hsc`
2. Check the patch output
3. Back up the existing dialog configuration:
 - a. UNIX systems:
`hydlgcfg.out DLGCFG.TYP=% DLGCFG.DLGUSR=% DLGCFG.DLG=%
DATEI=dialog.dlg`
 - b. Windows systems:
`hydlgcfg.exe DLGCFG.TYP=% DLGCFG.DLGUSR=% DLGCFG.DLG=%
DATEI=dialog.dlg`
4. Now load the new dialog configurations with the following command:
 - a. UNIX systems:
`hymw.out -u9999 -b db_sql/aip_kbn.dlg`
 - b. Windows systems:
`hymw.exe -u9999 -b db_sql/aip_kbn.dlg`

The dialogs KBN_BOARD, KBN_FILL, KBN_EMPTY are then imported **as template** (with type "AIPDEF" and dialog user "999") or existing dialogs are updated, if required.
5. Go to the MOC application: System administration → Terminals → Dynamic dialogs (transaction code ddconf). Copy the dialogs KBN_BOARD, KBN_FILL, KBN_EMPTY from the template (type "AIPDEF" with dialog user "999") to type "AIPDEF" and dialog user "0". To do so, switch to the HYDRA Professional Mode.
6. Activate the new dynamic dialogs:
 - a. UNIX systems:
`hydialog.scr AIPTNR 0`
 - b. Windows systems:
`sh.exe hydialog.scr AIPTNR 0`



This command activates the default dialogs. If you use terminal-specific dialogs in the system, these dialogs need to be modified by an MPDV consultant.

Configuration: Order types

Menu	Master data → Order → Order types
------	-----------------------------------

Configure one [Order type](#) for the kanban orders and one order type for the kanban capacity orders.

Kanban orders

You can use the preconfigured order type "KBN" as order type for kanban orders.

Kanban capacity orders

If you want to generate kanban orders from kanban capacity orders, you must create a separate order type (e.g. "ZKABA"). The behavior of the order type for kanban capacity orders must be similar to the behavior of production orders (order type 0).



Do not mix up the order type for kanban capacity orders (e.g. "ZKAPA") with the preconfigured order type 3.

Configuration: Order status texts

Menu	Master data → Order → Order status texts
------	--

Create a status text for planned kanban orders and operations:

Parameter name	Value
Status text	e.g. 901
Status text name	planned

Configuration: Order status

Menu	Master data → Order → Order status assignment
------	---

Configure the [status](#) "P" as order status "planned" for the order type, which is defined as order type for kanban orders (e.g. "KBN").

Parameter name	Value
----------------	-------

Parameter name	Value
Order type	e.g. "KBN"
Status	"P"
Entry: Control	S = None
Entry: can be logged on	☒
Planning: Planning	N = No planning
Options: Initial status during creation	☒

Configuration: Operation status

Menu	Master data → Order → Order status assignment
------	---

Configure the [status](#) "P" as order status "planned" for the order type, which is defined as order type for kanban orders (e.g. "KBN").

Parameter name	Value
Order type	e.g. "KBN"
Status	"P"
Entry: Control	S = None
Entry: can be logged on	☒
Entry: Sequencing list	☒
Planning: Planning	N = No planning
Options: Initial status during creation	☒

INI configuration

Menu	System administration → System settings → INI configuration System administration → System settings → INI data configuration
------	---

Configure in the [INI configuration](#) under the name "MPL" in the "KANBAN" section:

Key	Value (example)	Comment
KBN_AUART	KBN	Kanban order type
KAPA_AUART	ZKAPA	Capacity order type



If the INI configuration KAPA_AUART is enabled, the system searches for kanban capacity orders when kanban orders are generated. Work plans are no longer used then.

Configuration: Scheduler

Menu System administration → System settings → Scheduler

Make the following entry in the [Scheduler](#) to automatically generate kanban orders:

Type	S – Standard
Alterable	Yes
Type	I – Interval
Visible	Visible
Active	☒ Active
HYDRA user	0
Command (Windows)	sh.exe ./kbn_sgen.scr
Command (Unix)	kbn_sgen.scr
Comment	Generation of kanban orders
Interval	Hour: 1 Minute: 00

Configuration: Resource status configuration

Menu Master data → Resources → Resource status

Configure the following three kanban [resource statuses](#) for the kanban objects (resource type):

Resource key	type	Status (example)	Designation	
KBN		1	Initial	
KBN		102	Full	
KBN		103	Empty	

Configuration: Advanced object configuration

Menu System administration → System settings → Advanced object configuration

Specify in the [Advanced object configuration](#) which status is used:

Parameter name	Value
Object type	MPL
Object ID 1	Initial status, e.g. 1
Object ID 2	Status for filled kanban, e.g. 102
Object ID 3	Status for empty kanban, e.g. 103
Parameter	RESTYP
Parameter value	KBN

Configuration: Number ranges

Menu System administration → System settings → Number ranges

Create a [number range](#) for the kanban orders. This number range is used for the generation of kanban orders.

Parameter name	Value
Object	AUNR
Key	AART
Value	KBN (value from INI configuration for KBN_AUART)
Assignment code	NUM
Prefix	KBN (see below)
Range from	100000 (see below)
Range to	199999 (see below)
Current value	0



The number of digits resulting from <prefix> and range from/to must be identical to the order number length configured in the [Basic settings](#).

AIP configuration



Minimum AIP version for e-kanban: 2.0.2.80

Display of electronic kanban board

Configuration in ctaipplay.ini (AIP 8.1, AIP 8.2):

```
[WF@KBOARD]
CMD=DLG=LIST;u_l_kbn|MOD=B|KBN.TNR:ID=<*TNR>|
FILTER=
SECTION=Kanban table
DATAFIELDS=
FILE=kanban.lst
AUTOFILTERCOL=
KBN_INTERVAL=60
;ORDER=KBN.STA=-

[Kanban table]
GRID_FONT=Arial
GRID_FONTSIZE=9
GRID_COLOR=clBlack
GRID_BACKGROUND=clWhite

GRID_CELLPAINT=ON
EXAMINE_CELLBKCOLOR=STA1,KBN.STA,1-clLime|2-clYellow|3-clRed

;Status
ALIAS STA1=(DUMMY)=C1,50,L,Status
KBN.STA=C1,0,L
;Kanban material number
KBN.ATK=C25,145,Z
;Control loop
KBN.ID=C15,90,Z
;Withdraw
KBN.ZLO=C30,90,Z
;Total quantity of kanban objects in circulation
KBN.ANZ=N12,90,R
;Configured/ planned quantity of the kanban object
KBN.EGR:P=N10,90,R
;Full KBN
KBN.ANZ:F=N10,90,R
;Empty KBN
KBN.ANZ:E=N10,90,R
;Minimum stock level
KBN.MIN=N10,100,R
;Maximum stock level
KBN.MAX=N10,100,R
```

Extensions of the order list

You can add configurations in ctaipplay.ini, section "[sequencing list (auto)]" (AIP 8.1, AIP 8.2):

```
; Enable coloring specific to the cell:
GRID_CELLPAINT=ON
; KANBAN orders: orange (here AUART=KBN - can deviate)
EXAMINE_CELLBKCOLOR=COL1,AUART,KBN-$0080FF
; Foreground color: planned/prepared OPs
EXAMINE_SCANEXPR1=AST=P
EXAMINE_SCANCOLOR1=clGreen
EXAMINE_SCANEXPR2=AST=V
EXAMINE_SCANCOLOR2=clBlue
; Dummy column for orange coloring
ALIAS COL1=(DUMMY2)=C1,100,L
; required column as color reference (is not shown)
AUART=C1,0,L
```

Fill kanban

Configuration of list in ctaipplay.ini (AIP 8.1, AIP 8.2):

```
[control loops]
GRID_FONT=Arial
GRID_FONTSIZE=9
GRID_COLOR=clBlack
GRID_BACKGROUND=clWhite
GRID_CAPTION=control loops

;KBN.STA= C15,120,L
;KBN.ATK=C15,120,L
KBN.ID=C15,120,L
KBN.ZLO=C15,120,L
KBN.PUFFER=C15,120,L
KBN.ANZ=N4,80,R
KBN.MENGE=N4,80,R
KBN.ANZ:F=N4,80,R
KBN.ANZ:E=N4,80,R
KBN.MIN=N4,80,R
KBN.MAX=N4,80,R
KBN.EGR:P=N4,80,R

[Kanban objects]
GRID_FONT=Arial
GRID_FONTSIZE=9
GRID_COLOR=clBlack
GRID_BACKGROUND=clWhite
GRID_CAPTION=control loops

;KBN.STA= C15,120,L
;KBN.ATK=C15,120,L
;KBN.ID=C15,120,L
KBN.RES:NR=C15,120,L
```

```
KBN.RES:LNR=N4,80,R  
KBN.ZLO=C15,120,L  
KBN.PUFFER=C15,120,L  
KBN.ANZ=N4,80,R  
KBN.MENGE=N4,80,R  
KBN.ANZ:F=N4,80,R  
KBN.ANZ:E=N4,80,R  
KBN.MIN=N4,80,R  
KBN.MAX=N4,80,R  
KBN.EGR:P=N4,80,R
```

Configuration of keys in ctaipbut.ini (AIP 8.1):

```
<n1>=KBN_BOARD,electronic kanban board  
<n2>=KBN_FILL,fill KANBAN
```

with <nx>=1, 2, 3, ... - depending on where the buttons are placed.

Configuration of keys in I_main.xml (AIP 8.2)

- Create a backup of the file I_main.xml.
- Open the file I_main.xml using a text editor.
- Search for the text
`<Caption Function="Translate" LanguageKey="lkeKanban">eKanban</Caption>`
- In the row above, change the value from false to true:
`<Visible>True</Visible>`
- Save the file I_main.xml and restart the terminal.