2026 Edition

eCandle 2

Portable Power Station



- 300W 双向逆变
- 1004Wh 超大容量
- 220W MPPT 光伏输入
- 6000+次循环次数
- 磷酸铁锂电芯
- UPS 不间断电源

Model	eCandle 2
光伏输入	
最大光伏输入功率	220W
光伏输入电压范围	12~60V
交流输入	
输入电压范围	90-280Vac
输入频率范围	45~65Hz
最大交流输入功率	300W
交流输出	
额定交流输出功率（逆变器模式）	300W
额定交流输出电压（逆变器模式）	110V，220-240VAC可选
额定交流频率	50Hz/60Hz
UPS切换时间	≤10ms
交流输出端口数量	1
直流输出	
5521	12V/1.5A,18W Max(x1)
USB-A	5V/2.4A,9V/2A,15W Max(x2)
电池	
电池类型	LiFePO4 (Lithium Iron Phosphate)
电池容量	1004Wh Max
循环寿命	≥6000 Times
一般参数	
产品尺寸	272×135×195mm
产品重量	≈10kg
工作温度范围	0~55℃
存储温度范围	-20~55℃
环境湿度	10% 至 90% 相对湿度（无冷凝）
最大工作海拔	4000m，以 3000m 为基础，海拔每升高 200 m，规格最高温度降低 1℃。
电池电量指示器	4段式LED
WiFi/4G	Optional
散热方式	风冷
颜色	可定制
出厂SOC	50~60%
认证等级	UN38.3
保护功能	
交流输入欠压保护	Yes
交流输入过压保护	Yes
电池欠压保护	Yes
电池过压保护	Yes
交流输出欠压保护	Yes
交流输出过压保护	Yes
交流输出过载保护	Yes
交流输出短路保护	Yes
过温保护	Yes

2026 Edition

eCandle 2

Portable Power Station



- **300W Bidirectional Inverter**
- **220W MPPT Photovoltaic Input**
- **Lithium Iron Phosphate Battery**
- **1004Wh Ultra-High Capacity**
- **Over 6,000 Cycles**
- **UPS Uninterruptible Power Supply**

Model	eCandle 2
PV Input	
Max. PV Input Power	220W
PV Input Voltage Range	12~60V
AC Input	
Input Voltage Range	90-280Vac
Input Frequency Range	45~65Hz
Maximum AC Input Power	300W
AC Output	
Nominal AC Output Power (Inverter Mode)	300W
Nominal AC Output Voltage (Inverter Mode)	110，220-240VAC可选
Nominal AC Frequency	50Hz/60Hz
UPS Switch Time	≤10ms
Number of AC Output Ports	1
DC Output	
5521	12V/1.5A,18W Max(x1)
USB-A	5V/2.4A,9V/2A,15W Max(x2)
Battery	
Battery Type	LiFePO4 (Lithium Iron Phosphate)
Battery Energy	1004Wh Max
Cycle Life	≥6000 Times
General Data	
Product Dimensions	272×135×195mm
Product Weight	≈10kg
Operating Temperature Range	0~55℃
Storage Temperature Range	-20~55℃
Environmental Humidity	10% to 90% RH (Non-condensing)
Max. Operating Altitude	4000m, >3000m Temperature Derating (1℃ per 200m increase)
Battery Level Indicator	4-segment LED
WiFi/4G	Optional
Cool Method	Air-cooled
Color	Customizable
Shipping SOC	50~60%
Authentication Level	UN38.3
Protection	
AC Input Under Voltage Protection	Yes
AC Input Over Voltage Protection	Yes
Battery Under Voltage Protection	Yes
Battery Over Voltage Protection	Yes
AC Output Under Voltage Protection	Yes
AC Output Over Voltage Protection	Yes
AC Output Overload Protection	Yes
AC Output Short Circuit Protection	Yes
Over-Temperature Protection	Yes