



Home VoIP0

Physical **Config** Attributes

GLOBAL

Settings

Global Settings

Display Name Home VoIP0

Server Address 10.3.0.1

Router0

Physical Config **CLI** Attributes

IOS Command Line Interface

255K bytes of non-volatile configuration memory.
249856K bytes of ATA System CompactFlash 0 (Read/Write)

--- System Configuration Dialog ---

Would you like to enter the initial configuration dialog? [yes/no]: n

Press RETURN to get started!

```
Router>
Router>
Router>
Router>en
Router#conf t
Enter configuration commands, one per line. End with CNTL/Z.
Router(config)#int fa0/0
Router(config-if)#ip address 10.3.0.1 255.255.255.0
Router(config-if)#no sh

Router(config-if)#
%LINK-5-CHANGED: Interface FastEthernet0/0, changed state to up
%LINEPROTO-5-UPDOWN: Line protocol on Interface FastEthernet0/0, changed state to up
```

```
Router(config-if)#ip dhcp excluded-address 10.3.0.1
Router(config)#ip dhcp pool Telephony
Router(dhcp-config)#network 10.3.0.0 255.255.255.0
Router(dhcp-config)#default-router 10.3.0.1
Router(dhcp-config)#option 150 ip 10.3.0.1
Router(dhcp-config)#
```

```
Router(dhcp-config)#telephony-service
Router(config-telephony)#max-ephones 10
Router(config-telephony)#max-dn 10
Router(config-telephony)#ip source-address 10.3.0.1 port 2000
Router(config-telephony)#auto assign 1 to 10
```

