Vite

Copy Page

Install and configure shadcn/ui for Vite.

Choose the setup that matches your starting point.

Use shadcn/create	Use the CLI	Existing Project
generate a Vite project command.	Scaffold a new terminal.	Configure existing Vite project.

Menu 127k New

Use shadcn/create

1 Build Your Preset

Open shadcn/create and build your preset visually. Choose your style, colors, fonts, icons, and more.

Open shadcn/create

2 Create Project

Click `Create Project`, choose your package manager, and copy the generated command.

The generated command will look similar to this:

pnpm npm yarn bun

```
npx shadcn@latest init --preset [CODE] --template vite
```

The exact command will include your selected options such as `--base`, `--monorepo`, or `--rtl`.

3 Add Components

Add the `Card` component to your project:

pnpm **npm** yarn bun

```
npx shadcn@latest add card
```

If you created a monorepo, run the command from `apps/web` or specify the workspace from the repo root:

pnpm **npm** yarn bun

```
npx shadcn@latest add card -c apps/web
```

The command above will add the `Card` component to your project. You can then import it like this:

src/App.tsx

```tsx
import {
  Card,
  CardContent,
  CardDescription,
  CardHeader,
  CardTitle,
} from "@/components/ui/card"

function App() {
  return (
    <Card className="max-w-sm">
      <CardHeader>
        <CardTitle>Project Overview</CardTitle>
        <CardDescription>
          Track progress and recent activity for your Vite app.
        </CardDescription>
      </CardHeader>
      <CardContent>
        Your design system is ready. Start building your next com
      </CardContent>
    </Card>
  )
}

export default App
```

If you created a monorepo, update `apps/web/src/App.tsx` and import from `@workspace/ui/components/card` instead.

Use the CLI

1 Create Project

Run the `init` command to scaffold a new Vite project. Follow the prompts to configure your project: base, preset, monorepo, and more.

pnpm npm yarn bun

```
npx shadcn@latest init -t vite
```

For a monorepo project, use `--monorepo` flag:

pnpm npm yarn bun

```
npx shadcn@latest init -t vite --monorepo
```

2 Add Components

Add the `Card` component to your project:

pnpm npm yarn bun

```
npx shadcn@latest add card
```

If you created a monorepo, run the command from `apps/web` or specify the workspace from the repo root:

pnpm npm yarn bun

```
npx shadcn@latest add card -c apps/web
```

The command above will add the `Card` component to your project. You can then import it like this:

src/App.tsx

```tsx
import {
  Card,
  CardContent,
  CardDescription,
  CardHeader,
  CardTitle,
} from "@/components/ui/card"

function App() {
  return (
    <Card className="max-w-sm">
      <CardHeader>
        <CardTitle>Project Overview</CardTitle>
        <CardDescription>
          Track progress and recent activity for your Vite app.
        </CardDescription>
      </CardHeader>
      <CardContent>
        Your design system is ready. Start building your next com
      </CardContent>
    </Card>
  )
}

export default App
```

If you created a monorepo, update `apps/web/src/App.tsx` and import from `@workspace/ui/components/card` instead.

Existing Project

1 Create Project

If you need a new Vite project, create one first and select the **React + TypeScript** template. Otherwise, skip this step.

pnpm npm yarn bun

```
npm create vite@latest
```

2 Add Tailwind CSS

If your project already has Tailwind CSS configured, skip this step.

pnpm npm yarn bun

```
npm install tailwindcss @tailwindcss/vite
```

Replace everything in `src/index.css` with the following:

src/index.css

```
@import "tailwindcss";
```

3 Edit tsconfig.json file

If your project already has the `@/*` alias configured, skip this step.

Vite splits TypeScript configuration across multiple files. Add the `baseUrl` and `paths` properties to the `compilerOptions` section of `tsconfig.json` and `tsconfig.app.json`:

tsconfig.json

```
{
  "files": [],
  "references": [
    {
      "path": "./tsconfig.app.json"
    },
    {
      "path": "./tsconfig.node.json"
    }
  ],
  "compilerOptions": {
    "baseUrl": ".",
    "paths": {
      "@/*": ["./src/*"]
    }
  }
}
```

4 Edit tsconfig.app.json file

Add the same alias to `tsconfig.app.json` so your editor can resolve imports:

tsconfig.app.json

```
{
  "compilerOptions": {
    // ...
    "baseUrl": ".",
    "paths": {
      "@/*": [
        "./src/*"
      ]
    }
    // ...
  }
}
```

5 Update vite.config.ts

Install `@types/node` and update `vite.config.ts` so Vite can resolve the `@` alias:

pnpm | npm | yarn | bun

```
npm install -D @types/node
```

vite.config.ts

```ts
import path from "path"
import tailwindcss from "@tailwindcss/vite"
import react from "@vitejs/plugin-react"
import { defineConfig } from "vite"

// https://vite.dev/config/
export default defineConfig({
  plugins: [react(), tailwindcss()],
  resolve: {
    alias: {
      "@": path.resolve(__dirname, "./src"),
    },
  },
})
```

6 Run the CLI

Run the `shadcn` init command to set up shadcn/ui in your project:

pnpm | npm | yarn | bun

```
npx shadcn@latest init
```

7 Add Components

You can now start adding components to your project.

pnpm | npm | yarn | bun

```
npx shadcn@latest add button
```

The command above will add the `Button` component to your project. You can then import it like this:

src/App.tsx

```tsx
import { Button } from "@/components/ui/button"

function App() {
  return (
    <div classNam="flex min-h-svh flex-col items-center justify-
      <Button>Click me</Button>
    </div>
  )
}

export default App
```

← Next.js

Laravel →