

DYNAMICS & CONTROL 3

CONTROL

Section:

Tutorials

Dr. Olaoluwa Popoola

Email: Olaoluwa.Popoola@glasgow.ac.uk



Dynamics and Control (UESTC 3001)

- Lecture 1: Root Locus Analysis
- Lecture 2: Root Locus II and Nyquist Plots
- Lecture 3: Bode Plots
- Lecture 4: Bode Plots II
- Lecture 5: Stability in Frequency Domain
- Lecture 6: Stability cont. and Stability Examples
- Lecture 7: Compensators
- **Lecture 8: Tutorials and Test Exercises**

Lecture delivered by: Dr Ola Popoola (Olaoluwa.Popoola@Glasgow.ac.uk)

Notes prepared by: Dr Ola R. Popoola

Tutorial Session 1 (16:25-16:55)

Attempt the question

Can work in groups

Can discuss solutions

Tutorial Session (16:25 – 16:55)

Q. Consider the unity feedback control system with an open loop transfer function of

$$G(s) = \frac{K}{s(s+5)(s+10)}$$

- a. Construct the root locus of the system and determine the value of K for which the system is marginally stable.
- b. Sketch the bode magnitude and phase plots of the system.
- c. Using the Nyquist criterion, find the range of values of K for which the system is stable

A. Root Locus:

Method to plot the root locus:

- 1- Find the number of asymptotes by identifying the poles and zeros of the transfer function;
- 2- Calculate the centre of gravity;
- 3- Calculate the angle of the asymptotes;
- 4- Find the breakaway point;
- 5- Plot the root locus.

B. Bode Plot:

Steps to sketch the bode plot:

1. Write transfer function in time constant form and identify the components
2. Identify corner frequencies and the magnitude and phase behaviour of components
3. Plot the Bode magnitude plot with magnitude in dB vs $\log(\omega)$
4. Plot the Bode phase plot with phase in deg vs $\log(\omega)$

C. Point/Region of instability:

Steps to find point of instability using Nyquist criterion:

1. Write $G(j\omega)$ and rationalise to get real part and imaginary parts
2. Equate the imaginary part to zero and find the value of ω_c where the Nyquist plot cuts the negative real axis
3. Put the value of ω_c into $G(j\omega)$ to get the range of K for stability where $G(j\omega_c) < 1$ or use 4
4. Write the magnitude of $G(j\omega)$ compute for $G(j\omega_c)$. The get the range of K for $G(j\omega_c) < 1$