Fix on next Revision
-source more durable on/off power switch
-change RGB Led to smaller type
-push out components for oled glass, resuse window
-find new location for miroSD holder
-somehow hide oled flex on bottom





















Title			
Size: C	Number:		Revision:
Date: 2017-04-25		Sheet of	
File: C:\Utility\..\Schematic_Rev1.1.SchDoc		Drawn By:	


RP2
D2
R9
RP1
R8
R7
S1
C17
S2
C16
C15
C3
R6
R5
L1
D1
C5
C6
C2
C4
R3
X1
C7
R4


B1
U3
C12
X2
U2
C9
C20
C19
U5
C21
C18
S3
C11
X3
C10
J1
U4
H2
R11
H3
R10
C8
R2
C1
R1
U1

Component list

SAMD21G18A Sensor Board with Color Oled

Source Data From:

Project:

Rev1

Report Date:	2017-04-25	5:59:04 PM
Print Date:	25-Apr-17	5:59:17 PM

#	Designator	Quantity	Vendor	PartNumber	Description	Manufacturer	Comment
1	C1	1	Digi-Key	C0603C100J5GACTU	10pF 50V Ceramic Capacitor C0G	Kemet	10pF
2	C2	1	Digi-Key	CL31B475KOHNFNE	CAP CER 4.7UF 16V 10% X7R 1206	Samsung	4.7uF
3	C3, C5, C6	3	Digi-Key	CL31B106KOHNNNE	CAP CER 10UF 16V 10% X7R 1206	Samsung	10uF
4	C4, C7	2	Digi-Key	GRM188R71C104KA01D	CAP CER 0.1UF 16V 10% X7R 0603	Murata	0.1uF
5	C8	1	Digi-Key	T491A475M025AT	4.7µF Molded Tantalum Capacitors	Kemet	4.7uF Tant
6	C9, C12, C15, C17, C21	5	Digi-Key	GRM188R71E104KA01D	CAP, 0.1uF, 25V, 0603	Murata	0.1uF
7	C10, C11	2	Digi-Key	GRM1885C1H220JA01D	CAP, 22pF, 0603	Murata	22pF
8	C16	1	Digi-Key	GRM188R71E105KA12D	CAP, 1uF, 25V, 0603	Murata	1uF
9	C18, C20	2	Digi-Key	GRM31CR71E475KA88L	CAP, 4.7uF, 25V, 1206	Murata	4.7uF
10	C19	1	Digi-Key	C0603C103K5REC7867	CAP CER 0603 10NF 50V X7R 10%	Kemet	10nF
11	D1	1	Digikey	MBR0520-TP	DIODE SCHOTTKY 20V 500MA SOD123	Micro	MBR0520-TP
12	D2	1	Digi-Key	ASMT-YTB7-0AA02	LED,RGB,20mA,6SMD,RoHS	BROADCOM	RGB
13	H2	1	Digi-Key	1981584-1	CONN RCPT MICRO USB TYPE AB	TE Connectivity	Micro USB
14	J1	1	Digi-Key	0473092851	9 (8 + 1) microSD SMT, Right Angle	Molex	0473092851
15	L1	1	Digikey	LQH43CN100K03L	INDUCTOR 10UH 10% 650MA 1812	Murata	LQH43CN100K03L
16	R1	1	Digi-Key	ERJ-3EKF1004V	RES SMD 1M OHM 1% 1/10W 0603	Panasonic	1M
17	R2	1	Digi-Key	RC0603FR-0795K3L	RES SMD 95.3K OHM 1% 1/10W 0603	Yageo	95K
18	R3	1	Digi-Key	ERJ-3EKF1204V	RES SMD 1.2M OHM 1% 1/10W 0603	Panasonic	1.2M
19	R4	1	Digi-Key	ERJ-3EKF1002V	RES SMD 10K OHM 1% 1/10W 0603	Panasonic	10K
20	R5, R6	2	Digi-Key	ERJ-PA3F4701V	RES SMD 4.7K OHM 1% 1/4W 0603	Panasonic	4.7K
21	R7, R8	2	Digi-Key	ERJ-3EKF1001V	RES SMD 1K OHM 1% 1/10W 0603	Panasonic	1K
22	R9	1	Digi-Key	ERJ-3EKF2201V	RES SMD 2.2K OHM 1% 1/10W 0603	Panasonic	2.2K
23	R10	1	Digi-Key	ERJ-3EKF3300V	RES, 330R, 0603	Panasonic	330R
24	RP1, RP2	2	Digi-Key	EXB-38V103JV	RES ARRAY 4 RES 10K OHM 1206	Panasonic	EXB38V_SEPERATED
25	S1	1	Digi-Key	FSM6JSMA	SWITCH TACTILE SPST-NO 0.05A 12V	TE Connectivity	Tactile_Switch
26	S2	1	DX.com	122745	DX_Navigation Switch		Navigation Switch
27	S3	1	Digi-Key	JS102000SAQN	SWITCH SLIDE SPDT R/A	C&K	SWITCH SLIDE
28	U1	1	Digi-key	TPS61040DBVR	IC LED DRVR WHITE BCKLGT SOT23-5	Texas Instruments	TPS61040DBVR
29	U2	1	Digi-Key	DS1340U-33+	IC RTC SERIAL 512K 8-TSSOP	Maxim	DS1340U-33+
30	U3	1	Digi-Key	HDC1080DMBT	Humidity/Temperature Sensor	Texas Instruments	HDC1080DMBT
31	U4	1	Digi-Key	ATSAMD21G18A-AU	IC MCU 32BIT 256KB FLASH 48-TQFP	Atmel	ATSAMD21G18A-AU
32	U5	1	Digi-Key	CAT6219-330TDGT3	IC REG LDO 3.3V 0.5A SOT23-5	On Semi	CAT6219-330TDGT3
33	X1	1	Buy-Display	ER-OLED0.95-2C	0.95 INCH OLED GLASS COLOR	Buy-Display	OLED_GLASS 0.95 inch
34	X2, X3	2	Digi-Key	ECS-.327-12.5-34B	CRYSTAL 32.768 KHZ 12.5PF SMD	ECS	ECS-.327-12.5-34B

Approved

Notes