

Shade Shifter - Complete Parts List

Master list covering immediate, local and later-stage purchasing decisions. Items: 24.

Actual product photo	Purchase	Exact part and source	Qty.	Required specification	Do not buy
	BUY ONLINE NOW â‚¬135 + delivery/import	Invisible Evaluation Kit 5.2 Open product/photo source	1	Complete EVKIT301H1F1PV1: 13 displays, Driver 5.2, IÂ°C interface, FPC adapter and instructions.	Do not buy raw electrochromic ink, an unpowered sample sheet, or a seven-segment-only loose display.
	BUY ONLINE NOW â‚¬870â‚¬â‚¬1,100 each	ESP32-C3-DevKitM-1 Open product/photo source	2	Official Espressif board, BLE, 4 MB flash and USB programming. Use for bench development.	Do not buy ESP8266, ESP32-S2 (no Bluetooth), or a board with no documented pinout.
	BUY ONLINE NOW â‚¬800â‚¬â‚¬1,250 each	Seeed XIAO ESP32-C3 Open product/photo source	2	21 Å— 17.8 mm board with BLE, USB-C and onboard single-cell battery charging.	Do not substitute XIAO ESP32-S3 unless firmware and pin mapping are deliberately updated.
	BUY ONLINE NOW â‚¬400â‚¬â‚¬1,000	Addressable RGB LED strip Open product/photo source	1 m	WS2812B or SK6812, 5 V, 60 LEDs/m. Buy one normal-width strip for the bench.	Do not buy a 12 V analog RGB strip, RGBW strip, or non-addressable four-wire strip.
	BUY ONLINE NOW â‚¬500â‚¬â‚¬2,000	SK6805-2020 RGB LED samples Open product/photo source	20â‚¬40	2.0 Å— 2.0 mm, 5 V addressable RGB, individually packaged or on a narrow sample PCB.	Do not buy bare 0201 LEDs, common-anode RGB LEDs, or large WS2812B 5050 packages.
	BUY ONLINE NOW â‚¬250â‚¬â‚¬700 total	74AHCT125 level shifter Open product/photo source	5	74AHCT125N in DIP-14 for breadboard tests; TTL-level input at 5 V supply.	Do not buy 74HC125 or a slow bidirectional IÂ°C level-shifter module for the LED data line.
	BUY IN PERSON â‚¬200â‚¬â‚¬500	LED protection components Open product/photo source	1 set	330 Î© resistors Å—20 and 1,000 ÅµF, â‚¬¥10 V electrolytic capacitors Å—5.	Do not buy 330 kÎ© resistors or polarized capacitors rated below the supply voltage.
	BUY IN PERSON â‚¬1,000â‚¬â‚¬2,000	Breadboards and jumper wires Open product/photo source	2 + sets	Two full-size solderless boards; maleâ‚¬male, maleâ‚¬female and femaleâ‚¬female jumpers.	Do not buy mini breadboards as the only boards or stiff Dupont wires for the wearable.

Actual product photo	Purchase	Exact part and source	Qty.	Required specification	Do not buy
	BUY ONLINE NOW Request current price	ITO-coated PET sheet Open product/photo source	3	Flexible PET, approximately 100 Å— 200 mm; supplier must state sheet resistance and conductive side.	Do not buy ITO glass, plain clear PET, privacy film, or PDLC smart film.
	BUY ONLINE NOW â‚¬300â‚¬â‚¬â‚¬1,000	Conductive copper foil tape Open product/photo source	2 rolls	3 mm and 6 mm widths with electrically conductive adhesive.	Do not buy copper-coloured decorative tape or foil whose adhesive is non-conductive.
	BUY ONLINE NOW â‚¬400â‚¬â‚¬â‚¬1,000	Kapton insulation tape Open product/photo source	3 rolls	6 mm, 10 mm and 20 mm polyimide tape rated for electronics work.	Do not substitute PVC electrical tape near display contacts or soldering heat.
	BUY ONLINE NOW â‚¬1,500â‚¬â‚¬â‚¬5,000	Digital multimeter Open product/photo source	1	Fused current input, continuity buzzer, DC volts/current and resistance; reputable manufacturer.	Do not buy an unfused novelty meter or use its current mode directly across a battery.
	BUY ONLINE NOW â‚¬700â‚¬â‚¬â‚¬2,000	USB power meter Open product/photo source	1	Measures 5 V voltage, current, accumulated mAh and Wh; USB-A or USB-C adapters as needed.	Do not buy a USB voltage-only indicator with no current or capacity measurement.
	BUY IN PERSON â‚¬800â‚¬â‚¬â‚¬3,000	Digital caliper Open product/photo source	1	0â‚¬150 mm range, 0.01 mm display resolution; verify zero and jaw alignment in store.	Do not buy a plastic caliper for final CAD measurements.
	BUY IN PERSON â‚¬4,000â‚¬â‚¬â‚¬15,000 total	Wide-temple donor frames Open product/photo source	6	Full-rim TR90/acetate; size near 55â‚¬18â‚¬145; outer temple 8â‚¬10 mm wide; removable demo lenses.	Do not buy thin wire frames, rimless frames, fixed decorative hinges or frames uncomfortable before electronics.
	BUY IN PERSON â‚¬1,000â‚¬â‚¬â‚¬4,000	Spectacle hinges, screws and demo lenses Open product/photo source	2 sets	M1â‚¬M1.4 screw assortment, conventional barrel hinges, spare plano/demo lenses fitted by an optician.	Do not fit prescription lenses into the engineering prototype.

