STANDARD OPERATING PROCEDURE

Water Transfer Pump Flushing

Document ID: DEMO-SOP-004 | Revision: 1.0 | Effective date: 07-Nov-2026

TRAINING SAMPLE ONLY. This fictional procedure is provided solely to test document upload, change requests, AI drafting and review workflows. It is not an approved engineering procedure. Do not use it to operate equipment.

Department	Utilities / Training	**Process owner**	Training Supervisor
Equipment	Demo water transfer pump P-101	**Review cycle**	Annual (training example)
Prepared by	SafeSOP AI Demo	**Approval status**	Unapproved sample

1. Purpose

Describe a controlled, training-only sequence for documenting a basic flush of a fictional water transfer pump after a demonstration run.

2. Scope

This example applies only to the fictional P-101 training rig using clean water. It excludes chemical service, hot fluids, pressurised systems and live industrial equipment.

3. Responsibilities

The trainee follows the approved site procedure under supervision. The supervisor confirms the training rig is isolated and safe. Any real equipment must be governed by its manufacturer instructions and the site's approved risk assessment.

4. Required items

Training checklist; clean-water container; labelled collection vessel; suitable gloves and eye protection; and the training rig's isolation indicator.

5. Safety notes

WARNING: Never perform this training example on live equipment or a system containing chemicals.

CAUTION: Stop the exercise if there is leakage, unexpected noise, damaged cabling or an unclear isolation state.

NOTE: The sample flush quantity below is a documentation value only; it is not an engineering instruction.

6. Procedure - Training Sequence

1. Review the training checklist and confirm that the exercise is authorised by the supervisor.

2. Identify the fictional equipment label P-101 and compare it with the training record.

3. Ask the supervisor to demonstrate the training rig's safe isolation state; do not operate controls independently.

4. Visually inspect the training area for spills, damaged cables or obstructions. Stop and report any concern.

5. Prepare a clean, labelled collection vessel in the designated training area.

6. Record the example flush quantity as **5 litres** in the training worksheet. This is a sample record value, not an instruction to operate a pump.

7. Have the supervisor demonstrate the approved training-rig flush simulation and confirm the collection vessel remains stable.

8. Record completion, note any observations, return training materials to storage and obtain the supervisor's sign-off.

7. Acceptance checks

Check	Expected training evidence
Identification	P-101 label matches the training record
Area condition	No visible spill, obstruction or reported damage
Record	Training worksheet contains the example quantity and observations
Review	Supervisor sign-off is recorded

8. Records

Retain the completed training checklist and supervisor sign-off in the training folder according to the organisation's document-control rules.

9. Revision history

Revision	Date	Description	Author
1.0	07-Nov-2026	Initial fictional sample for software testing	SafeSOP AI Demo

End of training sample. All values and equipment references are fictional. Human review and formal approval are required before any real-world procedure is used.