# Project planning report

Saved project inputs and selected calculation results

2026-10-27 01:49:28.071723+00:00

## Project

This report presents saved project inputs and the original results of the selected calculations. Country-specific requirements, electrical design and installation checks remain open. It does not approve the complete installation.

| | |
|---|---|
| Project | Berlin · Beispielprojekt · PV und Speicher |
| Project reference | c7795bc2c1e14e389622015c809ace45 |
| Input revision | 24 |

## Site and project inputs

| | |
|---|---|
| Location | Berlin · Beispielstandort |
| Country | DE |
| Time zone | Europe/Berlin |
| Project note | Interaktives Beispiel mit echten JRC-Wetterdaten und nachgewiesenen Trina-Moduldaten; Dachgeometrie und Verbrauch sind Beispielannahmen. |

## PV wiring plan

The wiring plan records the assigned roof modules. Cold open-circuit voltage uses the stated ambient temperature and the module's voltage coefficient. STC operating points do not establish hot or cold MPP performance, design currents or wiring protection.

| | |
|---|---|
| Lowest design ambient temperature | -10 °C |
| Temperature source and location | Example condition: -10 °C for this wiring example; the local design extreme has not been verified. |

| String | MPPT | Input | Modules | Vmpp at STC | Cold Voc |
|---|---|---|---|---|---|
| 1 | 1 | 1 | 12 | 544.8 V | 699.83 V |
| 2 | 1 | 2 | 12 | 544.8 V | 699.83 V |

## Modeled electrical operating points

These estimates use a fitted single-diode model at the stated uniform module conditions. They do not include shading or establish manufacturer performance, design extremes, protection ratings or country approval.

Illustrative uniform operating cases for this saved example: effective irradiance 1000 W/m²; hot cell 60 °C, cold cell 20 °C. Mounting, ventilation, wind and local design extremes have not been established. These are entered scenario conditions, not site measurements or manufacturer release.

| | |
|---|---|
| Effective irradiance | 1000 W/m² |
| Hot operating cell temperature | 60 °C |
| Cold operating cell temperature | 20 °C |

| String | Case | Vmpp | Impp | Isc |
|---|---|---|---|---|
| 1 | Hot operating case | 487.173 V | 10.2021 A | 10.9611 A |
| 1 | Cold operating case | 553.062 V | 10.1291 A | 10.7884 A |
| 2 | Hot operating case | 487.173 V | 10.2021 A | 10.9611 A |
| 2 | Cold operating case | 553.062 V | 10.1291 A | 10.7884 A |

## Model, inputs and datasheet comparisons

Batzelis initialization and De Soto fitting use the saved STC points and temperature coefficients. The fitted compound parameters do not identify the physical cell-series count. Numerical fit precision is separate from physical accuracy.

pvlib 0.16.1

| | |
|---|---|
| Source document · Page 2 | https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Fitting method | Batzelis<br>https://pvlib-python.readthedocs.io/en/v0.16.1/reference/generated/pvlib.ivtools.sdm.fit_desoto_batzelis.html |
| Numerical refinement | De Soto<br>https://pvlib-python.readthedocs.io/en/v0.16.1/reference/generated/pvlib.ivtools.sdm.fit_desoto.html |
| Temperature translation | De Soto<br>https://pvlib-python.readthedocs.io/en/v0.16.1/reference/generated/pvlib.pvsystem.calcparams_desoto.html |
| Model reference | cdba01f814f63187c5b485df22a93a2c7c7409585535f21ed3fddac086a72dfa |

| Quantity | Value |
|---|---|
| □Isc | 0.04 %/°C |
| □Voc | -0.24 %/°C |
| Cell technology | N-type i-TOPCon monocrystalline |
| Impp (STC) | 10.14 A |
| Isc (STC) | 10.81 A |
| Vmpp (STC) | 45.4 V |
| Voc (STC) | 53.8 V |

## Fitted model parameters

| | |
|---|---|
| a,ref | 1.84665 V |
| IL,ref | 10.8242 A |
| I0,ref | 2.34402e-12 A |
| Rs | 0.244312 Ω |
| Rsh,ref | 185.625 Ω |
| □Isc | 0.004324 A/K |
| Silicon bandgap assumption | 1.121 eV |
| Bandgap temperature assumption | -0.0002677 1/K |
| Relative numerical residual | 3.8848e-11 |
| Numerical fit tolerance | 1.49012e-08 |

## Datasheet comparisons

The power coefficient and NOCT values were not fitting targets. These comparisons show differences; they do not certify extrapolation accuracy.

| | |
|---|---|
| Declared power temperature coefficient | -0.29 %/°C |
| Model power temperature coefficient | -0.282132 %/°C |
| NOCT reference irradiance | 800 W/m² |
| NOCT cell-temperature interval | 41 °C – 45 °C |

| | |
|---|---|
| Declared NOCT cell temperature | 43 °C |
| Declared NOCT power | 352 W |
| Model power at nominal NOCT | 349.996 W |
| Model powers at the NOCT temperature limits | 352.127 W / 347.861 W |

## Equipment checks

Country requirements are not assessed by the selected calculations.

| | |
|---|---|
| Assessment status | Further checks required |

## Converter output

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 10 kW |
| Source document · Page 2 | 10000 W<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## Inverter output limit in grid-connected operation

In grid-connected operation, the requested continuous active power from the battery cannot exceed the applicable documented maximum output of the whole inverter. Where the source gives a maximum apparent power S, $|P| \leq S$ is a necessary upper bound only; S is not an active-power rating. Passing this check does not establish continuous battery output.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 11 kW |
| Requirement | 5 kW |
| Source document · Page 2 | 11000 VA<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## Grid phases

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 3 |
| Requirement | 3 |

## PV input power

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 20 kWp |
| Requirement | 11.04 kWp |
| Source document · Page 2 | 20000 Wp<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## Roof module assignment

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 24 |
| Requirement | 24 |

## String 1 · MPPT assignment

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 1 |
| Requirement | 3 |
| Source document · Page 2 | 3<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 1 · Inverter input assignment

The input number identifies the proposed connection. A cited manufacturer connector map is still required.

| | |
|---|---|
| Assessment status | Further checks required |
| Result | 1 |

## String 1 · Cold open-circuit voltage

Voc = modules per string × module Voc at STC × [1 + □Voc × (lowest design ambient temperature − 25 °C)]. □Voc is the relative Voc temperature coefficient in 1/°C; divide a value in %/°C by 100. The design temperature and its source are required.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 699.83 V |
| Requirement | 1,000 V |
| Source document · Page 2 | 53.8 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 1000 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 1 · Module system voltage (IEC rating)

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 699.83 V |
| Requirement | 1,500 V |
| Source document · Page 2 | 53.8 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |

## String 1 · MPP voltage at STC

This comparison uses STC values: 1,000 W/m² irradiance, 25 °C cell temperature and the AM1.5 reference spectrum.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 544.8 V |
| Requirement | 180 – 900 V |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 180~900 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 2 · MPPT assignment

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 1 |
| Requirement | 3 |
| Source document · Page 2 | 3<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 2 · Inverter input assignment

The input number identifies the proposed connection. A cited manufacturer connector map is still required.

| | |
|---|---|
| Assessment status | Further checks required |
| Result | 2 |

## String 2 · Cold open-circuit voltage

Voc = modules per string × module Voc at STC × [1 + □Voc × (lowest design ambient temperature − 25 °C)]. □Voc is the relative Voc temperature coefficient in 1/°C; divide a value in %/°C by 100. The design temperature and its source are required.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 699.83 V |
| Requirement | 1,000 V |
| Source document · Page 2 | 53.8 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 1000 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 2 · Module system voltage (IEC rating)

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 699.83 V |
| Requirement | 1,500 V |
| Source document · Page 2 | 53.8 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |

## String 2 · MPP voltage at STC

This comparison uses STC values: 1,000 W/m² irradiance, 25 °C cell temperature and the AM1.5 reference spectrum.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 544.8 V |
| Requirement | 180 – 900 V |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 180~900 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## Wired PV nameplate power

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 11.04 kWp |
| Requirement | 11.04 kWp |

## MPPT 1 · Strings per MPPT

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 2 |
| Requirement | 2 |
| Source document · Page 2 | 2<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## MPPT 1 · MPPT operating current at STC

Parallel-string currents are added at STC. Design irradiance, temperature and applicable rating factors require separate checks.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 20.28 A |
| Requirement | 40 A |
| Source document · Page 2 | 10.14 A<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 40 A<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## MPPT 1 · MPPT short-circuit current at STC

Parallel-string currents are added at STC. Design irradiance, temperature and applicable rating factors require separate checks.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 21.62 A |
| Requirement | 50 A |
| Source document · Page 2 | 10.81 A<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 50 A<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## MPPT 1 · Parallel string lengths and orientations

| | |
|---|---|
| Assessment status | Checked requirements met |

## Single-diode model fit

The fitted parameters reproduce the supplied STC points within the stated numerical tolerance. This is a numerical check, not a manufacturer performance validation.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |

## Model applicability to this module

The fit does not establish model accuracy for this exact module over its operating range. Validation against manufacturer performance data remains required.

| | |
|---|---|
| Assessment status | Further checks required |

## Operating-condition domain

The calculation applies the stated effective irradiance uniformly to the modules at each declared cell temperature.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Requirement | -40 – 85 °C |
| Source document · Page 2 | -40 to +85 °C<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |

## String 1 · Modeled MPP voltage: hot case

This compares the modeled MPP voltage at the declared case with the documented MPPT window. Other irradiance, temperature and shading conditions require their own assessment.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 487.173 V |
| Requirement | 180 – 900 V |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 180~900 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 1 · Modeled MPP voltage: cold case

This compares the modeled MPP voltage at the declared case with the documented MPPT window. Other irradiance, temperature and shading conditions require their own assessment.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 553.062 V |
| Requirement | 180 – 900 V |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 180~900 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 2 · Modeled MPP voltage: hot case

This compares the modeled MPP voltage at the declared case with the documented MPPT window. Other irradiance, temperature and shading conditions require their own assessment.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 487.173 V |
| Requirement | 180 – 900 V |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |

| | |
|---|---|
| Source document · Page 2 | 180~900 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## String 2 · Modeled MPP voltage: cold case

This compares the modeled MPP voltage at the declared case with the documented MPPT window. Other irradiance, temperature and shading conditions require their own assessment.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 553.062 V |
| Requirement | 180 – 900 V |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 180~900 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## MPPT 1 · Modeled MPPT current: hot case

Parallel currents are modeled at the declared uniform case. These points do not replace design-current or protection-rating checks.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 20.404 A |
| Requirement | 40 A |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 40 A<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## MPPT 1 · Modeled short-circuit current: hot case

Parallel currents are modeled at the declared uniform case. These points do not replace design-current or protection-rating checks.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 21.922 A |
| Requirement | 50 A |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 50 A<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## MPPT 1 · Modeled MPPT current: cold case

Parallel currents are modeled at the declared uniform case. These points do not replace design-current or protection-rating checks.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 20.258 A |
| Requirement | 40 A |

| | |
|---|---|
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 40 A<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## MPPT 1 · Modeled short-circuit current: cold case

Parallel currents are modeled at the declared uniform case. These points do not replace design-current or protection-rating checks.

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 21.577 A |
| Requirement | 50 A |
| Source document · Page 2 | 45.4 V<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |
| Source document · Page 2 | 50 A<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |

## Design current

Design currents require documented irradiance, temperature and applicable rating rules.

| | |
|---|---|
| Assessment status | Further checks required |

## Wiring and protection

Cable routes, conductor ratings, connector compatibility, fuses and isolation still require project-specific design.

| | |
|---|---|
| Assessment status | Further checks required |

## Required accessory

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | SAJ BC2-HV1 |

## Manufacturer pairing

| | |
|---|---|
| Assessment status | Further checks required |

## Module count

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 4 |
| Requirement | 2 – 5 |

## Parallel arrangement

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 1 |

## Battery voltage

| | |
|---|---|
| Assessment status | Checked requirements met |
| Source document · Page 2 | 180~800 V<br>https://de-linker.com/wp-content/uploads/2026/09/H2-10-30K-T2T3-datasheet-EN-BEU.pdf |
| Source document · Page 2 | 89.6-115.2 / 179.2-230.4 / 268.8-345.6 / 358.4-460.8 / 448-576.0 V<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |

## Sales unit

| | |
|---|---|
| Assessment status | Checked requirements met |
| Source document · Page 2 | Battery module<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |

## Usable energy

4.5 × 4 = 18 kWh

| | |
|---|---|
| Assessment status | Checked requirements met |
| Result | 18 kWh |
| Requirement | 10 kWh |
| Source document · Page 2 | 4.5 kWh<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |

## Continuous AC discharge power

| | |
|---|---|
| Assessment status | Further checks required |
| Requirement | 5 kW |

## Battery discharge path

| | |
|---|---|
| Assessment status | Further checks required |

## Components and manufacturer conditions

The H2 T3 ships with a smart meter, three current transformers and a 10 m meter communication cable (H2 manual, section 2.2 Unpacking, PDF p. 36 English / p. 7 German).

SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and the B2 manual (V1.2, PDF p5) says the B2 can only be used as such a set: the control module is an article of its own.

SAJ's Configuration Instructions V1.0 (Section 2) give the H2 series system as H2 + BC2 + BU2. SAJ's B2 datasheet names B2-5.0 to B2-25.0 as one to five BU2-5.0 modules with one BC2-HV1 control module, and SAJ's B2 manual (V1.2, PDF p5) says the B2 can only be used as a set with SAJ's H2 high voltage series storage inverter. The listing does not cover the one-module B2-5.0, whose operating voltage lies below the H2 T3's battery voltage range.

One BU2-5.0 module alone operates at 89.6 to 115.2 V (SAJ's B2 datasheet gives this for the one-module B2-5.0), below the H2 T3's battery voltage range of 180 to 800 V; two modules operate at 179.2 to 230.4 V.

| | |
|---|---|
| Source document · Page 36 | https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf<br>https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf |

| | |
|---|---|
| Source document | https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf<br>https://de-linker.com/wp-content/uploads/2026/09/H2_HS2_HS3_AS2_AS3_Configuration_Instructions_V1.0_en.pdf |
| Source document | https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf<br>https://de-linker.com/wp-content/uploads/2026/10/B2-5.0-HV1-HV5-user-manual-EN-EU.pdf |
| Source document · Page 2 | https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf<br>https://de-linker.com/wp-content/uploads/2026/09/B2-5-25K-HV1HV5-datasheet-EN-BEU.pdf |
| Source document · Page 37 | https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf<br>https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf |

## Provisional bill of materials

This list combines the selected equipment, saved roof modules and documented included components. Quantities are shown where established. Mounting, cabling, protection and other installation materials still require project-specific design.

Source document · Page 36 — Manufacturer package contents
https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_10-30K_User-Manual_DE-EN_EU.pdf

| Quantity | Product | Reference | Supply scope |
|---|---|---|---|
| 1 pc | SAJ H2-10K-T3 | DLK-SAJ-H210KT3 | Selected equipment |
| 5 pc | M5×12 screw assembly | | Included with the equipment · SAJ H2-10K-T3 |
| 6 pair | PV connector pair (T3) | | Included with the equipment · SAJ H2-10K-T3 |
| 2 pc | 2-pin pluggable terminal block | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | 3-pin pluggable terminal block | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | 6-pin pluggable terminal block | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | Communication terminal cover | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | Inverter mounting bracket | | Included with the equipment · SAJ H2-10K-T3 |
| 2 pc | Positive battery connector | | Included with the equipment · SAJ H2-10K-T3 |
| 2 pc | Negative battery connector | | Included with the equipment · SAJ H2-10K-T3 |
| 10 pc | AC terminal | | Included with the equipment · SAJ H2-10K-T3 |
| 4 pc | M6×50 screw assembly | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | eSolar AIO3 | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | AC terminal cover | | Included with the equipment · SAJ H2-10K-T3 |

| Quantity | Product | Reference | Supply scope |
|---|---|---|---|
| 1 pc | Smart meter | | Included with the equipment · SAJ H2-10K-T3 |
| 3 pc | Current transformer | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | Meter communication cable (10 m) | | Included with the equipment · SAJ H2-10K-T3 |
| 10 pc | RJ45 plug | | Included with the equipment · SAJ H2-10K-T3 |
| 1 pc | SAJ BC2-HV1 | DLK-SAJ-BC2HV1 | Selected equipment |
| 4 pc | SAJ BU2-5.0-HV1 | DLK-SAJ-BU250HV1 | Selected equipment |
| 24 pc | Trina Solar TSM-460NEG9R.28 | | PV reference module · project quotation |

## PV modules used in the calculation

Module counts come from the saved roof used by the selected equipment check. The modules are design references; electrical and mounting suitability require project-specific assessment.

| | |
|---|---|
| Input revision | 24 |
| PV nameplate power | 11.04 kWp |
| Source document · Page 2 | Trina Solar TSM-460NEG9R.28<br>https://de-linker.com/wp-content/uploads/2026/09/240831_Datasheet_Vertex-S_NEG9R.28_EN_2024_C_web.pdf |

| Quantity | Model | Module power (STC) |
|---|---|---|
| 24 | Trina Solar TSM-460NEG9R.28 | 460 W |

## Saved calculation references

| | |
|---|---|
| Calculation reference | e851a81cadf24da78fa09cf81259faeb · Input revision 24 |

## Certificates and related product documents

These documents were linked to the selected products when this result was recorded. Their applicability to this project’s models, firmware, configuration, standard editions and annexes has not been assessed here. Compliance with country-specific requirements, installation approval and grid-operator acceptance require separate evidence.

| | |
|---|---|
| BU2-5.0-HV1 | SAJ B2 battery systems and BU2-5.0 battery modules: EU declaration of conformity (multilingual)<br>https://de-linker.com/wp-content/uploads/2026/10/SAJ_B2_BU2-5.0_EU-Declaration-of-Conformity.pdf?linker_document_sha256=6a45702bfe4ae9de06c173b084b3decbf6ac9cc3cc5f77cbe0f8686885c9ad6e |
| SHA-256 | 6a45702bfe4ae9de06c173b084b3decbf6ac9cc3cc5f77cbe0f8686885c9ad6e |
| Recorded document revision | cead73235a8d8b291c22189e9f589c4d6f5c89dd45383599ac97c500bbceb4fb |
| BC2-HV1 | SAJ B2 battery systems and BC2-HV1 control module: EU declaration of conformity (multilingual)<br>https://de-linker.com/wp-content/uploads/2026/10/SAJ_B2_BC2-HV1_EU-Declaration-of-Conformity.pdf?linker_document_sha256=9cb10f8699f660cbbde4197f30b392b8b7b77d95723a8a0ad4c18a416b854a61 |
| SHA-256 | 9cb10f8699f660cbbde4197f30b392b8b7b77d95723a8a0ad4c18a416b854a61 |
| Recorded document revision | dd94420889a64b164722a24f947f6e4404df7e99739b6741b35b686639448773 |

| | |
|---|---|
| H2-10K-T3 | EU declaration of conformity for the SAJ H2 inverters, 13 languages including English and German (names the H2-25K-T3)<br>https://de-linker.com/wp-content/uploads/2026/10/SAJ_H2_EU-Declaration-of-Conformity.pdf?linker_document_sha256=9881d06dabba6e53893923e93ebb90365b966429967104cb92890de39573b443 |
| SHA-256 | 9881d06dabba6e53893923e93ebb90365b966429967104cb92890de39573b443 |
| Recorded document revision | 77800e74a3c6fff9de321ad9a6225955df5e7d863eaa392bfdd52598a245cf45 |