

Introduction

Summary:

This course is intended for beginning ECEN students taking ECEN 191 at BYU. We assume that students taking this course have a high school level education and are not required to know anything about electrical engineering or hobby engineering. If you are a beginner this is the course for you!

Learning Outcomes:

The final product from this course is a simple autonomous car named the AutonoMouse. Students will learn the following skills while developing their car:

- Learn what Arduino is
- Learn how to solder pins onto a PCB
- Learn how to code an Arduino Nano
- Learn how to prototype with breadboards
- Learn how LEDs work
- Learn about servos and pulse width modulation signals
- Learn about voltage regulators
- Learn how to spin a servo
- Learn how to use a sensor
- Learn about the HC-SR04
- Learn about PCBs
- System integration
- Troubleshooting

Materials You Need to Buy:

The following materials you will need to buy yourself:

Arduino Nano				
Part	Quantity	Unit Price	Subtotal	Notes
1 inch diameter bottle cap	2		\$0.00	Buy your own, Gatorade bottles work best
Zip ties	3	\$0.03	\$0.09	
Arduino Nano	1	\$4.00	\$4.00	
Switch-SPDT-BB	1	\$0.06	\$0.06	
Voltage Regulator (Q-7805c)	1	\$1.65	\$1.65	
0.1 μ F Ceramic Capacitors	1	\$0.06	\$0.06	
0.33 μ F Ceramic Capacitor	1	\$0.06	\$0.06	
330 Ohm Resistor	1	\$0.04	\$0.04	

9V Battery	1	\$1.25	\$1.25	
Battery Cap	1	\$0.44	\$0.44	
1x3 Male header	2	\$0.06	\$0.12	
1x4 Female header	1	\$0.08	\$0.08	
2x15 Female header	2	\$0.30	\$0.60	You will need to purchase 2 10x1 and 2 5x1 female header pins.
Continuous Servo	2	\$1.80	\$3.60	
PCB	1	\$1.20	\$1.20	3 in^2 @ \$0.40 per in^2
Ultra-sonic sensor	1	\$2.20	\$2.20	Sensor-Ultrasonic used for angry engineers
LED Colored	1	\$0.05	\$0.05	
CABLE-USB A-Mini	1	\$0.99	\$0.99	
Acrylic	1	\$1.62	\$1.62	\$0.08 per in^2
Laser Time Acrylic	2	\$0.06	\$0.12	
Total			\$18.23	

Buy these from the ELC (CB 416.) This is a requirement for part of this lab. (This table is just an estimate for these parts, pricing may have changed.) Also, take the time to get acquainted with the ELC. It is a valuable resource on campus.

Project Requests:

Students can request PCBs, Laser Cuts, and 3D prints from the shop staff. There are two of these for this lab: the PCB and acrylic base. The PCB will be milled and acrylic base laser cut by the shop.

PCB:

We have a number of these PCB's already fabricated and should be picked up and paid for with the rest of the autnomouse kit.

First, search the GitHub repository in your web browser (<https://github.com/BYU-ELC/AutonoMouse>). Then navigate to Arduino_Nano->Build_Files->Chassis1.1 and download the zip file, Chasiss1.1_2021-09-27.zip.

Next, search the ELC project request application (<https://byu-elc.mendixcloud.com/p/home>) and click the button "PCB Mill Request". Follow the instructions to fill out the form with your information. You will upload the zip file you just downloaded. The area of the PCB is 3in sq. Things to watch out for: select **PCB prototyping** for "Requested Service"; **single-sided** for "Single or Double Sided"; **BYU ID #** (not netID) for Student ID; and **Class** for "Purpose". Click submit.

Once PCB is finished the ELC will let you know when to pick it up.

Acrylic Base:

We have a number of these Acrylic base's already fabricated and should be picked up and paid for with the rest of the autonomouse kit.

The acrylic base project request process is similar to the PCB.

First, search the GitHub repository in your web browser (<https://github.com/BYU-ELC/AutonoMouse>). Then navigate to Arduino_Nano->Build_Files and download Arduino_Nano_chassis.svg. This file will allow the shop to laser cut your car's base.

Next, search the ELC project request application (<https://byu-elc.mendixcloud.com/p/home>) and click the button "Laser Cut Request". Follow the instructions to fill out the form with your information. **I would like to use acrylic supplied by the shop. Use any available acrylic on hand** (unless you would like to provide or choose your own) for "Material"; **1/8th inch** for "Thickness"; **BYU ID #**, (not netID), for Student ID; **Class** for "Purpose"; and **4.5-inch x 4.5 inch** for "Major Dimension for scaling". Do not forget to upload the .svg you previously downloaded. Click submit.

After your base is finished the ELC will let you know to pick it up.

Other:

- 2 x 1-inch diameter bottle caps for wheels (Gatorade or milk bottle caps work nicely for this)
- Computer (this is for programing; a laptop works best because you can bring it into the lab, but a desktop at home would also work)

Tools Required:

You will need access to the following tools. These can be found in student workshops in the ELC CB41, or you may buy your own as part of your personal electronic kit.

- Breadboard
- Jumper Wires
- Hot glue gun + hot glue
- Soldering station

How to Access Code for the Labs:

In this course you are not required to know how to code; however, you will still need to know how to download and use Arduino IDE to upload code to your Arduino Nano. Each time the labs ask you to download and upload code go to <https://github.com/BYU-ELC/AutonoMouse>. This is a GitHub repository that stores all the files for this course. If you're familiar with GitHub you can git clone the repository. If you're not familiar then navigate to **Arduino_Nano/Labs/(lab# that**

you're on). The code file is a .ino file. Copy and paste the code into Arduino IDE and you'll be good.