

```
clear
% ECSE 563 assignmenet 4
% Ali Seifeldin
% https://github.com/Bakalala/MGCILL-ECSE-563
```

```
% Question 1
```

```
clear; clc; close all;
```

```
% Load table 1 data.
run("A4Q3_scopf_data.m")
```

```
%% Load levels and tolerance
loads = [300 400 600 700]; % MW
toler = 0.5;
```

```
nGen = numel(co);
nCases = numel(loads);
```

```
G = zeros(nGen, nCases); % generator outputs (MW)
C_total = zeros(1, nCases); % total cost ($/h)
Lambda = zeros(1, nCases); % system lambda ($/MWh)
Profit = zeros(nGen, nCases); % per-unit profit ($/h)
TotalProfit = zeros(1, nCases); % total profit ($/h)
```

```
%% Run ED for each load level and store results
```

```
for k = 1:nCases
    d = loads(k);

    [gk, Ck, lambdak] = ed(co, a, b, gmin, gmax, d, toler);

    G(:, k) = gk;
    C_total(k) = Ck;
    Lambda(k) = lambdak;

    Cost_i = co + a .* gk + 0.5 * b .* (gk.^2); % each unit's cost
    Revenue_i = lambdak * gk; %  $\lambda * g_i$ 
    Profit_i = Revenue_i - Cost_i; % profit_i

    Profit(:,k) = Profit_i;
    TotalProfit(k) = sum(Profit_i);
end
```

```
%% Build a single results table (with profits)
```

```
Results = table( ...
    loads(:), ... % Load
```

```

Lambda(:), ... % Lambda
G(1,:).', ... % g1
G(2,:).', ... % g2
G(3,:).', ... % g3
Profit(1,:).', ... % Profit1
Profit(2,:).', ... % Profit2
Profit(3,:).', ... % Profit3
TotalProfit(:), ... % Total system profit
C_total(:), ... % Total cost
'VariableNames', { ...
    'Load_MW', 'Lambda', ...
    'g1_MW', 'g2_MW', 'g3_MW', ...
    'Profit1', 'Profit2', 'Profit3', ...
    'TotalProfit', 'TotalCost'} ...
);

%% Display the table
fprintf('=== ED algorithm Table ===\n');

```

=== ED algorithm Table ===

```
disp(Results)
```

| Load_MW | Lambda | g1_MW  | g2_MW  | g3_MW  | Profit1 | Profit2 | Profit3 | TotalProfit | Tot |
|---------|--------|--------|--------|--------|---------|---------|---------|-------------|-----|
| 300     | 26.067 | 202.24 | 87.631 | 10     | -186.51 | -265.61 | -701.33 | -1153.4     | 89  |
| 400     | 27.883 | 250    | 139.53 | 10     | 233.37  | -59.307 | -683.17 | -509.1      | 1   |
| 600     | 57.99  | 250    | 300    | 49.761 | 7760.1  | 8522.1  | -350.48 | 15932       | 1   |
| 700     | 61.987 | 250    | 300    | 149.66 | 8759.1  | 9721    | 47.981  | 18528       | 2   |

```

%% Plot incremental cost curves and operating points for one load
% Choose which load to illustrate graphically:
d_plot = 600; % MW (change if you like)
k_plot = find(loads == d_plot, 1)

```

```

k_plot =
3

```

```

for k = 1:nCases

    d_plot = loads(k); % MW (change if you like)

    if ~isempty(k)
        lambda_plot = Lambda(k);
        g_plot = G(:, k);

        figure; hold on; grid on;
        title(sprintf('Incremental cost curves at d = %d MW (lambda = 
%.3f)', ...
            d_plot, lambda_plot));
    end
end

```

```


xlabel('Generator output g_i (MW)');
ylabel('Incremental cost dC_i/dg_i ($/MWh)');



for i = 1:nGen
    g_range = linspace(gmin(i), gmax(i), 200);
    mc       = a(i) + b(i) .* g_range;    % dC_i/dg_i = a_i + b_i*g_i


    plot(g_range, mc, 'DisplayName', sprintf('Unit %d MC', i));
    plot(g_plot(i), lambda_plot, 'o', 'HandleVisibility', 'off');
    text(g_plot(i), lambda_plot, sprintf(' U%d', i), ...
        'VerticalAlignment', 'bottom');
end

yline(lambda_plot, '--', 'DisplayName', '\lambda');
legend('Location', 'best');
end
end

```







```

%% Compute minimum outputs to recover fixed costs at each lambda
% Solve for each unit and each lambda:
%   lambda * g = c0 + a*g + 0.5*b*g^2
% -> 0.5*b*g^2 + (a - lambda)*g + c0 = 0

g_break_even = NaN(nGen, nCases);

for k = 1:nCases
    lam = Lambda(k);

    for i = 1:nGen

        % Solve A*g^2 + B*g + C = 0 using MATLAB's roots()
        coeffs = [0.5*b(i), a(i) - lam, co(i)];
        r = roots(coeffs);

        % Select real, positive roots only
        r = r(imag(r)==0 & r > 0);

        if ~isempty(r)
            g_break_even(i, k) = min(r);    % smallest positive real root
        end
    end
end

%% Table: Minimum outputs to recover fixed costs at each lambda
% (solution of lambda*g = c0 + a*g + 0.5*b*g^2)

```

```

BreakEven = table( ...
    loads(:), ... % Load for each case
    Lambda(:), ... % Lambda for each case
    g_break_even(1,:).', ... % g_be1 for each case (column)
    g_break_even(2,:).', ... % g_be2 for each case
    g_break_even(3,:).', ... % g_be3 for each case
    'VariableNames', {'Load_MW', 'Lambda', 'g_be1_MW', 'g_be2_MW', 'g_be3_MW'}
    ...
);

```

```

%'Minimum outputs to recover fixed costs at each lambda'
% solution of  $\lambda * g = c_0 + a * g + 0.5 * b * g^2$ 

```

```

fprintf('=== ED algorithm BREAKEVEN Table ===\n');

```

```

=== ED algorithm BREAKEVEN Table ===

```

```

disp(BreakEven)

```

| Load_MW | Lambda | g_be1_MW | g_be2_MW | g_be3_MW |
|---------|--------|----------|----------|----------|
| 300     | 26.067 | NaN      | NaN      | NaN      |
| 400     | 27.883 | 137.4    | NaN      | NaN      |
| 600     | 57.99  | 21.236   | 11.498   | NaN      |
| 700     | 61.987 | 19.185   | 10.308   | 100.68   |

```

% The table shows that for 300MW, we never break even as the prices are too
% low
% For 700 MW, we breakeven with all 3 generators.

```

```

fprintf('=== ED algorithm Table ===\n');

```

```

=== ED algorithm Table ===

```

```

disp(Results)

```

| Load_MW | Lambda | g1_MW  | g2_MW  | g3_MW  | Profit1 | Profit2 | Profit3 | TotalProfit | Total |
|---------|--------|--------|--------|--------|---------|---------|---------|-------------|-------|
| 300     | 26.067 | 202.24 | 87.631 | 10     | -186.51 | -265.61 | -701.33 | -1153.4     | 80    |
| 400     | 27.883 | 250    | 139.53 | 10     | 233.37  | -59.307 | -683.17 | -509.1      | 1     |
| 600     | 57.99  | 250    | 300    | 49.761 | 7760.1  | 8522.1  | -350.48 | 15932       | 1     |
| 700     | 61.987 | 250    | 300    | 149.66 | 8759.1  | 9721    | 47.981  | 18528       | 2     |

```

% Question 2

```

```

clear; clc; close all;

```

```

% Load table 1 data.
run("A4Q3_scofp_data.m")

```

```

loads = [300 400 600 700]; % MW

```

```

toler = 0.5;

nGen    = numel(co);
nCases  = numel(loads);

U        = zeros(nGen, nCases); % generator scheduling status
G        = zeros(nGen, nCases); % generator outputs (MW)
C_total  = zeros(1, nCases);    % total cost ($/h)
Lambda   = zeros(1, nCases);    % system lambda ($/MWh)
Profit   = zeros(nGen, nCases); % Profit (MW)

for k = 1:nCases
    d = loads(k);
    [u,g,C,lambda] = uc(co,a,b,gmin,gmax,d,toler);

    % Per-unit costs & profits at that lambda:
    Cost_i    = u .* co + a .* g + 0.5 * b .* (g.^2);
    Revenue   = lambda * g; %  $\lambda * g_i$ 
    Profit_i  = Revenue - Cost_i;

    U(:,k)    = u;
    G(:,k)    = g;
    C_total(k) = C;
    Lambda(k)  = lambda;
    Profit(:,k) = Profit_i;
end

fprintf('=== UC algorithm Table ===\n');

```

=== UC algorithm Table ===

```

TotalProfit = sum(Profit, 1); % Calculate total profit for each case

%% Build a single results table
Results = table( ...
    loads(:), ... % Load
    Lambda(:), ... % Lambda
    U(1,:).', ... % U1
    U(2,:).', ... % U2
    U(3,:).', ... % U3
    G(1,:).', ... % g1
    G(2,:).', ... % g2
    G(3,:).', ... % g3
    Profit(1,:).', ... % Profit1
    Profit(2,:).', ... % Profit2
    Profit(3,:).', ... % Profit3
    TotalProfit(:), ... % <-- ADD THIS
    C_total(:), ... % Total cost
    'VariableNames', { ...

```

```

        'Load_MW','Lambda', ...
        'U1','U2','U3', ...
        'g1_MW','g2_MW','g3_MW', ...
        'Profit1','Profit2','Profit3', ...
        'TotalProfit', ...
        'TotalCost'} ...
);

```

```

%% Display the table
fprintf('=== UC algorithm Table ===\n');

```

```

=== UC algorithm Table ===

```

```

disp(Results)

```

| Load_MW | Lambda | U1 | U2 | U3 | g1_MW  | g2_MW  | g3_MW  | Profit1 | Profit2 | Profit3 |
|---------|--------|----|----|----|--------|--------|--------|---------|---------|---------|
| 300     | 26.227 | 1  | 1  | 0  | 207.56 | 92.193 | 0      | -153.79 | -251.26 | 0       |
| 400     | 28.249 | 1  | 1  | 0  | 250    | 149.97 | 0      | 324.71  | -6.4258 | 0       |
| 600     | 57.99  | 1  | 1  | 1  | 250    | 300    | 49.761 | 7760.1  | 8522.1  | -350.48 |
| 700     | 61.987 | 1  | 1  | 1  | 250    | 300    | 149.66 | 8759.1  | 9721    | 47.981  |

```

% Using the UC algorithm, we can see that at the 400MW load, we make a
% profit, as opposed to losing money using the ED algo. This is due to the
% fact that we completely shut off generator 3, as opposed to keeping it
% on.
% We get a sense of that using from the breakeven calculations we did,
where it
% is impossible to have any of the generator breakeven until we reach at
least
% 300MW. Instead of keeping it on we shut it off.
% we still lose money when we generate 300 MW but we minimized the losses
% from ~ -1100 to ~ 400 per hour
% 600 and 700 MW loads were profitable in both solutions. since all
% generators need to be so the solutions are identical
% we can notice that Generator 3 for both solutions with 600 MW is
% unprofitable, even if the system as a whole is profitable.

```

```

% Question 3

```

```

clear; clc; close all;

```

```

% Load table 1 data.
run("A4Q3_scopf_data.m")

```

```

%% A4Q3 main script

```

```

%% 1) Economic dispatch ignoring network (from Q1)

```



```

Dt = sum(d); % total demand (MW)
[g_ed, C_ed, lambda_sys] = ed(co,a,b,gmin,gmax,Dt,dp);

%% 2) DC "SCOPF" with network
out = dc_scopf(ifrom, ito, x, fmax, ...
               d, co, a, b, gmin, gmax, ngen, is);

g_scopf = out.g;
C_scopf = out.C;
LMP      = out.LMP;
MS       = out.MS;
flows    = out.f;

%% 3) Cost of security
cost_of_security = C_scopf - C_ed;

%% 4) Display key results
disp('--- Economic Dispatch (no network) ---');

```

--- Economic Dispatch (no network) ---

```

disp(table((1:length(g_ed))', g_ed, ...
           'VariableNames', {'Gen', 'P_ED_MW'}));

```

| Gen | P_ED_MW |
|-----|---------|
| 1   | 250     |
| 2   | 265.38  |
| 3   | 10      |

```

fprintf('Total ED cost = %.2f $/h\n', C_ed);

```

Total ED cost = 15435.69 \$/h

```

disp(' ');

```

```

disp('--- DC SCOPF (with 9-bus network) ---');

```

--- DC SCOPF (with 9-bus network) ---

```

disp(table((1:length(g_scopf))', g_scopf, ...
           'VariableNames', {'Gen', 'P_SCOPF_MW'}));

```

| Gen | P_SCOPF_MW |
|-----|------------|
| 1   | 242.36     |
| 2   | 250        |
| 3   | 32.637     |

```

fprintf('Total SCOPF cost = %.2f $/h\n', C_scopf);

```

Total SCOPF cost = 16021.09 \$/h

```
fprintf('Cost of security = %.2f $/h\n\n', cost_of_security);
```

Cost of security = 585.41 \$/h

```
disp('Bus LMPs ($/MWh):');
```

Bus LMPs (\$/MWh):

```
disp(table((1:length(LMP))', LMP, ...  
    'VariableNames', {'Bus', 'LMP'}));
```

| Bus | LMP        |
|-----|------------|
| 1   | 29.354     |
| 2   | 4.4791     |
| 3   | 30.035     |
| 4   | 4.4788e-14 |
| 5   | 10.547     |
| 6   | 30.035     |
| 7   | 41.59      |
| 8   | 49.844     |
| 9   | 68.3       |

```
disp('Line flows (MW):');
```

Line flows (MW):

```
disp(table((1:length(flows))', ifrom, ito, flows, fmax, ...  
    'VariableNames', {'Line', 'From', 'To', 'Flow', 'Fmax'}));
```

| Line | From | To | Flow    | Fmax |
|------|------|----|---------|------|
| 1    | 1    | 4  | 242.36  | 250  |
| 2    | 4    | 5  | 137.36  | 250  |
| 3    | 5    | 6  | -62.637 | 150  |
| 4    | 3    | 6  | 32.637  | 300  |
| 5    | 6    | 7  | -30     | 150  |
| 6    | 7    | 8  | -130    | 250  |
| 7    | 8    | 2  | -250    | 250  |
| 8    | 8    | 9  | 120     | 250  |
| 9    | 9    | 4  | -105    | 105  |

```
fprintf('Merchandizing surplus (congestion surplus) = %.2f $/h\n', MS);
```

Merchandizing surplus (congestion surplus) = 12421.57 \$/h

% Question 4

```
clear; clc; close all;
```

```
% Load table 1 data.
```

```
run("A4Q4_wlsse_data.m")
```

```
%% Run state estimator
```

```
[delta, V, Niter, elapsed] = fdwlsse( ...  
    nfrom, nto, r, x, b, ...  
    Pinj, Qinj, Pflow, Qflow, Vnode, ...  
    toler, maxiter);
```

```
%% Display results
```

```
fprintf('=== WLS State Estimation Results ===\n');
```

```
=== WLS State Estimation Results ===
```

```
fprintf('Iterations: %d    Time: %.6f s\n\n', Niter, elapsed);
```

```
Iterations: 4    Time: 0.010275 s
```

```
nbus = numel(V);
```

```
fprintf('Bus    Voltage(pu)    Angle(deg)\n');
```

```
Bus    Voltage(pu)    Angle(deg)
```

```
for k = 1:nbus
```

```
    fprintf('%3d    %10.4f    %10.4f\n', k, V(k), delta(k)*180/pi);
```

```
end
```

```
1      1.0062      0.0000  
2      1.0099     -5.4242  
3      1.0101      2.5313  
4      1.0582     -8.1495  
5      1.0014     -18.1090
```

```
% Comparing the output to table 4.
```

```
% V1, V3 and V4 are respectively 1,1,1.05.
```

```
% Our state estimated 1.0062, 1.0101, 1.0582
```

```
% This is reasonable, with less than a 1% difference
```

```
% we can also infer that bus 3 has a generator with a + angle
```

```
% we also notice bus 4 has a negative angle bus has a generator
```

```
% that is because the load is higher than what is generated so that is ok
```

```
% Calculation for observability
```

```
% 9 states to observe, 4 angles and 5 voltages.
```

```
% Angle at slack is 0
```

```
N = max(max(nfrom), max(nton));
```

```
Id = eye(N);
```

```
A = Id(1:N, nfrom) - Id(1:N, nto);
```

```
A = A'
```

```
A = 7x5
    1    -1     0     0     0
    1     0     0    -1     0
    0     1    -1     0     0
    0     0     1    -1     0
    0     0     1     0    -1
    0     0     0     1    -1
    0     1     0    -1     0
```

```
% For Active powere,
```

```
Maa = [1 1 0 0 0 0 0;
       0 0 -1 1 1 0 0;
       0 -1 0 -1 0 1 -1;
       1 0 0 0 0 0 0]
```

```
Maa = 4x7
    1     1     0     0     0     0     0
    0     0    -1     1     1     0     0
    0    -1     0    -1     0     1    -1
    1     0     0     0     0     0     0
```

```
A_noslack = A(:, 2:end)
```

```
A_noslack = 7x4
   -1     0     0     0
    0     0    -1     0
    1    -1     0     0
    0     1    -1     0
    0     1     0    -1
    0     0     1    -1
    1     0    -1     0
```

```
Haa = Maa * A_noslack
```

```
Haa = 4x4
   -1     0    -1     0
   -1     3    -1    -1
   -1    -1     4    -1
   -1     0     0     0
```

```
Gaa = transpose(Haa) * Haa
```

```
Gaa = 4x4
    4    -2    -2     2
   -2    10    -7    -2
   -2    -7    18    -3
    2    -2    -3     2
```

```
rankGaa = rank(Gaa)
```

```
rankGaa =
4
```

```
% Rank is 4 --> all 4 angles are observable
```

```
Mrr = [1 1 0 0 0 0 0;
       0 0 -1 1 1 0 0;
       0 -1 0 -1 0 1 -1;
       1 0 0 0 0 0 0 ;]
```

```
Mrr = 4x7
      1      1      0      0      0      0      0
      0      0     -1      1      1      0      0
      0     -1      0     -1      0      1     -1
      1      0      0      0      0      0      0
```

```
% add measurement for V2
Hrr = [Mrr * A;
       0 1 0 0 0]
```

```
Hrr = 5x5
      2     -1      0     -1      0
      0     -1      3     -1     -1
     -1     -1     -1      4     -1
      1     -1      0      0      0
      0      1      0      0      0
```

```
Hrr = transpose(Hrr) * Hrr
```

```
Hrr = 5x5
      6     -2      1     -6      1
     -2      5     -2     -2      2
      1     -2     10     -7     -2
     -6     -2     -7     18     -3
      1      2     -2     -3      2
```

```
rankGrr = rank(Hrr)
```

```
rankGrr =
5
```

```
totalRank = rankGaa + rankGrr
```

```
totalRank =
9
```

```
% Rank is 5 --> all 5 magnitudes are observable
```

```
%Rank 4 + 5 = 9 --> fully observable. If we remove 1 measurement we would
%lose a rank for sure, so we would not have full observability
```