

GPIO	Input	Output	Verwendung	Notes
0	pulled up	OK	Boot auf Board	outputs PWM signal at boot, must be LOW to enter flashing mode
1	TX pin	OK	-	debug output at boot
2	OK	OK	-	connected to on-board LED, must be left floating or LOW to enter flashing mode
3	OK	RX pin	-	HIGH at boot
4	OK	OK	MIDI OUT	
5	OK	OK	LED Data	outputs PWM signal at boot, strapping pin
6	x	x		connected to the integrated SPI flash
7	x	x		connected to the integrated SPI flash
8	x	x		connected to the integrated SPI flash
9	x	x		connected to the integrated SPI flash
10	x	x		connected to the integrated SPI flash
11	x	x		connected to the integrated SPI flash
12	OK	OK	-	boot fails if pulled high, strapping pin
13	OK	OK	Pedal 5	
14	OK	OK	Pedal 4	outputs PWM signal at boot
15	OK	OK	MIDI IN	outputs PWM signal at boot, strapping pin
16	OK	OK	Pedal 15	
17	OK	OK	Pedal 8	
18	OK	OK	-	
19	OK	OK	Pedal 6	
21	OK	OK	Display SCL	
22	OK	OK	Display SDA	
23	OK	OK	Pedal 7	
25	OK	OK	Pedal 1	
26	OK	OK	Pedal 2	
27	OK	OK	Pedal 3	
32	OK	OK	Pedal 11 ADC	
33	OK	OK	Pedal 12 ADC	
34	OK		Pedal 13 ADC	input only
35	OK		Pedal 14 ADC	input only
36	OK		Pedal 9 ADC	input only
39	OK		Pedal 10 ADC	input only