CONNECT



1. Connect the device to power/computer and to Radio/Scanner
2. Use phone/tablet/computer Wi-Fi to connect
   ssid 'Boondock-AP'
   password 'boondockecho'
3. Navigate to the device setup address at
   http://192.168.4.1
4. Select a 2.4 GHz Wi-Fi and enter the password
5. Copy the device's local IP address and MAC address

GET STARTED

1. Navigate to boondockecho.com/login
2. Create an account
3. Go to "Devices"
4. Use the MAC address to register your device on boondockecho.com
5. Go to "Dashboard"

1. Navigate to the device's local IP address
2. Select "Recorder" Menu Option
3. Ensure your radio/scanner is sending audio to device
4. Adjust volume out on your radio/scanner so that audio peaks at ~85% of Full-Scale
5. Set 'Threshold' to ~5-10% above the noise-floor
6. Set minimum, maximum, and silence values
7. Save settings and send sample audio to device