



5 captures

14 Oct 2007 - 16 Oct 2021

Sep OCT **May**

◀ 14 ▶

2006 2007 **2017**

success

fail

About this capture

COLLECTED BY

Organization: **Alexa Crawls**

Starting in 1996, **Alexa Internet** has been donating their crawl data to the Internet Archive. Flowing in every day, these data are added to the **Wayback Machine** after an embargo period.

Collection: [52_crawl](#)

this data is currently not publicly accessible.

TIMESTAMPS



The Wayback Machine -

<https://web.archive.org/web/20071014022614/http://grmods.com:80/modchips/octopus/zero/installation/v3/v3.htm>



Playstation2 Plug&Play Hacking - Ok - **Worlds Exclusive!**
Playstation2/P\$two Minimum Soldering - **Soon - 1-1-2006!**
Xbox All models All modchips Plug&Play Hacking - Ok - **GRmods Exclusive!**

Cont



PS2**Lusifer mod*****Worlds Exclusive Product!***

Octapus Zero
Lusifer mod v7
Lusifer mod v3
Octapus 3D
Octapus Rev
Octapus Ice
Octapus Plug-

Ins

PS2 models
PS2 Forums

Lusifer mod v3-v4 is used to automatically open-close the dvd tray of PS2, allowing you to perform the swap trick with Swap magic Disks and boot your safety backups! For the installation no soldering required but only Plug&Play actions! Lusifer mod is absolutely safe for your PS2, having absolutely no effect in the right operation of your console!

Installation Info

Installation of Lusifer mod v3-v4 kit requires to open the console and lose the guarantee. No-soldering required, but we are not responsible if anything happens during the installation because of a wrong action!

XBOX

X-elixis Basic
X-elixis Pro
X-elixis Plus
X-taxis Basic
X-taxis Pro
X-taxis Plus
X-Adaptor
X-Programmer
Devil mod 1
Devil mod 2
Lpcmmod

The installation will be performed by a 12 years old boy, who has modified his PS2 by himself!
We really like to thank SLuR..!

Installation Guide

Remove the plastic covers in the bottom side of PS2, to get access to the screws.
Unscrew 10 screws with a Philips type screwdriver.



Pull the upper protective case of PS2, starting from the back side first!

Warning: The top cap is connected to the console, with a sensitive Ribbon Cable!



Place the upper protective cap, as shown in the photo, to proceed with the installation.

Unscrew the 2 gold-coloured screws, that are holding the CD-Rom.



Lift the CD-Rom, as shown in the photo.

Warning: CD-Rom is connected with the mainboard, with a sensitive Ribbon Cable!



Install G1-Plug In by unplugging the wad with red/black wires, and plugging it to G1-Plug In. Then connect the short edge of G1-Plug In to the mainboard.



Connect the long edge of G1-Plug In to Lusifer mod.



Disconnect the original Ribbon Cable from the Eject/Reset button.



Connect the original Ribbon Cable to Lusifer mod connector shown in the photo.



Use the extra Ribbon Cable that comes with Lusifer mod, to the connector shown in the photo.



Connect the other side of the extra Ribbon Cable to the Eject/Reset button.



Put back the Eject/Reset button.



Place Lusifer mod in the upper protective cap of PS2,
with a double side sticker.



Reassemble your PS2,
and ENJOY YOUR GAME!

4 years GRmods..!
100% Safe Console Hacking!