BUILD PLAN SKETCH, PLAN NOT YET BUILT

CanalRung · github.com/BoujeeEnjinia1701/canalrung

REV	DESCRIPTION	DATE	BY
P1	Making sketch for the prototype build plan	2026-10-03	AC

TOP VIEW

Scale 1:50; looking down (along -Z)

FRONT VIEW

Scale 1:50; looking at the front (along +Y)

RIGHT VIEW

Scale 1:50; looking at the right side (along -X)

WHERE IT GOES

This part in colour, its neighbours in grey

HOW TO MAKE IT AND HOW IT FITS

Cut 7.9 m; tape, cut and heat seal both ends.
Top loop: figure-eight on a bight with a 60 tail, loop about 80 long (fits the 10 mm screw link).
From the loop's knot measure 1,106 down: mark rung 1.
Then mark every 335 for rungs 2 to 13 (12 more marks).
Mark both ropes side by side so the marks match.
At each mark: overhand stopper knot, its top at the mark, tied when the rung is threaded (build step 11).
Below rung 13: 280 to a figure-eight loop for the bottom link.
Dress and set every knot by hand before loading.

CANALRUNG

github.com/BoujeeEnjinia1701/canalrung

Side rope: making sketch (make 2)

DRAWING NO.	REV	SHEET	SIZE
CNR-DWG-109	P1	1 of 1	ANSI B

SCALE	UNITS	PROJECTION	DATE	DRAWN
1:50	mm		2026-10-03	Amish Chadha

MATERIAL / NOTES

9 mm EN 1891 type B low-stretch kernmantle, polyester preferred

Licensed CERN-OHL-S-2.0 · Design Molecule Lab · designmolecule.com

Generated from cad/src; do not edit by hand