BUILD PLAN SKETCH, PLAN NOT YET BUILT

DewDrive · github.com/BoujeeEnjinia1701/dewdrive

REV	DESCRIPTION	DATE	BY
P1	Making sketch for the prototype build plan	2026-10-01	AC



TOP VIEW

Scale 1:5; looking down (along -Z)

FRONT VIEW

Scale 1:5; looking at the front (along +Y)

RIGHT VIEW

Scale 1:5; looking at the right side (along -X)



WHERE IT GOES

This part in colour, its neighbours in grey

HOW TO MAKE IT AND HOW IT FITS

Blank 920 x 110 x 1 mm. Fold a 10 mm foot along one long edge at 90 degrees; the fin is then 100 deep below the plate.

Drill 4.1 mm through the foot at 140 pitch, 5 mm from the fold (seven holes, the first 40 from each end).

Fit: the foot lies flat on the underside of the plate. Fins at 50 pitch, the outer ones 40 from the east and west plate edges, 30 from the north and south edges. Feet point toward the centre line.

Bond each foot with high-temperature epoxy (rated 120 C or more), then rivet through the plate with 4 mm closed-end aluminium rivets, heads on the top (wetted) face. Paint the fins and the plate underside matt with a high-emissivity exterior paint.

Check: the fin stands square to the plate within 2 degrees.

DEWDRIVE

github.com/BoujeeEnjinia1701/dewdrive

DewDrive condenser fin (make 21): making sketch

DRAWING NO.	REV	SHEET	SIZE
DWD-DWG-104	P1	1 of 1	ANSI B

SCALE	UNITS	PROJECTION	DATE	DRAWN
1:5	mm		2026-10-01	Amish Chadha

MATERIAL / NOTES

Aluminium sheet 1 mm

Licensed CERN-OHL-S-2.0 · Design Molecule Lab · designmolecule.com

Generated from cad/src; do not edit by hand