


| REV | DESCRIPTION                                | DATE       | BY |
|-----|--------------------------------------------|------------|----|
| P1  | Making sketch for the prototype build plan | 2026-10-01 | AC |



TOP VIEW

Scale 1:20; looking down (along -Z)



FRONT VIEW

Scale 1:20; looking at the front (along +Y)



RIGHT VIEW

Scale 1:20; looking at the right side (along -X)



WHERE IT GOES

This part in colour, its neighbours in grey

HOW TO MAKE IT AND HOW IT FITS

Cut 2,450 mm of 40 x 2 mm 6061-T6 tube; square and deburr both ends.

Measure from the bottom end. Drill two 12 mm holes through one wall

only and fit a rubber grommet in each:

- at 1,220 mm, on the side that will face east (away from the wall), for the humidity sensor lead;

- at 1,250 mm, turned 90 degrees to face south (toward the panel), for the panel lead.

Pull the mast cable through the tube before the end cap goes on.

Fit: the plastic end cap with its grommet goes in the bottom end; the mast-top sleeve slides 40 mm over the top end (two set screws).

The mast stands 700 mm off the gable wall, bottom 2.25 m above the ground, top 4.70 m.

Check: length 2,450 mm within 2 mm; no burrs to cut the cable.

EMBERGUARD

[github.com/BoujeeEnjinia1701/emberguard](https://github.com/BoujeeEnjinia1701/emberguard)

EmberGuard mast tube: making sketch

|                                                                                                             |                    |                                                                                                     |                                             |                        |                              |
|-------------------------------------------------------------------------------------------------------------|--------------------|-----------------------------------------------------------------------------------------------------|---------------------------------------------|------------------------|------------------------------|
| DRAWING NO.<br><b>EGD-DWG-104</b>                                                                           |                    |                                                                                                     | REV<br><b>P1</b>                            | SHEET<br><b>1 of 1</b> | SIZE<br><b>ANSI B</b>        |
| SCALE<br><b>1:20</b>                                                                                        | UNITS<br><b>mm</b> | PROJECTION<br> | DATE<br><b>2026-10-01</b>                   |                        | DRAWN<br><b>Amish Chadha</b> |
| MATERIAL / NOTES<br><b>Aluminium tube 40 x 2 mm, 6061-T6</b>                                                |                    |                                                                                                     |                                             |                        |                              |
| Licensed CERN-OHL-S-2.0 · Design Molecule Lab · <a href="https://designmolecule.com">designmolecule.com</a> |                    |                                                                                                     | Generated from cad/src; do not edit by hand |                        |                              |