

GRAINGUARD · CALCULATION

GrainGuard sizing calculations

Design Molecule Lab · designmolecule.com

DOCUMENT CONTROL

Document ID	GGD-CAL-001	Version	0.6
Status	Draft	Date	2026-10-02
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/grainguard		
Source	docs/04-calcs/01-sizing.md @ uncommitted		

REVISION HISTORY

Version	Date	Author	Change
0.6	2026-10-02	Amish Chadha	Follow-ups to the 2026-10-02 decisions carried out. 20 W panel in the model and BOM; section D and the mast check (F4 to F6) rerun for it; R8 not met to met; stay-off check no longer holds at 45 m/s, so a 30 m/s service limit is proposed; adjustable disconnect (D4); kit USD 389.50 to USD 406.50
0.5	2026-10-02	Amish Chadha	R8 row, section D and section G note the 2026-10-02 decisions (GGD-DEC-001, items 2 and 6); no number changed
0.4	2026-10-01	Amish Chadha	Design for construction (GGD-DDR-003). Radio uses the modelled antenna height; mast check uses the modelled panel and shield heights; new checks F5 (stay) and F6 (mast with the stay off); cable and conduit lengths; cost reported against the value-engineering target
0.3	2026-09-26	Amish Chadha	Budget approved by Amish (\$250 to \$260, GGD-DDR-002); script rerun;

			R13 not met, overrun accepted, to met
0.2	2026-09-25	Amish Chadha	Recommendations accepted by Amish (DDR-002). Plenum probe in the base kit; new check B10 on measured fan heat; R4 from at risk to met; kit \$247.00 to \$256.50 with the \$6.50 overrun accepted (R13)
0.1	2026-09-25	Amish Chadha	First issue for TRL 3 (bin and airflow, fan heat, moisture error, rewetting in cool mode, coverage, power, radio, cable loads, mast, cost, requirement status)

GrainGuard sizing calculations

On paper, GrainGuard meets eight of its fourteen requirements, has three at risk, and has two that cannot be verified at TRL 3; cost (R13) is reported against a value-engineering target. Power (R8) is now met: with the relay input specified at 3 mA the battery lasts 7.7 days with no sun, and the 20 W panel decided on 2026-10-02 refills it from half charge in 2.9 winter days (the 10 W panel needed 7.3). The price is a larger load on the mast: with the stay off, the mast alone no longer meets the 1.5 times margin at a 45 m/s gust, so a service limit of 30 m/s is proposed (section F, awaiting Amish). Version 0.4 followed the design for construction (GGD-DDR-003) and version 0.6 adds the 2026-10-02 decisions: the constructable design costs USD 406.50 per bin against a value-engineering target of USD 260 (USD 146.50 over the target), with the farmhouse receiver costed per farm; the radio margin, mast stresses and cable lengths now come from the modelled antenna, bracket and route, and all still meet their requirements. Amish adopted the plenum temperature probe into the base kit on 2026-09-25 (GGD-DDR-002), so the fan's own heat, worth about one point of moisture per degree, is measured and the fan decision (R4) is met. The three at risk are the moisture estimate (R2), heating detection away from the center (R6) and the environment (R9). The calculations also corrected three TRL 2 figures: the reference bin holds about 88.8 t, not 95 t, because the aeration floor sits 0.4 m above the pad; the fan heat of "about 1 °C" is right only for a 0.4 kW fan; and the radio margin at 1 km past a building is about 18 dB, not 48 dB. Every number in this note is printed by `docs/04-calcs/sizing.py`; the tag in brackets, for example [A3], is the line of that script's output that carries it.

Safety: These are first-principles estimates for a paper proof of concept. They do not replace the bin maker's roof and hanger ratings, a licensed electrician's design of the starter interface, or a confined-space entry procedure. Nothing may be installed in a bin on the strength of this note. GrainGuard must never be used to judge whether a bin is safe to enter. See GGD-PRC-001, Safety.

■ Scope and method

The note checks every requirement in GGD-REQ-001 v0.8 against the design in GGD-PRC-001 v0.9, as made constructable in GGD-DDR-003, and the parametric model `cad/src/model.py`. The script imports the model's `PARAMS` and `derived()`, so the bin, pod positions, rope length, cable route and mast dimensions used here are the ones in the STEP files and on drawing GGD-DWG-001. It also reads `bom/bom.csv` and `budget_usd` in `project.yaml`, and writes the requirement table to `docs/04-calcs/results.csv`. Run it from the repo root with `python docs/04-calcs/sizing.py`.

The reference case is unchanged from TRL 2: a 5.49 m (18 ft) corrugated steel bin with a 5.6 m eave, a full perforated floor and one aeration fan, holding shelled corn at a target of 15.0 % moisture, wet basis, in the US Corn Belt (GGD-DDR-001, D11).

■ Assumptions

Table 1. Main assumptions.

Area	Assumption	Basis
Bin	Aeration floor 0.4 m above the pad; grain level with the eave, so 5.2 m deep	Model PARAMS ; typical floor supports
Grain	Corn at 721 kg/m ³ bulk; specific heat 1.465 + 0.0356 M kJ/(kg·K) with M in % wet basis	Common handbook values
Moisture	ASABE D245.6 modified Henderson equation for corn (K 8.6541e-5, N 1.8634, C 49.81)	ASABE standard
Airflow	0.2 cfm/bu; Shedd resistance for corn (ASABE D272, a 2.07e4, b 30.4), packing factor 1.5, 50 Pa for duct and floor	ASABE standard; packing and duct losses assumed
Fan	0.37 kW (1/2 hp) class, 0.40 kW input, motor in the air stream, so all input power heats the air; range 0.2 to 1.1 kW checked	Assumed; fans on real bins vary
Sensors	SHT45 ±1.0 % RH and ±0.1 °C typical (Sensirion); SHT40 ±1.8 % RH typical, ±3.5 % RH maximum (Sensirion), ±0.2 °C typical (SHT4x datasheet); plenum probe DS18B20 ±0.5 °C from -10 °C to +85 °C (Analog Devices)	Datasheets
Power	Controller 25 mW; pod bus 0.72 W for 3 s every 10 min; LoRa 0.15 W for 0.37 s every 10 min; charge controller 6 mA; relay input 3 mA at 12 V; 7 Ah AGM, 50 % usable (low-voltage disconnect at about 12.1 V), 60 % of that at -20 °C; 20 W panel; winter 1.5 peak sun hours, 60 % derating	As at TRL 2, except the relay input (was 10 mA) and the panel (was 10 W)
Radio	14 dBm, -132 dBm at SF10 and 125 kHz, 0 dBi antennas, 1 dB cable loss each end; antennas 2.22 m (mast, from the model) and 2.0 m (farmhouse); 20 dB for one farm building; plane-earth path loss	Typical SX1262 figures; building loss assumed
Cable loads	Janssen pressures with K 0.5 and wall friction 0.4; grain on steel 0.3; pod drag = vertical pressure on the pod face plus side friction; unloading overpressure factor 2.0	Screening values, not a bin-load standard
Mast	45 m/s gust (1,215 Pa); drag coefficient 1.2 on the panel (350 x 430 mm) and 1.0 on the shield; mast welded to its base plate and propped by the stay, which is bolted twice at each end; S235 pipe and angle	Screening values

■ A. Bin, airflow and fan heat (R4)

- **Grain.** The bin's cross-section is 23.67 m² and the grain is 5.2 m deep [A1], so it holds 123.1 m³, about 3,493 bu or 88.8 t of corn [A2]. The TRL 2 figures of 132 m³ and 95 t took the full 5.6 m eave height as grain depth and are corrected in all documents.
- **Airflow and pressure.** At 0.2 cfm/bu the fan moves 0.330 m³/s (699 cfm), a superficial speed of 13.9 mm/s [A3]. The static pressure is about 139 Pa (0.56 in wc) [A4], so the air power is only 46 W [A5]. Fans on real bins are much larger than this air power suggests; 0.40 kW input is assumed.
- **Fan heat.** With the motor in the air stream, all of the fan's input power warms the air, at 0.415 kW/K [A6]. The rise is 0.5 °C for a 0.2 kW fan, 1.0 °C for 0.4 kW, 1.8 °C for 0.75 kW and 2.7 °C for 1.1 kW [A7]. The TRL 2 figure of "about 1 °C" holds only for the smallest fans.
- **Cooling time.** A cooling front passes through the bin in 75 h by the extension rule to 119 h by a sensible-heat balance [A8]. Cooling the grain by 10 °C removes about 493 kWh; the fan uses about 48 kWh per cycle, about \$6 of electricity [A9].

■ B. Moisture estimate and the decision rule (R2, R3, R4)

- **The key sensitivity.** Air at 10 °C and 70 % RH has an EMC for corn of 15.70 %; warmed 1.0 °C by the fan it drops to 65.5 % RH and 14.73 %, so each degree of fan heat moves the plenum EMC by about 0.97 points [B1], [B2]. Across fans of 0.2 to 1.1 kW the same outside air gives a plenum EMC from 13.36 % to 15.21 %, a spread of 1.85 points [B3]. That is more than twice the whole moisture tolerance in R2, so an unmeasured fan heat would be the largest error in the decision rule.
- **Plenum probe, now in the base kit.** Heating does not change the air's humidity ratio, so the plenum RH follows from the ambient humidity ratio and the plenum temperature alone. A temperature-only probe in the fan transition (BOM item 14, \$9.50) therefore removes the fan heat error without a second RH pod. Amish adopted it into the base kit on 2026-09-25 (GGD-DDR-002). With the DS18B20 at ± 0.5 °C and the ambient SHT45 at ± 0.1 °C, the measured fan heat is known within ± 0.51 °C, so the plenum EMC is known within about ± 0.50 points, against the 1.85-point spread when the fan heat is only a setting [B10]. The probe's ± 0.5 °C rating applies from -10 °C to +85 °C; below -10 °C its error is larger and not quantified here; checking the probe against the ambient sensor with the fan off is a TRL 4 bench task. The fan heat is measured during each run; the controller uses the last measured rise to decide whether to start the fan. R4 is **met** on paper.
- **Sensor error.** The sensor-induced EMC error at 15 °C and 60 % RH is 0.17 points for the SHT45 and 0.31 points for the SHT40 (typical accuracy). Over 20 % to 75 % RH and 0 to 30 °C, the worst case is 0.23 and 0.42 points, both at 0 °C and 75 % RH. At the SHT40's maximum tolerance of ± 3.5 % RH it reaches 0.81 points, just over the 0.8-point target [B5]. At 85 % RH (wet grain) the SHT45 error is still only 0.29 points, but this is where the equation itself is least reliable [B6].
- **What is not included.** Membrane lag, sensor hysteresis and drift, and the fit error of the EMC equation are not in these figures [B7]. The equation's fit error for a given corn lot is not known at TRL 3 and is likely to be of the same order as the target. R2 is therefore **at risk**, not met.
- **Rewetting in cool mode.** The cool-mode allowance lets the fan run with plenum air up to 1.0 point of EMC above target. At an 11.0 °C plenum, air at 66.9 % RH holds corn at 15.0 % and air at 72.1 % RH holds it at 16.0 %; the difference is 0.42 g of water per kilogram of air [B8]. Over one 119 h cooling cycle at the full allowance, that is at most 74 kg of water, enough to raise the bottom 0.37 m of grain (7 % of the depth) by one point [B9]. The reworded pitch ("without rewetting it") is therefore true for hold mode and for cool mode within this bound; see `docs/REVIEW.md`.
- **Ambient air (R3).** The SHT45 meets ± 0.3 °C and ± 2 % RH on its own, but the radiation error of a passive shield in sun and low wind is not known without a test. R3 is **not verifiable at TRL 3**.

■ C. Sensing geometry, coverage and alarm latency (R1, R6)

- **Profile.** Six pods at 0.94 m pitch sit 0.25 m to 4.95 m above the floor, with the top pod 0.25 m below a level grain surface [C1]. With ± 0.1 °C (SHT45) and ± 0.2 °C (SHT40) typical accuracy, R1 is **met**.
- **Coverage.** A sensor sees a developing hot spot only within about 0.5 m (Ileleji et al., Purdue). One center cable watches 0.79 m² of the 23.7 m² section, 3.3 % [C2]; covering the whole section at that spacing would take about 31 cables [C3]. The center core, where fines collect under the fill spout, is watched; the outer ring is not.
- **Latency.** With 10 min sampling and up to three LoRa retries a minute apart, an alarm reaches the farmhouse within about 13 min [C4], inside the 15 min target. R6 is **at risk** because of coverage, not latency.

■ D. Power (R8, R12)

Table 2. Daily energy use [D1] to [D3].

Load	Wh per day
Controller and regulators, 25 mW	0.600
Pod bus, 0.72 W for 3 s every 10 min	0.086
LoRa transmit, 0.15 W for 0.37 s every 10 min	0.002
Charge controller self-use, 6 mA	1.728
Relay input, 3 mA while the fan runs	0.288 at 8 h; 0.864 continuous
Total, fan 8 h per day / continuous	2.70 / 3.28

- **Autonomy.** The TRL 2 design had a 10 mA relay input and used 5.30 Wh per day with the fan running continuously [D2]. The 7 Ah AGM battery gives 25.2 Wh usable at -20 °C [D4] with the adjustable low-voltage disconnect set to about 12.1 V (GGD-DEC-001, item 6; the 50 % figure the earlier assumption already used), so it lasted 4.8 days. Raising the disconnect to 60 % state of charge, to protect the battery at -30 °C, would leave 20.2 Wh and 6.1 days with the fan continuous, still over 5 days [D4]. With the relay input specified at 3 mA or less (an optically isolated input, BOM item 11), daily use falls to 3.28 Wh and autonomy rises to 7.7 days with the fan continuous and 9.3 days at 8 h per day [D3], [D5]. The autonomy half of R8 is met with no added cost.
- **Recovery.** The 10 W panel yielded 9.0 Wh per day at 1.5 winter peak sun hours and needed 7.3 days to refill 42 Wh from half charge. Refilling in 3 days takes a panel of about 19 W [D7]. Amish decided on 2026-10-02 to fit a 20 W panel (GGD-DEC-001, item 2; BOM line 8, USD 34.00). It yields 18.0 Wh per day, a net 14.7 Wh with the fan continuous, and refills from half charge in 2.9 days at 1.5 peak sun hours and 1.6 days at 2.5 [D6]. The margin against the 3-day target is thin (2.9 days), so a worse winter than 1.5 peak sun hours would miss it. Both halves of R8 are **met** on paper, subject to the stay-off service rule in section F.
- **Charging voltage (R12).** A temperature-compensated AGM charger raises its absorption voltage to 15.75 V at -20 °C and 16.05 V at -30 °C, over the 15 V limit in R12. The charge controller is therefore specified with its compensation clamped at 15.0 V [D8]. With that specification R12 is **met**.

■ E. Radio (R7)

- The link budget is 144 dB [E1]. The TRL 2 margin of about 48 dB used free-space loss at 2 km (97.7 dB) [E2], which is optimistic for antennas 2 m above the ground.
- With the antenna on its mast bracket (centre 2.22 m above the pad, GGD-DDR-003), plane-earth loss at 1 km is 107.1 dB, well past the 54 m breakpoint; with 20 dB for one farm building the margin is 16.9 dB [E3]. With a 10 dB fade margin the same model gives about 1.49 km [E4]. R7 is **met** on paper; the 95 % delivery figure needs a site survey.
- A packet of 24 bytes takes 371 ms at SF10, inside the 400 ms dwell limit in the US 915 MHz band; 25 bytes would take 412 ms [E5]. The payload is therefore limited to 24 bytes.

■ F. Cable loads and mast (R10)

- **Pull-down force.** Janssen's method gives 25.8 kPa vertical and 12.9 kPa lateral pressure at the floor [F1]. The static drag is 213 N on the rope and 825 N on the six pods, 1,038 N in all, and about 2,076 N with an unloading overpressure factor of 2.0 [F2]. The TRL 2 design force of 2.5 kN is kept, 1.2 times this estimate [F3]. The

measured maximum of 4.7 kN on the largest commercial cable ([Illinois Experts](#), [ASABE](#)) is consistent with a larger cable in a larger bin.

- **Rope.** A 20 kN rope gives a factor of 8.0 on 2.5 kN against R10's 4 [F3]. The roof hanger rating comes from the bin maker, bin by bin, so R10 as a whole is **not verifiable at TRL 3**.
- **Mast.** At a 45 m/s gust, the 20 W panel (350 x 430 mm, centre 2.24 m up on its bracket) and the shield (1.89 m) put 219 N and 31 N on the mast (the 10 W panel gave 128 N), a moment of 155 N·m at the stay. The DN25 pipe (section modulus 2.14 cm³) sees 73 MPa, 3.2 times below yield [F4].
- **Stay.** The stay props the mast with about 348 N. It is bolted twice at each end, so wind along the wall bends it as a guided cantilever 592 mm long: 67 MPa in the 40 x 40 x 4 angle, 3.5 times below yield. Toward the wall it is a strut with a buckling load of about 104 kN [F5].
- **Mast with the stay off.** If the stay is removed for service, the welded base carries the mast alone. With the 20 W panel at a 45 m/s gust that is 550 N·m at the base and 257 MPa in the pipe, 0.9 times yield, so the condition Amish set on 2026-10-02 (the check "still passes") is **not met at 45 m/s** (the 10 W panel gave 161 MPa, 1.5 times below yield). The 1.5 times margin holds up to a 35 m/s gust; at 30 m/s the pipe sees 114 MPa (2.1 times below yield) and each M10 anchor pulls 0.82 kN [F6]. A service rule is therefore proposed, awaiting Amish: take the stay off only on a calm day with no strong wind forecast (gusts under 30 m/s, about 65 mph), and refit it before leaving. The alternative is a heavier DN32 mast, which would change the mast, base plate, clamps and the BOM and was not approved.
- **Lengths.** The rope hangs 6.51 m below its thimble. The bus cable is 16.8 m (main run 10.5 m, five pod jumpers 5.4 m, 0.9 m of ends inside the pods and the box), 7.3 m of it inside the bin; the BOM carries 18.5 m. The conduit is 6.2 m [G1].

■ G. Environment (R9)

Lead-acid electrolyte freezes near -25 °C at 50 % state of charge and below -50 °C when full (typical manufacturer tables, to confirm on the chosen battery's datasheet) [G2]. At the -30 °C lower limit of R9, the low-voltage disconnect must keep the battery well above half charge, which cuts the usable energy assumed in section D. Amish decided on 2026-10-02 (GGD-DEC-001, item 6) on a controller with an adjustable disconnect set to the battery maker's 50 % figure at -20 °C, about 12.1 V, to be confirmed at TRL 4. Phosphine resistance of the pods is still unverified. R9 is **at risk**.

■ H. Cost (R13)

`budget_usd` is a hypothetical value-engineering target, not a limit (Amish, 2026-10-01).

- Value-engineering target: USD 260. Estimated cost of the constructable design: USD 406.50 per bin, items 1 to 11 and 13 to 17 (USD 146.50 over the target) [H1].
- The concept kit was USD 256.50 (USD 247.00 after the GGD-DDR-001 trims, plus the USD 9.50 plenum probe [H3]). Making it buildable added USD 133.00, and the 2026-10-02 decisions a further USD 17.00 (the 20 W panel, USD 9.00, and an adjustable-disconnect charge controller, USD 8.00; both indicative, no quotes) [H4]: the mast weldment, stay, wall bracket, anchors and six clamps (line 10, now USD 53.00), the pod glands and stops, the enclosure mounting plate, and three lines missing from the concept (antenna, battery fuse and surge protection, conduit). The cost drivers and savings worth trying are in the design decisions register, GGD-DEC-001.
- The farmhouse receiver adds USD 22.00 once per farm; a first prototype with one bin costs USD 428.50 [H2].

■ Requirement status

Table 3. Status of every requirement in GGD-REQ-001 v0.8 [I1], [I2]. Not met items first (none now).

ID	Requirement	Value at TRL 3	Target	Status
R2	Moisture estimate	Sensor-only error 0.23 points (SHT45) and 0.42 points (SHT40) worst case; 0.81 at the SHT40 maximum; equation error not included	±0.8 points, 20 % to 75 % RH	At risk
R6	Heating alert	Center core only, 3.3 % of the section; latency about 13 min	Any pod, alarm within 15 min	At risk
R9	Environment	AGM may freeze near -25 °C at 50 % charge; phosphine unverified	-30 °C to +50 °C; IP66; one fumigation	At risk
R3	Ambient air	SHT45 ±0.1 °C and ±1.0 % RH; shield error unknown	±0.3 °C, ±2 % RH	Not verifiable at TRL 3
R10	Mechanical strength	Rope 8 times 2.5 kN; estimate 2.08 kN; hanger rating per bin	Rope 4 times; hanger rated	Not verifiable at TRL 3
R8	Power autonomy	7.7 days with no sun and the fan continuous; refill from 50 % in 2.9 days with the 20 W panel (7.3 days with 10 W); subject to the stay-off service rule in section F	5 days; refill in 3 days	Met
R4	Fan decision rule	Rule as specified; fan heat measured by the plenum probe within ±0.51 °C, about ±0.5 points of EMC	Rule, minimum run and off times, starts per hour	Met
R1	Temperature profile	6 levels at 0.94 m; ±0.1 to ±0.2 °C; every 10 min	6 or more, 1.0 m or less; ±0.3 °C	Met
R5	Fail-safe control	Normally open relay, stale-data timeout, hand position independent of GrainGuard	Stop in 60 s; hand runs the fan	Met
R7	Radio link	16.9 dB margin at 1 km past one building	1 km, one building, 95 % delivery	Met
R11	Install without grain entry	Empty-bin installation sequence	No entry into a bin holding grain	Met
R12	Electrical isolation	12 V system, charging clamped at 15.0 V; relay input 2.5 kV	15 V or less; 2.5 kV	Met
R13	Cost per bin	USD 406.50 per bin, constructable design; receiver USD 22.00 per farm	Value-engineering target USD 260 per bin, receiver per farm	Over the value-engineering target by USD 146.50
R14	Local data	Farmhouse receiver logs locally	No cloud account	Met

■ Corrections to the TRL 2 documents

- Grain in the reference bin: 123.1 m³, about 3,493 bu, 88.8 t (was about 132 m³, 3,760 bu, 95 t) [A2].
- Airflow at 0.2 cfm/bu: 0.330 m³/s, 699 cfm (was 0.36 m³/s, 760 cfm) [A3].

- Heat to cool the grain 10 °C: about 493 kWh (was about 500 kWh); fan energy per cycle about 48 kWh at 0.40 kW (was 110 kWh at an assumed 1.1 kW) [A9].
- Fan heat: 0.5 to 2.7 °C depending on the fan (was "about 1 °C") [A7].
- Hot spot coverage: 3.3 % (was about 3 %) [C2].
- Autonomy: 7.7 days with the fan continuous and the 3 mA relay input (was 4.8 days) [D5]; recovery 2.9 days with the 20 W panel (7.3 days with 10 W) [D6].
- Radio margin: 16.9 dB at 1 km past a building with the modelled antenna (was about 48 dB over free space at 2 km) [E3].
- Cost: \$247.00 per bin at TRL 3 (was about \$271); \$256.50 with the plenum probe adopted under GGD-DDR-002 [H1], [H3].