DMP Electronics Inc. 瞻營全電子股份有限公司
No.15, Wugong 5th Rd., Xinzhuang Dist., New Taipei City, #24890, Taiwan, R.O.C
Tel:+886-2 22980770 Fax:+886-2 22991883 email:info@dmp.com.tw.

Power budget for Vortex86DX3 (A9126)

Date: 2015/03/18 (V1.0)

Condition	CPU at 1000Hz Dual Core, DDR3 at 800MHz, PCI at 33MHz, Chip Surface Temperature: 85℃	
Voltage	Power Consumption	Recommended Regulator current
Vcore (1.0V)	4A (Maximum)	6A
1.2V	0.45A	0.8A
1.5V	0.4A **(not including DDR3 DRAM chips)**	Note
1.8V	0.15A	0.8A
3.3V	Depending on I/O usage	

Note: External DDR3 components will be a factor that affects 1.5V DDR3 power consumption, thus, the recommended regulator current for 1.5V is not provided.

----------END----------