



# SQ-Panel

Air Quality

**Getting Started for Commissioning  
Devices**

**Getting Started**

Thank you for choosing our air quality sensor. We're glad that you care about your health and the air you breathe – and thank you for letting us support you in monitoring the quality of your indoor air.

To get started, you'll need a smartphone running Android 9.0 or higher or an Apple iPhone.

## 1. Install the Carenuty Home App

- Open the Google Play Store or Apple App Store.
- Search for "Carenuty Home" and install the app.
- Open the app and create your personal account.



## 2. Activate Your Account

- You'll receive an activation eMail.
- Open the eMail and click the activation link to confirm your account.

### 3. Set Up the Connector (Gateway)

- Connect the SQ-Connector to your home internet router (e.g., Fritzbox) using a network cable.

*Note: The red network cable is not included.*

- Use the green micro-USB cable (included) to power the connector.
- The LED next to the network cable will flash yellow. Wait while data exchange completes.
- Follow the instructions in the Carenuty Mobile App.



### 4. Add Your Home Location

In the app, tap "Add another location" and enter a name for your home.

## 5. Add the Connector (Gateway)

- Select "Add Gateway".
- After scanning for available gateways, choose your connector from the list.

*Note: If no connector appears after selecting "Select Gateway", please contact our support team: +49 89 – 1222469 – 40*

## 6. Register the Carenuity Gateway

Execute "Register Carenuity Gateway" to complete the registration.

## 7. Name Your Gateway and Add Your First Room

Give your connector a name and create your first room where your display device will later be placed.



## 8. Open Your Location

Tap the tab showing the name of your location to enter it.

## 9. Add a New Device

Swipe from bottom to top and select "Add New Device".

## 10. Set Up the Display Device (SQ-Panel)

- Plug in the display device using a USB Type-C cable (not included).
- A QR code will appear directly on the display (SQ-Panel).
- Scan this QR code using the built-in scanner in the Carenuity Mobile App.

Note: The display device can be placed at very long distances, well beyond normal Wi-Fi range.

## 11. Assign a Name and Room for the Display Device

Choose a name and select the room where this device belongs.

### Device Setup Complete!

Your SQ-Panel is now connected, and the air quality data is visible on the screen.

You can also access your measurements securely at [Carenuity.com](https://Carenuity.com) using your login details.

The SQ-Panel Webpage includes explanations for readings such as: ppm, TVOC, kPa ... and more, so you always look-up what the values mean.

### Navigator Overview

Inside the Navigator you can:

- Configure your rooms and set threshold values under Carenuity Gateways.
- Add more SQ-Panels under Carenuity Devices.

To add another device:

- Open Carenuity Devices and tap the green plus (+) symbol to activate the QR scanner.
- Scan the QR code shown on the new display device.

