Flux Capacitor

Single button actions		
1 Play "key1.mp3" [3001]	**2** **Music Player :** Previous song [3002]	**3** Play "key3.mp3" [3003]
4 Play "key4.mp3" [3004]	**5** **Music Player :** Play/Stop [3005]	**6** Play "key6.mp3" [3006]
7 Play "key7.mp3" [3007]	**8** **Music Player :** Next song [3008]	**9** Play "key9.mp3" [3009]
★ Start command sequence	**0** **Time Travel**	**#** Abort command
	↑ Volume +	
← Chase speed –	**OK** Execute command	**→** Chase speed +
	↓ Volume –	

Flux Capacitor

Special key sequences	IR	TCD
Set original chase sequence	*10↵	3010
Set alternative chase sequence	*1x↵	301x
Disable **flux sound**	*20↵	3020
Enable **flux sound**	*21↵	3021
Enable **flux sound** (30 seconds)	*22↵	3022
Enable **flux sound** (60 seconds)	*23↵	3023
Set **minimum box light level** (0-4)	*3x↵	303x
Reset chase speed	*40↵	3040
Select volume level (00 - 19)	*3xx↵	33xx
Enable volume knob	*399↵	3399
Music Player : Set folder number	*5x↵	305x
Music Player : Shuffle off	*222↵	3222
Music Player : Shuffle on	*555↵	3555
Music Player : Go to song 000	*888↵	3888
Music Player : Go to song xxx	*888xxx↵	3888xxx
Toggle **IR remote command lock**	*70↵	3070
Toggle usage of Speed knob	*81↵	3081
Say current IP address	*90↵	3090
Restart the Flux Capacitor	*64738↵	3064738
Delete static IP address	*123456↵	3123456
Forget learned IR rem. control	*654321↵	3654321

Control through TCD requires BTTFN connection.