

Flux Capacitor

DR. E. BROWN ENTERPRISES
24 HR. SCIENTIFIC SERVICES



R10001986

Single button actions		
1	2 Music Player : Previous song [3002]	3 Play "key3.mp3" [3003]
4	5 Music Player : Play/Stop [3005]	6 Play "key6.mp3" [3006]
7	8 Music Player : Next song [3008]	9
★ Start command sequence	0 Time Travel	# Abort command
	↑ Volume +	
← Chase speed -	OK Execute command	→ Chase speed +
	↓ Volume -	

Flux Capacitor

DR. E. BROWN ENTERPRISES
24 HR. SCIENTIFIC SERVICES



Special key sequences	IR	TCD
Set original chase sequence	*10↵	3010
Set alternative chase sequence	*1x↵	301x
Disable flux sound	*20↵	3020
Enable flux sound	*21↵	3021
Enable flux sound (30 seconds)	*22↵	3022
Enable flux sound (60 seconds)	*23↵	3023
Set minimum box light level (0-4)	*3x↵	303x
Reset chase speed	*40↵	3040
Music Player : Set folder number	*5x↵	305x
Music Player : Shuffle off	*222↵	3222
Music Player : Shuffle on	*555↵	3555
Music Player : Go to song 000	*888↵	3888
Music Player : Go to song xxx	*888xxx↵	3888xxx
Toggle IR remote command lock	*70↵	3070
Toggle usage of Volume knob	*80↵	3080
Toggle usage of Speed knob	*81↵	3081
Say current IP address	*90↵	3090
Restart the Flux Capacitor	*64738↵	3064738
Delete static IP address	*123456↵	3123456
Forget learned IR rem. control	*654321↵	3654321

Control through TCD requires BTTFN connection.