

Adding and Removing of Basic and additional services on a number

List of basic and additional services: GPRS, telephony, IDD and International roaming, voice, sms and data bundles, postpaid data limit

Steps to add on a prepaid line

1. Enter and query customer's number on order entry (individual portal),
2. Navigate to operations (found at the end of the column with phone number) and click the button for a dropdown menu
3. Scroll down and select modify offer
4. Click on the add button (Under select offer) and search for the desired service, e.g, gprs (for bundles if D.A already exist, click the copy icon after the name of the bundle)
5. Click on the check box to mark the service and click okay to confirm selection of service
6. On order reason (Under order information), select the drop-down and select other reason
7. Put the ticket ID or remarks of your order
8. Click on next to process your order
9. Check the box to confirm customer's order and click next to complete order
10. For bundles, click on waiver, then waiver with a 100 percent discount, put remarks and click okay to waiver, then lastly hit next to process order

Steps to deactivate

1. Enter and query customer's number on order entry (individual portal),
2. Navigate to operations (found at the end of the column with phone number) and click the button for a dropdown menu
3. Scroll down and select modify offer
4. Click the delete icon at the end of the row on queried service

5. On order reason (Under order information), select the drop-down and select other reason
6. Put the ticket ID or remarks of your order
7. Click on next to process your order
8. Check the box to confirm customer's order and click next to complete order

SIM CARD REPLACEMENT

Steps of doing a sim replacement on order entry individual portal

1. Switch to Econet back-office portal
2. If it's a normal card, authenticate sim card first
3. Enter and query customer's number on order entry (individual portal)
4. Navigate to operations (found at the end of the column with phone number) and click the button for a dropdown menu
5. Click on sim replacement
6. Enter Sim card number/ ICCID
7. On order reason (Under order information), select the drop-down and select other reason
8. Put the ticket ID or remarks of your order
9. Check the box to confirm customer's order and click next to complete order
10. Click on next to process your order

Balance adjustment, adding a new account/ D.A. and bundle conversion

Steps for balance adjustment

1. Enter and query customer's number on account receivable,
2. Identify queried balance/ account and click on Adjust
3. Enter number of units, select the unit of measurement, input remarks/ ticket ID, or change the window period, then select ok to confirm adjustment

Steps for adding a new account/ new DA

1. Enter and query customer's number on account receivable,
2. Select add account balance
3. Select dropdown menu on account balance type to pick queried account type
4. Add balance (a number, e.g, 11) and select unit of measurement for specified account type.
5. Select effective date and Expiry date to determine window period
6. Select dropdown to select service number (suggested)
7. Press okay to create and complete order

Steps for bundle conversion

1. Enter and query customer's number on account receivable,
2. Identify queried balance/ account and click on Adjust
3. Enter number of units, select the unit of measurement, input remarks/ ticket ID, or change the window period, then select ok to confirm adjustment
4. Select the correct currency and do adjustment (see balance adjustment steps)

One way block or two-way block activation and deactivation (Suspension under request and Sim card lost)

Steps for activation

1. Enter and query customer's number on order entry (individual portal),
2. Navigate to operations (found at the end of the column with phone number) and click the button for a dropdown menu
3. Scroll down and select either suspension under request or sim card lost
4. On order reason (Under order information), select the drop-down and select order reason
5. Put the ticket ID or remarks of your order
6. Click on next to process your order
7. Check the box to confirm customer's order and click next to complete order

Steps for deactivation

1. Enter and query customer's number on order entry (individual portal),

2. Navigate to operations (found at the end of the column with phone number) and click the button for a dropdown menu
3. Scroll down and select reactivation or restore
4. On order reason (Under order information), select the drop-down and select order reason
5. Put the ticket ID or remarks of your order
6. Click on next to process your order
7. Check the box to confirm customer's order and click next to complete order

Checking for Basic and Additional services on a number

Steps

1. Enter and query customer's number on order entry (individual portal),
2. Click on the queried phone number
3. Scroll down and select on additional services to identify the service being queried

Checking for complete and hanging orders

Steps

1. Enter and query customer's number on order entry (individual portal),
2. Click on Order to view the orders
3. Click on detail to view detailed order information

Line Reconnection

Steps for reconnection

1. Switch to Econet back-office portal
2. Enter and query customer's number on order entry (individual portal)
3. Compare the shared ICCID, ID number and Customer's full name and proceed if details are matching

4. Open system menu, Expand Sales Inventory Center and click on SIM Card Lifecycle
5. Enter ICCID on FROM section then click the TO tab to auto populate the ICCID and query
6. Check the results and if sim is in disabled state, tick the box and click on recycle then click ok to complete order, if state is available, then escalate to billing so that state can be changed to inactive
7. Open system menu, Expand Sales Inventory Center and click on SIM Card binding/ unbinding
8. Enter the phone number on FROM and TO boxes, then click on Service Number Quantity
9. Enter the ICCID on FROM and TO boxes, then click on Service Number Quantity
10. Click on Query to load information
11. Click on Bind to bind the ICCID and the phone number
12. Enter and query customer's number on order entry (individual portal)
13. Click on the House like Icon
14. Select service class and order
15. Input ICCID and remarks then click on next
16. Check the box to confirm customer's order and click next to complete order and number will go in an inactive state
8. On Oder Entry, navigate to operations (found at the end of the column with phone number) and click the button for a dropdown menu
17. Click on PPS first dial, click on next, and confirm order to activate sim card
18. Authenticate SIM Card so that it will be able to attach to network

BASIC TROUBLE SHOOTING

Hanging Orders/ Incomplete orders (Basic service provisioning, sim replacement, bundles, One way or two-way block)

Steps for hanging order for sim replacement

1. Enter and query customer's number on order entry (individual portal),
2. Click on Order to view the order and state
3. Open system menu, expand the Provisioning tab, then open Dispatch Order Query
4. Enter service number starting with prefix (263), then click on query
5. Copy the dispatch order
6. Open system menu, expand the Provisioning tab, then click on Online Work Order Query
7. Select the Abnormal Work Order tab, then enter the dispatch order ID of your hanging order and click query
8. Double click on the order to see check out remarks (why the order couldn't complete)
9. If there is no Authentication, then authenticate card on HLR, then come back to Abnormal work order query, tick your order then click on redo to complete order, then check again if order has been pushed
10. If there is a Change Over already initiated, then use the HGIRI command on HLR, then come back to Abnormal work order query, tick your order then click on redo to complete order, then check again if order has been pushed
11. If there is IMSI Already Initiated or any other errors, check if order has gone through HLR, then use the Check in button under Abnormal order query

Failing to roam

Steps

1. Check if customer is provisioned for roaming on cvBS
2. Check if customer has the correct roaming parameters (RSA) on HLR, (RSA 2- Prepaid FULL Roaming, RSA 6- Prepaid Voice and SMS, RSA 5- Postpaid Voice and SMS, RSA 4-Postpaid FULL Roaming)
3. Check if network addresses are not blocked or restricted (VLR, SGSN), do a reset if they are restricted
4. Check the Country they are in, if we have roaming partners
5. Check the Country if it requires LTE roaming activation
6. If LTE roaming is active, verify if all parameters are correct
7. Advice customer to Lock in to 4G, then try manual section of network
8. Lastly escalate to roaming team, might be an issue with the partner.

Failing to Access USSD Codes

Steps

1. Check if number is active (no one way or two-way block)
2. Check on HLR if number has no OBSSM, remove using command with SUD if available
3. Advice customer to use a different device to check if its not handset related
4. Advice customer to do a sim replacement and see if issue can be resolved
5. Escalate to VAS to check for possible blacklists (most cases if there is no OBSSM, it's a device or Sim Card issue)

Failing to Buy bundles

Steps