

What it is: A compact, grab-and-go **293Wh power station** — quiet, no fumes, recharges fast. Perfect for camping, road trips, tailgates, and short power outages.

293Wh

CAPACITY

300w

OUTPUT

500w

SURGE PEAK

7.1lb

WEIGHT

TOP SELLING POINTS

- ✓ **Ultra-portable** — only ~7 lbs with a sturdy handle; toss it in the car
- ✓ **6 ports** — 2 AC wall outlets, USB-C PD (60W), USB-A ports, and a 12V car port
- ✓ **Fast recharge** — wall + USB-C together in as little as ~2.5 hrs; solar-ready
- ✓ **Solar generator** — pair with a SolarSaga panel for free off-grid power
- ✓ **Silent & safe indoors** — no gas, no fumes, no noise like a generator
- ✓ **Pure sine wave AC** — safe for phones, laptops, cameras & small electronics

WHAT IT CAN RUN (APPROX.)

- ✂ Phone — **20+ recharges**
- ✂ Laptop — **4 charges**
- ✂ Mini fridge — a few hours
- ✂ CPAP — overnight (DC)
- ✂ Camera, drone, lights, fan

PORTS

- 2× AC outlets (300W / 500W peak)
- 1× USB-C PD (60W)
- 1× USB-A QuickCharge 3.0
- 1× USB-A
- 1× 12V car port

FULL SPECIFICATIONS

Capacity	293 Wh (Lithium-ion)
AC Output	300W continuous • 500W surge peak (pure sine)
USB-C	60W Power Delivery
Recharge (AC)	~4.5 hrs wall • ~2.5 hrs wall + USB-C
Recharge (Solar)	~3.5 hrs to 80% w/ SolarSaga 100W
Weight	~7.1 lb (3.2 kg)
Best For	Camping, road trips, tailgating, short outages

Verify on your box before you quote it live: exact weight & recharge time can differ if you're selling the newer **Explorer 300 v2 (LiFePO4)** or **300 Plus** instead of the original 300. Solar panel is sold separately.