JIANT FM · SOUND · FX · MOD

engines, effects, modulation, sequencer and songs

firmware v0.6.10 · M-VAVE FM-1 · juanjiant-bit.github.io/JIANT

ENGINES · EDIT 1 / EDIT 2

EIGHT ENGINES, ALL SYNTHESIS

ENGINE	EDIT 1				EDIT 2				WHAT TO KNOW
ANALOG	WAVE	DTN	MIX	NOIS	CUT	RES	DRV	INT	SAW SQR TRI SIN PWM **SYNC RING SAW3**; INT: osc 2 ±24 st. Its filter is per voice.
FM6	ALG	FB	MLVL	MRAT	MEG	VMOD	DTUN	SLOT	Dexed's 6 operators, 32 algorithms drawn, .syx patches (SLOT), MLVL / MRAT move the modulators. **OPERATOR · OP ENV · OPERATOR 2**: each operator on the device (ratio / fixed, fine, level, its envelope, mode, detune, velocity).
PHASE	WAVE	WAVE2	DCW	ENV	DTN	LINE	SUB	FB	Phase distortion (CZ); **FB** feeds the output back into the phase: hard edge to growl.
LOFI	CHIP	WAVE	DUTY	CRSH	-	VIB	BEND	MASK	Chip: PLS TRI SAW NOIS WRAM. **BYTE**: ALGO VAR · MOTN GRIT BEND LOOP. **FLOAT** (floatbeat): ALGO VAR · MOTN FBK BEND LOOP; CHIP sets FULL / 4BIT / 1BIT.
VOICE	VOWL	VOWL2	TALK	SHIFT	BUZZ	BRTH	Q	RAND	Formant voice (after klattsch): vowels, talk, breath.
WHEEL	REG	SUB	BODY	TOP	PERC	CLICK	DRV	ROTR	Drawbar organ: registrations, percussion, rotary.
NOISE	MODE	COLR	FREQ	PEAK	TRK	DENS	DRFT	CRSH	Coloured and metallic noise, tracked or free.
DRUM-X	MRPH	TUNE	TONE	DECY	NOIS	FM	FOLD	DRV	8 sounds BD SD CP CH OH TM RS CB, sides A / B: **MRPH** morphs the kit. SOUND 1–3: LANE SIDE PTCH PMOD · DCAY NOIS COLR MODE · LANE PMOD DRV WAVE. **X-MOD**: RATE DPTH SHPE RAND.

FILTER · EVERY ENGINE

TYPE | CUT | RES | DRV

LP · HP · BP · COMB. COMB rings tuned to the note: CUT moves it ±32 st, RES how much it rings. ANALOG and LOFI: per voice; the others: on the track, following LFO / ENV DEST FLT (DRV = the track's DIST).

VOICE · PLAYING

VCE | GLD | GLMOD | PRIO

POLY · MONO · LEG · UNI; glide and its mode; LAST / LOW / HIGH priority. **8 voices** shared by the six tracks (MONO and LEGATO keep their note).

DICE

SELECT off HOME / GLOBAL: a random factory preset of the engine, every parameter moved up to a quarter of its range. DRUM-X: both sides of every sound around the factory kit. Roll until something clicks.

MODULATION

ENV · LFO

ENV

ATK | DEC | SUS | REL

ENV DEST

FLT | PIT | SHP | LOOP

LOOP: held, the envelope cycles from the sustain: an ADSR-shaped LFO.

LFO

RATE | WAVE | PHS | FADE

SIN TRI SAW SQR S&H

LFO DEST

PIT | FLT | SHP | AMP

MOD MATRIX · 4 SLOTS A TRACK

SLOT | SRC | DST | AMT

SOURCES

LFO · ENV · VEL · KEY · RAND · MODW · AT · EXPR · M1 · M2 · M3 · M4 · STEP

DESTINATIONS

PITCH · CUT · SHP · AMP · PAN · DIST · CHO · DLY · REV · RATE · VIB · E1…E8 · CLIP · PNCH

E1…E8: the engine's own EDIT knobs. CLIP / PNCH: the master.

MSEQ · MACROS

MSEQ · A CV SEQUENCER PER TRACK

STEP | LVL | LEN | SLEW

16 levels, DIV on MSEQ 2, in time with the transport. Use it from MOD, SRC STEP.

MACROS M1–M4

Hold LFO: the knobs are M1–M4, latched until LFO again. Each session starts with 2 random routes a track; SELECT / F3 roll new ones, G3 clears. By hand: MOD, SRC M1…M4. Saved with the project.

SEQUENCER

64 steps a track, up to 4 notes a step, piano roll and drum grid. **Hold a step + turn a knob**: a parameter lock. CHANCE (0–100 %) and RATCH (x1–x4) per step. REC + knobs while playing: automation (64 records a section, MOTION page plays / clears them, AUTO LIST edits them).

PATTERN · SHIFT

LEN | DIV | SWG | GATE

OFS | PIT | - | -

SCALE · ARP

ROOT and SCALE are every melodic track's: CHR MAJ MIN DOR MIX PEN MPEN HARM PHRY LYD LOC MEL BLUES WHOLE DIMHW DIMWH. QNT snaps keys or the sequence, TRN transposes, **STRN** (SCL 2) moves every sequence along the scale.

ARP MODES

OFF UP DN UPDN RND ORD REPEAT DNUP UP+8 CONV DIVG PINKY THUMB WALK CHORD **TRNS** (the keys transpose the sequence)

SONGS

8 songs × 4 sections (A–D), a chain of up to 16 rows by bars (SEQ › SONG), SLOOP style. Each row can hold a **scene**: mutes, DRUM-X group mutes, macros and MIDI punch-ins. SAVE held plays sections live on the next bar, stores them, records the song (SONG REC). Each section keeps its sounds, steps, motion, kit and its SLICER.

EFFECTS

PER TRACK

FX · SENDS

DST | CHO | DLY | REV

DIST

DST | TYPE | TONE | -

SOFT · HARD · FOLD · CRUSH · RECT.

AUTOPAN

DPTH | RATE | SYNC | WAVE

The track's pan swung L–R around its PAN. SYNC **BEAT**: RATE 4 BARS … 1/32, in time with the bar; **FREE**: in Hz. SIN · TRI · SAW · SQR · S&H, never a click.

SLICER · ONE ON A BUS

SLCR | PAT | RATE | DEPTH

OFF · GATE · STUT, 16 patterns, 1/8 … 32T. **SL BUS**: T1–T6 and **FX** (the delay / reverb / chorus returns) ON / OFF: everything on = the whole mix chopped after the effects. **SL PITCH**: the repeats' 16-step pitch (±24 st, tape style, QNT SCL to the scale).

DELAY · CHORUS

DLY

TIME | FDBK | TONE | MIX

DLY 2

WIDE | PITCH | SPRY | -

Synced or free (5 ms – 1.48 s); PITCH / SPRY: a grain delay.

CHORUS

RATE | DEPTH | STER | -

STER: 0 as always, down to mono, up to twice as wide.

REVERB · FIVE MODELS

TYPE | SIZE | DAMP | PRE

MOD | RATE | FILT | WIDE

TYPE	WHAT IT IS	SIZE	DAMP	MOD	RATE	WIDE
ROOM	Classic room	decay	darkens	chorus on the tail	its speed	stereo
SPRING	Amp spring tank	length · decay	darkens	wobble	wobble speed	stereo
SHIMR	Up an octave on every pass	decay	darkens	how much shimmer	—	—
RESO	4 strings tuned to the scale; **PRE → PITCH** (0–14 steps up), **DAMP → FOLW** (OFF / T1–T6: the chord follows that track's notes)	how long they ring	FOLW	past half: the chord opens	—	—
CLOUD	Granular wash; SIZE max **freezes** it	decay · freeze	darkens	grains pitched + chorus	grain density	grain spread

MASTER

CLIP | PNCH | DUCK | REL

CLIP saturates without getting louder. **PNCH** drives the drums: denser body. **DUCK**: the kick pulls the rest down (REL its release). An always-on **leveler** (slow 2:1, –9…+6 dB) before the limiter keeps patches at a steady volume.

PUNCH-IN FX (FX HELD)

REPEAT 1/8 · 1/16 · 1/32, LPF, HPF; on the notes: OCT–/+, ½ TEMPO, DEC–/+, STUTTER, ATK+, ARP, RANDOM. Knobs: FILTER CRUSH THROW DEPTH. Recordable per section.