UNITED STATES POSTAL SERVICE.

DBCS Processing Methodology

Job Instructions

January 2013

Job Instruction: DPS-01 Feeder Duties - 918 & 919 Set Up

IMPORTANT STEPS	KEY POINTS	REASONS
1. Load the 1st pass sort plan and start processing	1. Enough volume to start the machine	1. To initiate 1st pass
2. Print 2nd pass labels and continue running 1st pass	1. While running 1st pass 2. Run all 1st pass mail	1 For sweeper to label 2nd pass racks 2. To maximize DPS
3. Notify maintenance	1. When 1st pass is completed 2. To allow clean up	1. Prepare for 2nd pass
4. Assist with sweep-down	1. Sweep from front end of the machine 2. "Up-down" technique	1. Closest to the feeder 2. To expedite pull down and reduce the static posture*
5. Pull down non-sequenced trays	1. Place in designated area 2. Non-DPS trays in 1st pass rack (top)	1. Reject and residue for subsequent handling 2. Carrier routed for dispatch
6. Prepare 2nd pass and start processing	1. Position first two tray racks to the feeder	1. Efficient changeover

* Safety

DPS-01 Feeder Duties- 918 & 919 Set Up

1. Before starting any DBCS, the feeder conveyor, including the jogger, is to be **fully edged and loaded** with mail.

2. Ensure old tray labels are removed and properly disposed, minimizing missent trays.

3. The machine operator is to work primarily **in front of the jogger**, not next to the feeder mechanism.

4. Ensure operators **cull** damaged, oversized, irregularly sized, and some types of open mail capable of causing jams.

5. Inform operators if large amounts of bi-fold, odd, poor candidate, or irregularly shaped mail is being fed, it is helpful to use the **plugging method** to increase the likelihood of processing and reducing mail piece damage.

6. After jogging, edging, and culling, the mail should then be pushed towards the feeder mechanism **using two hands.** The feed paddle should then be placed behind the last piece of mail.

7. The feeder operator is responsible for maintaining full ledges and a constant mail flow to the feeder.

8. The feeder operator is responsible to clear the jams in the feeder section. On DBCS's this includes the elevator transport section.

9. The machines have been engineered to have little interaction with the feeder mechanism. The feeder is designed to control the pressure on the pick-off belt. An operator **can not maintain the machine loading at the feeder table.**

10. The paddle is designed to keep the mail in a vertical position. The operator **should not apply pressure to the paddle.**

11. The **slide** must remain in the **closed position** unless there is a machine problem. Running the DBCS with slide in the open position deteriorates machine performance. The only acceptable time when the slide should be in the open position is when clearing jams in the feeder pick-off area.

12. Ensure operators are aware of the Machine Acceptance Rate (**MAR**) & Gross Acceptance Rate (**GAR**). These values indicate how well the machine is reading barcodes and sorting correctly.

Job Instruction: DPS-02 Sweeper Duties-918 & 919 Set Up

IMPORTANT STEPS	KEY POINTS	REASONS
1. Prepare the 1st & 2nd pass racks	1. While running 1st pass 2. Place empty trays 3. Label trays for 2nd pass	1. Mail is distributed evenly and slowly into the bins at the beginning of the run
2. Sweep bins at the end of 1st pass	1. Reduce bin volume for final sweep 2.From back end toward middle 3. "Up-down" technique	1. To expedite sweep 2. To meet the feeder in middle of the machine 3. To expedite pull down and to reduce static posture*
3. Position first 2 racks of the 1st pass	1. Align them parallel to the feeder	1. Easy for feeder to pull out trays to the TMT for jogging
4. Position remaining 1st pass racks	1. While replacing with 2nd pass racks	1. Keep racks in order
5. Set up the dispatch containers for 2nd pass	1. APC or APC with inserts 2. Place the dispatch placards	1. Ready to pull down when 2nd pass is done
6. Take care of all non-DPS mail	1. Rejects to the designated area 2. Dispatch non-DPS mail	1. For subsequent handling 2. Per local SOP

* Safety

DPS-02 Sweeper Duties- 918 & 919 Set Up

1. Upon machine startup the Sweeper is to fill all the tray racks with empty trays and place labels in the trays.

2. The Sweeper is responsible to sweep stackers when the mail has filled at least half the stacker.

3. The stacker blade support arm should not be allowed to activate the 100% bin full switch during the sweeping process.

4. Always leave approximately 2 inches of mail in the stacker pocket when sweeping a machine that is running. This is called the **"2 inch rule"**. It prevents exposure to and potential injury from moving parts.

5. The Sweeper is to **rotate** assignments during the tour with the Feeder. It is recommended **at least every two hours**. Ensure replacements are capable of performing each task properly, maintaining the same level of performance.

6. **Periodically verify** that the tray labels and contents are accurate. When errors are found, those should be corrected because that mail being in the wrong tray causes the out of sequence stops during 2nd pass, requiring subsequent handling, or causes 3 M's at the Station and potentially impacting service.

7. Ensure operators **verify labels** before dispatching. Missents negatively impact service and costs.

8. Ensure trays are **not overstuffed**. This often causes mail to fall out of overstuffed trays in transit.

9. During final dispatch, the feeder is to work with the sweeper to sweep and dispatch the entire machine.

10. Employees must **set-up for the next tour** as much as possible, have mail and support MTE on hand.