MILITARY SPECIFICATION

VOLTAGE REGULATOR SUBASSEMBLY: 10525760

This amendment forms a part of Military Specification MIL-V-60218(MU), dated 3 March 1965.

Paragraph 1.1: Delete "+143 volt +78 volt and substitute "+138 volt, +73 volt.

Table I, under Load Current Settings: Delete "(+3 percent)" and substitute "(± 3 percent)".

Following paragraph 4.1.1: Add paragraphs 4.1.2, 4.1.2.1 and 4.1.2.2 as follows:

"4.1.2 First Article (Initial Production) Approval.- The requirement for first article approval and the responsibility (Government or contractor) for first article testing shall be as specified in the contract. The sample for first article approval tests shall consist of three (3) voltage regulators manufactured in the same manner using the same materials, equipment, processes, and procedures as used in regular production. All parts and materials, including packaging and packing, shall be obtained from the same source of supply as used in regular production.

4.1.2.1 Government Testing.- When the Government is responsible for conducting first article approval tests, the contractor, prior to submitting the sample to the Government, shall inspect the sample to insure that it conforms to all the requirements of the contract and submit a record of this inspection with the sample, including certificates of conformance for materials.

4.1.2.2 Contractor Testing.- When the contractor is responsible for conducting first article approval tests, the sample shall be inspected by the contractor for all the requirements of the contract. The sample and a record of this inspection, including certificates of conformance for materials, shall be submitted to the Government for approval. The Government reserves the right to witness the contractor's inspection."

Paragraph 4.2.3: Add the following sentence: "No lots shall be accepted until control samples have been satisfactorily tested."

Paragraph 4.3.2: Delete first sentence and substitute:

"Voltage regulator units shall be selected at random by Government representatives as control samples from each three (3) months production or portion thereof as follows:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:19Z
Check the source to verify that this is the current version before use.

3 units per first 100 produced
5 units per 200 "
7 units per 300 "
9 units per 400 "
10 units per 500 "
12 units per 700 "
15 units per 1000 "
and 2 units for each 100 items produced in excess of 1000.

Paragraph 4.5.1.3.2: Delete in its entirety and substitute:

"4.5.1.3.2 Operating.- This test shall be conducted in accordance with the humidity test defined in Procedure III of MIL-F-13926, except that the humidity shall be maintained at 92 to 97 percent for the 24 hour period, and the tests shall cease at the end of that period (Method 106 of MIL-STD-202 shall be excluded). Throughout the test period, the board shall be capable of performing the test of 4.5.2.4. In order to demonstrate this capability, the tests of 4.5.2.4 shall be performed a minimum of once each 6 hours of the period. The final test shall be conducted during the final portion of the 24-hour period. Between tests, the board shall be electrically de-energized.

Paragraph 4.5.1.4: Delete in its entirety and substitute:

"4.5.1.4 Salt spray.- This test shall be conducted in accordance with the salt spray test defined in Method 101, Condition B of MIL-STD-202 using a 5 percent salt solution. At the end of the exposure period, salt deposits shall be removed from the board by a gentle wash, not exceeding 30 minutes, in running water not warmer than 100°F, using a soft-hair brush or plastic-bristle brush. The board shall be air dried in a controlled environment at 72°F ± 5°F and a relative humidity of 30 to 50 percent for a period of 24 hours. The board shall be inspected visually for any physically damage, then tested in accordance with 4.5.2.2 to 4.5.2.4.2.2 inclusive."

Table VI, Part Number column: Delete "10525778-8 and 10525778-9" and substitute "10525778-3 and 10525778-16 respectively".

Table VII: under Power Supply No., add "11"; under Nominal Voltage, add: "32"; under Current Requirement (amperes), add: "0.200"; under Positive Terminal, add: "Load ground"; under Negative Terminal, add: (see Figure#3).

Paragraph 4.5.2.1.1.3: Delete "9.5 ± 0.095 amperes and substitute "9.5 $^{+\ 0.57}_{-\ 0.00}$ amperes"; delete "9.5 ± 0.285 amperes" and substitute "9.5 $^{+\ 0.57}_{-\ 0.00}$ amperes."

Paragraph 4.5.2.1.1.4: Add to end of paragraph "except for the trip current resistors. The trip resistor values shall be those determined by selecting the ratio of resistors (R9 to R10) that causes tripping at a current nearest to but ≥ 9.5 amperes.

Paragraph 4.5.2.4.1.4: Delete "9.5 + 0.85 amperes" and substitute "9.5 $^{+\ 1.5}_{-\ 0.0}$ amperes".

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:19Z
Check the source to verify that this is the current version before use.

* Paragraph 4.5.2.4.1.5: Next to last sentence: Change "3 seconds" to "4 seconds"

Figure 2: Delete "53B" and substitute "35B"
35B 37B
37B 38B
38B 36B
36B"

* The outside margins have been marked to indicate where additions to the previous amendment have been made. This has been done as a convenience only and the Government assumes no liability whatsoever for any inaccuracies in this notation. Bidders and contractors are cautioned to evaluate the requirements of this document based on the entire content as written irrespective of the marginal notations and relationship to the last previous amendment.

Custodian:

Army - MU

Preparing Activity:

Army - MU

Project No. 1220-A198

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:19Z
Check the source to verify that this is the current version before use.