MILITARY SPECIFICATION

POWER SUPPLY PP-1104( )/G

This specification is approved for use by all Departments and Agencies of the Department of Defense.

1. SCOPE

1.1 Scope. - This specification covers one type of power supply which will convert 115 or 230 volts (nominal), 60 cycles per second, single phase alternating current to 14 and 28 volts direct current.

2. APPLICABLE DOCUMENTS

2.1 The following documents of the issue in effect on date of invitation for bids, form a part of this specification to the extent specified herein.

SPECIFICATIONS

FEDERAL

QQ-S-781	Strapping, Steel, Flat and Seals
PPP-B-585	Box, Wood, Wirebound
PPP-B-601	Boxes, Wood, Cleated-Plywood
PPP-B-621	Box, Wood, Nailed and Lock Corner
PPP-B-636	Box, Fiberboard
PPP-F-320	Fiberboard, Corrugated and Solid, Sheet Stock (Container Grade) and Cut Shapes
PPP-T-76	Tape, Pressure-Sensitive Adhesive Paper, Water Resistant, (For Carton Sealing)

MILITARY

MIL-P-116	Preservation, Methods of
MIL-P-11268	Parts, Materials and Processes Used in Electronic Equipment
MIL-M-13231	Marking of Electronic Items
MIL-F-14072	Finishes for Ground Signal Equipment

STANDARDS

MILITARY

MIL-STD-105	Sampling Procedures and Tables for Inspection by Attributes.

FSC 6130

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

MIL-STD-129	Marking for Shipment and Storage
MIL-STD-252	Wired Equipment, Classification of Visual and Mechanical Defects
MIL-STD-454	Standard General Requirements for Electronic Equipment
MIL-STD-781	Reliability Tests: Exponential Distribution
MIL-STD-810	Environmental Test Methods

DRAWINGS

ELECTRONICS COMMAND

SC-DL-398200	Power Supply PP-1104( )/G

(Copies of specification, standards, and drawings required by contractors in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer. Both title and number or symbol should be stipulated when requesting copies.)

3. REQUIREMENTS

3.1 First article. - When specified in the contract or purchase order, the contractor shall furnish first articles in accordance with 4.3.

3.2 Construction. - The equipment shall be constructed in accordance with Drawing SC-DL-398200.

3.3 Parts, materials and processes; general. - In addition to the requirements of this specification and on the drawings specified in 3.2, the requirements of MIL-P-11268, shall apply where practicable.

3.4 Performance

3.4.1 Input. - The power supply shall operate from both 115 volts and 230 volts (± 10%), 60 Hz, single phase, alternating current.

3.4.1.1 No load input current. - The no load input current shall not exceed 4.5 amperes with 115 volts AC RMS input and the INCREASE VOLTAGE switch in position 4.

3.4.1.2 Full load input current with 115 volts AC RMS. - The input current shall not exceed 24 amperes with 115 AC RMS volts input and the INCREASE VOLTAGE switch in position 4, under full load conditions.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

3.4.1.3 Full load input current with 230 volts AC RMS. - The input current shall not exceed 12 amperes with 230 volts AC RMS input and the INCREASE VOLTAGE switch in position 4, under full load conditions.

3.4.2 Output. - The power supply shall furnish the following direct current outputs (not simultaneously):

a. 11.5 volts to 17.5 volts at 100 amperes (14 volts nominal).
b. 23 volts to 35 volts at 50 amperes (28 volts nominal).

3.4.2.1 Output voltage range, full load. - When the INCREASE VOLTAGE switch is rotated from position 1 to 8, the output voltage shall progressively increase, and the following requirements shall be met for the position when tested in accordance with 4.8.1 and 4.9.1.

a. Operation, 14 volts D.C.

Position 1	11.5 volts ± .6 volts
Position 4	14.0 volts ± 0.75 volts
Position 8	17.5 volts ± .96 volts

b. Operation, 28 volts D.C.

Position 1	23 volts ± .92 volts
Position 4	28 volts ± 1.0 volt
Position 8	35 volts ± 1.4 volts

3.4.3 Regulation.

3.4.3.1 Operation, 14 volts D.C. - When tested as specified in 4.8.2, the regulation shall not exceed 6 percent.

3.4.3.2 Operation, 28 volts D.C. - When tested as specified in 4.9.2, the regulation shall not exceed 4 percent.

3.4.4 Ripple. - The AC RMS component shall not exceed 0.9 percent of the output under full load conditions. The peak to peak value shall not exceed 2.5 percent.

3.5 Finish. - The equipment shall be finished in accordance with Specification MIL-F-14072, and the equipment drawings. This includes finish of hardware, such as handles, hinges, screws, etc., and necessary touch up after mounting. The final paint film on Type 1 surfaces shall be final film E, semigloss, light gray enamel, conforming to Specification MIL-F-14072. (See 4.4)

3.6 Marking. -

3.6.1 General. - Marking shall conform to Specification MIL-M-13231, except that any group 1, 11, or 111 marking and any material and process for labels, as described in that specification, may be used for surfaces exposed to view during use or storage of the equipment. (See 4.4)

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

3.6.2 Visibility. - Wherever practicable, parts shall be so mounted that their identification markings will be readily visible with minimum disassembly of the equipment.

3.6.3 Serial Numbers. - Each PP-1104( )/G Power Supply shall have a serial number.

3.7 Cleaning. - The equipment shall be cleaned prior to subjection to any first article or quality conformance inspection, and all equipment on contract or purchase order shall be cleaned in the same manner. The cleaning procedure and cleaning agents shall have no deleterious effect on the performance requirements of the equipment. The cleaning process shall remove such contaminants as corrosion products, dust, fingerprints, excess lubricating oils, mold release agents, sand, solder flux residues, outgassing products and any other contaminants which could contribute to corrosion, fungus growth or loss of moisture resistance.

3.8 Breakdown voltage, insulation. - Electrical insulation shall have the minimum breakdown voltage shown in table I. After 10-second application of the voltage, there shall be no visible deterioration and the equipment shall meet performance requirement of 3.4. (See 4.10)

Table I - Breakdown voltage, insulation

Operating voltage (Note A)	Breakdown voltage (Note B)
0 to 30 volts ------	400 volts
30 to 125 volts -----	500 volts
125 to 500 volts -----	4 times operating voltage

NOTE A: Operating voltage shall be maximum instantaneous AC plus DC during use of the equipment under specified service conditions.

NOTE B: Minimum breakdown voltage shall be DC or peak AC. If AC, the waveform shall be approximately sinusoidal and the frequency not over 100 cycles per second.

3.9 Interchangeability. - Like units, assemblies, subassemblies, and replaceable parts shall conform to requirement 7 of MIL-STD-454. (See 4.17)

3.10 Service conditions. - The equipment shall meet the following service conditions:

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the currentversion before use.

3.10.1 Temperature.

3.10.1.1 Low. - During and after testing as specified in 4.11.1, the equipment shall meet the requirements of 3.4.2.1.

3.10.1.2 High. - During and after testing as specified in 4.11.2, the equipment shall meet the requirements of 3.4.2.1.

3.10.2 Humidity. - The Power Supply PP-1104( )/G shall exhibit no physical damage (such as corrosion, rust, blistering, swelling, or deterioration) of parts and materials, and shall meet the requirements of 3.4.2.1 during operating times specified in the test. (See 4.12)

3.10.3 Altitude (elevation). - The equipment shall meet the requirements of 3.4.2.1 both during and after testing as specified in 4.13.

3.10.4 Fungus. - After the fungus test of 4.15 the power supply shall be visually examined, using a 10 power magnifier. The power supply shall show no more than six minute unrelated spots, no greater than 0.125 square inch in area as sparse microbial growth (6.6.3) as evidenced by growth colonization (6.6.2) (which includes branching (6.6.1) and sporulation (6.6.4) on or within each cubic foot of equipment assembly volume. Isolated instances of partial tubular germination (6.6.5) shall not be included in this evaluation.

3.10.5 Vibration. - When tested in accordance with 4.14, the amplitude of vibration of any part, subassembly, or structural member of the equipment shall not exceed twice the amplitude of the vibration applied to the equipment at any frequency between 10 and 55 Hz per second.

3.11 Preconditioning. -

3.11.1 Burn-In. - Each equipment produced shall be subjected to the burn-in of 4.6 prior to Group A inspection.

3.12 Technical literature, tools, and running spare parts. - Technical literature, tools, and running spare parts shall be furnished if specified in the contract. Running spare parts shall be identical to corresponding parts in the equipment furnished on the order. (See 6.2)

Source: https://assist.dla.mil -- Downloaded: 202640-26T04:14Z
Check the source to verify that this is the current version before use.

3.13 Workmanship. - The equipment shall be manufactured and assembled in accordance with the applicable portions of the following paragraphs herein:

3.5	Finish, Protective
3.6	Marking
3.7	Cleaning

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. - Unless otherwise specified in the contract or purchase order, the contractor is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or purchase order, the contractor may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.2 Classification of inspection. - The inspection requirements specified herein are classified as follows:

a. First article inspection. (See 4.3) Does not include preparation for delivery.

b. Inspections covered by subsidiary documents. (See 4.4)

c. Quality conformance inspections.

(1) Quality conformance inspections of equipment before preparation for delivery. (See 4.5)

(2) Quality conformance inspection of preparation for delivery. (See 4.18)

4.3 First article. - Unless otherwise specified in the contract or purchase order, the first article inspection shall be performed by the contractor.

4.3.1 First article units. - The contractor shall furnish three (3) first article units of the complete Power Supply PP-1104( )/G.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the current version before use.

4.3.2 First Article Inspection. - The first article inspection shall consist of inspections specified in Table II, and shall be performed in the order specified therein.

4.3.3 First Article Data. - The first article test plan and test report(s) shall be as required in the contract or purchase order.

Table II First Article Inspection

Inspections	Req't. Para.	Test Para.	Unit 1	Unit 2	Unit 3
1. Inspections covered by subsidiary documents		4.4	Inspections to be performed on all units.		
2. Burn-In	3.11.1	4.6	Inspections to be performed on all units.		
3. Group A inspection	see Table III		inspections to be performed on all units.		
4. Group B inspection	see Table IV		inspection to be performed on all units.		
5. Environmental					
Low temperature	3.10.1.1	4.11.1	1		
High temperature	3.10.1.2	4.11.2	2		
Humidity	3.10.2	4.12		1	
Altitude	3.10.3	4.13	3		
Vibration	3.10.5	4.14			1
Fungus	3.10.4	4.15			2

See Notes for Table II on next page.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

Table II First Article inspection (Cont'd)

NOTES:

a. The inspections 1 through 4, in the order shown, shall be performed on all first article units before subjecting these units to any other inspection requirements specified in the table.

b. The implementation of inspections covered by 5 shall be expedited to satisfy contract delivery requirements.

c. The numbers in the unit columns in the table covered by 5 specify the order of inspections for the indicated unit.

d. The equipment shall be thoroughly washed, cleaned, dried and refurbished after the fungus test before proceeding with subsequent inspection.

4.4 Inspection covered by subsidiary documents. - The following shall be inspected under the applicable subsidiary documents as part of the inspection required by this specification, and the inspection requirements specified in the contract or purchase order.

Item	Where Required
Parts, materials, and processes - general	3.3
Finish	3.5
Marking	3.6

4.5 Quality conformance inspection of equipment before preparation for delivery. - The contractor shall perform the inspection specified in 4.4, 4.6, and 4.5.1 through 4.5.4. This does not relieve the contractor of his responsibility for performing any additional inspection which is necessary to control the quality of the product and to assure compliance with all specification requirements.

4.5.1 Group A inspection. - Each unit on contract or purchase order shall be inspected for conformance to the inspections specified in Table III. Discrete lots shall be formed from units that pass this inspection. Factors of lot composition not defined herein, or in the contract or purchase order, shall be in accordance with MIL-STD-105. Each lot shall be subject to sampling inspection, utilizing the procedures of MIL-STD-105, using the general inspection levels, and AQL's indicated in Table III.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the currentversion before use.

4.5.1.1 Order of inspection within Group A. - Group A inspection shall be performed in an order satisfactory to the Government.

Table III Group A inspection

Inspection	Requ. Para.	Test Para.	AQL MAJOR	AQL MINOR
Visual and mechanical	3.13	4.16	1.5 dphu *	6.5 dphu **
Electrical				
Input current (no load)	3.4.1.1	4.7.1		
Input current (full load)				
115 VAC	3.4.1.2	4.7.2		
230 VAC	3.4.1.3	4.7.3		
VOLTAGE RANGE			1.5 dphu	
14 VDC	3.4.2.1a	4.8.1	For the	
28 VDC	3.4.2.1b	4.9.1	group	
			combined	
REGULATION				
14 VDC	3.4.3.1	4.8.2		
28 VDC	3.4.3.2	4.9.2		
RIPPLE				
14 VDC 115 VAC	3.4.4	4.8.3		
28 VDC 115 VAC	3.4.4	4.9.3		
28 VDC 230 VAC	3.4.4	4.9.4		

* Defects per hundred units.
** All electrical defects are major.

4.5.2 Group B inspection. - Group B inspection shall normally be performed on inspection lots that have passed Group A inspection and on samples selected from units that have been subjected to and met the Group A inspection. This inspection shall conform to Table IV and to the special inspection levels of Table I of MIL-STD-105.

4.5.2.1 Group B sampling plans. - The Group B AQL shall be 6.5 percent defective and the inspection level shall be S-4.

4.5.2.2 Order of inspection within Group B. - Group B inspection shall be performed in an order satisfactory to the Government.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the current version before use.

Table IV Group B inspection

Inspection	Requirement Paragraph	Test Paragraph
Electrical		
Insulation breakdown	3.8	4.10
Interchangeability	3.9	4.17

4.5.3 Group C inspection. - Group C inspection shall be performed on units that have passed Group A and Group B inspection. The inspection shall consist of the inspections specified in Table V. Samples shall be selected in accordance with 4.5.3.1.

4.5.3.1 Sampling for Group C inspection. - One sample unit shall be selected at random for each group of inspections in Table V from every 200 or fraction thereof produced. The first samples selected shall be at the start of the contract from the first quality conformance inspection production lot.

4.5.3.2 Order of inspection within Group C. - Group C inspection shall be performed in the order shown in each subgroup in Table V.

4.5.3.3 Group C failures. - Actions required relative to Group C failures shall be as specified in the contract or purchase order.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

Table V Group C inspection

Inspection	Req. Para.	Insp. Para.
Subgroup 1		
Low Temperature	3.10.1.1	4.11.1
High Temperature	3.10.1.2	4.11.2
Altitude	3.10.3	4.13
Subgroup 2		
Humidity	3.10.2	4.12
Subgroup 3		
Vibration	3.10.5	4.14
Fungus	3.10.4	4.15

4.5.4 Reinspection of conforming group B and group C sample units. - Unless otherwise specified, sample units which have been subjected to and passed both group B and group C inspection may be accepted on contract or order provided all damage is repaired and the sample units are resubjected to and pass group A inspection.

4.6 Burn-In. - Each unit of each lot shall be subjected to a 24-hour burn-in period. Each unit which fails during this period must be repaired and returned to test until it successfully survives a 24-hour period without failure. Failures which occur during burn-in will be noted and reported, but will not be counted toward the establishment of any MTBF. The test environment utilized during burn-in will be test level C, paragraph 4.1.4 of MIL-STD-781B with the following exception: The unit will not be in the operating mode during vibration:. Input voltage shall be 230 VAC +5 -2%.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

4.7 Input current tests.

4.7.1 No load test. - With 115 volts AC RMS input, the INCREASE VOLTAGE switch in position 4, the output connected for 14 volts DC, and no load, the input current shall meet the requirements of 3.4.1.1.

4.7.2 Full load test with 115 volts AC RMS input. - With the Increase Voltage Switch in Position 4, the output connected for 14 volts DC, and a full load of 100 amperes at the output, the input current shall be measured and shall meet the requirements of 3.4.1.2.

4.7.3 Full load test with 230 volts AC RMS input. - With the Increase Voltage Switch in Position 4, the output connected for 28 volts DC, and a full load of 50 amperes at the output, the input current shall be measured and shall meet the requirement of 3.4.1.3.

4.8 Output tests 14 volts. -

4.8.1 Voltage range test (14 volt operation). - With 115 volts AC input and the output connected for 14 volts DC operation, with a full load of 100 amperes, set the Increase Voltage Switch to position 1 and measure the output voltage. Repeat for positions 2 through 8. The output voltage shall meet the requirements of 3.4.2.1a.

4.8.2 Voltage regulation test (14 volt operation). - Set the Increase Voltage Switch to position 4 and connect the output for 14 volt operation. With 115 volts AC input, record the no-load output voltage and the output voltage with a full load of 100 amperes. The regulation shall meet the requirements of 3.4.3.1.

4.8.3 Ripple test (14 volt operation). - Set the Increase Voltage Switch to position 4 and connect the output for 14 volt operation. With 115 volts AC input measure the DC output voltage with a full load of 100 amperes and the AC RMS component. The ripple voltage shall meet the requirements of 3.4.4.

4.9 Output tests 28 volts. -

4.9.1 Voltage range test (28 volt operation). - With 115 volts AC RMS input and the output connected for 28 volts DC operation, with a full load of 50 amperes, set the Increase Voltage Switch to position 1 and measure the output voltage. Repeat for positions 2 through 8. The output voltage shall meet the requirements of 3.4.2.1b.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

4.9.2 Voltage regulation test (28 volt operation). Set the Increase Voltage Switch to position 4 and connect the output for 28 volt operation. With 115 volts AC input, record the no load output voltage and the output voltage with a full load of 50 amperes. The regulation shall meet the requirements of 3.4.3.2.

4.9.3 Ripple test (28 volt operation, 115 volts AC RMS input). - Set the Increase Voltage Switch to position 4 and connect the output for 28 volt operation. With 115 volts AC input measure the DC output voltage with a full load of 50 amperes and the AC RMS component. The ripple voltage shall meet the requirements of 3.4.4.

4.9.4 Ripple test (28 volt operation, 230 volts AC RMS input). - Set the Increase Voltage Switch to position 4 and connect the output for 28 volt operation. With 230 volts AC input measure the DC output voltage with a full load of 50 amperes and the AC RMS component. The ripple voltage shall meet the requirements of 3.4.4.

4.10 Insulation breakdown tests. - Strap the input terminals for 115 volts AC input and put the breaker switch in the ON position.

4.10.1 Input to ground test. - Apply 1500 volts AC across terminal 1 and the cabinet for 10 seconds. After test the equipment shall meet the requirements of 3.8.

4.10.2 Transformer test. - Apply 1500 volts AC across terminal 2 and each of the transformer secondary windings for 10 seconds. After test the equipment shall meet requirements of 3.8.

4.10.3 Output to ground test. - Apply 500 volts AC across the cabinet and the positive and negative output terminals for 10 seconds. After test the equipment shall meet requirements of 3.8.

4.11 Temperature test.

4.11.1 Low Temperature. - The equipment shall be tested in accordance with Method 502, Procedure I, of MIL-STD-810. The storage temperature shall be + 32°F, and the operating temperature shall be + 113°F. Prior to and during testing, the equipment shall meet the requirements of 3.10.1.1.

4.11.2 High temperature. - The equipment shall be tested in accordance with Method 501, Procedure II, of MIL-STD-810. The operating temperature shall be + 160°F. Prior to and during testing, the equipment shall meet the requirements of 3.10.1.2.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the currentversion before use.

4.12 Humidity. - The Power Supply PP-1104( )/G shall be subjected to the humidity test specified in Method 507, Procedure II of MIL-STD-810, with test measurements during step 4, during the last 5 hour period of the fifth 48 hour cycle and step 8. Inability of the equipment to meet the requirements of 3.4.2.1 shall constitute failure of the test.

4.13 Altitude (elevation) test. - The equipment shall be tested in accordance with Method 500, Procedure I, of MIL-STD-810. Prior to testing the equipment shall meet the requirements of 3.4.2.1.

4.14 Vibration. - The equipment shall be tested in accordance with Method 514, Procedure IX, Part 1, vibration, (resonance search) of MIL-STD-810.

4.15 Fungus. - The equipment shall be subjected to the fungus test specified in Method 508, Procedure I of MIL-STD-810. There shall be abundant growth colonization on 50 percent or more of the area of the control item after 14 and 28 days. No cleaning of the equipment is permitted for 72 hours prior to fungus test. Inability of the equilment to meet the requirements of 3.10.4 shall constitute failure of this test.

4.16 Visual and mechanical inspection. - Equipment shall be examined for the defects listed in Standard MIL-STD-252.

4.17 Inspection for interchangeability. - The dimensions listed below shall be gaged or measured to determine conformance to the physical interchangeability requirement of paragraph 3.9. When a listed dimension is not within specified or design limits, it shall be considered a major defect.

(a) External and internal dimensions of cases, covers, and insertable assemblies.

(b) Location of hinges and fasteners on separable parts or assemblies which must mate, such as cases, covers, and mountings.

(c) Locations of connectors, locking pins, fasteners, slides, and mountings which receive mating parts of plug-in assemblies and major units; and location of the mating parts on the plug-in assembly or major unit.

4.18 Quality conformance inspection of preparation for delivery. - Preparation for delivery shall be inspected in accordance with Specification MIL-P-116 to determine conformance to the requirements of section 5.

4.19 Rough handling test (preparation for delivery). - When rough handling test in accordance with Specification MIL-P-116 is required by the contract (see 6.2(c), the tests of 4.8 and 4.9 shall be conducted to determine freedom from operational malfunction caused by rough handling.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

5. PREPARATION FOR DELIVERY

5.1 Preservation and packaging. - Preservation and packaging shall be level A or C as specified. (See 6.2(b)).

5.1.1 Level A

5.1.1.1 Cleaning. - Power Supply PP-1104( )/G shall be cleaned in accordance with process C-1 of MIL-P-116.

5.1.1.2 Drying. - Power Supply PP-1104( )/G shall be dried in accordance with the applicable procedure of MIL-P-116.

5.1.1.3 Preservation application. - None required.

5.1.1.4 Unit packaging. - Unit packaging shall be in accordance with the methods prescribed in MIL-P-116 as prescribed herein.

5.1.1.4.1 Technical literature. - Each technical literature shall be packaged method IC-1.

5.1.1.4.2 Power Supply PP-1104( )/G. - Each power supply PP-1104( )/G, shall be packaged method III as follows: Cushion each power supply on all surfaces with cells or pads or both fabricated of fiberboard conforming to PPP-F-320, type CF, class weather-resistant variety SW, grade W5c, designed to protect all projections and absorb the shock of impact in handling and transit. Place the cushioned unit within a close-fitting fiber-board box conforming to PPP-B-636, W5c, close the box in accordance with the appendix of the box specification.

5.1.2 Level C. - Power Supply PP-1104( )/G shall be preserved and packaged in a manner that will afford adequate protection against physical and environmental damage during shipment, handling and limited intransit storage.

5.2 Packing. - Packing shall be level A, B or C, as specified. Shipping containers for all levels shall be capable of stacking and supporting superimposed loads during shipment and storage without damaging the container(s) or its contents. (See 6.2(b)).

5.2.1 Level A. - Power Supply PP-1104( )/G, packaged as specified in 5.1, shall be individually packed within a close-fitting box conforming to PPP-B-601, overseas type, PPP-B-621, style 4, class 2; or PPP-B-585, style 2 or 3, Class 3. Fiberboard boxes being placed directly in the shipping container shall be waterproofed with tape conforming to PPP-T-76, in accordance with the taping requirements of the appendix of the box specification.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the currentversion before use.

5.2.1 Level A. - (Cont'd) Skids, 3 x 4 inch, laid flat, shall be applied in accordance with the requirements of the container specification, or if not specified in the specification, in a manner which will adequately support the item and facilitate the use of material handling equipment. Place the technical literature, packaged as specified in 5.1.1.4.1, on top of the contents, directly under the lid of the container. Closure and strapping shall be in accordance with the applicable container specification or appendix thereto except that metal strapping shall conform to QQ-S-781, type I, class B.

5.2.2 Level B. - Power Supply PP-1104( )/G, packaged as specified in 5.1, shall be individually packed within a close-fitting box conforming to PPP-B-601, domestic type, PPP-B-621, style 4, class 1; or PPP-B-585, style 2 or 3, class 3. Skids, 3 x 4 inch, laid flat, shall be applied in accordance with the requirements of the container specification, of it not specified in the specification, in a manner which will adequately support the item and facilitate the use of material handling equipment. Place the technical literature, packaged as specified in 5.1.1.4.1, on top of the contents, directly under the lid of the container. Closure and strapping shall be in accordance with the applicable container specification or appendix thereto.

5.2.3 Level C. - Power Supply PP-1104( )/G, packaged as specified in 5.1, shall be packed in shipping containers that comply with Federal or Military specifications, in a manner that will afford adequate protection to the package and its contents against physical and environmental deterioration and damage, during limited shipment,handling and intransit storage.

5.3 Marking. - In addition to any special marking required by the contract or order, interior packages and exterior shipping containers shall be marked in accordance with MIL-STD-129.

6. NOTES

6.1 Intended use. - The power supply is used in maintenance shops as source of low-voltage direct current for maintenance of communication equipment.

6.2 Ordering data. - Procurement documents should specify the following:

(a) Title, number, and date of this specification and any amendment thereto.

(b) Levels of preservation and packaging and packing. (See section 5)

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

(c) When rough handling and functional tests are required.

(d) Preproduction inspection:

(1) Three sample units of each item cited in section 1 are generally required so that lengthy environmental tests can be distributed between them. (See 3.1)

(e) Marking and shipping of samples.

(f) Place of final inspection.

(g) Technical literature required. (See 3.12)

(h) Quantity of tools and running spare parts required. (See 3.12)

6.3 Group C inspection. - Approval to ship may be withheld, at the discretion of the Government, pending the decision from the contracting officer on the adequacy of corrective action. (See 4.5.3.3)

6.4 Nomenclature. - The parenthesis in the nomenclature will be deleted or replaced by a letter identifying the particular design; for example: PP-1104Z/G. The contractor should apply for nomenclature in accordance with the applicable clause in the contract. (See 1.1)

6.5 Verification inspection. - Verification by the Government will be limited to the amount deemed necessary to determine compliance with the contract and will be limited in severity to the definitive quality assurance provisions established in this specification and the contract. The amount of verification inspection by the Government will be adjusted to make maximum utilization of the contractor's quality control system and the quality history of the product.

6.6 Definitions.

6.6.1 Branching. - Branching is a connected arrangement of filaments (hyphae) formed by shoots or secondary stems growing from the main stem or filament (hypha).

6.6.2 Growth colonization. - Growth colonization is a mass of individual plants, generally of one species, living together, or a group of hyphae which is from one spore or cell and may be one individual plant. Colonization which completely covers the surface of the nutriant material constitutes abundant growth.

6.6.3 Microbial growth. - Microbial growth is the growth of very minute organisms. Such organisms when present in large numbers may provide a colony visible to the naked eye.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the currentversion before use.

6.6.4 Sporulation. - Sporulation is the formation of minute unicelluar reproductive or dormant bodies, called spores.

6.6.5 Tubular germination. - Tubular germination is partial growth by the production of hyphae, which are tubular shaped, individual spore fungal filaments. Tubular germination constitutes restricted growth not proceeding to colonization.

CUSTODIAN:

ARMY EL

Preparing activity:

ARMY EL

Project Nr. 6130-A136

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.

SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 22-R255

INSTRUCTIONS: This sheet is to be filled out by personnel, either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments and suggestions submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or serve to amend contractual requirements.

SPECIFICATION MIL-P-55151B(NE) POWER SUPPLY PP-1104( )/G

ORGANIZATION

CITY AND STATE | CONTRACT NUMBER

MATERIAL PROCURED UNDER A
☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

3. IS THE SPECIFICATION RESTRICTIVE?

☐ YES ☐ NO *(If "yes", in what way?)*

4. REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers attach to form and place both in an envelope addressed to preparing activity)*

SUBMITTED BY *(Printed or typed name and activity - Optional)* | DATE

DD FORM 1426

REPLACES EDITION OF 1 OCT 64 WHICH MAY BE USED.

ESC-FM 1068-68

To detach this form, cut along this line

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:14Z
Check the source to verify that this is the current version before use.

FOLD

Department of the Army
Headquarters
U.S.Army Electronics Command
Fort Monmouth, New Jersey 07703

POSTAGE AND FEES PAID

OFFICIAL BUSINESS

Commanding General
U.S.Army Electronics Command
ATTN: AMSEL-RD-ED
Fort Monmouth, New Jersey 07703

FOLD

To detach this form, cut along this line

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:14Z
Check the source to verify that this is the current version before use.