MIL-T-82402(CG)
5 March 1965

MILITARY SPECIFICATION

TRANSFORMERS, DRY-TYPE, POWER DISTRIBUTION,
STEP UP AND STEP DOWN SERVICE, 1000 KVA AND BELOW

1. SCOPE

1.1 Scope.- This specification covers single or three-phase, 60 cycle, dry-type self-cooled power distribution transformers of 1000 KVA capacity and below, for indoor or outdoor shore installations as specified in procurement documents (see 6.1).

1.2 Classification.- Transformers shall be of the following sizes, as stipulated (see 6.2).

Size 1 - 3 KVA		Size 11 - 75 KVA	
Size 2 - 5 KVA		Size 12 - 100 KVA	
Size 3 - 7.5 KVA		Size 13 - 112.5 KVA	
Size 4 - 10 KVA		Size 14 - 150 KVA	
Size 5 - 15 KVA		Size 15 - 167 KVA	
Size 6 - 25 KVA		Size 16 - 225 KVA	
Size 7 - 30 KVA		Size 17 - 300 KVA	
Size 8 - 37.5 KVA		Size 18 - 500 KVA	
Size 9 - 45 KVA		Size 19 - 750 KVA	
Size 10 - 50 KVA		Size 20 - 1000 KVA	

2. APPLICABLE DOCUMENTS

2.1 The following specifications and standards, of the issue in effect on date of invitation for bids, form a part of this specification to the extent specified herein:

SPECIFICATIONS

Federal

W-C-375	Circuit Breaker, Molded Case, Branch-Circuit and Service
PPP-B-591	Box, Fiberboard, Wood-Cleated

7

FSC 6120

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:40Z
Check the source to verify that this is the current version before use.

Military

JAN-P-100	Packaging and Packing for Overseas Shipment General Specification
MIL-W-583	Wire, Magnet, Electrical
MIL-E-917	Electric Power Equipment, Basic Requirements for (Naval Shipboard Use)
MIL-E-4957	Enclosure, Electromagnetic-Shielding, Demountable, Prefabricated for Electronics Test Purposes
MIL-P-15024	Plates, Identification - Information and Marking for Identification of Electrical, Electronic and Mechanical Equipment
MIL-E-17555	Electronic and Electrical Equipment and Associated Repair Parts Preparation for Delivery of

STANDARDS

Federal

FED-STD-595	Colors

Military

MIL-STD-108	Definitions of and Basic Requirements for Enclosure for Electric and Electronic Equipment
MIL-STD-129	Marking for Shipment and Storage

(Copies of specifications and standards required by contractors in connection with specific procurement functions should be obtained from the procuring agency or as directed by the contracting officer.)

2.2 Other publications.- The following documents form a part of this specification. Unless otherwise indicated, the issue in effect on date of invitation for bids shall apply.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

American Standards Association

C57.12.90-1958	Distribution, Power, and Regulating Transformers, and Reactors Other Than Current-Limiting Reactors
C57.94	Operation and Maintenance of Dry Type Transformers

(Application for copies should be addressed to the American Standards Association, 70 East Forty-fifth Street, New York 17, N. Y.)

National Electrical Manufacturer's Association

TR-1 - 1964 - NEMA Transformers, Regulators and Relators

(Application for copies should be addressed to the National Electrical Manufacturer's Association, 155 East 44th Street, New York 17, N. Y.)

3. REQUIREMENTS

3.1 Description.- Transformers shall be designed for distribution of 60 cycle single or three phase voltages, as stipulated (see 6.2). Transformers shall be of the kilovolt amperage capacity specified in 1.2, according to size. Windings shall be of the configuration and voltage stipulated see 6.2).

3.2 Material.- Material shall be of a good commercial quality for his type of equipment and shall conform to the requirements of this pecification.

3.3 Insulation.- Insulation shall be Class B or Class H conforming o the definitions and requirements of Specification MIL-E-917. Unless otherise stipulated, sizes 1 through 6 transformers shall be provided with Class B nsulation, and sizes 7 through 20 transformers shall be provided with Class H nsulation. The ends of the coils shall have additional insulation to provide or surges due to switching, lighting, etc.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

3.4 Enclosure.- Unless otherwise specified in contract or order, all transformer enclosures shall be of heavy gage sheet steel and shall conform to the basic requirements of Standard MIL-STD-108 for dripproof enclosures. The cabinet shall be provided with suitable openings or louvers for ventilation. All burrs and sharp edges shall be removed from the enclosure. The material used in the construction of enclosures shall be consistent with the strength required for sturdiness, serviceability, and safety.

3.4.1 Lifting eyes.- Lifting eye or eyes shall be provided to enable convenient lifting of the assembled unit.

3.5 Maintainability.- The design of the transformers shall provide for suitable entrance of the cables. Ready accessibility shall be provided with clearance in the vertical direction for installation and maintenance of electrical connections, and, in addition, ready accessibility shall be provided for routine cleaning of the windings. Sufficient space shall be provided in the terminal compartment for making connection of single phase transformers in closed delta or wye banks. The terminal compartment shall be so constructed that it is possible to disconnect readily a transformer connected in a three-phase bank without disturbing the cable to the remaining transformers or other units comprising the bank.

3.6 Ambient temperature.- The rating of transformers shall be based upon ambient temperature of 20 degrees centigrade.

3.7 Duty.- Unless otherwise specified in the contract or order, all transformers shall be designed for continuous duty.

3.8 Temperature rise.- Above the 20 degrees centigrade ambient the limits for temperature rise for the windings shall not exceed 80 degrees centigrade for Class B insulation or 150 degrees centigrade for Class H insulation.

3.9 Audio sound level.- Transformers shall be so designed that the audio sound level is low. All parts shall be securely fastened so that they will not chatter or resonate. Transformers shall be provided with built-in vibration dampers if and as required to limit the noise as follows: in a 40 decibel or less (db) ambient: up to and including 225 KVA, a maximum of 45 db; 300 KVA, 50 db; 500 KVA, 55 db; 750 and 1000 KVA, 60 db.

4.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:40Z
Check the source to verify that this is the current version before use.

3.10 Windings.- The transformers shall have separate primary and secondary windings suitably insulated from each other, and from metal parts conforming to TR-1-0.15 of N.E.M.A Transformers, Regulators, and Relators for clearances.

3.10.1 Taps.- The high voltage winding of each transformer shall have four, two and half percent (2½%) taps, two (2) above and two (2) below the primary voltage at full nameplate capacity. External tap changer shall apply when specified in the procurement document (see 6.2).

3.10.2 Winding wire.- Winding wire for transformers shall be either rectangular or round wire in accordance with Specification MIL-W-583.

3.10.3 Shielding.- If specified (see 6.2) transformers shall be furnished with Faraday (electrostatic) shielding between windings as follows: Shielding shall be complete between windings to provide a minimum of 35 decibels attenuation from 80 KCS to 120 KCS and a minimum of 35 decibels attenuation at 200 KCS. Also, a minimum of 35 decibels attenuation from 1800 KCS to 2000 KCS and a minimum of 20 decibels attenuation from 3600 KCS to 4000 KCS.

3.11 Core.- The laminations shall be properly insulated from each other. In the assembly of the core, care shall be taken to remove all burrs or projecting laminations which might result in injury to the coils. The laminations shall be clamped together in such a manner as to insure a tight core. During the process of manufacture the assembled core shall be given a varnish dip in accordance with Specification MIL-E-917.

3.12 Circuit breaker.- Circuit breakers required with rated continuous current from 70 to 800 amperes shall be ambient compensated molded case units calibrated at 50° C. ambient temperature. Circuit breakers required with rated continuous current from 70 to 800 amperes shall be in accordance with Specification W-C-375. Circuit breakers required with rated continuous current from 800 to 1600 amperes shall be molded case units calibrated at 25° C. ambient temperature. Circuit breakers shall have thermal and adjustable magnetic trip with interchangeable trip unit.

3.13 Terminal compartment.- A terminal compartment shall be built into the bottom of each transformer, with conduit knockouts provided in the sides and bottom.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

3.14 Grounding lug.- Each transformer case shall be provided with an equipment grounding lug.

3.15 Identification plates.-

3.15.1 General.- Identification plate shall be as specified in Specification MIL-P-15024 and shall be installed on and furnished as a part of the transformer for which they are intended. Plate material shall be as indicated in paragraph 3.5.1 (a), (b), (c), or (d), of MIL-P-15024. Plates shall be located in a readily accessible position where they can be read at all times without danger to personnel. Unless otherwise specified the identification plates shall be located on the front of the enclosing case.

3.15.2 Data on identification plates.- The minimum data to be marked on the identification plates for transformers shall be as follows:

Manufacturer's name, identification, symbols, serial number, bureau or agency, number of assembly drawing.
Salient design characteristics, namely, type, frequency, KVA, capacity, primary voltage, secondary voltage, class shock, class insulation, ambient temperature and temperature rise.
Percent of rated KVA at 20 degrees centigrade ambient.
Percent impedance.
The word "Transformer".
Manufacturer's catalog number, bureau or agency standard stock number and contract or order number.
Concise instructions on initial dry-out and tests to be made at installation.
Note.- These instructions may be a separate plate at the manufacturer's option.

3.16 Mounting.- Transformers shall be indoor or out-of-door and shall be floor or wall mounted, as stipulated (see 6.2).

3.17 Instruction manuals.- All transformers shall be provided with instruction manuals. Four of these manuals shall accompany the first of any size and two shall accompany all other transformers of the same size in an order. Also include one copy of A.S.A, C57.94-Operation and Maintenance of Dry, Type Transformers for each transformer in the contract or order.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

e balance of the manuals shall be delivered f.o.b. destination with nsignee's premises to the address specified in the procurement documents ee 6.2). Instruction manuals shall include wiring diagrams, instruction r installation and maintenance, weights and price list of parts (if cluded with transformers) dimensional outline drawings, circuit breaker plication and safety precautions.

3.17.1 Preliminary approval of instruction manuals.- The Contractor all furnish one (1) preliminary instruction manual for each contract em to the Contracting Officer within thirty (30) calendar days after ntract award for approval prior to final printing.

3.18 Repair parts.- Repair parts, when required, shall be interangeable with and of the same material as identical parts in the sembled unit. See 6.3.2.

3.19 Workmanship.- The workmanship shall be first class in every spect. The transformers shall be free from burrs, sharp edges, and her imperfections which may impair serviceability.

3.20 Painting.- The internal supporting structure and the inside d outside of the transformer enclosure shall be painted in accordance th Specification MIL-E-917 except that metal parts in contact with or jacent to the transformers which may be subject to an electrical disarge, shall be coated with insulating varnish.

3.21 Color.- The transformers shall be coated with at least two ats of gray paint, color No. 16187 of Federal Standard No. 595 and shall nform to type II, class I of Specification MIL-E-917.

4. QUALITY ASSURANCE PROVISIONS

4.1 All units will be inspected by a Government representative. The pplier is responsible for the performance of all test requirements as ecified herein. Except as otherwise stipulated, the supplier may utilize s own or any other facilities and services acceptable to the Government. mplete records of the tests shall be kept and made available to the vernment as specified in the contract or order. The Government reserves e right to witness performance of any of the tests set forth in this ecification where such tests are deemed necessary to assure supplies and rvices conform to prescribed requirements.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

Unless otherwise stipulated, tests on production models shall be conducted by the contractor and witnessed by the Government inspector.

4.2 Standard tests.- Standard tests for all transformers shall conform to A.S.A test code C57.12.90-1958 or latest issue thereof.

4.3 General examination.- Each transformer shall be subjected to a thorough examination to ascertain that the material, design, and workmanship are in conformance with this specification.

4.4 Sampling for lot acceptance.- All transformers of the same size which are presented for testing at one time shall be considered a lot for purposes of acceptance testing. One sample transformer shall be selected at random from the lot for acceptance testing. This sample shall be selected for the following tests on paragraphs 4.5 through 4.13.

4.5 Resistance.- The resistance of both the primary and secondary windings shall be accurately measured. The temperature at which the resistance readings are taken shall also be recorded. On a percent basis, the average of variations in resistance of the primary and secondary windings for transformers of the same size and design shall be not more than 5 percent.

4.6 Polarity.- The polarity of each transformer shall be determined by either of the following methods at the manufacturer's option:

4.6.1 Polarity by inductive kick.- Test of polarity by inductive kick shall conform to A.S.A, C57.12.90, paragraph 12-97.140.

4.6.2 Polarity by alternating-voltage.- Test of polarity by alternating-voltage shall conform to A.S.A, C57.12.90, paragraph 12-97.150.

4.6.3 Polarity by standard transformer.- Test of polarity by standard transformer shall be in accordance with A.S.A, C57.12.90, paragraph 12-92.120.

4.7 Impulse tests.- The impulse test when specified in the procurement document (see 6.2) shall be in accordance with A.S.A, C57.12.90, paragraph 12-92.300.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

4.8 Ratio.- The turn ratio between the primary and the secondary windings shall be accurately determined by either of the following methods at the manufacturer's option. The variation of the value of ratio between transformers of the same size, design, and type shall be within plus or minus one-half of 1 percent.

4.8.1 Voltmeter method.- The ratio test shall be made with rated or lower voltage at rated or higher frequency applied to either the high or low voltage leads of the transformer. Simultaneous readings of a voltmeter in the high-voltage winding and a voltmeter in the low-voltage winding shall be taken and recorded. The meters shall be interchanged and another set of readings obtained, the average of these two sets of readings shall be used in checking the ratio.

4.8.2 Standard transformer method.- The transformer to be tested shall be connected in parallel with a standard transformer of the same nominal ratio. The secondaries shall also be connected in parallel but with a voltmeter or detector in the connection between two terminals of similar polarity and so arranged as to read the difference between the two secondary voltages. If the manufacturer desires, the voltages in each secondary winding may be obtained. When this method is used, however, the voltmeters shall be interchanged and a second set of readings shall be obtained. The average of the results shall be used in determining the ratio.

4.9 No-load losses.- The no-load losses shall be accurately determined. Rated voltage shall be applied to either the primary or secondary windings. The frequency shall be 60 cycles. Simultaneous readings shall be made of frequency, voltage, watts (low power factor wattmeter), and amperes. The actual design value appears on the drawings. The no-load loss for transformers of the same size, and design, may exceed the value shown on the Descriptive Schedule by no more than 10 percent.

4.10 Dielectric test.-

4.10.1 General.- The dielectric test shall be made after all other tests have been completed. This test shall be made upon the completely assembled unit.

4.10.2 Applied potential.- The test voltage shall be applied successively between each winding and all other windings and metal parts grounded.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

4.10.2.1 Test voltage.- The test voltage shall approximate a true sine wave. The insulation of the high-voltage winding shall withstand a dielectric test voltage (r.m.s) of 4,000 volts AC, 60 cycles, for a period of 1 minute with the low-voltage winding and case and core grounded. The low-voltage winding insulation shall withstand a dielectric test voltage (r.m.s) of 4,000 volts AC, 60 cycles, for a period of 1 minute with the high-voltage winding and case and core grounded.

4.10.2.2 Measurement of test voltage.- The voltmeter method shall be used. In measuring the voltage with a voltmeter, the meter shall derive its voltage from the high voltage circuit either directly or through an auxiliary ratio transformer or by means of a voltmeter coil placed in the testing transformer.

4.10.3 Induced potential.- The test voltage shall be applied to either winding and shall approximate a true sine wave. The insulation of the low-voltage and the high-voltage windings shall withstand a voltage applied to either winding of twice normal operating voltage at a frequency of not less than 120 cycles for a period of not less than 7,200 cycles at the frequency of the applied test voltage.

NOTE.- The frequency of the voltage should be such that the exciting current is not in excess of 30 percent of rated load current.

4.11 Sound level test.- The contractor shall be responsible for furnishing proper environment and instruments, meters and other equipment for sound level test. Tests shall be performed to determine conformance with the requirements of 3.9. An approved sound level meter or pick-up microphones and calibrated meter shall be used for tests.

4.12 Faraday shielding test.- Faraday shielding tests shall be performed in a shielded room, of approved design, to determine conformance with the requirements of 3.10.3. The enclosure shall provide a minimum of 45 db attenuation to electric fields from 14 kc to 1000 mc. The enclosure shall also provide a minimum of 30 db at 14 kc rising to 100 db at 250 kc to magnetic fields. Measurements shall be of the type specified in Specification MIL-E-4957.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

4.13 Load test.- All transformers up to and including 50 KVA shall be subjected to full load tests. All transformers above 50 KVA shall be tested by shorting the secondary winding and applying a voltage to the primary, at 60 cycles, which will cause full load current in the secondary. Transformer secondary windings shall not exceed 80 degrees Centigrade and 150 degrees Centigrade temperature rise for class B and class H insulation respectively.

4.14 Rejection.- Failure of the sample transformer to pass any of the tests specified in paragraphs 4.5 through 4.13 will be grounds for rejection of the entire lot.

5. PREPARATION FOR DELIVERY

5.1 Preparation for delivery shall be for immediate use and limited storage or for overseas packaging (see 6.2).

5.2 Domestic shipment - immediate use.- Cleaning and packaging of equipment shall be in accordance with the manufacturer's commercial practice. Equipment shall be packed in accordance with applicable carrier rules and regulations.

5.3 Domestic shipment involving storage or overseas shipment general requirements.- Each transformer shall be cleaned by process C-1 and packaged by method III of Specification MIL-E-17555. When practicable, each packing container shall contain an identical number of items and shall be of the same uniform size. In addition, all containers shall be new and shall be able to withstand storage, rehandling, and reshipment without the necessity of repacking. Boxes shall be modified by the addition of skids and the item bolted through the skids and base where the gross weight of an individual item exceeds 200 pounds. Cushioning methods and materials required to protect items from damage due to shock shall be in accordance with Specification JAN-P-100. The gross weight of shipping containers shall not exceed 200 pounds, unless the weight of an individual item exceeds this amount.

5.3.1 Packing for domestic shipment and storage.- Transformers, packaged as specified in 5.3, shall be packed in snug fitting wood cleated fiberboard, cleated plywood (domestic type), nailed wood, or corrugated or solid fiberboard boxes conforming to Specification PPP-E-591. Items exceeding 200 pounds gross weight shall be packed in containers as specified in 5.3.2.

5.3.2. Packing for overseas shipment.- Transformers, packaged as specified in 5.3, shall be packed in snug fitting wood cleated plywood (overseas type), nailed wood, or fiberboard boxes conforming to Specification PPP-B-591. Wood or wood cleated boxes shall be lined with a sealed waterproof caseliner conforming to Specification MIL-E-17555. Shipping containers shall be closed and strapped in accordance with applicable container specification and appendix thereto.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

5.4 Marking.- In addition to any special marking required by the contract or order, unit packages and exterior shipping containers shall be marked for shipment in accordance with Standard MIL-STD-129.

6. NOTES

6.1 Intended use.- The transformers specified herein are intended for indoor or outdoor use in power distribution systems of shore installations.

6.2 Ordering data.- Procurement documents should stipulate the followin

(a) Title, number, and date of this specification.
(b) Sizes required (see 1.2).
(c) Configuration and voltage required (see 3.1).
(d) Faraday shielding (see 3.10.3).
(e) Impulse tests, if required (see 4.7).
(f) External tap changer (see 3.10.1).
(g) Circuit breaker (see 3.12).
(h) Whether indoor or outdoor installation and shall be floor or wall mounted (see 3.16).
(i) Number of instruction manuals to be furnished (see 3.17).
(j) Method of preparation for delivery (see 5.1).

6.3 Bid requirements.-

6.3.1 Each bid must be accompanied with a description of the equipment the bidder proposes to furnish. This description shall be complete and in accordance with the Descriptive Schedule form attached to this specification as Appendix A which may be detached and used for this purpose.

6.3.2 The bidder shall submit with his quotation a list of recommended repair parts, with unit prices, sufficient to service the unit for a period of two years. Quotations should be made on complete units only.

6.4 The Contractor shall notify the Contracting Officer of readiness for inspection at least two weeks before the complete units are ready for inspection.

NOTICE.- When Government drawings, specifications, or other data are used for any purpose other than in connection with a definitely related Government procurement operation, the United States Government thereby incurs no responsibility nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use, or sell any patented invention that may in any way be related thereto.

Preparing Activity:
U. S. Coast Guard

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

DESCRIPTIVE SCHEDULE

TRANSFORMER, DRY-TYPE, POWER DISTRIBUTION

Manufacturer's name _____
Circuit breaker _____ Catalog no. _____
Model _____ Amps _____ Volts _____
Step up or step down service _____
Enclosure _____
Primary voltage and configuration _____
Secondary voltage and configuration _____
Taps _____
KVA _____ Phase _____ Cycles _____
Duty _____
Temperature rise _____ Ambient _____
Mounting _____
Polarity _____
Insulation class _____
Weight, lbs. _____
Volume, cu. ft. _____
Dimensions _____
Performance data: _____
Primary No Load Voltage _____
Primary Amperes _____
Secondary No Load Voltage _____
Secondary Amperes _____
Watts Loss, No Load _____
Watts Loss, Total _____
100% PF Regulation _____
80% PF Regulation _____
Exciting current % _____
Impedance _____
Maximum Peak Inrush Current, Amperes _____
Finish, including method of treatment of enclosure for painting, color, and applicable specification of paint _____
_____
_____
_____
Manufacturer's catalog number _____

APPENDIX A
to
MIL-T-82402 (CG)

GPO 890-694

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:40Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:40Z
Check the source to verify that this is the current version before use.

SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 119-R004

INSTRUCTIONS

This sheet is to be filled out by personnel either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity *(as indicated on reverse hereof)*.

CIFICATION

ANIZATION *(Of submitter)* | CITY AND STATE

TRACT NO. | QUANTITY OF ITEMS PROCURED | DOLLAR AMOUNT
$

ERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES.

COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

IS THE SPECIFICATION RESTRICTIVE?

☐ YES ☐ NO IF "YES", IN WHAT WAY?

REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity)*

MITTED BY *(Printed or typed name and activity)* | DATE

FORM 1426
APR 63

REPLACES NAVSHIPS FORM 4863, WHICH IS OBSOLETE

PLATE NO. 15419

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:40Z
Check the source to verify that this is the current version before use.

FOLD

'ARTMENT OF THE NAVY

POSTAGE AND FEES PAI
NAVY DEPARTMENT

OFFICIAL BUSINESS

COMMANDANT
U. S. COAST GUARD HEADQUARTERS
STATION 6-19
WASHINGTON, D. C. 20226

FOLD

PLATE NO. 15419 (

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:40Z
Check the source to verify that this is the current version before use.