"This material contains information affecting the national defense of the United States within the meaning of the espionage laws, title 18, U. S. C., secs 793 and 794, the transmission or revelation of which in any manner to an unauthorized person is prohibited by law."

C-MIL-T-21684(NOrd)

19 November 1958
SUPERSEDING
NAVORD OS 5881E
18 May 1956

DOWNGRADED BY AUTHORITY
OF NAVORDINST 5511.7A
ORD-065 28 MARCH 1972

# MILITARY SPECIFICATION

# TEST SET MARK 96 MOD 1

## 1. SCOPE

1.1 This specification establishes the requirements for the procurement of Test Set Mark 96 Mod 1. This test set, used in conjunction with Power Supply Mark 20 Mod 1, furnishes signals for testing and adjusting Circuit Breaks Mark 1 Mod 0 and Mark 2 Mod 0, and indicates operation of the circuit breaks in response to the signals.

## 2. APPLICABLE DOCUMENTS

2.1 The following specifications, standards, drawings, and publications of the issue in effect on date of invitation for bids, form a part of this specification.

SPECIFICATIONS

FEDERAL

| | |
|---|---|
| PPP-B-601 | Boxes, Wood, Cleated-Plywood. |
| PPP-B-621 | Boxes, Wood, Nailed and Lock-corner. |
| PPP-B-636 | Boxes, Fiber. |

MILITARY

| | |
|---|---|
| MIL-P-116 | Preservation, Methods of. |
| MIL-B-131 | Barrier Material: Water-Vapor-proof, Flexible. |
| MIL-V-173 | Varnish, Moisture-and Fungus resistant for the Treatment of Communications, Electronic and Associated Electrical Equipment. |
| MIL-S-6872 | Soldering Processes, General Specifications for. |

FSC 6625

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

| | |
|---|---|
| MIL-P-17555 (SHIPS) | Preparation for delivery of Electronic Equipment; Miscellaneous Electrical Equipment (Except Rotating Electrical Equipment) and Associated Repair Parts. |

STANDARDS

MILITARY

| | |
|---|---|
| MIL-STD-105 | Sampling Procedures and Tables for Inspection by Attributes. |
| MIL-STD-129 | Marking for Shipment and Storage. |

DRAWINGS

BUREAU OF ORDNANCE

| | |
|---|---|
| LD 166764 | Test Set Mark 96 Mod 1. |
| LD 284866 | Preparation for Delivery for Test Set Cable Assemblies. |
| 1476194 | Marking Instructions for Storage and Shipping Containers. |

And all documents listed in the above LD's and drawings.

PUBLICATIONS

BUREAU OF ORDNANCE

| | |
|---|---|
| OP 400 | General Instructions for the Design, Manufacture and Inspection of Naval Ordnance Equipment. |

(Copies of specifications, standards, drawings, and publications required by contractors in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.)

3. REQUIREMENTS

3.1 General.

3.1.1 Test Set Mark 96 Mod 1 shall be manufactured in accordance with LD 166764 and all documents listed thereon.

3.1.2 The requirements and procedures established in OP 400 shall be complied with as applicable.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

3.1.3 Preproduction sample. - Unless otherwise specified in the contract or order, a preproduction sample shall be manufactured by the same procedures and processes and at the same location as proposed for full production. This sample will be tested for the purpose of determining compliance with the requirements of this specification, the drawings, and the contract. See 4.1.2.

3.1.4 Interchangeability. - Component parts of assembled units (unless otherwise specified on the applicable drawings) fabricated in strict agreement with their applicable drawings shall be interchangeable and shall assemble with mating components of the unit without selection or fitting. If, during assembly of the fabricated parts of a unit, selection or fitting is required and changes in dimensions are necessary, no changes in the parts as delineated on applicable drawings shall be made without prior approval of the Bureau of Ordnance.

3.2 Moisture - and fungus-resistant treatment. - Materials and parts of this test set which are not moisture and fungus resistant shall be treated, before assembly, with a varnish conforming to Military Specification MIL-V-173.

3.3 Requests for deviation. - Requests for deviation from this specification, applicable drawings, specifications, publications, materials and processes specified herein, shall be as set forth in OP 400.

3.4 Conflicting requirements. - Conflicting requirements arising between this specification or any specifications, publications, or drawings listed herein shall be referred in writing to the procuring agency or appointed agent for interpretation and clarification.

3.5 Soldering. - Unless otherwise specified, soldering processes shall conform to the requirements specified in Military Specification MIL-S-6872. Only non-corrosive and non-volatile fluxes shall be used. Rosin shall be used when soldering wires to contacts and terminals. The use of rosin core solder is permitted. Electrical connections shall be mechanically secure and electrically continuous before soldering. Sufficient heat shall be applied during the soldering process to avoid "cold" solder joints.

3.6 Wiring. - All internal wiring shall be cabled wherever possible.

3.7 Performance requirements and product characteristics. - The test set covered by this specification shall meet the following performance requirements and product characteristics:



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

3.7.1 Insulation resistance. - The insulation resistance between electrical circuits and between each circuit and the chassis shall be not less than 50 megohms when tested in accordance with 4.5.12.

3.7.2 GALV-CLK switch. - The CALV-CLK switch circuitry shall indicate 1310 ohms ±12 percent in the center position and shall indicate an open and closed circuit in the GALV position when tested as specified in 4.5.3.

3.7.3 SIG switch. - The SIG switch shall be properly connected as verified by testing as specified in 4.5.4.

3.7.4 GALV-CHK switch. - The GALV-CHK switch circuitry shall indicate a closed circuit in the "-" position and an open circuit in the mid-position when tested as specified in 4.5.5.

3.7.5 Terminal switch TS1 and CA-597 cable female receptacle continuity. - The Terminal Switch TS1 and CA-597 Cable Female receptacle circuitry shall indicate 0.5 ohm or less for each step when tested as specified in 4.5.6.

3.7.6 RECT connector and CA-597 Cable Female receptacle continuity. - The RECT connector and CA-597 Cable Female receptacle circuitry shall indicate an open or closed circuit for each step when tested as specified in 4.5.7.

3.7.7 Clock reset. - With the GALV-CLK switch in the CLK position, timer operation shall start and with the GALV-CLK switch in the mid-position, timer operation shall stop when tested as specified in 4.5.8.

3.7.8 115 V OUT-IN plug. - Output receptacle shall be properly connected to input plug as verified by testing as specified in 4.5.9.

3.7.9 GALV-CHK switch and terminals continuity. - The GALV-CHK switch shall be properly connected to terminals as verified by testing as specified in 4.5.10.

3.7.10 Galvanometer circuit sensitivity. - The galvanometer and potentiometer shall be properly connected in test set circuitry when tested as specified in 4.5.11.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

3.8 Workmanship and cleanliness. - The test set shall be free from dust, dirt, metal filings, moisture, solder splashes, chips, and other foreign matter. Necessary precautions shall be taken during manufacture and assembly to insure these conditions.

4. QUALITY ASSURANCE PROVISIONS AND TEST REQUIREMENTS

4.1 Government inspection. - The Government inspector will make such inspections as are necessary to determine that all components and assemblies are in accordance with the requirements of the contract, pertinent specifications and drawings. Unless otherwise specified, these inspections will be conducted in accordance with instructions contained in OP 400.

4.1.1 Sampling. - Unless otherwise specified, and when applicable, the sampling plans and procedures used by the Government inspector in the determination of the acceptability of products submitted by a supplier for Government inspection will be in accordance with the provisions of MIL-STD-105.

4.1.2 Preproduction sample. - Unless otherwise specified for each contract or order, a representative sample of one test set shall be manufactured using the methods and procedures proposed for full production. The Government inspector shall perform, witness, or participate in such inspections and tests on the sample as are required for full production. Upon conditional acceptance by the inspector, the preproduction sample shall be forwarded, together with a report of inspection, to an activity designated in the contract or by the procuring agency, for the purpose of determining compliance with the requirements of the contract, specifications and drawings. Further production of the item by the contractor prior to approval of the contracting activity or the completion of the tests on preproduction samples shall be at the contractor's risk. Preproduction samples accepted will be applied as part of the quantity specified by the contract or order.

4.1.2.1 Preproduction sample for a subsequent contract. - The necessity for a preproduction sample will be determined by the procuring agency when production under a new contract by the same contractor at the same location follows the manufacture of satisfactory material as covered by this document.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

4.1.3 Lot. - As applied to the Government inspection of units of product, the term "lot" shall mean "inspection lot", i.e., a collection of units of the product used as a basis for Government inspection. Unless otherwise specified, the number of units of product in "inspection lots" shall be as determined by the Government inspector, and may differ from the quantity designated in the contract or order as a lot for production, shipment, or other purpose.

4.2 Contractor's inspection. - Contractor's inspection shall be conducted in accordance with provisions of "Inspection by Contractor" as contained in OP 400.

4.3 Classification of tests. - The inspection and testing of mechanisms covered by this document shall be classified as follows:

(a) acceptance tests

(b) preproduction tests

4.3.1 Acceptance tests. - Acceptance tests for acceptance of the test set covered by this specification shall consist of tests to determine compliance with all requirements specified in this document.

4.3.2 Preproduction tests. - Preproduction tests are those performed on samples submitted in accordance with 4.1.2 to determine that the lot and production meet all the requirements of this specification. Acceptance shall be based on no defects in a sample.

4.4 Test equipment.

4.4.1 Test and inspection equipment and facilities. - Unless otherwise specified, the manufacturer shall furnish and maintain all necessary test equipment, facilities and personnel for performing all acceptance tests under the supervision of the Government inspector. The test equipment shall be adequate in quantity, and unless definite requirements are specified, they shall be of sufficient accuracy and quality to permit performance of the required acceptance tests.

4.4.1.1 Equipment required for performing these tests is as follows:



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

(a) One (1) ohmmeter, multiple ranges 0-1000 ohms, 0-10,000, 0-100,000, 0-1 meg, 0-10 meg, 0-100 meg, accuracy within ±2 percent.

(b) 115-volt, 60 cycle a-c supply.

(c) 1.5-volt d-c battery supply capable of delivering at least 300 milliamperes at 1.5 volts.

(d) One (1) microammeter, 0-20 range, accuracy within ±2 percent.

(e) One (1) potentiometer, 1 megohm wire wound, 2 watt.

(f) One (1) megohmmeter, 500 volts d-c, range 10.0-100 megohms accuracy within ±10 percent.

4.5 Tests.

4.5.1 Test conditions. - Unless otherwise specified, tests shall be performed at 80° ±10° F and ambient relative humidity.

4.5.2 Visual inspection. - The test set and its component parts shall be inspected to verify that the materials, design, construction, physical dimensions, soldering and workmanship are in accordance with this document and the drawings.

4.5.3 GALV-CLK switch check.

(a) Set CALV-CLK switch at center position.

(b) Connect ohmmeter leads to contacts J1 and J2 of terminal switch TSL. Ohmmeter shall indicate 1310 ohms ±12 percent.

(c) Set GALV-CLK switch at CALV. Ohmmeter shall indicate open circuit.

(d) Move ohmmeter lead from contact J2 to contact N1 of terminal switch TSL. Ohmmeter shall indicate 0.5 ohm or less.

(e) Remove ohmmeter.

4.5.4 SIG switch test.

(a) Set SIG switch at mid-position.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

(b) Connect ohmmeter leads to pin E of the male connector of CA-597 cable and to pin A of RECT. receptacle. Ohmmeter shall indicate 0.5 ohm or less.

(c) Set SIG switch at minus. Ohmmeter shall indicate 100,000 ohms ±12 percent.

(d) Remove ohmmeter lead from pin E of CA-597 cable receptacle and connect it to pin D. Ohmmeter shall indicate 0.5 ohm or less.

(e) Set SIG switch at plus. Ohmmeter shall indicate 100,000 ohms ±12 percent.

(f) Set all test set switches at their mid-positions.

(g) Remove ohmmeter.

(h) Remove panel from case.

(i) Install jumper across capacitor C-1 terminals.

(j) Connect ohmmeter leads to pins A and B of RECT. connector. Ohmmeter shall indicate 2.75 meg ±12 percent.

(k) Remove ohmmeter leads from RECT. connector and connect to pins D and E of CA-597 cable male connector. Ohmmeter shall indicate 0.5 ohm or less.

(l) Repeat step k with SIG switch at plus and minus. Ohmmeter shall still indicate 0.5 ohm or less.

(m) Set SIG switch at mid-position.

(n) Remove jumper from capacitor C-1. Ohmmeter shall indicate 0.5 ohm or less.

(o) Set SIG switch at plus and minus. Ohmmeter shall indicate 100,000 ohms ±12 percent at each switch position.

(p) Remove ohmmeter leads from CA-597 cable connector and connect to pins A and E of RECT connector. Ohmmeter shall indicate 12.75 megs ±12 percent.

(q) Remove ohmmeter.

(r) Replace panel in case.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

4.5.5 GALV-CHK switch test.

(a) Connect ohmmeter leads to pin A of RECT. connector and pin N2 of switch TS1.

(b) Set GALV-CHK switch at minus. Ohmmeter shall indicate 0.5 ohm or less.

(c) Set GALV-CHK switch at mid-position. Ohmmeter shall indicate open circuit.

(d) Remove ohmmeter.

4.5.6 Terminal switch TS1 and CA-597 cable female receptacle continuity test.

(a) Connect ohmmeter, in sequence, to terminals listed in steps of following table. Ohmmeter shall indicate 0.5 ohm or less for each step.

| STEP | OHMMETER CONNECTION | |
|---|---|---|
| | CA-597 cable female receptacle terminal | TS-1 terminal |
| 1 | A | A |
| 2 | B | B |
| 3 | C | C |
| 4 | D | E |
| 5 | E | D |

(b) Remove ohmmeter.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

4.5.7 RECT. connector and CA-597 cable female receptacle continuity test.

(a) Connect ohmmeter, in sequence, to terminals listed in steps of the following table and open or close terminal switch TS1 lid as shown. Ohmmeter shall indicate as specified for each step.

| | OHMMETER CONNECTION | | | |
|---|---|---|---|---|
| STEP | RECT connector terminal | CA-597 cable female receptacle terminal | Terminal Switch Lid Position | Ohmmeter Indication |
| 1 | A | A | closed | 0.5 ohm or less |
| 2 | A | A | open | open circuit |
| 3 | B | B | open | open circuit |
| 4 | B | B | closed | 0.5 ohm or less |
| 5 | C | C | open | open circuit |
| 6 | C | C | closed | open circuit |
| 7 | E | D | closed | 0.5 ohm or less |
| 8 | E | D | open | oper circuit |
| 9 | D | E | closed | 0.5 ohm or less |
| 10 | D | E | open | open circuit |

(b) Remove ohmmeter.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

4.5.8 Clock reset test.

(a) Connect test set power cable to 115-volt, 60-cycle a-c supply.

(b) Set OFF-ON switch at ON.

(c) Set GALV-CLK switch at CLK. Timer shall start to operate.

(d) Set GALV-CLK switch in mid-position. Timer shall stop.

(e) Reset timer to zero.

(f) Set OFF-ON switch at OFF.

(g) Remove power cable from a-c supply.

4.5.9 115 V OUT-IN plug test.

(a) Remove power indicator light bulb LP-1. Set OFF-ON switch at ON.

(b) Connect ohmmeter leads to one pin of 115 V IN plug and one socket of the OUT receptacle. Ohmmeter should indicate 350 ±50 ohms or 0.5 ohm or less.

(c) Remove ohmmeter lead from pin of 115 V IN plug and connect to other pin of plug. Ohmmeter indication shall be opposite to that obtained in step b. (If in step b, ohmmeter indicated 350 ±50 ohms, it should now indicate 0.5 ohm or less: if ohmmeter indicated 0.5 ohm or less, it shall now indicate 350 ± 50 ohms.)

(d) Remove ohmmeter lead from socket of OUT-IN receptacle and connect to other socket of receptacle. Ohmmeter shall indicate as in step b.

(e) Remove ohmmeter.

(f) Set OFF-ON switch at OFF and replace power indicator light bulb LP-1.

4.5.10 GALV-CHK switch and terminals continuity test.

(a) Close lid of terminal switch TS1.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

(b) Set GALV-CLK switch at GALV.

(c) Connect ohmmeter, in sequence, to terminals listed in steps of the following table and set switches as shown.

(d) Ohmmeter shall indicate as specified in each step.

| | OHMMETER CONNECTION | | | | |
|---|---|---|---|---|---|
| STEP | RECT. receptacle terminal | TS1 terminal | CA-597 cable female receptacle terminal | GALV-CHK switch setting | Ohmmeter indication |
| 1 | D | - | C | mid-position | open circuit |
| 2 | A | J2 | - | + | less than 0.5 ohm |
| 3 | - | N2 | D | + | 13.4 meg ±3% |
| 4 | - | J2 | D | mid-position | open circuit |
| 5 | - | J2 | D | + or - | 13.4 meg ±3% |

(e) Set GALV-CLK and GALV-CHK switches at mid-positions.

(f) Connect ohmmeter leads to terminal A of RECT. receptacle and J2 of terminal switch TS1. Ohmmeter shall indicate open circuit.

(g) Set GALV-CHK switch at plus.

(h) Set GALV-CLK switch at GALV. Ohmmeter shall indicate 0.5 ohm or less.

(i) Remove ohmmeter.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

4.5.11 Galvanometer circuit sensitivity test.

(a) Level test set.

(b) Zero galvanometer mechanically with knob on top of galvanometer.

(c) Connect 1.5 volt d-c supply to outer terminals of 1 megohm potentiometer.

(d) Connect center terminal of potentiometer to terminal N2 on terminal switch TS-1.

(e) Connect positive terminal of microammeter to positive terminal of 1.5 volt d-c supply.

(f) Connect microammeter negative terminal to terminal J2 on terminal switch TS 1.

(g) Set GALV-CLK switch to GALV.

(h) Turn 1 megohm potentiometer until microammeter indicates 5 microamperes.

(i) Turn GALV SENS ADJ until galvanometer indicates 5 divisions.

(j) Turn 1 megohm potentiometer until microammeter indicates 10 ±1 divisions.

(k) Reverse J2 and N2 terminal connections. Galvanometer should indicate 10 ±1 divisions in opposite direction.

(l) Remove connections from terminals J2 and N2.

4.5.12 Insulation resistance. - The test set shall be subjected to a conditioning period of 24 hours at a temperature of 77° ±2° F, and a relative humidity of 75 ±5 percent. A test potential of 500 °20 volts d-c is then applied as specified in 3.7.1. The insulation resistance shall be not less than 50 megohms.

4.5.13 Acceptance criteria. - Failure of any test set to meet any of the requirements and tests of this specification shall result in rejection of the test set. If the number of failing test sets exceeds the number permitted by the associated criteria, the lot represented will be rejected.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

## 5. PREPARATION FOR DELIVERY

(NOTE: This equipment is very fragile, contractor shall contact Bureau of Ordnance(Mablg) for special handling instructions.)

5.1 Preservation and packaging.

5.1.1 Level A. - In addition to the following, Level A packaging shall be in accordance with Specification MIL-P-17555.

5.1.1.1 Cleaning, drying, and preservative application. - (Not applicable)

5.1.1.2 Unit packaging. - Prior to unit packaging, all test set cables shall be packaged in accordance with Bureau of Ordnance LD No. 284866. Each test set shall be packaged in a Type I, Class 1, Style RSC corrugated fiberboard box, having a minimum Mullen test of 275 pounds, conforming to the requirements of Federal Specification PPP-B-636. Sufficient fillers and folded corner pads, fabricated from the same box material, shall be utilized within the carton to provide a tight pack and to prevent direct contact between protrusions of the test set case and the walls of the fiberboard box.

5.1.1.2.1 The unit package, prepared as described above, shall be further packaged Method IA-14 conforming to the requirements of Military Specification MIL-P-116. The inner carton with all corners blunted shall be inserted into a water-vaporproof bag fabricated from Class I barrier material conforming to the requirements of Military Specification MIL-B-131, and closure heat-sealed. The outer carton shall be a Class 2, Style RSC fiberboard box conforming to the requirements of Federal Specification PPP-B-636, W5c or W5s compliance symbol.

5.1.1.3 Intermediate package. - (Not applicable)

5.1.2 Level B. - (Not applicable)

5.1.3 Level C.

5.1.3.1 Cleaning, drying, and preservative application. - (Not applicable)

5.1.3.2 Unit packaging. - Unit packaging shall be in accordance with Method III of Military Specification MIL-P-116. The unit package shall contain one (1) test set.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

5.1.3.3 Intermediate package. - (Not applicable)

5.2 Packing.

5.2.1 Level A. - In addition to the following, Level A packaging shall be in accordance with Military Specification MIL-P-17555.

5.2.1.1 Exterior containers. - Each test set, individually packaged as specified above for Level A protection, shall be packed in an overseas type wood-cleated plywood box or in a Class 2, Style 2, 2 1/2, 3 or 4 nailed wood box conforming to the requirements of Federal Specifications PPP-B-601 or PPP-B-621, respectively.

5.2.1.1.1 When a nailed wood box is selected to be used for shipment, box lumber shall conform to Group I, II or III woods of Federal Specification PPP-B-621. The lumber shall be of one (1) inch nominal thickness and surfaced on both sides.

5.2.2 Level B. - In addition to the following, Level B packaging shall be in accordance with Military Specification MIL-P-17555.

5.2.2.1 Exterior containers. - Each test set, individually packaged as specified above for Level A protection, shall be packed in a domestic type wood-cleated plywood box or in a Class 1, Style 2, 2 1/2, 3 or 4 nailed wood box conforming to the requirements of Federal Specifications PPP-B-601 or PPP-B-621, respectively.

5.2.3 Level C.

5.2.3.1 Exterior containers. - Each test set, packaged in accordance with 5.1.3.2, shall be packed in a manner which will provide protection against damage during direct shipment from the supply source to the first receiving activity for immediate use. Containers shall comply with common carrier rules and regulations applicable to the mode of transportation.

5.3 Marking.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

5.3.1 Special marking. - The following precautionary marking shall be stenciled or stamped on the top, one (1) side and one (1) end of the shipping container:

DELICATE INSTRUMENT
HANDLE WITH CARE

5.3.2 Normal marking. - In addition to any special marking required by the contract or order, all marking shall be in accordance with Military Standard MIL-STD-129, including serial numbers.

5.3.2.1 For detailed marking requirements, see Bureau of Ordnance Drawing Number 1476194.

6. NOTES

6.1 Ordering data. - Procurement documents shall specify the title, number, and date of this specification, and exceptions to this specification, applicable drawings, and other documents. Procurement documents shall also specify the desired level of packaging and packing. The attention of the contracting officer is invited to the Quality Assurance Provisions and options in Specification MIL-P-116, and to paragraph 6.1.1 of this document.

6.1.1 Criteria for use of proper level of preservation, packaging and packing shall be as follows:

For Level A. This level shall be used for those items which are to be shipped to indeterminate destinations or stored under indeterminate conditions for redistribution anywhere.

For Level B. This level shall be used only when it is definitely known that the item will be held in covered storage in overseas locations for 6 months or less or in domestic locations for an indefinite period.

For Level C. This level shall be used only when it is definitely known that the packaged item is to be shipped to domestic installations for immediate use at the first receiving activity.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.

Notice. - When Government drawings, specifications, or other data are used for any purpose other than in connection with a definitely related Government procurement operation, the United States Government thereby incurs no responsibility nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use, or sell any patented invention that may in any way be related thereto.



Source: https://assist.dla.mil -- Downloaded: 2026-10-19T10:19Z
Check the source to verify that this is the current version before use.