MIL-S-63383(AR)
AMENDMENT 4
22 October 1984
SUPERSEDING
AMENDMENT 3
22 November 1982

MILITARY SPECIFICATION

SAFE AND ARMING (NON-HAZARDOUS) ASSEMBLY
M718/M741

This amendment forms a part of Military Specification MIL-S-63383(AR), dated 23 June 1980, and is approved for use by the U.S. Army Armament, Munitions and Chemical Command, and is available for use by all Departments and Agencies of the Department of Defense.

Delete "Safe and Arming (Clearing Charge Train) Assembly" and substitute, "Safe and Arming (Non-Hazardous) Assembly" wherever mentioned.

PAGE 1

2.1 Under SPECIFICATIONS, delete word "FEDERAL" and substitute "MILITARY".

Add "MIL-S-48747 - Safe and Arming Device for Mines, M718/M741 System.

* MIL-S-45743 - Soldering, Manual Type, High Reliability, Electrical and Electronic Equipment.

* MIL-P-50884 - Printed Wiring, Flexible, General Specification for"

PAGE 2

3.3 Add to the end of the sentence: "as evidenced by the presence of a length of solder in the dummy center lead and the absence of main charge leads and clearing charge propellant".

3.3 Delete from second sentence: "as well as flexible cable assembly".

FSC 1345

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

PAGE 3

3.4 Delete the second line and substitute: "aft ejection charge assembly (without M5 propellant) shall all function high order when the detonators".

3.4.1 Delete paragraph in its entirety.

* 3.9 Add new paragraphs as follows:

"3.9 Flexible cable solder pads.

3.9.1 Lifted or overheated pads. The flexible cable shall contain no lifted, burned or overheated pads.

3.9.2 Solderability. When the flexible cable is tested for solderability in accordance with MIL-P-50884, the cable shall show full wetting and new solder coverage of at least 95% of conductor area not covered by insulating material or extruded adhesive. There shall be no distortion or delamination.

Solderability of each batch of flexible cable solder pads shall be demonstrated a maximum of thirty (30) days prior to assembly to S&A's.

3.9.3 Process control. All solder pad areas shall accept solder evenly, i.e., meet the solderability requirements of 3.9.2 when a solder iron from the assembly operation heats the pad area for a maximum of three (3) seconds and solder from the assembly operation is applied during this period."

* 3.10 Add new paragraph as follows:

"3.10 "G" weight lock spring position. A properly positioned "G" weight lock spring is not kinked, is contained within the lock recess and has its flat end entirely against the surface of the spring retainer."

PAGE 4

4.3.1 Delete "Cable and Detonator Assembly 9277868 10"

Add "-2" after 9277986 and 9277858 in drawing column.

PAGE 5

* TABLE II - Sheet 1 of 2: Delete and substitute new TABLE II, Sheet 1 of 2, attached.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

PAGE 6

* TABLE II - Sheet 2 of 2: Delete and substitute new TABLE II, Sheet 2 of 2, attached.

PAGE 7

4.4.1 Delete paragraph in its entirety and substitute the following new paragraph:

"4.4.1 Inspection lot formation. Inspection lots shall comply with the lot formation provisions of MIL-A-48078. In addition, lots of safe and arming assemblies and sub-assemblies shall contain:

a. Parts bearing the same lot interfix number from one manufacturer and drawn from an accepted lot of representative parts used in the assembly of one lot of safe and arm assemblies, part number 9278015.

b. Explosive detonators, transfer leads, and aft-ejection charge assemblies (without M5 propellant) from the same lot interfix number from one manufacturer and drawn from an accepted lot of representative parts used in the assembly of one lot of safe and arm assemblies, part number 9278015.

Lot numbering shall comply with the lot numbering provisions of MIL-A-48078. Each lot of the Safe and Arming (Non-Hazardous Assemblies) shall be assigned a lot interfix number from within the 500 to 599 number group. All other lot number information shall be consistent with the lot number of safe and arming assembly lot, part number 9278015, from which the representative parts have been selected.

For example, if the Safe and Arming Assembly, part number 9278015, has a lot number of ABC80A001-001, the representative non-hazardous safe and arming assemblies, part number 9317620, would have a lot number of ABC80A500-001."

PAGES 9 and 10

* 4.4.2.2 Delete in its entirety and substitute new paragraph attached.

PAGE 11

4.4.2.3 Delete paragraph in its entirety.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

PAGES 12 and 12a

* 4.4.2.4 Delete in its entirety and substitute new paragraph attached as pages 12 and 12a.

PAGE 13

* 4.4.2.5 Delete in its entirety and substitute new paragraph attached.

PAGE 14

* 4.4.2.6 Delete in its entirety.

PAGES 15a and 15b

* 4.4.2.8 Add new paragraph attached.

PAGE 16

4.4.3.1 Delete paragraph in its entirety.

4.4.3.3 Add the following new paragraph:

"4.4.3.3 Centrifugal lock hole inspection. The inside diameter of the centrifugal lock holes in the S&A housing shall be inspected after staking of the centrifugal lock spring holders. The inspection shall be performed on three (3) centrifugal lock/housing subassemblies from each staking tool at the start of each shift and then on one (1) subassembly randomly selected from each group of 100 produced continuously from lock staking tool. The contractor shall not enter into production with any staking tool unless all three (3) samples pass the initial inspection. Both centrifugal lock holes on each sample shall be inspected. Inspection shall be performed in accordance with 4.5.9. The contractor may request a change in frequency of the inspection provided he presents substantive evidence to support the request."

* 4.4.3.4 Delete in its entirety and substitute new paragraph as follows:

"4.4.3.4 Solder workmanship. The contractor shall assure that the solder process/procedure at each solder assembly station does not contaminate or create a potential short circuit condition(s) on the bottom side of the flexible cable. The contractor shall examine the interface between the detonators and the cable for flux, excessive solder or other unacceptable

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

criteria specified in the solder standard listed on the drawing. The examination shall be performed on five (5) detonator/grounding clip/cable assemblies prior to the start of each shift, after every two (2) hours, and at the end of the shift until three (3) consecutive shifts have been accepted. Thereafter, the examination may be performed on two (2) assemblies prior to the start of each shift and one (1) sample after four (4) hours of production and at the end of the shift. Failure of the sample at any time will cause the examination to revert to the initial conditions until three (3) consecutive shifts have been accepted."

* 4.4.3.5 Add new paragraph as follows:

"4.4.3.5 Flexible cable solderability process control. The samples from 4.4.3.4 shall be used for this examination. Any solder pad failing to comply with the specified requirements shall have its flexible cable/detonator/ground clip assembly classed defective."

* 4.4.3.6 Add new paragraph as follows:

"4.4.3.6 Detonator/clip assembly process control. The contractor shall maintain a positive process control to assure that both detonators and the grounding clip are fully seated in the S&A housing. For the purpose of this examination, fully seated is defined as having the two (2) detonators or the grounding clip flush to above flush by no more than .0025 inch while the other is fully seated. The samples from 4.4.3.4 shall be used to verify the process. Any assembly failing to comply with the specified requirement shall be classed defective."

4.5.4 Delete paragraph 4.5.4 in its entirety and substitute new paragraph 4.5.4 as follows:

"4.5.4 Radiographic examination. The safe and arming assemblies radiographic plates shall be of a quality such that the Technical Agency of 6.5 or their appointed representatives shall be able to view all of the requirements to the Agency's satisfaction. The radiographic plates shall clearly define all explosive components; positively show that the assembly is in the full non-armed condition; the flexible cable shall not be pinched, twisted or damaged; the MDF assembly shall not show evidence of any damage and all components shall be in the non-armed position and the S&A explosive loading complies

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

with the requirement of 3.3. Any assembly failing to comply with all of the specified requirements shall be classed defective and removed from the lot. The vendor will have the option of substituting a paper base sensitive emulsion for the film base (Ref. MIL-STD-453) provided that this material produces the required definition specified above. (Non-destructive test)"

4.5.5.1 Delete paragraph 4.4.5.1 in its entirety and substitute new paragraph 4.4.5.1 as follows:

"4.5.5.1 Detonator continuity resistance. The measurement of the detonator resistance (value specified on Dwg. 9317620) shall be obtained on the final safe and arming assembly, (including staked shield assembly) utilizing an approved milliohmeter whose excitation current does not exceed the no fire condition of the detonators. The resistance measurement shall be obtained across the eyelets on the flexible cable (Dwg. 9277774). Any assembly failing to comply with the specified resistance requirement shall be classed defective. The exposed conductor (shorting loop) in the flexible cable (Dwg. 9277774) must be cut to perform this test and soldered to reconnect the above conductor after completion of test. (Non-destructive test)"

PAGE 20

4.5.6.2 Delete paragraph in its entirety.

PAGE 21

Delete page 21 in its entirety.

PAGE 22

Delete page 22 in its entirety.

PAGE 23

Delete page 23 in its entirety.

PAGE 24

Delete page 24 in its entirety.

PAGE 25

Delete page 25 in its entirety.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

PAGE 26

Delete page 26 in its entirety.

PAGE 27

4.5.9 Add the following new paragraphs:

"4.5.9 Centrifugal lock hole inspection. Both centrifugal lock spring holders shall be removed using approved tooling and procedures. The housing shall be rotated and the centrifugal locks allowed to fall from the housing.

A .2495 - .005 inch pin gage shall fall freely (without applying pressure) to the bottom of the hole (shoulder). If one or both locks fail to fall out under their own weight or the pin gage fails to insert freely in one or both holes, the unit shall be classed defective and that quantity of subassemblies from which the sample was drawn shall be rejected. (Destructive test)"

4.5.10 Critical defect reporting. The contractor shall proceed as follows whenever a critical defect is discovered during the examinations or tests described in this specification:

a. Immediately notify the cognizant technical agency.

b. Tentatively reject and quarantine all previously accepted S&A subassemblies in process.

c. Determine root cause of defect and proceed as directed by the contracting officer.

* 4.5.11 Delete in its entirety and substitute:

"4.5.11 Solder workmanship. The flexible cable/detonator/grounding clip assembly shall be examined under a stereo microscope at a four to ten power (4X to 10X) magnification. Lighting shall be as specified in MIL-S-45743 for inspection purposes. The assembly shall be examined for the specified solder workmanship requirements. Any assembly containing one (1) or more defets shall be classed defective. Any unit failing to comply with the soldering requirements at the start of the shift shall result in the contractor not proceeding with production until corrective action is taken and a subsequent sample passes. Any sample failing during the subsequent examinations or at the end of the shift shall result in all production following the last successful examination being rejected. (Destructive examination)"

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

* 4.5.12 Add new paragraph as follows:

"4.5.12 Flexible cable solder pad process control and solderability. The solder pads to be soldered to the electronic lens assembly shall be tested for the specified requirement utilizing the solder operator's solder iron and solder used in the normal production assembly process. The pad shall demonstrate the solderability requirements during the maximum time period specified for heat application. Any pad failing to fully demonstrate full solderability shall be classed defective. Any unit failing to comply with the soldering requirements at the start of the shift shall result in the conractor not proceeding with production until corrective action is taken and a subsequent sample passes. Any sample failing during the subsequent examinations or at the end of the shift shall result in all production following the last successful examination being rejected. (Destructive examination)"

* 4.5.13 Add new paragraph as follows:

"4.5.13 Detonator/clip assembly process control. The contractor shall describe the process control procedures and gaging techniques required to assure compliance to the seating requirement. These procedures shall be forwarded to the government for approval prior to use (see 6.3). Any assembly failing to comply with the requirement at the start of the shift shall result in the contractor not proceeding with production until correcive action is taken and a subsequent sample passes. Any sample failing during the subsequent examinations or at the end of the shift shall result in all production following the last successful examination being rejected. (Non-destructive examination)"

PAGE 28

6.2 Add "A quantity of Safe and Arming (Non-Hazardous) Assemblies, P/N 9317620 shall be fabricated with each lot of Safe and Arming Assemblies, P/N 9278015 manufactured. Quantity and requirement for delivery shall be as specified in the contract".

* 6.3 Delete "ARRADCOM, ATTN: DRDAR-QAA-I" and substitute "ARDC, ATTN: DRSMC-QAT-I(D)".

* 6.5 Delete "ARRADCOM, ATTN: DRDAR-QAA-M" and substitute ARDC, ATTN: DRSMC-QAT-M(D)".

* 6.6 Delete "ARRADCOM, ATTN: DRDAR-QAA-M" and substitute "ARDC, ATTN: DRSMC-QAT-M(D)".

* 6.7 Delete "ARRADCOM" and substitute "AMCCOM".

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

* 6.8 Add new paragraph as follows:

"6.8 Special defect. A defect other than critical, that judgement and experience indicate may, depending upon the degree of variance from the design requirement:

a. Result in hazardous or unsafe conditions for individuals using, maintaining or depending upon the product or,

b. Prevent performance of the tactical function of a major end item."

The margins of this amendment are marked with an asterisk or vertical lines to indicate where changes (additions, modifications, corrections, deletions) from the previous amendment were made. This was done as a convenience only and the Government assumes no liability whatsoever for any inaccuracies in these notations. Bidders and contractors are cautioned to evaluate the requirements of this document based on the entire content irrespective of the marginal notations and relationship to the last previous amendment.

Custodian:
Army-AR

Preparing activity:
Army-AR

(Project 1345-A314)

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

TABLE I. First article inspection

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE	SHEET	DRAWING NUMBER
	Safe and Arming (Non-Hazardous) Assembly for M718/M741 System	1 OF 2	See Below
			NEXT HIGHER ASSEMBLY

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
	Slider Assembly (Dwg. No. 9317618)				
	Examination for defects	10		3.2	4.4.2.1
	Safe and Arming (Non-Hazardous) Subassembly (Dwg. No. 9317620)				
	Examination for defects	10		3.2	4.4.2.2
	Non-Arming Test	10		3.2	4.5.1
	Non-Arming Test of Centrifugal Weights	10		3.2	4.5.3
	Arming Test	10		3.2	4.5.2
	Safe and Arming (Non-Hazardous) Assembly (Inprocess) (Dwg. No. 9317620)				
	Examination for defects	10		3.2	4.4.2.4
	Closure firing pin stake push off test	5		3.2	4.5.7
	Closure slider stake push off test	5		3.2	4.5.7
	Solder workmanship under cable	5		3.2	4.5.11
	Flexible cable solder pad solderability	5		3.9.2	4.5.12
	Detonator/clip assembly seating	5		3.2	4.5.13

NOTES:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

TABLE I. First article inspection

MIL-S-63383(AR)
AMENDMENT 4

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE		SHEET 2 OF 2		DRAWING NUMBER
Cont'd	Safe and Arming (Non-Hazardous) Assembly for M718/M741 System				See Below
					NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
	Safe and Arming (Non-Hazardous) Assembly (Dwg. No. 9317620)				
	Examination for defects	10		3.2	4.4.2.4
	Detonator Resistance	25		3.2	4.5.5.1
	Detonator Short Circuit	25		3.5	4.5.5.2
	Radiographic Examination	25		3.3	4.5.4
	Explosive Test	25		3.4	4.5.6
	Chamber Assembly (Without M5 Propellant) (Dwg. No. 9277986-2)				
	Examination for defects	10		3.2	4.4.2.5
	Setback Pin Assembly (Dwg. No. 9317617)				
	Examination for defects	10		3.2	4.4.2.7

NOTES:

DRSMC-OA (D) Form 160, 1 Aug 83 replaces edition of 1 Jul 77 which may be used until exhausted.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE	SHEET	DRAWING NUMBER
4.4.2.2	Safe and Arming (Non-Hazardous) Subassembly	1 OF 2	9317620(3)
			NEXT HIGHER ASSEMBLY

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	(5)				
1	Spring, centrifugal lock missing		100%(1)	3.2	Visual/Manual
2	Holder, spring, missing, improperly oriented or loose		100%	3.2	Visual/Manual
3	Lock, centrifugal missing		100%	3.2	Visual
4	Any spring missing or improperly positioned		100%	3.2	Visual/Manual
5	Presence of "G" weight		100%	3.2	Visual/Manual
6	Presence of ball		100%	3.2	Visual/Manual
7	Presence of "G" weight lock		100%	3.2	Visual/Manual
8	Presence of set back pin assembly		100%	3.2	Visual/Manual
9	Non-arming test		100%	3.2	4.5.1
10	Non-arming centrifugal lock test		100%(4)	3.2	4.5.3
11	Deformation of centrifugal lock hole(s) after spring holder staking	4.4.3.3	-	3.2	4.5.9
Major					
101	Presence of more than one spring per cavity		100%	3.2	Visual/Manual
102	Staking missing or improper		100%	3.2	Visual
103	Presence of rear locks		100%	3.2	Visual
104	Presence of rear lock springs		100%	3.2	Visual
105	Any closure missing, loose or improperly staked		100%	3.2	Visual/Manual

NOTES:

Source: https://assist.dla.mil - Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE	SHEET	DRAWING NUMBER
4.4.2.2 Cont'd	Safe and Arming (Non-Hazardous) Subassembly	2 OF 2	9317620(3)
			NEXT HIGHER ASSEMBLY

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
106	Arming test		100% (2)(4)	3.2	4.5.2
107	Closure, Slider oriented properly		0.40%	3.2	Visual
Minor 201	Poor workmanship		1.00%	3.8	Visual

NOTES:

(1) Manual inspection is defined as the allowable probing of the unit by means of an approved instrument which will not cause damage to the sample.
(2) Test is to be performed prior to inserting rear lock assembly.
(3) Parts list shall be in accordance with 4.5.1.
(4) Arming test shall always precede the non-arming tests.
(5) Paragraph 4.5.10 applies whenever critical defects are discovered.

NOTES:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE	SHEET 1 OF 1	DRAWING NUMBER
4.4.2.4	Safe and Arming (Non-Hazardous) Assembly (In-process Examination/Test)		9317620
			NEXT HIGHER ASSEMBLY

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Interrupter free to move		100%	3.2	Dwg. 9317620 (Note 4)
102	Chamber assembly improperly staked		100%	3.2	Visual
103	Grounding clip not fully seated			3.2	4.4.3.6/4.5.13
104	Detonators not fully seated			3.2	4.4.3.6/4.5.13
105	Solder workmanship (Note 1)		100%	3.2	Visual
106	Presence of all closure discs		100%	3.2	Visual/Manual
107	Cable spacer improperly installed		100%	3.2	Visual
108	Closure firing pin stake push off test			3.2	4.4.3.2/4.5.7
109	Closure slider stake push off test			3.2	4.4.3.2/4.5.7
110	Closure, slider oriented improperly		0.40%	3.2	Visual
111	Detonator placement incorrect		100%	3.2	Visual

NOTES: 1. Solder workmanship of detonator terminals and grounding clip tab to flexible cable pads.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE		SHEET 2 OF 2	DRAWING NUMBER 9317620
4.4.2.4 Cont'd	Safe and Arming (Non-Hazardous) Assembly (In-process Examination/Test)			NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH / PARAGRAPH REFERENCE /INSPECTION METHOD
112	Solder workmanship under flexible cable improper	100%		3.2 4.4.3.4/4.5.11
113	Flexible cable overheated or lifted solder pads			3.9.1 Visual
114	Flexible cable solder pad solderability and process control			3.9.2/ 3.9.3 4.4.3.5/4.5.12
Minor 201	Poor workmanship		1.00%	3.8 Visual

NOTES:

DRSMC-OA (D) Form 160, 1 Aug 83 replaces edition of 1 Jul 77 which may be used until exhausted.

Source: https://assist.dla.mil - Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE	SHEET 1 OF 1	DRAWING NUMBER
4.4.2.5	Chamber Assembly		9277986-2
			NEXT HIGHER ASSEMBLY 9317620

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Aft ejection charge assembly missing or not fully seated in dual MDF chamber		100%	3.2	Visual/Manual
102	Pin, locating missing or improperly installed		0.40%	3.2	Visual
103	Stake missing or improper		0.40%	3.2	Visual
104	Molded insert(s) missing or improperly seated		0.40%	3.2	Visual/Manual
105	Crack or break in MDF		100%	3.2	Visual
Minor					
201	Poor workmanship		1.0%	3.8	Visual

NOTES:

DRSMC-OA (D) Form 160, 1 Aug 83 replaces edition of 1 Jul 77 which may be used until exhausted.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE		SHEET 1 OF 2		DRAWING NUMBER
4.4.2.8	Safe and Arming (Non-Hazardous) Assembly				9317620
					NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	(Note 1)				
1	Assembly in partially armed, armed state, missing components or improper explosive loading		100%	3.3	4.5.4/Visual
Special					
A	"G" Weight lock spring missing or improperly positioned		100%	3.10	Visual
Major					
101	Shield assembly missing, loose, not staked or improperly installed		100%	3.2	Visual/Manual
102	Explosive test (see para 6.8)			3.4	4.5.6
103	MDF Damaged		100%	3.2	Visual
104	Detonator resistance		100%	3.2	4.5.5.1
105	Detonator not shorted (Note 2)		100%	3.5	4.5.5.1
106	Foreign material on flexcable solder pads		100%	3.2	Visual
107	Cable spacer missing		100%	3.2	Visual

NOTES:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE		SHEET	OF	DRAWING NUMBER
4.4.2.8 Cont'd	Safe and Arming (Non-Hazardous) Assembly		2	2	9317620
					NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Minor 201	Poor workmanship		1.0%	3.8	Visual
NOTES:	1. Para. 4.5.10 applies whenever an inspection or test item is classed critical. 2. Short circuit shall be verified after resistance measurements have been taken and the short circuit has been replaced.				

NOTES:

Source: https://assist.dla.mil - Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.